



Designation: ~~A1009 – 05 (Reapproved 2010)~~ **A1009 – 18**

Standard Specification for Soft Magnetic MnZn Ferrite Core Materials for High Frequency (10 kHz-1 MHz) Power Transformer and Filter Inductor Applications¹

This standard is issued under the fixed designation A1009; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon (ϵ) indicates an editorial change since the last revision or reapproval.

1. Scope

1.1 This specification covers the requirements to which the specified grades of soft magnetic manganese zinc (MnZn) ferrite materials shall conform. Cores made from these materials are used primarily in ~~power~~ transformers and ~~filter~~ inductors.

1.2 *Frequency*—MnZn ferrite cores are primarily used for frequencies in the range of 10 kHz to 1 MHz. Many inductors have a DC component as well.

1.3 *Magnetic Flux Density*—Applications consist of two main categories, high and low magnetic flux density.

1.3.1 *High Magnetic Flux Density*—Transformers used for power conversion. Inductors or chokes used in high current applications.

1.3.2 *Low Magnetic Flux Density*—Transformers, inductors, chokes used for signal conditioning.

1.4 The values stated in ~~customary (cgs-emu and inch-pounds)~~ SI units are to be regarded as standard. The values given in parentheses are mathematical conversions to ~~SI~~ ~~customary (cgs-emu and inch-pound)~~ units, which are provided for information only and are not considered standard.

1.5 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety, health, and environmental practices and determine the applicability of regulatory limitations prior to use.*

1.6 *This international standard was developed in accordance with internationally recognized principles on standardization established in the Decision on Principles for the Development of International Standards, Guides and Recommendations issued by the World Trade Organization Technical Barriers to Trade (TBT) Committee.*

2. Referenced Documents

2.1 *ASTM Standards:*²

[A340 Terminology of Symbols and Definitions Relating to Magnetic Testing](#)

[A1013 Test Method for High-Frequency \(10 kHz-1 MHz\) Core Loss of Soft Magnetic Core Components at Controlled Temperatures Using the Voltmeter-Ammeter-Wattmeter Method](#)

3. Terminology

3.1 The terms and symbols used in this specification are defined in Terminology [A340](#).

3.2 *Definitions of Terms Specific to This Standard:*

3.2.1 *Inductance Index (AL value)*—the self inductance per winding turn squared (L/N^2) expressed in units of nanohenries per turns squared (nH/N^2).

where:

n = nano = 10^{-9} ,

nH = inductance in nanohenries, and

¹ This specification is under the jurisdiction of ASTM Committee [A06](#) on Magnetic Properties and is the direct responsibility of Subcommittee [A06.02](#) on Material Specifications.

Current edition approved Nov. 1, 2010/Oct. 1, 2018, Published December 2010/November 2018. Originally approved in 2000. Last previous edition approved in 2005/2010 as ~~A1009 – 05~~ A1009 – 05 (2010). DOI: ~~10.1520/A1009-05R10~~ 10.1520/A1009-18.

² For referenced ASTM standards, visit the ASTM website, www.astm.org, or contact ASTM Customer Service at service@astm.org. For *Annual Book of ASTM Standards* volume information, refer to the standard's Document Summary page on the ASTM website.

N = number of turns on winding (example: 0.005 H with a 100 turn coil = $0.005/(100)^2 \text{ H/N}^2 = 500 \text{ nH/N}^2$).

3.2.2 *Mated Core Set*—Two or more core segments assembled with the magnetic flux path perpendicular to the mating surface.

3.2.3 Air core inductance, L_{air} , is the inductance of a core with the same magnetic path length and cross-sectional core area but with the relative permeability of air:

3.2.3.1 *Customary Units*

$$L_{\text{air}} = 4\pi AN^2 10^{-9}/l_1, \text{ H}$$

where:

N = number of turns on winding;

A = cross-sectional area of core specimen, cm^2 ; and

l_1 = effective magnetic path length, cm.

3.2.3.2 *SI Units*

$$L_{\text{air}} = 4\pi AN^2 10^{-7}/l_1, \text{ H}$$

where:

N = number of turns on winding;

A = cross-sectional area of core specimen, m^2 ; and

l_1 = effective magnetic path length, m.

3.2 *Definitions of Terms Specific to This Standard:*

3.2.1 *air core inductance (L_{air})*—the A_L value, assuming an effective permeability of one. A_L is proportional to the factors of shape and size of the core. The air core inductance is expressed as nanohenries per turn squared (nH/N^2).

$$L_{\text{air}} = \mu_o A_e L_e \tag{1}$$

where:

A_e = effective cross-sectional area of core in mm^2 ,

L_e = effective magnetic path length of core in mm, and

μ_o = the magnetic constant as $0.4 \pi \text{ nH/mm}$.

3.2.2 *effective initial permeability (μ_e)*—the initial permeability of the material as defined in **A340**, adjusted for known processing variables that are not accounted for in the L_{air} term such as mating surface finish and heat treatment. Can vary with size, shape, and material.

3.2.3 *inductance index (A_L value)*—the inductance normalized for the number of turns. Is proportional to the factors of effective initial permeability of the material core, shape, and size. It allows quick determination of expected inductance when used with the number of turns on the winding of the intended application. The inductance index is expressed as nanohenries per turn squared (nH/N^2):

$$A_L = L_{\text{air}} \mu_e \tag{2}$$

And therefore the expected inductance (L) is:

$$L = A_L N^2 \tag{3}$$

where:

nH = inductance in nanohenries, 10^{-9} Henries,

N = the number of turns of winding,

L = the expected inductance, for a given A_L and number of turns.

3.2.4 *mated core set*—two or more core segments assembled with the magnetic flux path perpendicular to the mating surface.

4. Classification

4.1 The soft magnetic MnZn ferrite material-type designations for power transformer and filter inductor high and low magnetic flux density materials covered by this specification are listed in **Table 1**, **Table 2**, and **Table X1.1.2**. The prefix of the type designations identifies each material's intended use. Power transformer High magnetic flux density materials are denoted with the prefix P and filter low magnetic flux density materials are denoted with the prefix F.

4.2 *High Magnetic Flux Density Materials*—The first and second digits of the type designations for a power transformer material identify the typical core loss density of the material in mW/cm^3 , and the remainder of the type designation identifies the temperatures in $^{\circ}\text{C}$ in which the core material must not exceed the maximum core loss density.

4.3 *Low Magnetic Flux Density Materials*—The last four digits of the type designations for filter materials identify the typical relative inductance permeability.

TABLE 1 Power Transformer Material Type Designations and Magnetic Requirements

ASTM Power Material Type	Maximum Core Loss Density ^A		Specified Temperatures That Core Loss Density Must Not Exceed Maximum	Minimum Saturation Flux Density ^B	
	Customary Units, mW/cm ²	SI Units, W/m ²	SI Units, °C	Customary Units, G	SI Units, T
P5025-100	65	65-000	25-100	5000	0.5
P5099	65	65-000	99	5000	0.5
P7070	80	80-000	70	5000	0.5
P7099	80	80-000	100	5000	0.5
P8040	90	90-000	40	5000	0.5

TABLE 1 High Magnetic Flux Density Material Type Designations and Magnetic Requirements

ASTM Power Material Type	Core Loss Density ^A kW/m ³ (mW/cm ³)		Temperature °C	Saturation Flux Density ^B mT (gauss)
	Nominal	Maximum		Minimum
P5025-100	50 (50)	65 (65)	25-100	500 (5000)
P5099	50 (50)	65 (65)	100	500 (5000)
P7070	70 (70)	80 (80)	70	500 (5000)
P7099	70 (70)	80 (80)	100	500 (5000)
P8040	80 (70)	90 (90)	40	500 (5000)

^ACore loss density test conditions: 100 kHz, 1000-G (0.1 T) at temperature of minimum core loss; 100 mT (100 gauss), at specified temperature.

^BSaturation flux density test conditions: 1 kHz, 15 Oe (1200 A/m); 1200 A/m (15 Oe), at 25°C.

TABLE 2 Filter Inductor Material Type Designations and Magnetic Requirements

ASTM Filter Material Type	Minimum Relative Inductance Permeability ^A	Maximum Relative Inductance Permeability ^A
	μ _r	μ _r
F010K	7000	13 000
F5000	3750	6 500
F3000	2250	3 900

TABLE 2 Low Magnetic Flux Density Material Type Designations and Magnetic Requirements

ASTM Filter Material Type	Relative Inductance Permeability ^A			
	Minimum	Nominal	Maximum	Tolerance
F010K	7000	10 000	13 000	±30 %
F7000	4900	7000	9100	±30 %
F5000	3750	5000	6250	±25 %
F3000	2500	3000	3750	±25 %

^ARelative inductance permeability test conditions: 100 kHz, 5-G (0.0005 T); 0.5 mT (5 gauss), at 25°C.

5. Ordering Information

5.1 Orders for material under this specification shall include such of the following information as is required to describe the material adequately.

5.1.1 ASTM specification number including year of issue or revision.

5.1.2 ASTM soft magnetic MnZn ferrite material-type designation.

5.1.3 Core shape, size, dimensions, and dimensional tolerances.

5.1.4 Whether the core is to be purchased with or without a gap.

5.1.4.1 The Inductance Index (AL value) or the mechanical gap depth.

5.1.4.2 If the mated core set is ordered gapped by an Inductance Index (AL value), the purchaser must specify whether the mated core set consists of a gapped core half mated with an ungapped un-gapped core half or if both core halves are equally gapped.