

INTERNATIONAL STANDARD



**Rotating electrical machines –
Part 2-1: Standard methods for determining losses and efficiency from tests
(excluding machines for traction vehicles)**

Document Preview

[IEC 60034-2-1:2024](https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024)

<https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024>





THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

International
Standards
Document Preview
standards.iteh.ai

[IEC 60034-2-1:2024](https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024)

<https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024>



IEC 60034-2-1

Edition 3.0 2024-03
REDLINE VERSION

INTERNATIONAL STANDARD



**Rotating electrical machines –
Part 2-1: Standard methods for determining losses and efficiency from tests
(excluding machines for traction vehicles)**

Document Preview

[IEC 60034-2-1:2024](https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024)

<https://standards.iteh.ai/catalog/standards/iec/9aa04680-cc41-4eb9-b358-c6f323e83ec3/iec-60034-2-1-2024>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.160.01

ISBN 978-2-8322-8542-8

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
4 Symbols and abbreviated terms.....	13
4.1 Symbols.....	13
4.2 Additional subscripts.....	14
5 Basic requirements.....	15
5.1 Direct and indirect efficiency determination.....	15
5.2 Uncertainty	15
5.3 Preferred methods and methods for customer-specific acceptance tests, field-tests or routine-tests	16
5.4 Power supply	16
5.4.1 Voltage.....	16
5.4.2 Frequency	16
5.5 Instrumentation.....	16
5.5.1 General	16
5.5.2 Measuring instruments for electrical quantities	16
5.5.3 Torque measurement.....	17
5.5.4 Speed and frequency measurement.....	18
5.5.5 Temperature measurement.....	18
5.6 Units.....	18
5.7 Resistance.....	18
5.7.1 Test resistance.....	18
5.7.2 Winding temperature	18
5.7.3 Correction to reference coolant temperature.....	19
5.8 State of the machine under test and test categories.....	19
5.9 Excitation circuit measurements.....	20
5.10 Ambient temperature during testing	21
6 Test methods for the determination of the efficiency of induction machines	21
6.1 Preferred testing methods.....	21
6.1.1 General	21
6.1.2 Method 2-1-1A – Direct measurement of input and output.....	22
6.1.3 Method 2-1-1B – Summation of losses, additional load losses according to the method of residual loss	24
6.1.4 Method 2-1-1C – Summation of losses with additional load losses from assigned allowance	33
6.2 Testing methods for field or routine-testing	38
6.2.1 General	38
6.2.2 Method 2-1-1D – Dual supply back-to-back-test.....	39
6.2.3 Method 2-1-1E – Single supply back-to-back-test	40
6.2.4 Method 2-1-1F – Summation of losses with additional load losses determined by test with rotor removed and reverse rotation test	41
6.2.5 Method 2-1-1G – Summation of losses with additional load losses determined by Eh-star method	46
6.2.6 Method 2-1-1H – Determination of efficiency by use of the equivalent circuit parameters.....	51
7 Test methods for the determination of the efficiency of synchronous machines.....	57

7.1	Preferred testing methods	57
7.1.1	General	57
7.1.2	Method 2-1-2A – Direct measurement of input and output.....	58
7.1.3	Method 2-1-2B – Summation of separate losses with a rated load temperature test and a short circuit test.....	59
7.1.4	Method 2-1-2C – Summation of separate losses without a full load test	65
7.2	Testing methods for field or routine testing	67
7.2.1	General	67
7.2.2	Method 2-1-2D – Dual supply back-to-back-test.....	67
7.2.3	Method 2-1-2E – Single supply back-to-back-test	68
7.2.4	Method 2-1-2F – Zero power factor test with excitation current from Potier-, ASA- or Swedish-diagram	70
7.2.5	Method 2-1-2G – Summation of separate losses with a load test without consideration of additional load losses	74
8	Test methods for the determination of the efficiency of DC machines	75
8.1	Testing methods for field or routine testing	75
8.2	Method 2-1-3A – Direct measurement of input and output.....	76
8.2.1	General	76
8.2.2	Test procedure	77
8.2.3	Efficiency determination.....	77
8.3	Method 2-1-3B – Summation of losses with a load test and DC component of additional load losses from test.....	78
8.3.1	General	78
8.3.2	Test procedure	79
8.4	Method 2-1-3C – Summation of losses with a load test and DC component of additional load losses from assigned value	85
8.4.1	General	85
8.4.2	Test procedure	86
8.4.3	Efficiency determination.....	87
8.5	Method 2-1-3D – Summation of losses without a load test	88
8.5.1	General	88
8.5.2	Test procedure	89
8.5.3	Efficiency determination.....	90
8.6	Method 2-1-3E – Single supply back-to-back test.....	91
8.6.1	General	91
8.6.2	Test procedure	91
8.6.3	Efficiency determination.....	92
Annex A (normative)	Calculation of values for the Eh-star method	93
Annex B (informative)	Types of excitation systems	96
Annex C (informative)	Induction machine slip measurement.....	97
Annex D (informative)	Test report template for method 2-1-1B.....	99
Bibliography	100
Figure 1	– Torque measuring devices	17
Figure 2	– Sketch for torque measurement test.....	22
Figure 3	– Efficiency determination according to method 2-1-1A	23
Figure 4	– Efficiency determination according to method 2-1-1B	26
Figure 5	– Smoothing of the residual loss data.....	32

Figure 6 – Efficiency determination according to method 2-1-1C	35
Figure 7 – Vector diagram for obtaining current vector from reduced voltage test	36
Figure 8 – Assigned allowance for additional load losses P_{LL}	37
Figure 9 – Efficiency determination according to method 2-1-1D	39
Figure 10 – Sketch for dual supply back-to-back test	39
Figure 11 – Efficiency determination according to method 2-1-1E	40
Figure 12 – Efficiency determination according to method 2-1-1F	43
Figure 13 – Efficiency determination according to method 2-1-1G	48
Figure 14 – Eh-star test circuit	49
Figure 15 – Induction machine, T-model with equivalent iron loss resistor	51
Figure 16 – Efficiency determination according to method 2-1-1H	52
Figure 17 – Induction machines, reduced model for calculation	55
Figure 18 – Sketch for torque measurement test	58
Figure 19 – Efficiency determination according to method 2-1-2A	58
Figure 20 – Efficiency determination according to method 2-1-2B	60
Figure 21 – Efficiency determination according to method 2-1-2C	66
Figure 22 – Efficiency determination according to method 2-1-2D	67
Figure 23 – Sketch for dual supply back-to-back test ($I_M = I_G, f_M = f_G$)	68
Figure 24 – Efficiency determination according to method 2-1-2E	69
Figure 25 – Single supply back-to-back test for synchronous machines	69
Figure 26 – Efficiency determination according to method 2-1-2F	70
Figure 27 – Efficiency determination according to method 2-1-2G	75
Figure 28 – Sketch for torque measurement test	76
Figure 29 – Efficiency determination according to method 2-1-3A	77
Figure 30 – Efficiency determination according to method 2-1-3B	79
Figure 31 – Sketch for single supply back-to-back test for determination of DC component of additional load losses	83
Figure 32 – Efficiency determination according to method 2-1-3C	86
Figure 33 – Efficiency determination according to method 2-1-3D	89
Figure 34 – Efficiency determination according to method 2-1-3E	91
Figure 35 – Sketch for single supply back-to-back test	91
Figure C.1 – Slip measurement system block diagram	98
Table 1 – Reference temperature	19
Table 2 – Induction machines: preferred testing methods	21
Table 3 – Induction machines: other methods	39
Table 4 – Synchronous machines with electrical excitation: preferred testing methods	57
Table 5 – Synchronous machines with permanent magnets: preferred testing methods	57
Table 6 – Synchronous machines: other methods	67
Table 7 – DC machines: test methods	76
Table 8 – Multiplying factors for different speed ratios	87

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ROTATING ELECTRICAL MACHINES –

**Part 2-1: Standard methods for determining losses and efficiency
from tests (excluding machines for traction vehicles)**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 60034-2-1:2014. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 60034-2-1 has been prepared by IEC technical committee 2: Rotating machinery. It is an International Standard.

This third edition cancels and replaces the second edition of IEC 60034-2-1 published in 2014. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

Harmonization of layout and requirements with IEC 60034-2-2 and IEC 60034-2-3.

The text of this International Standard is based on the following documents:

Draft	Report on voting
2/2165/FDIS	2/2177/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 60034 series, published under the general title *Rotating electrical machines*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

ROTATING ELECTRICAL MACHINES –

Part 2-1: Standard methods for determining losses and efficiency from tests (excluding machines for traction vehicles)

1 Scope

This part of IEC 60034 is intended to establish methods of determining efficiencies from tests, and also to specify methods of obtaining specific losses.

This document applies to DC machines and to AC synchronous and induction machines of all sizes within the scope of IEC 60034-1 *rated for mains operation*.

NOTE These methods may be applied to other types of machines such as rotary converters, AC commutator motors and single-phase induction motors.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60027-1, *Letter symbols to be used in electrical technology – Part 1: General*

IEC 60034-1:2010/2022, *Rotating electrical machines – Part 1: Rating and performance*

~~IEC 60034-4:2008, *Rotating electrical machines – Part 4: Methods for determining synchronous machine quantities from tests*~~

IEC 60034-4-1:2018, *Rotating electrical machines – Part 4-1: Methods for determining electrically excited synchronous machine quantities from tests*

IEC 60034-19, *Rotating electrical machines – Part 19: Specific test methods for DC machines on conventional and rectifier-fed supplies*

IEC 60034-29, *Rotating electrical machines – Part 29: Equivalent loading and superposition techniques – Indirect testing to determine temperature rise*

IEC 60034-30-1, *Rotating electrical machines – Part 30-1: Efficiency classes of line operated AC motors (IE code)*

IEC 60051(all parts), *Direct acting indicating analogue electrical measuring instruments and their accessories*

IEC 60051-1, *Direct acting indicating analogue electrical measuring instruments and their accessories – Part 1: Definitions and general requirements common to all parts*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60034-1, IEC 60051-1 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1

efficiency

ratio of output power to input power expressed in the same units and usually given as a percentage

3.2

direct efficiency determination

method by which the determination of efficiency is made by measuring directly the input power and the output power

~~3.3~~

~~**dynamometer**~~

~~device for measuring torque applied to the rotating part of the machine under test. It is equipped with means for measuring and indicating torque and speed, and is not limited to a cradle base construction. An in-line torque transducer may be used to provide a direct measurement of torque at the shaft of the machine under test.~~

~~3.4~~

~~**dynamometer test**~~

~~test in which the mechanical power output of a machine acting as a motor is determined by a dynamometer. Also a test in which the mechanical input power of a machine acting as a generator is determined by a dynamometer.~~

3.3

dual-supply back-to-back test

test in which two identical machines are mechanically coupled together, and the total losses of both machines are calculated from the difference between the electrical input to one machine and the electrical output of the other machine

3.4

indirect efficiency determination

method by which the determination of efficiency is made by measuring the input power or the output power and determining the total losses. Those losses are added to the output power, thus giving the input power, or subtracted from the input power, thus giving the output power

3.5

single-supply back-to-back test

test in which two identical machines are mechanically coupled together and are both connected electrically to the same power system. The total losses of both machines are taken as the input power drawn from the system

3.6

no-load test

test in which a machine is run as a motor providing no useful mechanical output from the shaft, or ~~when~~ if run as a generator with its terminals open-circuited

3.7**zero power factor test** ~~(synchronous machines)~~

no-load test on a synchronous machine, which is over-excited and operates at a power factor very close to zero

3.8**equivalent circuit method** ~~(induction machines)~~

test on an induction machine in which the losses are determined by help of an equivalent circuit model

3.9**test with rotor removed and reverse rotation test** ~~(induction machines)~~

combined test on an induction machine in which the additional load losses are determined from a test with rotor removed and a test with the rotor running in reverse direction to the rotating magnetic field of the stator

3.10**short-circuit test** ~~(synchronous machines)~~

test on a synchronous machine in which a machine is run as a generator with its terminals short-circuited

3.11**locked rotor test**

test in which the rotor is locked to prevent rotation

3.12**Eh-star test**

test in which the motor is run in star connection on unbalanced voltage

3.13**losses****3.13.1****total losses**

P_T

difference between the input power and the output power, equivalent to the sum of the constant losses (see 3.13.2), the load losses (see 3.13.4), the additional load losses (see 3.13.5) and the excitation circuit losses (see 3.13.3)

3.13.2**constant losses**

P_c

losses incorporating the sum of windage, friction and iron losses

Note 1 to entry: Although these losses change with voltage and load, they are historically called "constant" losses and the name is retained in this document.

3.13.2.4**constant losses**

P_c

~~sum of the iron losses and the friction and windage losses~~

3.13.2.1**iron losses**

P_{fe}

losses in active iron and additional no-load losses in other ~~metal~~ magnetic and conductive parts

3.13.2.2 friction and windage losses

P_{fw}

losses incorporating the sum of windage and friction

3.13.2.2.1 friction losses

losses due to friction (bearings and brushes, if not lifted at rated conditions) not including any losses in a separate lubricating system

3.13.2.2.2 windage losses

total losses due to aerodynamic friction in all parts of the machine, including power absorbed in shaft mounted fans, and in auxiliary machines forming an integral part of the machine

Note 1 to entry: Losses in a separate ventilating system should be listed separately.

Note 2 to entry: For machines indirectly or directly cooled by hydrogen, see IEC 60034-1.

3.13.3 excitation circuit losses

3.13.3.1 excitation circuit losses

P_e

sum of the excitation winding losses (see 3.13.3.2), the exciter losses (see 3.13.3.3) and, for synchronous machines, electrical brush loss (see 3.13.3.5), if any

3.13.3.2 excitation winding losses

P_f

excitation (field) winding losses are equal to the product of the exciting current I_e and the excitation voltage U_e

3.13.3.3 exciter losses

P_{Ed}

exciter losses for the different excitation systems (see Annex B) are defined as follows:

a) shaft driven exciter

exciter losses are the power absorbed by the exciter at its shaft (reduced by friction and windage losses) plus the power P_{1E} drawn from a separate source at its excitation winding terminals, minus the useful power which the exciter provides at its terminals. The useful power at the terminals of the exciter is equal to the excitation winding losses as per 3.13.3.2 plus (in the case of a synchronous machine) the electrical brush losses as per 3.13.3.5.

Note 1 to entry: If the exciter can be decoupled and tested separately its losses can be determined according to 7.1.3.2.1.5.

Note 2 to entry: Whenever the exciter makes use of separate auxiliary supplies, their consumptions are to be included in the exciter losses unless they are considered together with the main machine auxiliaries consumption.

b) brushless exciter

exciter losses are the power absorbed by the exciter at its shaft, reduced by friction and windage losses (when the relevant test is performed on the set of main machine and exciter), plus the electrical power P_{1E} from a separate source (if any) absorbed by its field winding or its stator winding (in the case of an induction exciter), minus the useful power which the exciter provides at the rotating power converter terminals.

Note 3 to entry: Whenever the exciter makes use of separate auxiliary supplies their consumptions are to be included in the exciter losses unless they are considered together with the main machine auxiliaries consumption.

Note 4 to entry: If the exciter can be decoupled and tested separately, its losses can be determined according to 7.1.3.2.1.

c) separate rotating exciter

exciter losses are the difference between the power absorbed by the driving motor, plus the power absorbed by separate auxiliary supplies, of both driving and driven machines, including the power supplied by separate source to their excitation winding terminals, and the excitation power supplied as per 3.13.3.2 and 3.13.3.4. The exciter losses may be determined according to 7.1.3.2.1.

d) static excitation system

static exciter

excitation system losses are the difference between the electrical power drawn from its power source, plus the power absorbed by separate auxiliary supplies, and the excitation supplied as per 3.13.3.2 and 3.13.3.4.

Note 5 to entry: In the case of systems fed by transformers, the transformer losses shall be included in the exciter losses.

e) excitation from auxiliary winding

auxiliary winding exciter

exciter losses are the copper losses in the auxiliary (secondary) winding and the additional iron losses produced by increased flux harmonics. The additional iron losses are the difference between the losses which occur when the auxiliary winding is loaded and when it is unloaded.

Note 6 to entry: Because separation of the excitation component of losses is difficult, it is recommended to consider these losses as an integral part of the stator losses when determining overall losses.

In the cases c) and d) no allowance is made for the losses in the excitation source (if any) or in the connections between the source and the brushes (synchronous machine) or between the source and the excitation winding terminals (DC machine).

If the excitation is supplied by a system having components as described in b) to e) the exciter losses shall include the relevant losses of the components pertaining to the categories listed in Annex B as applicable.

3.13.3.4 separately supplied excitation power

P_{1E}

excitation power P_{1E} supplied from a separate power source is:

- for exciter types a) and b) the exciter excitation power (DC or synchronous exciter) or stator winding input power (induction exciter). It covers a part of the exciter losses P_{Ed} (and further losses in induction exciters) while a larger part of P_e is supplied via the shaft;
- for exciter types c) and d) equal to the excitation circuit losses, $P_{1E} = P_e$;
- for exciter type e) $P_{1E} = 0$, the excitation power being delivered entirely by the shaft. Also, $P_{1E} = 0$ for machines with permanent magnet excitation.

Exciter types shall be in accordance with 3.13.3.3.

3.13.3.5 brush losses (excitation circuit)

P_b

electrical brush loss (including contact loss) of separately excited synchronous machines

3.13.4 load losses

3.13.4.1 load losses

P_L

sum of the winding (I^2R) losses (see 3.13.4.2) and the electrical brush losses (see 3.13.3.5), if any

3.13.4.2 winding losses

winding losses are I^2R losses:

- in the armature circuit of DC machines;
- in the stator and rotor windings of induction machines;
- in the armature and field windings of synchronous machines

3.13.4.3 brush losses ~~(load circuits)~~

P_b

electrical brush loss (including contact loss) in the armature circuit of DC machines and in wound-rotor induction machines

3.13.5 additional load losses ~~(stray-load losses)~~

P_{LL}

losses produced in active iron and other ~~metal~~ magnetic and conductive parts by alternating stray fluxes when the machine is loaded; eddy current losses in winding conductors caused by load current-dependent flux pulsations and additional brush losses caused by commutation

Note 1 to entry: These losses do not include the additional no-load losses of 3.13.2.2.

3.13.6 short-circuit losses

$P_k P_{sc}$

current-dependent losses in a synchronous machine and in a DC machine when the armature winding is short-circuited

3.14 test quantities <polyphase AC machines>

3.14.1 terminal voltage

for polyphase AC machines, the arithmetic average of line voltages

3.14.2 line current

for polyphase AC machines, the arithmetic average of line currents

3.14.3 line-to-line resistance

for polyphase AC machines, the arithmetic average of resistances measured between each pair of terminals

Note 1 to entry: For Y-connected three-phase machines, the phase-resistance is 0,5 times the line-to-line resistance. For Δ -connected machines, the phase-resistance is 1,5 times the line-to-line resistance.

Note 2 to entry: In Clauses 6 and 7 explanations and formulae given are for three-phase machines, unless otherwise indicated.