

---

---

**Električne inštalacije zgradb - 4-44. del: Zaščitni ukrepi - Zaščita pred prenapetostmi - Zaščita pred napetostnimi motnjami in pred elektromagnetnimi motnjami**

Electrical installations of buildings - Part 4-44: Protection for safety - Protection against voltage disturbances and electromagnetic disturbances

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[SIST IEC 60364-4-44:2006](https://standards.iteh.ai/catalog/standards/sist/9312ac2a-dad5-4f87-883c-5ff3ee62ad7c/sist-iec-60364-4-44-2006)

<https://standards.iteh.ai/catalog/standards/sist/9312ac2a-dad5-4f87-883c-5ff3ee62ad7c/sist-iec-60364-4-44-2006>



NORME  
INTERNATIONALE

CEI  
IEC

INTERNATIONAL  
STANDARD

60364-4-44

Première édition  
First edition  
2001-08

---

---

**Installations électriques des bâtiments –**

**Partie 4-44:**

**Protection pour assurer la sécurité –  
Protection contre les perturbations de tension  
et les perturbations électromagnétiques**

(standards.iteh.ai)

**Electrical installations of buildings –**

SIST IEC 60364-4-44:2006

<https://standards.iteh.ai/standards/sist/9312ac2a-dad5-4f87-883c-5ff3ee62ad7c/sist-60364-4-44-2006>

**Part 4-44:  
Protection for safety –  
Protection against voltage disturbances  
and electromagnetic disturbances**

© IEC 2001 Droits de reproduction réservés — Copyright - all rights reserved

Aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'éditeur.

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission  
Telefax: +41 22 919 0300

e-mail: [inmail@iec.ch](mailto:inmail@iec.ch)

3, rue de Varembé Geneva, Switzerland  
IEC web site <http://www.iec.ch>



Commission Electrotechnique Internationale  
International Electrotechnical Commission  
Международная Электротехническая Комиссия

CODE PRIX  
PRICE CODE

X

*Pour prix, voir catalogue en vigueur  
For price, see current catalogue*



## CONTENTS

|   |    |
|---|----|
| FOREWORD .....  | 7  |
| 440 Introduction.....   | 9  |
| 440.1 (442.1.1) Scope .....   | 13 |
| 440.2 (442.1.4) Normative references .....  | 13 |
| 441 (Number available).....   | 15 |
| 442 Protection of low-voltage installations against temporary overvoltages and faults<br>between high-voltage systems and earth ..... | 15 |
| 442.1 General requirements .....  | 15 |
| 442.2 Earthing systems in transformer sub-stations .....  | 17 |
| 442.3 Earthing arrangements in transformer sub-stations.....  | 17 |
| 442.4 Earthing arrangements with regard to type of earthing systems in LV installations....   | 19 |
| 442.5 Limitation of stress-voltage in LV equipment of transformer sub-stations .....  | 21 |
| 442.6 Stress voltage in case of loss of the neutral conductor in a TN and TT system.....  | 21 |
| 442.7 Stress voltage in case of accidental earthing of an IT system .....   | 21 |
| 442.8 Stress voltage in case of a short-circuit between a line conductor and<br>the neutral conductor .....                           | 21 |
| 443 Protection against overvoltages of atmospheric origin or due to switching.....  | 43 |
| 443.1 General .....   | 43 |
| 443.2 Classification of impulse withstand categories (overvoltage categories) .....   | 43 |
| 443.3 Arrangements for overvoltage control.....   | 45 |
| 443.4 Selection of equipment in the installation.....   | 47 |
| 444 (Number available).....   | 49 |
| 444.1 (Number available).....   | 49 |
| 444.2 (Number available).....   | 49 |
| 444.3 Measures against electric and magnetic influences on electrical equipment.....  | 49 |
| 444.4 Measures for signal connections .....   | 51 |
| 445 (45) Protection against undervoltage .....  | 63 |
| 445.1 (451) General requirements .....  | 63 |
| Annex A (informative) Explanatory notes concerning 442.1, 442.1.2.....  | 65 |
| Annex B (informative) Guidance for protective control applied in the overhead lines<br>according to note 1 of 443.3.2.1.....          | 69 |
| Annex C (informative) IEC 60364 – Parts 1 to 6: Restructuring.....  | 73 |
| Bibliography .....  | 81 |

|  |    |
|--|----|
| Figure 44A – Maximum duration of fault-voltage $F$ and touch voltage $T$ due to an earth-fault in the HV system.....                 | 23 |
| Figure 44B – TN systems.....   | 25 |
| Figure 44C – TT systems.....   | 27 |
| Figure 44D – IT system, example a.....   | 29 |
| Figure 44E – IT system, example b.....   | 31 |
| Figure 44F – IT system, example c1 .....   | 33 |
| Figure 44G – IT system, example c2.....  | 35 |
| Figure 44H – IT system, example d.....   | 37 |
| Figure 44J – IT system, example e1.....  | 39 |
| Figure 44K – IT system, example e2.....  | 41 |
| Figure 44L – TN-C and TN-C-S systems in a building.....  | 53 |
| Figure 44M – Avoidance of neutral conductor currents in a bonding structure by using the TN-S system within the building system..... | 55 |
| Figure 44N – Armoured cables and metal pipes entering the buildings (examples) .....   | 57 |
| Figure 44O – Illustration of measures described in this standard in an existing building .....                                       | 59 |
| Figure 44P – Overview of an earthing system of building according to IEC 60364-5-54, IEC 61000-2-5 and IEC 61024-1 .....             | 61 |
| Table 44A – Permissible stress voltage.....  | 17 |
| Table 44B – Required rated impulse withstand voltage of equipment.....   | 47 |
| Table B.1 – Different possibilities for IT systems .....   | 71 |
| Table C.1 – Relationship between restructured and original parts.....  | 73 |
| Table C.2 – Relationship between new and old clause numbering .....  | 77 |

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

## ELECTRICAL INSTALLATIONS OF BUILDINGS –

**Part 4-44: Protection for safety –  
Protection against voltage disturbances and  
electromagnetic disturbances**

## FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.
- 3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical specifications, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.
- 5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.
- 6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60364-4-44 has been prepared by IEC technical committee 64: Electrical installations and protection against electric shock.

The IEC 60364 series (parts 1 to 6), is currently being restructured, without any technical changes, into a more simple form (see annex C).

According to a unanimous decision by the Committee of Action (CA/1720/RV (2000-03-21)), the restructured parts of IEC 60364 have not been submitted to National Committees for approval.

The text of this first edition of IEC 60364-4-44 is compiled from and replaces

- part 4-442, first edition (1993), its amendment 1 (1995) and its amendment 2 (1999)
- part 4-443, second edition (1995) and its amendment 1 (1998),
- part 4-444, first edition (1996) and
- part 4-45, first edition (1984).

This publication has been drafted, as close as possible, in accordance with the ISO/IEC Directives, Part 3.

Annexes A, B and C are for information only.

The committee has decided that the contents of this publication will remain unchanged until 2006. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

## 440 Introduction

Part 4-44 of IEC 60364 provides rules for the protection against the effects of conducted and radiated disturbances on electrical installations.

The rules of this standard do not apply to systems which are wholly or partly under control of public power supply companies (see scope of IEC 60364-1).

The fault-current flowing in the earth electrode of the exposed-conductive-parts of the sub-station causes a significant rise of the potential of the exposed-conductive-parts of the sub-station to the general mass of the earth, i.e. a fault-voltage, whose magnitude is governed by

- the fault-current magnitude, and
- the resistance of the earth electrode of the exposed-conductive-parts of the sub-station.

The fault-current may cause

- a general rise of the potential of the low-voltage system with respect to earth, i.e. stress-voltages which may cause a breakdown of the insulation in low-voltage equipment,
- a general rise of the potential of the exposed-conductive-parts of the low-voltage system with respect to earth, which may give rise to fault-voltage and touch voltages.

NOTE In this standard, the expression "high-voltage" (HV) refers to voltages exceeding the upper limit of voltage band II. The expression "low-voltage" (LV) refers to voltages not exceeding the upper limit of voltage band II.

Clause 443 is intended to describe the means by which transient overvoltages can be limited to reduce the risk of failures in the installation, and in electrical equipment connected to it, to an acceptable level. This approach is in line with the principles of insulation co-ordination in IEC 60664. IEC 60664-1 requires technical committees to specify an appropriate impulse withstand category (overvoltage category) for their equipment, that means a minimum impulse withstand voltage for the equipment, according to its application and the related impulse withstand categories.

NOTE Following 2.2.2 of IEC 60664-1, technical committees should specify the relevant information. It is recommended to indicate the rated impulse withstand voltage to be supplied with the equipment and the way in which this should be done.

(Introduction IEC 60374-4-444, in part).

In clause 444, basic recommendations are described to mitigate electromagnetic disturbances. Actually electromagnetic interferences (EMI) can disturb or damage information technology systems or equipment, equipment with electronic components or circuits. Currents due to lightning, switching operations, short-circuits and other electromagnetic phenomena can cause overvoltages and electromagnetic interference.

These effects appear

- where large metal loops exist<sup>1)</sup>; and
- where different electrical wiring systems are installed on different routes, e.g. for power supply and for signalling information technology equipment within a building.

<sup>1)</sup> Equipotential bonding systems, structural metalwork or pipe systems for non-electrical supplies, e.g. for water, gas, heating or air conditioning, can create such induction loops.



The value of the induced voltage depends on the rate of rise ( $di/dt$ ) of the interference current, and on the size of the loop.

Power cables carrying large currents with a high rate of rise of current ( $di/dt$ ) (e.g. the starting current of lifts or currents controlled by rectifiers) can induce overvoltages in cables of information technology systems, which can influence or damage information technology or similar electrical equipment.

In or near rooms for medical use, electric or magnetic fields of electrical installations can interfere with medical electrical equipment.

Clause 445 deals with the precautions to be taken in the case of undervoltages.

iTeh STANDARD PREVIEW  
(standards.iteh.ai)

SIST IEC 60364-4-44:2006

<https://standards.iteh.ai/catalog/standards/sist/9312ac2a-dad5-4f87-883c-5ff3ee62ad7c/sist-iec-60364-4-44-2006>

## ELECTRICAL INSTALLATIONS OF BUILDINGS –

### Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances

#### 440.1 (442.1.1) Scope

The rules of this part of IEC 60364 are intended to provide for the safety of persons and equipment in a LV system in the event of a fault between the HV system and earth in the HV part of transformer stations which supply low-voltage systems.

#### 440.2 (442.1.4) Normative references

The following normative documents contain provisions which, through reference in this text, constitute provisions of this part of IEC 60364. For dated references, subsequent amendments to, or revisions of, any of these publications do not apply. However, parties to agreements based on this part of IEC 60364 are encouraged to investigate the possibility of applying the most recent editions of the normative documents indicated below. For undated references, the latest edition of the normative document referred to applies. Members of IEC and ISO maintain registers of currently valid International Standards.

IEC 60038:1983, *IEC standard voltages*

IEC 60050(604):1987, *International Electrotechnical Vocabulary – Chapter 604: Generation, transmission and distribution of electricity – Operation*

IEC 60050(826):1982, *International Electrotechnical Vocabulary – Chapter 826: Electrical installations of buildings*

IEC 60364-1:2001, *Electrical installations of buildings – Part 1: Scope, object and fundamental principles*

IEC 60364-4-41:2001, *Electrical installations of buildings – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-42:2001, *Electrical installations of buildings – Part 4-42: Protection for safety – Protection against thermal effects*

IEC 60364-5-53:2001, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60364-5-54, *Electrical installations of buildings – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements and protective conductors and equipotential bonding*<sup>1)</sup>

IEC 60364-5-548:1996, *Electrical installations of buildings – Part 5: Selection and erection of electrical equipment – Section 548: Earthing arrangements and equipotential bonding for information technology installations*

IEC 60479-1:1994, *Effects of current on human beings and livestock – Part 1: General aspects*

<sup>1)</sup> To be published.

IEC 60664-1:1992, *Insulation co-ordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60742:1983, *Isolating transformers and safety isolating transformers – Requirements*

IEC 61000-2-5:1995, *Electromagnetic compatibility (EMC) – Part 2: Environment – Section 5: Classification of electromagnetic environments. Basic EMC publication*

IEC 61024-1:1990, *Protection of structures against lightning – Part 1: General principles*

IEC 61312-1:1995, *Protection against lightning electromagnetic impulse – Part 1: General principles*

#### 441 (Number available)

NOTE This has been introduced to enable the later text to retain the original number.

### 442 Protection of low-voltage installations against temporary overvoltages and faults between high-voltage systems and earth

#### 442.1 General requirements

NOTE The following clauses consider only four situations which generally cause the most severe temporary overvoltages such as defined in IEC 60050(604), definition 604-03-12:

- fault between the high-voltage system(s) and earth. The corresponding subclauses should be read in conjunction with annex A;
- loss of the neutral in a low-voltage TN and TT system (see 442.6);
- accidental earthing of a low-voltage IT system (see 442.7);
- short-circuit in the low-voltage installation (see 442.8).

#### 442.1.2 Fault-voltage

The magnitude and the duration of the fault-voltage or the touch voltage due to an earth-fault in the high-voltage system shall not exceed the values given by curve F and T respectively of figure 44A.

#### 442.1.3 Stress-voltage

The magnitude and the duration of the power-frequency stress voltage of the LV equipment in the consumer's installation due to an earth fault in the high voltage system shall not exceed the values of table 44A.

NOTE 1 The power-frequency stress voltage is the voltage which appears across the insulation.

NOTE 2 A higher stress voltage is permitted for the low-voltage equipment of the sub-station if the insulation level of the equipment is compatible and under the conditions of 442.3.

**Table 44A – Permissible stress voltage**

| Permissible a.c. stress voltage on equipment in low-voltage installations<br>V | Disconnecting time<br>s |
|--|-------------------------|
| $U_0 + 250$ V  | >5                      |
| $U_0 + 1\,200$ V   | ≤5                      |

NOTE 1 In particular cases (e.g. line conductor earthed), where the (highest) nominal voltage of the low-voltage system to earth is not  $U_0$ , this voltage shall be specified.

NOTE 2 The first line of the table relates to systems having long disconnection times, for example inductively earthed high-voltage system. The second line relates to systems having short disconnection times, for example solidly earthed high-voltage systems. Both lines together are relevant design criteria for insulation of low-voltage equipment with regard to temporary overvoltage (see 1.3.7.1 of IEC 60664-1).

NOTE 3 Such temporary a.c. overvoltage is also to be expected in basic, double and reinforced insulation of low-voltage equipment used outside the main equipotential bonding and connected to a TN system (whose neutral conductor is earthed in the transformer substation through the protective earth electrode of the high-voltage system). It is not necessary to expect such overvoltage within the area of main equipotential bonding which is connected to the protective conductor of a TN system at the origin of the installation of the building.

#### 442.2 Earthing systems in transformer sub-stations

At the transformer sub-station, there shall be one earthing system to which shall be connected

- earth electrodes,
- the transformer tank,
- metallic coverings of high-voltage cables,
- metallic coverings of low-voltage cables except where the neutral conductor is earthed via a separate earth electrode,
- earth wires of high-voltage systems,
- the exposed-conductive-parts of high-voltage and low-voltage equipment,
- extraneous-conductive-parts.

#### 442.3 Earthing arrangements in transformer sub-stations

The conditions enumerated under 442.4 and 442.5 are deemed to be complied with if one or both of the conditions stated in 442.3.1 or the condition in 442.3.2 is met. Where none of the conditions of 442.3.1 or 442.3.2 is met, the requirements of 442.4 and 442.5 shall be applied.

**442.3.1** The transformer sub-stations shall be connected to cables with suitable earthed metallic coverings, whether high-voltage cables, low-voltage cables or a combination of both high- and low-voltage cables.

The total length of these cables shall exceed 1 km.

**442.3.2** The earthing resistance of the exposed-conductive-parts of the transformer sub-station does not exceed 1  $\Omega$ .

## 442.4 Earthing arrangements with regard to type of earthing systems in LV installations

### 442.4.1 Symbols

In the following subclauses, the symbols are

$I_m$  that part of the earth fault current in the high-voltage system that flows through the earth electrode of the exposed-conductive-parts of the transformer sub-station.

$R$  is the resistance of the earth electrode of the exposed-conductive-parts of the transformer sub-station.

$U_0$  is the line-to-neutral voltage of the low-voltage system.

$U$  is the line-to-line voltage of the low-voltage system.

$U_f$  is the fault-voltage in the LV system between exposed-conductive-parts and earth.

$U_1$  is the stress-voltage in the LV equipment of the transformer sub-station.

$U_2$  is the stress-voltage in the LV equipment of the consumer's system.

### 442.4.2 TN systems

- a) When the fault-voltage  $R \times I_m$  is disconnected within a time given in figure 44A, the neutral conductor of the LV system may be connected to the earthing electrode of the exposed-conductive-parts of the transformer sub-station (see TN-a in figure 44B).

NOTE If the exposed-conductive-parts of the low-voltage equipment of the consumer's installation within the building are connected to the main equipotential bonding by a protective conductor, the touch voltage will be effectively zero.

- b) If the condition under a) is not fulfilled, the neutral conductor of the LV system shall be earthed via an electrically independent earth electrode (see TN-b in figure 44B). In this case, the conditions of 442.5.1 apply.

### 442.4.3 systems

- a) When the relation between the stress-voltage ( $R \times I_m + U_0$ ) and the disconnecting time given in table 44A is complied with for the LV equipment of the consumer's installation, the neutral conductor of the LV system may be connected to the earthing electrode of the exposed-conductive-parts of the transformer sub-station (see TT-a in figure 44C).

- b) If the condition under a) is not fulfilled, the neutral conductor of the LV system shall be earthed via an electrically independent earth electrode (see TT-b in figure 44C). In this case, the conditions of 442.5.1 apply.

If the exposed-conductive-parts of the low-voltage equipment of the consumer's installation within the building are connected to the main equipotential bonding by a protective conductor, the touch voltage will be effectively zero.

### 442.4.4 IT-systems

- a) When the fault-voltage  $R \times I_m$  is disconnected within a time given in figure 44A, the exposed-conductive-parts of the LV equipment of the consumer's installation may be connected to the earthing electrode of the exposed-conductive-parts of the sub-station (see figures 44D, 44J and 44K).

If this condition is not fulfilled, the exposed-conductive-parts of the LV equipment of the LV installation shall be connected to an earthing system electrically independent from the earthing electrode of the exposed-conductive-parts of the sub-station (see figures 44E to 44H).