

INTERNATIONAL STANDARD

IEC
60076-5

Third edition
2006-02

Power transformers –

**Part 5:
Ability to withstand short circuit**

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60076-5:2006](https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006)

<https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006>

*This **English-language** version is derived from the original **bilingual** publication by leaving out all French-language pages. Missing page numbers correspond to the French-language pages.*



Reference number
IEC 60076-5:2006(E)

Publication numbering

As from 1 January 1997 all IEC publications are issued with a designation in the 60000 series. For example, IEC 34-1 is now referred to as IEC 60034-1.

Consolidated editions

The IEC is now publishing consolidated versions of its publications. For example, edition numbers 1.0, 1.1 and 1.2 refer, respectively, to the base publication, the base publication incorporating amendment 1 and the base publication incorporating amendments 1 and 2.

Further information on IEC publications

The technical content of IEC publications is kept under constant review by the IEC, thus ensuring that the content reflects current technology. Information relating to this publication, including its validity, is available in the IEC Catalogue of publications (see below) in addition to new editions, amendments and corrigenda. Information on the subjects under consideration and work in progress undertaken by the technical committee which has prepared this publication, as well as the list of publications issued, is also available from the following:

- **IEC Web Site** (www.iec.ch)

- **Catalogue of IEC publications**

The on-line catalogue on the IEC web site (www.iec.ch/searchpub) enables you to search by a variety of criteria including text searches, technical committees and date of publication. On-line information is also available on recently issued publications, withdrawn and replaced publications, as well as corrigenda.

- **IEC Just Published**

This summary of recently issued publications (www.iec.ch/online_news/justpub) is also available by email. Please contact the Customer Service Centre (see below) for further information.

- **Customer Service Centre**

If you have any questions regarding this publication or need further assistance, please contact the Customer Service Centre:

Email: custserv@iec.ch
Tel: +41 22 919 02 11
Fax: +41 22 919 03 00

<https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006>

INTERNATIONAL STANDARD

IEC 60076-5

Third edition
2006-02

Power transformers –

Part 5: Ability to withstand short circuit

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60076-5:2006](https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006)

<https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006>

© IEC 2006 Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembé, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

CONTENTS

FOREWORD.....	5
1 Scope.....	9
2 Normative references	9
3 Requirements with regard to ability to withstand short circuit.....	9
3.1 General	9
3.2 Overcurrent conditions	11
4 Demonstration of ability to withstand short circuit.....	17
4.1 Thermal ability to withstand short circuit.....	17
4.2 Ability to withstand the dynamic effects of short circuit	23
 Annex A (informative) Theoretical evaluation of the ability to withstand the dynamic effects of short circuit	 41
Annex B (informative) Definition of similar transformer.....	71
 Figure 1 – Star/delta connected transformer	 29
Figure 2 – Star/star auto-transformer	31
 Table 1 – Recognized minimum values of short-circuit impedance for transformers with two separate windings	 13
Table 2 – Short-circuit apparent power of the system.....	13
Table 3 – Maximum permissible values of the average temperature of each winding after short circuit.....	21
Table 4 – Values for factor $k \times \sqrt{2}$	25
Table A.1 – Comparison of forces and stresses in core-type transformers	61
Table A.2 – Comparison of forces and stresses in shell-type transformers	65
Table A.3 — Values for factor K_3	69
Table A.4 — Values for factor K_4	69

INTERNATIONAL ELECTROTECHNICAL COMMISSION

POWER TRANSFORMERS –**Part 5: Ability to withstand short circuit**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60076-5 has been prepared by IEC technical committee 14: Power transformers.

This third edition cancels and replaces the second edition published in 2000. This third edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) introduction of Annex A (informative) – "Theoretical evaluation of the ability to withstand the dynamic effects of short circuit", in place of previous Annex B (normative) – "Calculation method for the demonstration of the ability to withstand short circuit" (blank);
- b) introduction of Annex B (informative) – "Definition of similar transformer", in place of previous Annex A (informative) – "Guidance for the identification of a similar transformer".

The text of this standard is based on the following documents:

FDIS	Report on voting
14/518/FDIS	14/523/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

IEC 60076 consists of the following parts, under the general title *Power transformers*:

- Part 1: General
- Part 2: Temperature rise
- Part 3: Insulation levels, dielectric tests and external clearances in air
- Part 4: Guide to the lightning impulse and switching impulse testing – Power transformers and reactors
- Part 5: Ability to withstand short circuit
- Part 6: Reactors¹
- Part 7: Loading guide for oil-immersed power transformers
- Part 8: Application guide
- Part 10: Determination of sound levels
- Part 10-1: Determination of sound levels – Application guide
- Part 11: Dry-type transformers
- Part 12: Loading guide for dry-type power transformers¹
- Part 13: Self-protected liquid-filled transformers
- Part 14: Design and application of liquid-immersed power transformers using high-temperature insulation materials
- Part 15: Gas-filled-type power transformers¹

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

¹ Under consideration.

POWER TRANSFORMERS –

Part 5: Ability to withstand short circuit

1 Scope

This part of IEC 60076 identifies the requirements for power transformers to sustain without damage the effects of overcurrents originated by external short circuits. It describes the calculation procedures used to demonstrate the thermal ability of a power transformer to withstand such overcurrents and both the special test and the theoretical evaluation method used to demonstrate the ability to withstand the relevant dynamic effects. The requirements apply to transformers as defined in the scope of IEC 60076-1.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60076-1:1993, *Power transformers – Part 1: General*
Amendment 1 (1999)²

IEC 60076-3:2000, *Power Transformers – Part 3: Insulation levels, dielectric tests and external clearances in air*

IEC 60076-8:1997, *Power transformers – Part 8: Application guide*

IEC 60076-11:2004, *Power transformers – Part 11: Dry-type transformers*

3 Requirements with regard to ability to withstand short circuit

3.1 General

Transformers together with all equipment and accessories shall be designed and constructed to withstand without damage the thermal and dynamic effects of external short circuits under the conditions specified in 3.2.

External short circuits are not restricted to three-phase short circuits; they include line-to-line, double-earth and line-to-earth faults. The currents resulting from these conditions in the windings are designated as overcurrents in this part of IEC 60076.

² There exists a consolidated edition 2.1 (2000) that includes edition 2.0 and its amendment.

3.2 Overcurrent conditions

3.2.1 General considerations

3.2.1.1 Application conditions requiring special consideration

The following situations affecting overcurrent magnitude, duration, or frequency of occurrence require special consideration and shall be clearly identified in transformer specifications:

- regulating transformers with very low impedance that depend on the impedance of directly connected apparatus to limit overcurrents;
- unit generator transformers susceptible to high overcurrents produced by connection of the generator to the system out of synchronism;
- transformers directly connected to rotating machines, such as motors or synchronous condensers, that can act as generators to feed current into the transformer under system fault conditions;
- special transformers and transformers installed in systems characterized by high fault rates (see 3.2.6);
- operating voltage higher than rated maintained at the unfaulted terminal(s) during a fault condition.

3.2.1.2 Current limitations concerning booster transformers

When the combined impedance of the booster transformer and the system results in short-circuit current levels for which the transformer cannot feasibly or economically be designed to withstand, the manufacturer and the purchaser shall mutually agree on the maximum allowed overcurrent. In this case, provision should be made by the purchaser to limit the overcurrent to the maximum value determined by the manufacturer and stated on the rating plate.

3.2.2 Transformers with two separate windings

3.2.2.1 For the purpose of this standard, three categories for the rated power of three-phase transformers or three-phase banks are recognized:

- category I: 25 kVA to 2 500 kVA;
- category II: 2 501 kVA to 100 000 kVA;
- category III: above 100 000 kVA.

3.2.2.2 In the absence of other specifications, the symmetrical short-circuit current (for the r.m.s. value, see 4.1.2) shall be calculated using the measured short-circuit impedance of the transformer plus the system impedance.

For transformers of category I, the contribution of the system impedance shall be neglected in the calculation of the short-circuit current if this impedance is equal to, or less than, 5 % of the short-circuit impedance of the transformer.

The peak value of the short-circuit current shall be calculated in accordance with 4.2.3.

3.2.2.3 Commonly recognized minimum values for the short-circuit impedance of transformers at the rated current (principal tapping) are given in Table 1. If lower values are required, the ability of the transformer to withstand short circuit shall be subject to agreement between the manufacturer and the purchaser.

Table 1 – Recognized minimum values of short-circuit impedance for transformers with two separate windings

Short-circuit impedance at rated current	
Rated power kVA	Minimum short-circuit impedance %
25 to 630	4,0
631 to 1 250	5,0
1 251 to 2 500	6,0
2 501 to 6 300	7,0
6 301 to 25 000	8,0
25 001 to 40 000	10,0
40 001 to 63 000	11,0
63 001 to 100 000	12,5
above 100 000	>12,5

NOTE 1 Values for rated power greater than 100 000 kVA are generally subject to agreement between manufacturer and purchaser.

NOTE 2 In the case of single-phase units connected to form a three-phase bank, the value of rated power applies to three-phase bank rating.

3.2.2.4 The short-circuit apparent power of the system at the transformer location should be specified by the purchaser in his enquiry in order to obtain the value of the symmetrical short-circuit current to be used for the design and tests.

If the short-circuit apparent power of the system is not specified, the values given in Table 2 shall be used.

Table 2 – Short-circuit apparent power of the system

Highest voltage for equipment, U_m kV	Short-circuit apparent power MVA	
	Current European practice	Current North American practice
7,2; 12; 17,5 and 24	500	500
36	1 000	1 500
52 and 72,5	3 000	5 000
100 and 123	6 000	15 000
145 and 170	10 000	15 000
245	20 000	25 000
300	30 000	30 000
362	35 000	35 000
420	40 000	40 000
525	60 000	60 000
765	83 500	83 500

NOTE If not specified, a value between 1 and 3 should be considered for the ratio of zero-sequence to positive-sequence impedance of the system.

3.2.2.5 For transformers with two separate windings, normally only the three-phase short circuit is taken into account, as the consideration of this case is substantially adequate to cover also the other possible types of fault (exception is made in the special case considered in the note to 3.2.5).

NOTE In the case of winding in zigzag connection, the single-line-to-earth fault current may reach values higher than the three-phase short-circuit current. However, these high values are limited, in the two limbs concerned, to a half of the coil and furthermore the currents in the other star-connected winding are lower than for a three-phase short circuit. Electrodynamical hazard to the winding assembly may be higher either at three- or single-phase short circuit depending on the winding design. The manufacturer and the purchaser should agree which kind of short circuit is to be considered.

3.2.3 Transformers with more than two windings and auto-transformers

The overcurrents in the windings, including stabilizing windings and auxiliary windings, shall be determined from the impedances of the transformer and the system(s). Account shall be taken of the different forms of system faults that can arise in service, for example, line-to-earth faults and line-to-line faults associated with the relevant system and transformer earthing conditions (see IEC 60076-8). The characteristics of each system (at least the short-circuit apparent power level and the range of the ratio between zero-sequence impedance and positive-sequence impedance) shall be specified by the purchaser in his enquiry.

Delta-connected stabilizing windings of three-phase transformers shall be capable of withstanding the overcurrents resulting from different forms of system faults that can arise in service associated with relevant system earthing conditions.

In the case of single-phase transformers connected to form a three-phase bank, the stabilizing winding shall be capable of withstanding a short circuit on its terminals, unless the purchaser specifies that special precautions will be taken to avoid the risk of line-to-line short circuits.

NOTE It may not be economical to design auxiliary windings to withstand short circuits on their terminals. In such cases, the overcurrent level should be limited by appropriate means, such as series reactors or, in some instances, fuses. Care should be taken to guard against faults in the zone between the transformer and the protective apparatus.

[IEC 60076-5:2006](https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006)

<https://standards.iteh.ai/catalog/standards/iec/fb56d2b-00b4-4645-9fad-5d046ffc6f47/iec-60076-5-2006>

3.2.4 Booster transformers

The impedance of booster transformers can be very low and, therefore, the overcurrents in the windings are determined mainly by the characteristics of the system at the location of the transformer. These characteristics shall be specified by the purchaser in his enquiry.

If a booster transformer is directly associated to a transformer for the purpose of voltage amplitude and/or phase variation, it shall be capable of withstanding the overcurrents resulting from the combined impedance of the two machines.

3.2.5 Transformers directly associated with other apparatus

Where a transformer is directly associated with other apparatus, the impedance of which would limit the short-circuit current, the sum of the impedance of the transformer, the system and the directly associated apparatus may, by agreement between the manufacturer and the purchaser, be taken into account.

This applies, for example, to unit generator transformers if the connection between generator and transformer is constructed in such a way that the possibility of line-to-line or double-earth faults in this region is negligible.

NOTE If the connection between generator and transformer is constructed in this way, the most severe short-circuit conditions may occur, in the case of a star/delta-connected unit generator transformer with earthed neutral, when a line-to-earth fault occurs on the system connected to the star-connected winding, or in the case of out-of-phase synchronization.

3.2.6 Special transformers and transformers to be installed in systems characterized by high fault rates

The ability of the transformer to withstand frequent overcurrents, arising from the particular application (for example, arc furnace transformers and stationary transformers for traction systems), or the condition of operation (for example, high number of faults occurring in the connected system(s)), shall be subjected to special agreement between the manufacturer and the purchaser. Notice of any abnormal operation conditions expected in the system(s) shall be given by the purchaser to the manufacturer in advance.

3.2.7 Tap-changing equipment

Where fitted, tap-changing equipment shall be capable of carrying the same overcurrents due to short circuits as the windings. However, the on-load tap-changer is not required to be capable of switching the short-circuit current.

3.2.8 Neutral terminal

The neutral terminal of windings with star or zigzag connection shall be designed for the highest overcurrent that can flow through this terminal.

4 Demonstration of ability to withstand short circuit

The requirements of this clause apply to both oil-immersed and dry-type transformers as specified in IEC 60076-1 and IEC 60076-11, respectively.

4.1 Thermal ability to withstand short circuit

4.1.1 General

According to this standard, the thermal ability to withstand short circuit shall be demonstrated by calculation. This calculation shall be carried out in accordance with the requirements of 4.1.2 to 4.1.5.

4.1.2 Value of symmetrical short-circuit current I

For three-phase transformers with two separate windings, the r.m.s. value of the symmetrical short-circuit current I shall be calculated as follows:

$$I = \frac{U}{\sqrt{3} \times (Z_t + Z_s)} \quad (\text{kA}) \quad (1)$$

where

Z_s is the short-circuit impedance of the system.

$$Z_s = \frac{U_s^2}{S}, \text{ in ohms } (\Omega) \text{ per phase (equivalent star connection)} \quad (2)$$

where

U_s is the rated voltage of the system, in kilovolts (kV);

S is the short-circuit apparent power of the system, in megavoltamperes (MVA).

U and Z_t are defined as follows:

a) for the principal tapping:

U is the rated voltage U_r of the winding under consideration, in kilovolts (kV);

Z_t is the short-circuit impedance of the transformer referred to the winding under consideration; it is calculated as follows:

$$Z_t = \frac{z_t \times U_r^2}{100 \times S_r}, \text{ in ohms } (\Omega) \text{ per phase (equivalent star connection)}^3 \quad (3)$$

where

z_t is the measured short-circuit impedance at rated current and frequency at the principal tap and at reference temperature, as a percentage;

S_r is the rated power of the transformer, in megavoltamperes (MVA);

b) for tapplings other than the principal tapping:

U is, unless otherwise specified, the tapping voltage⁴ of the winding under consideration, in kilovolts (kV);

Z_t is the short-circuit impedance of the transformer referred to the winding and the tapping under consideration, in ohms (Ω) per phase.

For transformers having more than two windings, auto-transformers, booster transformers and transformers directly associated with other apparatus, the overcurrents are calculated in accordance with 3.2.3, 3.2.4 or 3.2.5, as appropriate.

For all transformers, excluding the case given in 3.2.2.2, the effect of the short-circuit impedance of the system(s) shall be taken into consideration.

NOTE At the zigzag connected windings, the short-circuit current for a single-line-to-earth fault may reach considerably higher values than at the three-phase fault. This increase in current should be taken into consideration when calculating the temperature rise of the zigzag winding.

4.1.3 Duration of the symmetrical short-circuit current

The duration of the current I to be used for the calculation of the thermal ability to withstand short circuit shall be 2 s unless a different duration is specified.

NOTE For auto-transformers and for transformers with short-circuit current exceeding 25 times the rated current, a short-circuit current duration below 2 s may be adopted by agreement between the manufacturer and the purchaser.

4.1.4 Maximum permissible value of the average temperature of each winding

The average temperature θ_1 of each winding after loading with a symmetrical short-circuit current I of a value and duration as specified in 4.1.2 and 4.1.3, respectively, shall not exceed the maximum value stated in Table 3 at any tapping position.

³ Here symbols Z_t and z_t are used instead of Z and z , respectively, adopted for the same quantities in IEC 60076-1, for the sake of clarity in connection with the content of 4.2.3.

⁴ For the definition of tapping voltage, see 5.2 of IEC 60076-1.