

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Information technology equipment – Safety –
Part 1: General requirements**

**Matériels de traitement de l'information – Sécurité –
Partie 1: Exigences générales**

IEC 60950-1:2005

<https://standards.iteh.ai/en/standards/iec/60950-1-2005>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2013 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.
If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.
Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

Useful links:

IEC publications search - www.iec.ch/searchpub

The advanced search enables you to find IEC publications by a variety of criteria (reference number, text, technical committee,...).

It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available on-line and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary (IEV) on-line.

Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Liens utiles:

Recherche de publications CEI - www.iec.ch/searchpub

La recherche avancée vous permet de trouver des publications CEI en utilisant différents critères (numéro de référence, texte, comité d'études,...).

Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

Just Published CEI - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications de la CEI. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (VEI) en ligne.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Information technology equipment – Safety –
Part 1: General requirements**

**Matériels de traitement de l'information – Sécurité –
Partie 1: Exigences générales**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 35.020; 35.260

ISBN 978-2-8322-0820-5

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	10
0 Principles of safety.....	10
0.1 General principles of safety.....	10
0.2 Hazards.....	11
0.3 Materials and components.....	14
1 General.....	15
1.1 Scope.....	15
1.2 Definitions.....	17
1.3 General requirements.....	32
1.4 General conditions for tests.....	33
1.5 Components.....	38
1.6 Power interface.....	46
1.7 Markings and instructions.....	46
2 Protection from hazards.....	55
2.1 Protection from electric shock and energy hazards.....	55
2.2 SELV circuits.....	64
2.3 TNV circuits.....	67
2.4 Limited current circuits.....	72
2.5 Limited power sources.....	73
2.6 Provisions for earthing and bonding.....	74
2.7 Overcurrent and earth fault protection in primary circuits.....	82
2.8 Safety interlocks.....	87
2.9 Electrical insulation.....	88
2.10 Clearances, creepage distances and distances through insulation.....	94
3 Wiring, connections and supply.....	123
3.1 General.....	123
3.2 Connection to a mains supply.....	126
3.3 Wiring terminals for connection of external conductors.....	133
3.4 Disconnection from the mains supply.....	136
3.5 Interconnection of equipment.....	139
4 Physical requirements.....	140
4.1 Stability.....	140
4.2 Mechanical strength.....	141
4.3 Design and construction.....	145
4.4 Protection against hazardous moving parts.....	154
4.5 Thermal requirements.....	156
4.6 Openings in enclosures.....	160
4.7 Resistance to fire.....	166
5 Electrical requirements and simulated abnormal conditions.....	173
5.1 Touch current and protective conductor current.....	173
5.2 Electric strength.....	181
5.3 Abnormal operating and fault conditions.....	185

6	Connection to telecommunication networks	189
6.1	Protection of telecommunication network service persons, and users of other equipment connected to the network, from hazards in the equipment.....	189
6.2	Protection of equipment users from overvoltages on telecommunication networks	191
6.3	Protection of the telecommunication wiring system from overheating.....	194
7	Connection to cable distribution systems	194
7.1	General	194
7.2	Protection of cable distribution system service persons, and users of other equipment connected to the system, from hazardous voltages in the equipment.....	195
7.3	Protection of equipment users from overvoltages on the cable distribution system	195
7.4	Insulation between primary circuits and cable distribution systems.....	195
	Annex A (normative) Tests for resistance to heat and fire	198
	Annex B (normative) Motor tests under abnormal conditions	201
	Annex C (normative) Transformers	207
	Annex D (normative) Measuring instruments for touch current tests	210
	Annex E (normative) Temperature rise of a winding.....	212
	Annex F (normative) Measurement of clearances and creepage distances.....	213
	Annex G (normative) Alternative method for determining minimum clearances.....	221
	Annex H (normative) Ionizing radiation.....	229
	Annex J (normative) Table of electrochemical potentials (see 2.6.5.6).....	230
	Annex K (normative) Thermal controls	232
	Annex L (normative) Normal load conditions for some types of electrical business equipment.....	234
	Annex M (normative) Criteria for telephone ringing signals	236
	Annex N (normative) Impulse test generators	241
	Annex P (normative) Normative references	243
	Annex Q (normative) Voltage dependent resistors (VDRs).....	248
	Annex R (informative) Examples of requirements for quality control programmes.....	250
	Annex S (informative) Procedure for impulse testing	253
	Annex T (informative) Guidance on protection against ingress of water	255
	Annex U (normative) Insulated winding wires for use without interleaved insulation	257
	Annex V (normative) AC power distribution systems	263
	Annex W (informative) Summation of touch currents	270
	Annex X (informative) Maximum heating effect in transformer tests	273
	Annex Y (normative) Ultraviolet light conditioning test.....	275
	Annex Z (informative) Overvoltage categories (see 2.10.3.2 and Clause G.2)	276
	Annex AA (normative) Mandrel test (see 2.10.5.8).....	277
	Annex BB (informative) Changes in the second edition	280
	Annex CC (normative) Evaluation of integrated circuit (IC) current limiters	283
	Annex DD (normative) Requirements for the mounting means of rack-mounted equipment.....	286
	Annex EE (normative) Household and home/office document/media shredders.....	288

Bibliography.....	292
Index	294
Figure 2A – Test finger	58
Figure 2B – Test pin	59
Figure 2C – Test probe	59
Figure 2D - Accessibility of internal conductive parts	60
Figure 2E – Voltages in SELV circuits under single fault conditions	66
Figure 2E.1 – Voltages in SELV circuits under single fault conditions for a single pulse above V_1	65
Figure 2E.2 – Voltages in SELV circuits under single fault conditions for multiple pulses above V_1	66
Figure 2F – Maximum voltages permitted after a single fault.....	68
Figure 2G – Test generator.....	72
Figure 2H – Examples of application of insulation	93
Figure 2J – Thermal ageing time.....	120
Figure 2K – Abrasion resistance test for coating layers.....	121
Figure 4A – Impact test using a steel ball.....	143
Figure 4B – Examples of cross-sections of designs of openings preventing vertical access	160
Figure 4C – Examples of louvre design.....	161
Figure 4D – Enclosure openings	162
Figure 4E – Typical bottom of a fire enclosure for partially enclosed component or assembly	163
Figure 4F – Baffle plate construction.....	163
Figure 5A – Test circuit for touch current of single-phase equipment on a star TN or TT power supply system	175
Figure 5B – Test circuit for touch current of three-phase equipment on a star TN or TT power supply system	175
Figure 6A – Test for separation between a telecommunication network and earth.....	191
Figure 6B – Application points of test voltage	192
Figure B.1 – Determination of arithmetic average temperature.....	202
Figure C.1 – Determination of arithmetic average temperature.....	208
Figure D.1 – Measuring instrument	210
Figure D.2 – Alternative measuring instrument.....	211
Figure F.1 – Narrow groove	213
Figure F.2 – Wide groove.....	213
Figure F.3 – V-shaped groove.....	214
Figure F.4 – Rib.....	214
Figure F.5 – Uncemented joint with narrow groove.....	214
Figure F.6 – Uncemented joint with wide groove	215
Figure F.7 – Uncemented joint with narrow and wide grooves	215
Figure F.8 – Narrow recess.....	216
Figure F.9 – Wide recess	217
Figure F.10 – Coating around terminals	217

Figure F.11 – Coating over printed wiring	218
Figure F.12 – Measurements through openings in enclosures	218
Figure F.13 – Intervening, unconnected conductive part	219
Figure F.14 – Solid insulating material	219
Figure F.15 – Thin sheet insulating material.....	219
Figure F.16 – Cemented joints in multi-layer printed board	220
Figure F.17 – Component filled with insulating compound.....	220
Figure F.18 – Partitioned bobbin.....	220
Figure M.1 – Definition of ringing period and cadence cycle.....	237
Figure M.2 – ITS1 limit curve for cadenced ringing signal	238
Figure M.3 – Peak and peak-to-peak currents.....	239
Figure M.4 – Ringing voltage trip criteria.....	240
Figure N.1 – ITU-T impulse test generator circuit.....	241
Figure N.2 – IEC 60065 impulse test generator circuit	242
Figure S.1 – Waveform on insulation without surge suppressors and no breakdown	253
Figure S.2 – Waveforms on insulation during breakdown without surge suppressors.....	254
Figure S.3 – Waveforms on insulation with surge suppressors in operation.....	254
Figure S.4 – Waveform on short-circuited surge suppressor and insulation.....	254
Figure V.1 – Examples of TN-S power distribution systems.....	265
Figure V.2 – Example of TN-C-S power distribution system	266
Figure V.3 – Example of TN-C power distribution system.....	266
Figure V.4 – Example of single-phase, three-wire TN-C power distribution system.....	267
Figure V.5 – Example of three line and neutral TT power distribution system	267
Figure V.6 – Example of three line TT power distribution system	268
Figure V.7 – Example of three line (and neutral) IT power distribution system.....	268
Figure V.8 – Example of three line IT power distribution system	269
Figure W.1 – Touch current from a floating circuit.....	270
Figure W.2 – Touch current from an earthed circuit.....	271
Figure W.3 – Summation of touch currents in a PABX.....	271
Figure AA.1 – Mandrel.....	277
Figure AA.2 – Initial position of mandrel.....	278
Figure AA.3 – Final position of mandrel	278
Figure AA.4 – Position of metal foil on insulating material.....	278
Figure EE.1 – Wedge probe (overall view)	290
Figure EE.2 – Wedge probe (tip detail)	291
Table 1A – Voltage ranges of SELV and TNV circuits	25
Table 1B – Equivalence of flammability classes	28
Table 1C – Capacitor ratings according to IEC 60384-14	39
Table 1D – Informative examples of application of capacitors	41
Table 2A – Distance through insulation of internal wiring	61
Table 2B – Limits for power sources without an overcurrent protective device	74
Table 2C – Limits for power sources with an overcurrent protective device	74

Table 2D – Minimum size of protective bonding conductors	77
Table 2E – Test duration, a.c. mains supplies	79
Table 2F – Informative examples of protective devices in single-phase equipment or subassemblies	84
Table 2G – Informative examples of protective devices in three-phase equipment	84
Table 2H – Examples of application of insulation	90
Table 2J – AC mains transient voltages	98
Table 2K – Minimum clearances for insulation in primary circuits and between primary and secondary circuits	100
Table 2L – Additional clearances in primary circuits	100
Table 2M – Minimum clearances in secondary circuits	102
Table 2N – Minimum creepage distances	107
Table 2P – Tests for insulation in non-separable layers	112
Table 2Q – Minimum separation distances for coated printed boards	116
Table 2R – Insulation in printed boards	118
Table 3A – Sizes of cables and conduits for equipment having a rated current not exceeding 16 A	128
Table 3B – Sizes of conductors	130
Table 3C – Physical tests on power supply cords	131
Table 3D – Range of conductor sizes to be accepted by terminals	134
Table 3E – Sizes of terminals for mains supply conductors and protective earthing conductors	134
Table 4A – Minimum property retention limits after UV exposure	151
Table 4B – Temperature limits, materials and components	157
Table 4C – Touch temperature limits	159
Table 4D – Size and spacing of openings in metal bottoms of fire enclosures	163
Table 4E – Summary of material flammability requirements	172
Table 5A – Maximum current	177
Table 5B – Test voltages for electric strength tests based on peak working voltages Part 1 ..	183
Table 5B – Test voltages for electric strength tests based on peak working voltages Part 2 ..	184
Table 5C – Test voltages for electric strength tests based on required withstand voltages ..	185
Table 5D – Temperature limits for overload conditions	188
Table B.1 – Temperature limits for motor windings (except for running overload test)	202
Table B.2 – Permitted temperature limits for running overload tests	203
Table C.1 – Temperature limits for transformer windings	208
Table F.1 – Value of X	213
Table G.1 – AC mains transient voltages	222
Table G.2 – Minimum clearances up to 2 000 m above sea level	227
Table J.1 – Electrochemical potentials (V)	230
Table N.1 – Component values for Figures N.1 and N.2	242
Table R.1 – Rules for sampling and inspection – coated printed boards	251
Table R.2 – Rules for sampling and inspection – reduced clearances	252
Table T.1 – Extract from IEC 60529	256
Table U.1 – Mandrel diameter	261

Table U.2 – Oven temperature	261
Table X.1 – Test steps	273
Table Z.1 – Overvoltage categories	276

Witholdrawn

iTech Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60950-1:2005](https://standards.iteh.ai/standards/iec/60950-1-2005)

<https://standards.iteh.ai/standards/iec/60950-1-2005>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**INFORMATION TECHNOLOGY EQUIPMENT –
SAFETY –****Part 1: General requirements**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendments has been prepared for user convenience.

IEC 60950-1 edition 2.2 contains the second edition (2005) [documents 108/135A/FDIS and 108/147/RVD], its corrigendum 1 (2006), its amendment 1 (2009) [documents 108/350/FDIS and 108/357/RVD] and its corrigendum 1 (2012), and its amendment 2 (2013) [documents 108/507/FDIS and 108/510/RVD].

A vertical line in the margin shows where the base publication has been modified by amendments 1 and 2. Additions and deletions are displayed in red, with deletions being struck through.

International Standard IEC 60950-1 has been prepared by IEC technical committee 108: Safety of electronic equipment within the field of audio/video, information technology and communication technology.

IEC 60950-1 includes the basic requirements for the safety of information technology equipment.

Additional parts of IEC 60950-1 will cover specific safety requirements for information technology equipment having limited applications or having special features as follows:

- Part 21: Remote feeding (published);
- Part 22: Equipment installed outdoors (planned);
- Part 23: Large data storage equipment (planned);

Except for notes, all text within a normative figure, or in a box under a normative table, is also normative. Text with a superscript reference is linked to a particular item in the table. Other text in a box under a table applies to the whole table.

Informative annexes and text beginning with the word "NOTE" are not normative. They are provided only to give additional information.

"Country" notes are also informative but call attention to requirements that are normative in those countries.

In this standard, the following print types are used:

- Requirements proper and normative annexes: roman type.
- Compliance statements and test specifications: italic type.
- Notes in the text and in tables: smaller roman type.
- Terms that are defined in 1.2: SMALL CAPITALS.

The committee has decided that the contents of the base publication and its amendments will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The “colour inside” logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this publication using a colour printer.

INTRODUCTION

0 Principles of safety

The following principles have been adopted by technical committee 108 in the development of this standard.

These principles do not cover performance or functional characteristics of equipment.

Words printed in SMALL CAPITALS are terms that are defined in 1.2 of this standard.

0.1 General principles of safety

It is essential that designers understand the underlying principles of safety requirements in order that they can engineer safe equipment.

These principles are not an alternative to the detailed requirements of this standard, but are intended to provide designers with an appreciation of the basis of these requirements. Where the equipment involves technologies, **components** and materials or methods of construction not specifically covered, the design of the equipment should provide a level of safety not less than those described in these principles of safety.

NOTE The need for additional detailed requirements to cope with a new situation should be brought promptly to the attention of the appropriate committee.

Designers shall take into account not only normal operating conditions of the equipment but also likely fault conditions, consequential faults, foreseeable misuse and external influences such as temperature, altitude, pollution, moisture, overvoltages on the MAINS SUPPLY and overvoltages on a TELECOMMUNICATION NETWORK or a CABLE DISTRIBUTION SYSTEM. Dimensioning of insulation spacings should take account of possible reductions by manufacturing tolerances, or where deformation could occur due to handling, shock and vibration likely to be encountered during manufacture, transport and normal use.

The following priorities should be observed in determining what design measures to adopt:

- where possible, specify design criteria that will eliminate, reduce or guard against hazards;
- where the above is not practicable because the functioning of the equipment would be impaired, specify the use of protective means independent of the equipment, such as personal protective equipment (which is not specified in this standard);
- where neither of the above measures is practicable, or in addition to those measures, specify the provision of markings and instructions regarding the residual risks.

There are two types of persons whose safety needs to be considered, **USERS** (or **OPERATORS**) and **SERVICE PERSONS**.

USER is the term applied to all persons other than **SERVICE PERSONS**. Requirements for protection should assume that **USERS** are not trained to identify hazards, but will not intentionally create a hazardous situation. Consequently, the requirements will provide protection for cleaners and casual visitors as well as the assigned **USERS**. In general, **USERS** should not have access to hazardous parts, and to this end, such parts should only be in **SERVICE ACCESS AREAS** or in equipment located in **RESTRICTED ACCESS LOCATIONS**.

When **USERS** are admitted to **RESTRICTED ACCESS LOCATIONS** they shall be suitably instructed.

SERVICE PERSONS are expected to use their training and skill to avoid possible injury to themselves and others due to obvious hazards that exist in **SERVICE ACCESS AREAS** of the equipment or on equipment located in **RESTRICTED ACCESS LOCATIONS**. However, **SERVICE**

PERSONS should be protected against unexpected hazards. This can be done by, for example, locating parts that need to be accessible for servicing away from electrical and mechanical hazards, providing shields to avoid accidental contact with hazardous parts, and providing labels or instructions to warn personnel about any residual risk.

Information about potential hazards can be marked on the equipment or provided with the equipment, depending on the likelihood and severity of injury, or made available for SERVICE PERSONS. In general, USERS shall not be exposed to hazards likely to cause injury, and information provided for USERS should primarily aim at avoiding misuse and situations likely to create hazards, such as connection to the wrong power source and replacement of fuses by incorrect types.

MOVABLE EQUIPMENT is considered to present a slightly increased risk of shock, due to possible extra strain on the supply cord leading to rupture of the earthing conductor. With HAND-HELD EQUIPMENT, this risk is increased; wear on the cord is more likely, and further hazards could arise if the units were dropped. TRANSPORTABLE EQUIPMENT introduces a further factor because it can be used and carried in any orientation; if a small metallic object enters an opening in the ENCLOSURE it can move around inside the equipment, possibly creating a hazard.

0.2 Hazards

Application of a safety standard is intended to reduce the risk of injury or damage due to the following:

- electric shock;
- energy related hazards;
- fire;
- heat related hazards;
- mechanical hazards;
- radiation;
- chemical hazards.

0.2.1 Electric shock

Electric shock is due to current passing through the human body. The resulting physiological effects depend on the value and duration of the current and the path it takes through the body. The value of the current depends on the applied voltage, the impedance of the source and the impedance of the body. The body impedance depends in turn on the area of contact, moisture in the area of contact and the applied voltage and frequency. Currents of approximately half a milliampere can cause a reaction in persons in good health and may cause injury indirectly due to involuntary reaction. Higher currents can have more direct effects, such as burn or muscle tetanization leading to inability to let go or to ventricular fibrillation.

Steady state voltages up to 42,4 V peak, or 60 V d.c., are not generally regarded as hazardous under dry conditions for an area of contact equivalent to a human hand. Bare parts that have to be touched or handled should be at earth potential or properly insulated.

Some equipment will be connected to telephone and other external networks. Some TELECOMMUNICATION NETWORKS operate with signals such as voice and ringing superimposed on a steady d.c. supply voltage; the total may exceed the values given above for steady-state voltages. It is common practice for the SERVICE PERSONS of telephone companies to handle parts of such circuits bare-handed. This has not caused serious injury, because of the use of cadenced ringing and because there are limited areas of contact with bare conductors normally handled by SERVICE PERSONS. However, the area of contact of a part accessible to

the USER, and the likelihood of the part being touched, should be further limited (for example, by the shape and location of the part).

It is normal to provide two levels of protection for USERS to prevent electric shock. Therefore, the operation of equipment under normal conditions and after a single fault, including any consequential faults, should not create a shock hazard. However, provision of additional protective measures, such as protective earthing or SUPPLEMENTARY INSULATION, is not considered a substitute for, or a relief from, properly designed BASIC INSULATION.

Harm may result from:

Contact with bare parts normally at HAZARDOUS VOLTAGES.

Breakdown of insulation between parts normally at HAZARDOUS VOLTAGES and accessible conductive parts.

Contact with circuits connected to TELECOMMUNICATION NETWORKS that exceed 42,4 V peak or 60 V d.c.

Breakdown of USER-accessible insulation.

TOUCH CURRENT (leakage current) flowing from parts at HAZARDOUS VOLTAGES to accessible parts, or failure of a protective earthing connection. TOUCH CURRENT may include current due to EMC filter components connected between PRIMARY CIRCUITS and accessible parts.

Examples of measures to reduce risks:

Prevent USER access to parts at HAZARDOUS VOLTAGES by fixed or locked covers, SAFETY INTERLOCKS, etc. Discharge accessible capacitors that are at HAZARDOUS VOLTAGES.

Provide BASIC INSULATION and connect the accessible conductive parts and circuits to earth so that exposure to the voltage which can develop is limited because overcurrent protection will disconnect the parts having low impedance faults within a specified time; or provide a metal screen connected to protective earth between the parts, or provide DOUBLE INSULATION or REINFORCED INSULATION between the parts, so that breakdown to the accessible part is not likely to occur.

Limit the accessibility and area of contact of such circuits, and separate them from unearthed parts to which access is not limited.

Insulation that is accessible to the USER should have adequate mechanical and electrical strength to reduce the likelihood of contact with HAZARDOUS VOLTAGES.

Limit TOUCH CURRENT to a specified value, or provide a high integrity protective earthing connection.

0.2.2 Energy related hazards

Injury or fire may result from a short-circuit between adjacent poles of high current supplies or high capacitance circuits, causing:

- burns;
- arcing;
- ejection of molten metal.

Even circuits whose voltages are safe to touch may be hazardous in this respect.

Examples of measures to reduce risks include:

- separation;