

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Optical amplifiers –
Part 6-1: Interfaces – Command set
STANDARD PREVIEW
(standards.iteh.ai)

Amplificateurs optiques –
Partie 6-1: Interfaces – Répertoire des commandes
IEC 61291-6-1:2008
<https://standards.iteh.ai/catalog/standards/sis/cd51978-4c6a-4032-9d12-a2be2bb3813e/iec-61291-6-1-2008>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

[IEC 61291-6-1:2008](http://www.iec.ch/online_news/justpub)

- Electropedia: www.electropedia.org www.electropedia.org/standards/sist/cd531978-4c6a-4032-9d12-

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00



IEC 61291-6-1

Edition 1.0 2008-08

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Optical amplifiers – **STANDARD PREVIEW**
Part 6-1: Interfaces – Command set
(standards.iteh.ai)

Amplificateurs optiques –
Partie 6-1: Interfaces – Répertoire des commandes
<https://standards.iteh.ai/catalog/standards/sist/4c6a-4032-9d12-a2be2bb3813e/iec-61291-6-1-2008>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

T

ICS 33.180.30

ISBN 2-8318-9957-5

CONTENTS

FOREWORD..... 3

INTRODUCTION..... 5

1 Scope..... 6

2 Normative references 6

3 Abbreviations 6

4 General rules and concepts 7

 4.1 Command set encoding language..... 7

 4.2 Module initiated commands 7

 4.3 Command set syntax structure 7

 4.4 Command arguments 7

 4.5 Command set terminators..... 7

 4.6 Module response prompt 7

 4.7 Echo mode 8

5 Supported commands..... 8

6 Universal command set 9

 6.1 Command set I..... 10

 6.2 Command set II..... 13

7 Optional command set (design dependant)..... 16

 7.1 Command set I..... 17

 7.2 Command set II..... 20

Annex A (normative) RST functionality..... 22

Annex B (informative) Alarm functionality..... 23

Table 1 – Software commands..... 8

Table 2 – Universal software command set I..... 10

Table 3 – Universal software command set II..... 13

Table 4 – Optional software command set I 17

Table 5 – Optional software command set II 20

Table A.1 – Setpoint memory locations 22

Table B.1 – Alarm status mode 23

Table B.2 – Alarm example 24

Table B.3 – Alarm action summary table 25

INTERNATIONAL ELECTROTECHNICAL COMMISSION

OPTICAL AMPLIFIERS –

Part 6-1: Interfaces –
Command set

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61291-6-1 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics.

The text of this standard is based on the following documents:

CDV	Report on voting
86C/803/CDV	86C/845/RVC

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the IEC 61291 series, published under the general title *Optical amplifiers* can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[IEC 61291-6-1:2008](#)

<https://standards.iteh.ai/catalog/standards/sist/cd531978-4c6a-4032-9d12-a2be2bb3813e/iec-61291-6-1-2008>

INTRODUCTION

Optical amplifiers are being developed and commercially deployed with an increasing degree of sophistication and functionality. Often, information is sent to the optical amplifier, or requested from it, in order to determine signal conditions, operating parameters, and to adjust the operational aspects of the optical amplifier. Currently, no International Standard exists in this area, yet the need for a common set of command statements to/from optical amplifiers has emerged.

This part of IEC 61291 proposes a set of command strings useful in controlling optical amplifiers. It is based on an existing set of commands widely used across the industry today. The standardization of this command set will result in broader market use of advanced designs of optical amplifiers, typically controlled by microprocessors. These advanced amplifier designs are needed for next generation optical networks, requiring adaptive provisioning of optical paths and intelligent configuration/reconfiguration for provision of telecommunications services in a dynamic environment.

This standard addresses the structure and content of the command set to control optical amplifiers. It does not cover the physical or hardware interface which is assumed to exist for communication of this command set to the optical amplifier. The specification of a physical interface will be the subject of a separate standard yet to be developed.

With the rapidly evolving technology, it is envisioned that this standard will be amended with additional commands and functionality as technology evolves, and will be updated on a periodic basis, incorporating all previous amendments and additions.

(standards.iteh.ai)

[IEC 61291-6-1:2008](https://standards.iteh.ai/catalog/standards/sist/cd531978-4c6a-4032-9d12-a2be2bb3813e/iec-61291-6-1-2008)

<https://standards.iteh.ai/catalog/standards/sist/cd531978-4c6a-4032-9d12-a2be2bb3813e/iec-61291-6-1-2008>

OPTICAL AMPLIFIERS –

Part 6-1: Interfaces – Command set

1 Scope

This part of IEC 61291 describes the optical amplifier command set (OACS) for use in communicating with and controlling intelligent optical amplifiers. These amplifiers can receive and possibly respond to such commands by using resident firmware or may be optical amplifiers controlled by a microprocessor.

This standard addresses the structure and content of the command set to control optical amplifiers. It does not cover the physical or hardware interface, which is assumed to exist for communication of this command set to the optical amplifier. The specification of a physical interface will be the subject of a separate Part to be developed in the IEC 61291-6 series.

The command set described in this standard is intended to enable a user or host to retrieve the amplifier module's status and/or adjust its settings.

This standard lists all of the commands currently defined and supported within the OACS framework. The commands described cover a wide range of applications, and not all commands will be applicable to every amplifier. To determine the supported commands on an OACS compliant amplifier, please refer to the product specification supplied by the manufacturer.

All OACS compliant amplifiers support the full set of “universal” OACS commands. Other commands, usually specific to a design or implementation, may support some or all of the “optional” commands.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 8859-1: *Information technology – 8-bit single-byte coded graphic character sets – Part 1: Latin alphabet No. 1*

3 Abbreviations

The following abbreviations are used in this standard:

ASCII	American standard character for information interchange
DC	dispersion compensator
EDFA	erbium doped fibre amplifier
OACS	optical amplifier command set
TEC	thermo-electric cooler
VOA	variable optical attenuator

4 General rules and concepts

4.1 Command set encoding language

All data sent to/from the module are encoded in 8-bit ASCII characters. Refer to ISO/IEC 8859-1.

4.2 Module initiated commands

The optical amplifier never sends an unsolicited response. Asynchronous notifications may be made, for example, by raising the appropriate “alarm” output hardware signal. However, the module may be configurable to send a prompt on power-on reset. This initial prompt may be preceded by one or more start-up messages.

4.3 Command set syntax structure

Commands consist of a command string, zero or more arguments, and end with a terminator. Command strings are case-insensitive. All commands have the following format:

```
COMMAND <argument_1> <argument_2> <argument_3> .....<CR><LF>
```

4.4 Command arguments

Arguments may be strings of letters, integers or floating-point numbers. Floating-point numbers shall be entered in fixed notation (e.g. 0.023 not 2.3e-2).

Command strings and arguments shall be separated by one or more separator characters. Separators shall be 8-bit ASCII space characters.

4.5 Command set terminators

The command terminator is <CR><LF>. In the case of <CR><LF>, the command is executed on receipt of the <CR> character and the <LF> character is ignored.

A successful command execution may be responded to with an “OK<CR><LF>”. Unacknowledged commands may be responded to with a “??<CR><LF>”.

Command response consists of an optional response or error message. Error messages always start with the “?” character and normal responses do not. If a command completes normally and has no useful information to report, its response will be empty (no characters). Contents of error messages are not specified within this standard. The following are examples of some of the types of errors that are possible (this list is not all-inclusive):

```
?Unknown command 'REBOOT'  
?Argument 'x' invalid  
?Argument '5' out of range [1,4]  
?Not implemented  
??
```

4.6 Module response prompt

All responses are followed by a prompt, which indicates that the module is ready to process another command. The default prompt is <CR><LF> “>”.

4.7 Echo mode

By default, the module doesn't echo characters sent to it. However, if echo mode is enabled, printable 8-bit ASCII characters are echoed. Also, echo mode enables command-line editing using the backspace key (the backspaces are echoed if there are characters to delete).

5 Supported commands

Table 1 summarizes the software commands that are supported through the OACS interface. The description of software commands in Table 1 is normative while the commands are informative. There are two sets of commands that are currently being used in the industry. It is recommended that the user choose the commands from only one of the sets, i.e. either from set I or II, and not mix the commands from the two sets. For detailed command syntax and the corresponding response, see Clause 6 for the universal set of commands used by all OACS compliant optical amplifiers or Clause 7 for additional optional command sets.

Table 1 – Software commands (page 1/2)

Description	Normative				Informative	
	Type		Applicability		Command Set I	Command Set II
	Read	Write	Universal	Optional		
Set alarm setpoints	x	x	x		ALRM	ALT, ALH
Display activated alarms	x		x		AST	ALO
Set alarm status mode		x	x		ASTM	ALS
Set baud rate	x	x	x		BAUD	BPS
Reboot firmware			x		BOOT	RBT
Set dispersion compensator parameters	x	x		x	DCM	DCS
Set command line echo	x	x	x		ECHO	ECH
Display signal gain	x		x		GAIN	APG
Set loss of signal mode	x	x	x		LOS	ASD
Set control mode	x	x	x		MODE	APS
Display module status	x		x		MST	AST
Display module case temperature	x		x		MT	CST
Display optimal flat gain setting	x			x	OFG	N/A
Display photodiode power	x		x		PD	PDP
Display input power	x		x		PIN	PDP
Display total output power	x		x		POUT	PDP
Display signal output power	x		x		PSIG	APP
Set pump power	x	x		x	PSP	LDP
Display pump status, set pump current	x	x	x		PUMP	LDC,LDT,LTS
Display pump power	x			x	PWR	LDP
Download protocol		x	x		RECV	UPD
Display reflected power at output	x			x	RFL	REF
Restore default settings		x	x		RST	RFD
Display per-stage signal gain	x			x	SGAIN	APG

Table 1 (continued, page 2/2)

Description	Normative				Informative	
	Type		Applicability		Command Set I	Command Set II
	Read	Write	Universal	Optional		
Set per-stage gain limit	x	x		x	SGLIM	GLM
Set per-stage control mode	x	x		x	SMODE	APS
Display per-stage status	x			x	SMST	APS
Display per-stage input power	x			x	SPIN	PDP
Set per-stage power limit	x	x		x	SPLIM	PLM
Display per-stage total output power	x			x	SPOUT	PDP
Display per-stage signal output power	x			x	SPSIG	APP
Display reflected power at stage output	x			x	SRFL	REF
Set output tilt	x	x		x	TILT	TLT
Display version information	x		x		VER	VER
Set VOA attenuation	x	x		x	VOA	VAS

iTeh STANDARD PREVIEW

6 Universal command set (standards.iteh.ai)

This clause describes the syntax of commands in the two command sets I and II. The commands are informative. It is recommended that the user choose the commands from only one of the sets, i.e. either from set I or II, and not mix the commands from the two sets. Each command is shown with arguments in italics. All OACS compliant amplifiers shall support commands shown in this clause. Variations due to optional arguments are shown on separate lines. In the examples, a sample of communications is shown starting with the prompt from the module and ending with the prompt following the final command. Text sent to the module from the host is shown in bold (assumes echo mode is on).

Table 2 (continued, page 2/4)

Sub-clause	Command	Description	Example
6.1.4	BAUD <i>x</i> BAUD	Sets baud rate to <i>x</i> bits per second. Allowed values are 9 600, 19 200, 38 400, 57 600, and 115 200. If no argument is provided, the current rate is displayed. Note that the baud rate change takes effect <i>after</i> the prompt in response to the command is sent	> baud BAUD: 9600 > baud 115200 >
6.1.5	BOOT	Reboots the firmware	> boot (startup messages) >
6.1.6	ECHO ON ECHO OFF ECHO	Sets command line echoing to “ON” or “OFF”. If no argument is provided, the current setting is displayed	> echo ECHO: ON > echo off > echo ECHO: OFF >
6.1.7	LOS <i>x</i> LOS	Specifies behaviour when the LOS alarm is active. Parameter <i>x</i> is one of the following: A: Pumps disabled in gain control, power control, and manual control modes. P: No effect in gain control mode, pumps disabled in power control and manual control modes. N: No effect in any mode. If <i>x</i> is not specified, the current LOS mode is displayed. For multistage EDFAs, the LOS mode applies to all stages in the same manner.	> los LOS: A > los p > los LOS: P >
6.1.8	MODE <i>x y</i> MODE <i>x</i> MODE	Sets the control mode of the amplifier to <i>x</i> with setpoint <i>y</i> . Control modes are: G: Gain control mode: <i>y</i> is the gain setpoint in dB. For fixed-gain modules, <i>y</i> may be specified as “OFG” to set the optimal flat gain. P: Output power control mode: <i>y</i> is the output power setpoint in dBm. S: Stage control mode: <i>y</i> is not supplied. <i>Applies to multistage EDFAs only.</i> P: Pump power control mode: <i>y</i> is not supplied. Each pump is driven to the optical power specified by the PSP command. M: Manual pump control: <i>y</i> is not supplied. In this mode, each pump is driven at a fixed current specified by the PUMP ISP command or automatically controlled if set to AUTO. See the PUMP ISP command for details. D: Disable mode: <i>y</i> is not supplied. All pumps are shut off. NOTE Using MODE alone shows the current system mode and setpoint	> mode MODE: G 23.00 dB > mode g ofg > mode MODE: G 22.65 dB > mode p 10.78 > mode MODE: P 10.78 dBm > mode d > mode MODE: D > mode s > mode MODE: S >

Table 2 (continued, page 3/4)

Sub-clause	Command	Description	Example
6.1.9	MST	<p>Displays module status which is one or more of the following keywords: DIS: Module disabled due to amplifier disable input or alarm ES: Module in eyesafe mode due to eyesafe input or alarm. Eyesafe mode is a mode in which the optical power level is limited for eye safety concerns. LIM: Module gain or output power limited by SGLIM/SPLIM OK: Module is operating normally.</p> <p>For multistage EDFAs, the module status is the union (logical OR) of the all of the stages' status indications (see SMST in 7.8)</p>	<pre>> mst MST: DIS ES > mst MST: OK ></pre>
6.1.10	MT	<p>Displays module case temperature in degrees °C</p>	<pre>> mt MT: 45.6 C ></pre>
6.1.11	PD x PD	<p>Displays power at photodiode x in dBm. Valid photodiode numbers range from 1 to the number of installed photodiodes. If the argument is omitted, all photodiode powers are displayed.</p> <p>Use of higher level commands such as PIN, SPOUT, VOA, etc. is recommended in lieu of the PD command. Photodiode numbering is not guaranteed to be consistent across designs. For example, on any given amplifier design the PIN command always reports input power whereas the "PD 1" command may report something else</p>	<pre>> pd 2 PD 2: -6.08 dBm > pd PD 1: -22.32 dBm PD 2: -6.08 dBm PD 3: -10.23 dBm PD 4: 11.01 dBm ></pre>
6.1.12	PIN POUT PSIG GAIN	<p>Displays input power, total output power, signal output power, and signal gain. Signal power is total power less estimated ASE power.</p>	<pre>> pin PIN: -20.00 dBm > pout POUT: 6.15 dBm > psig PSIG: 5.00 dBm > gain GAIN: 25.00 dB ></pre>
6.1.13	PUMP x ISP z PUMP x AUTO	<p>Sets fixed current of z milliamps for pump x. If x is not specified, all pumps are set to this current. Setting a fixed pump current overrides automatic control of the pump which may compromise control. The AUTO parameter restores automatic pump control. This command is permitted only when the module is in manual mode (MODE M). Manual pump settings are temporary and are not preserved across power-on reset (they revert to ISP 0 after reset)</p>	<pre>> pump 2 isp 25.0 > pump 2 isp PUMP 2 ISP: 25.0 mA > pump 2 auto > pump 2 isp PUMP 2 ISP: AUTO ></pre>

Table 2 (continued, page 4/4)

Sub-clause	Command	Description	Example
6.1.14	PUMP x y PUMP x PUMP	Displays status of pump x. Valid pump numbers range from 1 to the number of installed pumps. The y parameter specifies the information displayed and can be one of the following: ILD: Laser diode current in mA EOL: Laser diode end-of-life current in mA TMP: Pump temperature in degrees C ITC: TEC current in mA VTC: TEC voltage in V ISP: Pump current setpoint in mA	> pump 2 ild PUMP 2 ILD: 102.7 mA > pump 1 PUMP 1 ILD: 167.5 mA PUMP 1 EOL: 350.0 mA PUMP 1 TMP: 25.1 C PUMP 1 ITC: 847.0 mA PUMP 1 VTC: 2.354 V PUMP 1 ISP: AUTO >
6.1.15	RECV x	Downloads file from the host system using the XMODEM file transfer protocol. The XMODEM protocol can be XMODEM 128 byte data, 2 byte CRC or XMODEM 1K byte data, 2 byte CRC. Parameter x indicates the type of file, which is vendor specific. Examples: FW: Downloads new firmware for the microcontroller S2: Download in S2 file format using ASCII transfer protocol	> recv fw > > recv s2 >
6.1.16	RST	Resets all settings to factory default values. Usually, changes do not take effect until the microcontroller is rebooted by issuing the BOOT command. NOTE See Annex A for additional comments on RST functionality	> rst >
6.1.17	VER	Display version information. This read-only command results in the amplifier responding with several lines of version and configuration information. The first 3 lines shall contain the information fields shown at right. Additional output lines may be added as agreed upon between amplifier supplier and customer. Explicit formatting requirements of any additional lines of output are not imposed by this document	> ver Configuration: GenericEDFA Firmware Vers: 1.0.0 Serial Number: 123000010 >

6.2 Command set II

Table 3 – Universal software command set II (informative) (page 1/4)

Sub-clause	Command	Description	Example
6.2.1	ALT x ALT x y	Displays alarm threshold level Sets alarm threshold level x is the number assigned by alarm. It is the alarm of the following contents: Input alarm Reflection alarm OUT alarm LD current alarm LD temperature alarm Case temperature alarm EDF heater temperature alarm y and z is sets alarm value	>ATL 2 20C > >ATL 2 20 OK >