



Designation: E 2047 – 99

## Test Method for Wet Insulation Integrity Testing of Photovoltaic Arrays<sup>1</sup>

This standard is issued under the fixed designation E 2047; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon ( $\epsilon$ ) indicates an editorial change since the last revision or reapproval.

### 1. Scope

1.1 This test method covers a procedure to determine the insulation resistance of a photovoltaic (PV) array (or its component strings), that is, the electrical resistance between the array's internal electrical components and is exposed, electrically conductive, non-current carrying parts and surfaces of the array.

1.2 This test method does not establish pass or fail levels. The determination of acceptable or unacceptable results is beyond the scope of this test method.

1.3 There is no similar or equivalent ISO standard.

1.4 *Units*—The values stated in either SI units or inch-pound units are to be regarded separately as standard. The values stated in each system may not be exact equivalents; therefore, each system shall be used independently of the other. Combining values from the two systems may result in non-conformance with the standard.

1.5 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety and health practices and determine the applicability of regulatory limitations prior to use.*

### 2. Referenced Documents

#### 2.1 ASTM Standards:

- E 772 Terminology Relating to Solar Energy Conversion<sup>2</sup>
- E 1328 Terminology Relating to Photovoltaic Solar Energy Conversion<sup>2</sup>
- E 1462 Standard Test Methods for Insulation Integrity and Ground Path Continuity of Photovoltaic Modules<sup>2</sup>

### 3. Terminology

3.1 *Definitions*—Definitions of terms used in this test method may be found in Terminologies E 772 and E 1328.

#### 3.2 Definitions of Terms Specific to This Standard:

3.2.1 *insulation resistance, n*—the electrical resistance of a photovoltaic array's insulation, measured between the photo-

voltaic circuit and exposed, electrically conductive non-current-carrying parts and surfaces of the array.

3.2.2 *metal oxide varistor MOV, n*—a surge protection device.

3.2.3 *photovoltaic circuit*—the active electrical circuit that conducts the photovoltaic generated power.

### 4. Summary of Test Method

4.1 A procedure is provided for testing the electrical isolation between the array's internal electrical components and its exposed, electrically conductive, non-current carrying parts and surfaces of the array.

4.2 The procedure offers two ways to connect the array during the test, either open-circuited or short-circuited. Each option has advantages and disadvantages (see 5.5).

4.3 A wetting solution is applied to the array, then a voltage is applied between the PV circuit and the exposed, electrically conductive, non-current carrying parts and surfaces of the array, while monitoring the current or resistance, to find localized regions where the insulation resistance is significantly reduced by the wetting solution. The array is then inspected for evidence of possible arcing.

### 5. Significance and Use

5.1 The design of a PV module or system intended to provide safe conversion of the sun's radiant energy into useful electricity must take into consideration the possibility of hazard should the user come into contact with the electrical potential of the array. In addition, the insulation system provides a barrier to electrochemical corrosion, and insulation flaws can result in increased corrosion and reliability problems. This test method describes a procedure for verifying that the design and construction of the array provides adequate electrical isolation through normal installation and use. At no location on the array should the PV-generated electrical potential be accessible, with the obvious exception of the output leads. The isolation is necessary to provide for safe and reliable installation, use, and service of the PV system.

5.2 This test method describes a procedure for determining the ability of the array to provide protection from electrical hazards. Its primary use is to find insulation flaws that could be dangerous to persons who may come into contact with the array. Corrective action taken to address such flaws is beyond the scope of this test method.

<sup>1</sup> This test method is under the jurisdiction of ASTM Committee E-44 on Solar, Geothermal and Other Alternative Energy Sources, and is the direct responsibility of Subcommittee E44.09 on Photovoltaic Electrical Power Conversion.

Current edition approved October 10, 1999. Published December 1999.

<sup>2</sup> *Annual Book of ASTM Standards*, Vol 12.02.

5.3 This procedure may be specified as part of a series of acceptance tests involving performance measurements and demonstration of functional requirements. Large arrays can be tested in smaller segments. The size of the array segment to be tested (called “circuit under test” in this test method) is usually selected at a convenient break point and sized such that the expected resistance or current reading is within the middle third of the meter’s range.

5.4 Insulation leakage resistance and insulation leakage current leakage are strong functions of array dimensions, ambient relative humidity, absorbed water vapor, and other factors. For this reason, it is the responsibility of the user of this test method to specify the minimum acceptable leakage resistance for this test.

5.4.1 Even though a numerical quantity is specified, actual results are often pass-fail in that when a flaw is found, the leakage current changes from almost nothing to the full scale value on the meter.

5.5 The user of this test method must specify the option used for connection to the array during the test. The short-circuited option requires a shorting device with leads to connect the positive and negative legs of the circuit under test. For larger systems, where the shorting device may have to be rated for high current and voltage levels, the open-circuited option may be preferred. The open-circuited option requires the user to correct readings to account for the PV-generated voltage, and the procedure for making such corrections is beyond the scope of this test method. The short-circuited option may be easier for small systems where the voltage and current levels are low and the distance between the plus and minus leads of the circuit under test are small. The short-circuited option minimizes the chance of exposing array components to voltage levels above those for which they are rated.

## 6. Apparatus

6.1 Choose one of the following, depending on the option selected (see 4.2 and 5.5):

6.1.1 *Variable dc Voltage Power Supply*—A dc voltage power supply capable of providing a nominal test voltage of 500 V, as specified in Test Method E 1462. A common term for this apparatus is insulation tester.

6.1.2 *Megohmmeter*—A high-impedance ohmmeter, or similar device, capable of adequately measuring leakage resistance in the range of anticipated readings, and that can provide a nominal test voltage of 500 V.

6.2 *Wetting Solution*—A solution of tap water and a wetting agent<sup>3</sup>, with a surface tension of 0.002 lb/ft (0.03 N/m) or less at 73°F (23°C).

6.3 *Spray Apparatus*—A system for applying the wetting solution to the array, capable of providing a water pressure of 5 psig (35 kPa).<sup>4</sup> The force and flow rate of the wetting solution

must be sufficient to reach all of the test segment surfaces and maintain wetted surfaces, front and back.

NOTE 1—The spray pressure is only enough to completely wet the exposed surfaces; it is not intended to penetrate enclosed spaces such as the interiors of junction boxes. It is not necessary to use a forceful stream because the wetting agent helps to penetrate small crevices.

6.4 *Array Shorter*—A dc-rated switch, circuit breaker or other device capable of interrupting the maximum short circuit current of the circuit under test. The array shorter is only required if the short-circuited option is used.

6.4.1 The array shorter must be rated for the maximum open-circuit voltage of the circuit under test plus the insulation tester or ohmmeter.

6.4.2 The wiring between the array shorter and the positive and negative terminals of the circuit under test must also be rated for the continuous maximum short-circuit current of the circuit under test.

## 7. Hazards

7.1 Touching the modules or array during the testing may be hazardous because of the high voltage applied.

7.2 Use caution whenever short circuiting any high voltage PV array. It may be advisable to reduce the risk involved by short-circuiting the array at night, when the current and voltage are minimized.

7.3 The megohmmeter or insulation tester should be turned off while wetting the array. This may not always be desirable, such as when trying to pinpoint the location of an insulation flaw. In these cases, appropriate personnel protection (electrical gloves with keepers, safety glasses, etc.) should be worn and care should be taken to keep the wetting solution from entering the gloves, boots, etc.

## 8. Procedure

8.1 Assemble the requisite equipment and personnel at the array to be tested.

8.2 Prepare the wetting solution.

8.3 Measure and record the site meteorological conditions (irradiance, ambient temperature, wind speed) or arrange for the data to be measured by the site data acquisition system.

NOTE 2—It is recommended that this test not be performed under conditions where the ambient temperature is greater than 100°F (40°C) or the wind speed is greater than 17 mph (7.5 m/s), since high values of either make it difficult to keep the array wet long enough to make the necessary measurements. If the short-circuited option is used, it may be necessary to conduct the test at a reduced irradiance to ensure that the currents produced in the short-circuited PV components are within manufacturer’s requirements. Refer to the manufacturer’s recommendations concerning shorting of modules and other array components at high irradiance.

8.4 Isolate the circuit(s) to be tested prior to the start of spraying. Depending on the design of the PV system, this may involve opening source circuit switches, taking out removable links, or disconnecting bolted connections or connectors. All poles of the circuit to be tested (positive, negative and neutral) must be isolated. Disconnect positive and negative monopoles from each other. Ground connections among module frames, panels, array structures and system/earth ground must be left in place.

<sup>3</sup> An acceptable wetting solution that has been found to produce adequate sheeting action is 1 part Liqui-nox detergent in 500 parts water. Liqui-Nox is available from Alconox, Inc., 9T East 40th St., New York, NY 10016, as part number C6308-2.

<sup>4</sup> Molded nylon Rain-Test spray heads are available from Underwriters’ Laboratories, Inc., 333 Pfingsten Rd., Northbrook, IL 60062, as part number SA0820B.