



# SLOVENSKI STANDARD SIST HD 60364-4-41:2007

01-oktober-2007

BUXca Yý U

SIST HD 384.4.41 S2:2000

SIST HD 384.4.41 S2:2000/A1:2003

SIST HD 384.4.46 S2:2002

SIST HD 384.4.47 S2:2000

B]n\_cbUdYtcgfbYYY\_f] bY]býHUMY!( !( %rXY.'NUý ]Hb]i \_fYd]!'NUý ]HdfYX  
YY\_f] b]a `i XUfca `f97 \* \$' \* ( !( ( %&\$) žgdfYa Yb^YbL

Low-voltage electrical installations -- Part 4-41: Protection for safety - Protection against electric shock

(standards.iteh.ai)

Errichten von Niederspannungsanlagen -- Teil 4-41: Schutzmaßnahmen - Schutz gegen elektrischen Schlag

<https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-6ffc286b6b09/sist-hd-60364-4-41-2007>

Installations électriques a basse tension - Partie 4-41: Protection pour assurer la sécurité - Protection contre les chocs électriques

Ta slovenski standard je istoveten z: HD 60364-4-41:2007

### ICS:

13.260	Xæ•ç[ Á ^áÁ ^\ dã} ã ~ áæ[ {	Protection against electric shock
91.140.50	Sistemi za oskrbo z elektriko	Electricity supply systems

SIST HD 60364-4-41:2007 en,de

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

SIST HD 60364-4-41:2007

<https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-6ffc286b6b09/sist-hd-60364-4-41-2007>

English version

**Low-voltage electrical installations –  
Part 4-41: Protection for safety -  
Protection against electric shock  
(IEC 60364-4-41:2005, modified)**

Installations électriques à basse tension –  
Partie 4-41: Protection pour assurer  
la sécurité -  
Protection contre les chocs électriques  
(CEI 60364-4-41:2005, modifiée)

Errichten von Niederspannungsanlagen –  
Teil 4-41: Schutzmaßnahmen -  
Schutz gegen elektrischen Schlag  
(IEC 60364-4-41:2005, modifiziert)

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

This Harmonization Document was approved by CENELEC on 2006-02-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for implementation of this Harmonization Document at national level. <https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-91e260600995541691049441-2007>

Up-to-date lists and bibliographical references concerning such national implementations may be obtained on application to the Central Secretariat or to any CENELEC member.

This Harmonization Document exists in three official versions (English, French, German).

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

**CENELEC**

European Committee for Electrotechnical Standardization  
Comité Européen de Normalisation Electrotechnique  
Europäisches Komitee für Elektrotechnische Normung

**Central Secretariat: rue de Stassart 35, B - 1050 Brussels**

## Foreword

The text of document 64/1489/FDIS, future edition 5 of IEC 60364-4-41, prepared by IEC TC 64, Electrical installations and protection against electric shock, was submitted to the IEC-CENELEC parallel vote.

A draft amendment, prepared by SC 64A, Protection against electric shock, of Technical Committee CENELEC TC 64, Electrical installations and protection against electric shock, was submitted to the formal vote.

The combined texts were approved by CENELEC as HD 60364-4-41 on 2006-02-01.

This Harmonization Document supersedes HD 384.4.41 S2:1996 + A1:2002, HD 384.4.46 S2:2001 and HD 384.4.47 S2:1995.

The following dates were fixed:

- latest date by which the existence of the HD has to be announced at national level (doa) 2006-08-01
- latest date by which the HD has to be implemented at national level by publication of a harmonized national standard or by endorsement (dop) 2007-08-01
- latest date by which the national standards conflicting with the HD have to be withdrawn (dow) 2009-02-01

Annexes ZA and ZB have been added by CENELEC.

[https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-](https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-6ff286b6b09/sist-hd-60364-4-41-2007)

In this document, the common modifications to the International Standard are indicated by a vertical line in the left margin of the text.

---

## Contents

Foreword .....	2
410 Introduction .....	4
410.1 Scope.....	5
410.2 Normative references .....	5
410.3 General requirements .....	6
411 Protective measure: automatic disconnection of supply .....	7
411.1 General .....	7
411.2 Requirements for basic protection .....	7
411.3 Requirements for fault protection .....	8
411.4 TN systems .....	9
411.5 TT systems.....	11
411.6 IT systems.....	12
411.7 Functional extra-low voltage (FELV) .....	14
412 Protective measure: double or reinforced insulation.....	15
412.1 General .....	15
412.2 Requirements for basic protection and fault protection .....	15
413 Protective measure: electrical separation .....	17
413.1 General .....	17
413.2 Requirements for basic protection.....	17
413.3 Requirements for fault protection.....	18
414 Protective measure: extra-low-voltage provided by SELV and PELV.....	18
414.1 General .....	18
414.2 Requirements for basic protection and fault protection .....	19
414.3 Sources for SELV and PELV .....	19
414.4 Requirements for SELV and PELV circuits.....	19
415 Additional protection.....	20
415.1 Additional protection: residual current protective devices (RCDs) .....	20
415.2 Additional protection: supplementary protective equipotential bonding .....	20
Annex A (normative) Provisions for basic protection (protection against direct contact) .....	21
Annex B (normative) Obstacles and placing out of reach .....	22
Annex C (normative) Protective measures for application only when the installation is controlled or under the supervision of skilled or instructed persons.....	24
Annex D (informative) Correspondence between IEC 60364-4-41:2001 and IEC 60364-4-41:2005.....	27
Bibliography.....	29
Annex ZA (normative) Special national conditions.....	30
Annex ZB (informative) A-deviations .....	32
Figure B.1 - Zone of arm's reach.....	23
Table 41.1 - Maximum disconnection times.....	9

## 410 Introduction

This Part 4-41 of HD 60364 deals with protection against electric shock as applied to electrical installations. It is based on EN 61140 which is a basic safety standard that applies to the protection of persons and livestock. EN 61140 is intended to give fundamental principles and requirements that are common to electrical installations and equipment or are necessary for their co-ordination.

The fundamental rule of protection against electric shock, according to EN 61140, is that hazardous-live-parts must not be accessible and accessible conductive parts must not be hazardous live, neither under normal conditions nor under single fault conditions.

According to 4.2 of EN 61140, protection under normal conditions is provided by basic protective provisions and protection under single fault conditions is provided by fault protective provisions. Alternatively, protection against electric shock is provided by an enhanced protective provision, which provides protection under normal conditions and under single fault conditions.

This standard in accordance with IEC Guide 104 has the status of a group safety publication (GSP) for protection against electric shock.

In the previous edition HD 384.4.41 S2:1996

- protection under normal conditions (now designated basic protection) was referred to as protection against direct contact and
- protection under fault conditions (now designated fault protection) was referred to as protection against indirect contact.

[SIST HD 60364-4-41:2007](https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-6ffc286b6b09/sist-hd-60364-4-41-2007)

<https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429fb57e-6ffc286b6b09/sist-hd-60364-4-41-2007>

#### 410.1 Scope

Part 4-41 of HD 60364 specifies essential requirements regarding protection against electric shock, including basic protection (protection against direct contact) and fault protection (protection against indirect contact) of persons and livestock. It deals also with the application and co-ordination of these requirements in relation to external influences.

Requirements are also given for the application of additional protection in certain cases.

#### 410.2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60364-5-52, *Electrical installations of buildings – Part 5-52: Selection and erection of electrical equipment - Wiring systems*

HD 60364-5-54, *Electrical installations of buildings – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements, protective conductors and protective bonding conductors* (IEC 60364-5-54, modified)

HD 60364-6, *Low-voltage electrical installations – Part 6: Verification* (IEC 60364-6, modified)

EN 60439-1, *Low-voltage switchgear and controlgear assemblies* (IEC 60439-1)

IEC 60449, *Voltage bands for electrical installations of buildings*

IEC 60614 (all parts), *Conduits for electrical installations - Specification*  
<https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429f-b57e-6ffc286b6b09/sist-hd-60364-4-41-2007>

IEC 61084 (all parts), *Cable trunking and ducting systems for electrical installations*

EN 61140, *Protection against electric shock – Common aspects for installation and equipment* (IEC 61140)

EN 61386 (all parts), *Conduit systems for cable management* (IEC 61386 – all parts)

EN 61558-2-6, *Safety of power transformers, power supply units and similar – Part 2-6: Particular requirements for safety isolating transformers for general use* (IEC 61558-2-6)

IEC Guide 104, *The preparation of safety publications and the use of basic safety publications and group safety publications*

### 410.3 General requirements

**410.3.1** In this standard the following specification of voltages is intended unless otherwise stated:

- a.c. voltages are r.m.s.;
- d.c. voltages are ripple-free.

Ripple-free is conventionally defined as an r.m.s. ripple voltage of not more than 10 % of the d.c. component.

**410.3.2** A protective measure shall consist of

- an appropriate combination of a provision for basic protection and an independent provision for fault protection, or
- an enhanced protective provision which provides both basic protection and fault protection.

Additional protection is specified as part of a protective measure under certain conditions of external influences and in certain special locations (see the corresponding Part 7 of HD 60364 or HD 384).

NOTE 1 For special applications, protective measures which do not follow this concept are permitted (see 410.3.5 and 410.3.6).

NOTE 2 An example of an enhanced protective measure is reinforced insulation.

**410.3.3** In each part of an installation one or more protective measures shall be applied, taking account of the conditions of external influence.

The following protective measures generally are permitted:

- automatic disconnection of supply (Clause 411),
- double or reinforced insulation (Clause 412),
- electrical separation for the supply of one item of current-using equipment (Clause 413),
- extra-low-voltage (SELV and PELV) (Clause 414).

The protective measures applied in the installation shall be considered in the selection and erection of equipment.

For particular installations see 410.3.4 to 410.3.9.

NOTE In electrical installations the most commonly used protective measure is automatic disconnection of supply.

**410.3.4** For special installations or locations, the particular protective measures in the corresponding Part 7 of HD 60364 or HD 384 shall be applied.

**410.3.5** The protective measures, specified in Annex B, i.e. the use of obstacles and placing out of reach, shall only be used in installations accessible to:

- skilled or instructed persons or
- persons under the supervision of skilled or instructed persons.



**410.3.6** The protective measures, specified in Annex C, i.e.

- non-conducting location,
- earth-free local equipotential bonding,
- electrical separation for the supply of more than one item of current-using equipment,

may be applied only when the installation is under the supervision of skilled or instructed persons so that unauthorized changes cannot be made.

**410.3.7** If certain conditions of a protective measure cannot be met, supplementary provisions shall be applied so that the protective provisions together achieve the same degree of safety.

NOTE An example of the application of this rule is given in 411.7.

**410.3.8** Different protective measures applied to the same installation or part of an installation or within equipment shall have no influence on each other such that failure of one protective measure could impair the other protective measures.

**410.3.9** The provision for fault protection (protection against indirect contact) may be omitted for the following equipment:

- metal supports of overhead line insulators which are attached to the building and are placed out of arm's reach;
- steel reinforced concrete poles of overhead lines in which the steel reinforcement is not accessible;
- exposed-conductive-parts which, owing to their reduced dimensions (approximately 50 mm x 50 mm) or their disposition cannot be gripped or come into significant contact with a part of the human body and provided that connection with a protective conductor could only be made with difficulty or would be unreliable.

NOTE This exemption applies, for example, to bolts, rivets, nameplates and cable clips.

- metal tubes or other metal enclosures protecting equipment in accordance with Clause 412.

## **411 Protective measure: automatic disconnection of supply**

### **411.1 General**

Automatic disconnection of supply is a protective measure in which

- basic protection is provided by basic insulation of live parts or by barriers or enclosures, in accordance with Annex A, and
- fault protection is provided by protective equipotential bonding and automatic disconnection in case of a fault in accordance with 411.3 to 411.6.

NOTE 1 Where this protective measure is applied, Class II equipment may also be used.

Where specified, additional protection is provided by a residual current protective device (RCD) with rated residual operating current not exceeding 30 mA in accordance with 415.1.

NOTE 2 Residual current monitors (RCMs) are not protective devices but they may be used to monitor residual currents in electrical installations. RCMs produce an audible or audible and visual signal when a preselected value of residual current is exceeded

### **411.2 Requirements for basic protection (protection against direct contact)**

All electrical equipment shall comply with one of the provisions for basic protection (protection against direct contact) described in Annex A or, where appropriate, Annex B.

### 411.3 Requirements for fault protection (protection against indirect contact)

#### 411.3.1 Protective earthing and protective equipotential bonding

##### 411.3.1.1 Protective earthing

Exposed-conductive-parts shall be connected to a protective conductor under the specific conditions for each type of system earthing as specified in 411.4 to 411.6.

Simultaneously accessible exposed-conductive-parts shall be connected to the same earthing system individually, in groups or collectively.

Conductors for protective earthing shall comply with HD 60364-5-54.

Each circuit shall have available a protective conductor connected to the relevant earthing terminal.

##### 411.3.1.2 Protective equipotential bonding

In each building the earthing conductor, the main earthing terminal and the following conductive parts shall be connected to the protective equipotential bonding:

- metallic pipes supplying services into the building, e.g. gas, water;
- structural extraneous-conductive-parts if accessible in normal use, metallic central heating and air-conditioning systems;
- metallic reinforcements of constructional reinforced concrete, where the reinforcements are accessible and reliably interconnected.

Where such conductive parts originate outside the building, they shall be bonded as close as practicable to their point of entry within the building.

Conductors for protective equipotential bonding shall comply with HD 60364-5-54.

Any metallic sheath of telecommunication cables shall be connected to the protective equipotential bonding, taking account of the requirements of the owners or operators of these cables.

#### 411.3.2 Automatic disconnection in case of a fault

**411.3.2.1** Except as provided by 411.3.2.5 and 411.3.2.6, a protective device shall automatically interrupt the supply to the line conductor of a circuit or equipment in the event of a fault of negligible impedance between the line conductor and an exposed-conductive-part or a protective conductor in the circuit or equipment within the disconnection time required in 411.3.2.2, 411.3.2.3 or 411.3.2.4.

NOTE 1 Higher values of disconnection time than those required in this subclause may be admitted in systems for electricity distribution to the public and power generation and transmission for such systems.

NOTE 2 Lower values of disconnection time may be required for special installations or locations according to the relevant Part 7 of HD 60364 or HD 384.

NOTE 3 For IT systems, automatic disconnection is not usually required on the occurrence of a first fault (see 411.6.1). For the requirements for disconnection after the first fault see 411.6.4.

**411.3.2.2** The maximum disconnection time stated in Table 41.1 shall be applied to final circuits not exceeding 32 A.

**Table 41.1 – Maximum disconnection times**

System	50 V < $U_o \leq 120$ V <sub>s</sub>		120 V < $U_o \leq 230$ V <sub>s</sub>		230 V < $U_o \leq 400$ V <sub>s</sub>		$U_o > 400$ V <sub>s</sub>	
	a.c.	d.c.	a.c.	d.c.	a.c.	d.c.	a.c.	d.c.
TN	0,8	Note 1	0,4	5	0,2	0,4	0,1	0,1
TT	0,3	Note 1	0,2	0,4	0,07	0,2	0,04	0,1

Where in TT systems the disconnection is achieved by an overcurrent protective device and the protective equipotential bonding is connected with all extraneous-conductive-parts within the installation, the maximum disconnection times applicable to TN systems may be used.

$U_o$  is the nominal a.c. or d.c. line to earth voltage.

NOTE 1 Disconnection may be required for reasons other than protection against electric shock.

NOTE 2 Where disconnection is provided by an RCD see Note to 411.4.4, Note 4 to 411.5.3 and Note to 411.6.4 b).

**411.3.2.3** In TN systems a disconnection time not exceeding 5 s is permitted for distribution circuits, and for circuits not covered by 411.3.2.2.

**411.3.2.4** In TT systems a disconnection time not exceeding 1 s is permitted for distribution circuits and for circuits not covered by 411.3.2.2.

**411.3.2.5** For systems with nominal voltage  $U_o$  greater than 50 V a.c. or 120 V d.c., automatic disconnection in the time required by 411.3.2.2, 411.3.2.3 or 411.3.2.4 as appropriate is not required if in the event of a fault to a protective conductor or earth, the output voltage of the source is reduced in not more than the applicable time value of Table 41.1 or 5 s (as appropriate) to 50 V a.c. or 120 V d.c. or less. In such cases consideration shall be given to disconnection as required for reasons other than electric shock.

**411.3.2.6** If automatic disconnection according to 411.3.2.1 cannot be achieved in the time required by 411.3.2.2, 411.3.2.3, or 411.3.2.4 as appropriate, supplementary protective equipotential bonding shall be provided in accordance with 415.2.

### 411.3.3 Additional protection

In a.c. systems, additional protection by means of a residual current protective device (RCD) in accordance with 415.1 shall be provided for

- socket-outlets with a rated current not exceeding 20 A that are for use by ordinary persons and are intended for general use and

NOTE An exemption may be made for:

- socket-outlets for use under the supervision of skilled or instructed persons, e.g., in some commercial or industrial locations or
- a specific socket outlet provided for connection of a particular item of equipment.

- mobile equipment with a current rating not exceeding 32 A for use outdoors.

### 411.4 TN system

**411.4.1** In TN systems the integrity of the earthing of the installation depends on the reliable and effective connection of the PEN or PE conductors to earth. Where the earthing is provided from a public or other supply system, compliance with the necessary conditions external to the installation is the responsibility of the supply network operator.

NOTE Examples of conditions are:

- the PEN is connected to earth at a number of points and is installed in such a way as to minimise the risk of a break in the PEN conductor,
- $R_B/R_E \leq 50 \text{ V}/(U_o - 50 \text{ V})$ .

Where

$R_B$  is the earth electrode resistance, in ohms, of all earth electrodes in parallel;

$R_E$  is the minimum contact resistance with earth, in ohms, of extraneous-conductive-parts not connected to a protective conductor, through which a fault between line and earth may occur;

$U_0$  is the nominal a.c. r.m.s. voltage to earth, in volts.

**411.4.2** The neutral point or the midpoint of the power supply system shall be earthed. If a neutral point or midpoint is not available or not accessible, a line conductor shall be earthed.

Exposed-conductive-parts of the installation shall be connected by a protective conductor to the main earthing terminal of the installation which shall be connected to the earthed point of the power supply system.

NOTE 1 If other effective earth connections exist, it is recommended that the protective conductors also be connected to such points wherever possible. Earthing at additional points, distributed as evenly as possible, may be necessary to ensure that the potentials of protective conductors remain, in case of a fault, as near as possible to that of earth.

In large buildings such as high-rise buildings, additional earthing of protective conductors is not possible for practical reasons. In such buildings protective-equipotential-bonding between protective conductors and extraneous-conductive-parts has, however, a similar function.

NOTE 2 It is recommended that protective conductors (PE and PEN) should be earthed where they enter any buildings or premises taking account of any diverted neutral currents.

**411.4.3** In fixed installations, a single conductor may serve both as a protective conductor and as a neutral conductor (PEN conductor) provided that the requirements of 543.4 of HD 60364-5-54 are satisfied. No switching or isolating device shall be inserted in the PEN conductor.

**411.4.4** The characteristics of the protective devices (see 411.4.5) and the circuit impedances shall fulfil the following requirement:

$$Z_s \times I_a \leq U_0$$

<https://standards.iteh.ai/catalog/standards/sist/45d9b232-7317-429f-b57e-6ffc286b6b09/sist-hd-60364-4-41-2007>

where

$Z_s$  is the impedance in ohms ( $\Omega$ ) of the fault loop comprising

- the source,
- the line conductor up to the point of the fault, and
- the protective conductor between the point of the fault and the source;

$I_a$  is the current in amperes (A) causing the automatic operation of the disconnecting device within the time specified in 411.3.2.2 or 411.3.2.3. When a residual current protective device (RCD) is used this current is the residual operating current providing disconnection in the time specified in 411.3.2.2 or 411.3.2.3.

$U_0$  is the nominal a.c. or d.c. line to earth voltage in volts (V).

NOTE Where compliance with this subclause is provided by an RCD, the disconnecting times in accordance with Table 41.1 relate to prospective residual fault currents significantly higher than the rated residual operating current of the RCD (typically  $5 I_{\Delta n}$ ).

**411.4.5** In TN systems, the following protective devices may be used for fault protection (protection against indirect contact):

- overcurrent protective devices;
- residual current protective devices (RCDs).

NOTE 1 Where an RCD is used for fault protection; the circuit should also be protected by an overcurrent protective device in accordance with IEC 60364-4-43.

A residual current protective device (RCD) shall not be used in TN-C systems.