

INTERNATIONAL STANDARD



**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A
per phase and not subject to conditional connection**

[IEC 61000-3-3:2008](https://standards.iteh.ai/catalog/standards/iec/63621f84-0e43-42b4-863a-36da8cd6cd4e/iec-61000-3-3-2008)

<https://standards.iteh.ai/catalog/standards/iec/63621f84-0e43-42b4-863a-36da8cd6cd4e/iec-61000-3-3-2008>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

Useful links:

IEC publications search - www.iec.ch/searchpub

The advanced search enables you to find IEC publications by a variety of criteria (reference number, text, technical committee,...).

It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available on-line and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary (IEV) on-line.

Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Liens utiles:

Recherche de publications CEI - www.iec.ch/searchpub

La recherche avancée vous permet de trouver des publications CEI en utilisant différents critères (numéro de référence, texte, comité d'études,...).

Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

Just Published CEI - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications de la CEI. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (VEI) en ligne.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD



**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A
per phase and not subject to conditional connection**

IEC 61000-3-3:2008

<https://standards.iteh.ai/catalog/standards/iec/63621f84-0e43-42b4-863a-36da8cd6cd4e/iec-61000-3-3-2008>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.100.10

ISBN 2-8318-9831-5

Warning! Make sure that you obtained this publication from an authorized distributor.

Withdrawn

iTech Standards
(<https://standards.iteh.ai>)
Document Preview

[iec-61000-3-3:2008](https://standards.iteh.ai/standards/iec/65621f84-0e43-42b4-863a-36da8cd6cd4e/iec-61000-3-3-2008)

<https://standards.iteh.ai/standards/iec/65621f84-0e43-42b4-863a-36da8cd6cd4e/iec-61000-3-3-2008>

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A per
phase and not subject to conditional connection**

**Compatibilité électromagnétique (CEM) –
Partie 3-3: Limites – Limitation des variations de tension, des fluctuations de
tension et du papillotement dans les réseaux publics d'alimentation basse
tension, pour les matériels ayant un courant assigné ≤ 16 A par phase et non
soumis à un raccordement conditionnel**

CONTENTS

FOREWORD.....	3
INTRODUCTION.....	5
1 Scope.....	6
2 Normative references	6
3 Definitions	7
4 Assessment of voltage changes, voltage fluctuations and flicker	8
4.1 Assessment of a relative voltage change, " d "	8
4.2 Assessment of the short-term flicker value, P_{st}	9
4.2.1 Flickermeter	9
4.2.2 Simulation method	9
4.2.3 Analytical method	9
4.2.4 Use of $P_{st} = 1$ curve.....	10
4.3 Assessment of long-term flicker value, P_{lt}	10
5 Limits	10
6 Test conditions	11
6.1 General.....	11
6.2 Measurement accuracy	12
6.3 Test supply voltage	12
6.4 Reference impedance.....	12
6.5 Observation period.....	12
6.6 General test conditions.....	13
Annex A (normative) Application of limits and type test conditions for specific equipment	18
Annex B (normative) Test conditions and procedures for measuring d_{max} voltage changes caused by manual switching	25
Figure 1 – Reference network for single-phase and three-phase supplies derived from a three-phase, four-wire supply.....	14
Figure 2 – Histogram evaluation of $U(t)$	15
Figure 3 – Relative voltage change characteristic	15
Figure 4 – Curve for $P_{st}=1$ for rectangular equidistant voltage changes	16
Figure 5 – Shape factors F for double-step and ramp-voltage characteristics.....	16
Figure 6 – Shape factors F for rectangular and triangular voltage characteristics.....	17
Figure 7 – Shape factor F for motor-start voltage characteristics having various front times	17
Table 1 – Assessment method.....	9
Table A.1 – Electrode parameters	23
Table A.2 – Frequency factor R related to repetition rate " r "	24

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTROMAGNETIC COMPATIBILITY (EMC) –**Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61000-3-3 has been prepared by subcommittee 77A: Low-frequency phenomena, of IEC technical committee 77: Electromagnetic compatibility.

This second edition IEC 61000-3-3 cancels and replaces the first edition published in 1994, amendment 1 (2001) and amendment 2 (2005). This edition constitutes a revised edition.

The document 77A/644/FDIS, circulated to the National Committees as amendment 3, led to the publication of the new edition.

The text of this standard is based on the first edition, its amendment 1, amendment 2 and on the following documents:

FDIS	Report on voting
77A/644/FDIS	77A/650/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this amendment and the base publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

iTech Standards
(<https://standards.itih.ai>)
Document Preview

<https://standards.itih.ai/standards/iec/61000-3-3:2008>

<https://standards.itih.ai/standards/iec/61000-3-3:2008>

WITHDRAWN

INTRODUCTION

IEC 61000 is published in separate parts according to the following structure:

Part 1: General

- General considerations (introduction, fundamental principles)
- Definitions, terminology

Part 2: Environment

- Description of the environment
- Classification of the environment
- Compatibility levels

Part 3: Limits

- Emission limits
- Immunity limits (in so far as they do not fall under the responsibility of product committees)

Part 4: Testing and measurement techniques

- Measurement techniques
- Testing techniques

Part 5: Installation and mitigation guidelines

- Installation guidelines
- Mitigation methods and devices

Part 9: Miscellaneous

Each part is further subdivided into sections which are to be published either as International Standards or as Technical Reports.

These standards and reports will be published in chronological order and numbered accordingly.

This part is a Product Family Standard.

The limits in this standard relate to the voltage changes experienced by consumers connected at the interface between the public supply low-voltage network and the equipment user's installation. Consequently, if the actual impedance of the supply at the supply terminals of equipment connected within the equipment user's installation exceeds the test impedance, it is possible that supply disturbance exceeding the limits may occur.

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection

1 Scope

This part of IEC 61000 is concerned with the limitation of voltage fluctuations and flicker impressed on the public low-voltage system.

It specifies limits of voltage changes which may be produced by an equipment tested under specified conditions and gives guidance on methods of assessment.

This part of IEC 61000 is applicable to electrical and electronic equipment having an input current equal to or less than 16 A per phase, intended to be connected to public low-voltage distribution systems of between 220 V and 250 V line to neutral at 50 Hz, and not subject to conditional connection.

Equipment which does not comply with the limits of this part of IEC 61000 when tested with the reference impedance Z_{ref} of 6.4, and which therefore cannot be declared compliant with this part, may be retested or evaluated to show conformity with IEC 61000-3-11. Part 3-11 is applicable to equipment with rated input current ≤ 75 A per phase and subject to conditional connection.

The tests according to this part are type tests. Particular test conditions are given in annex A and the test circuit is shown in Figure 1.

NOTE The limits in this part of IEC 61000 are based mainly on the subjective severity of flicker imposed on the light from 230 V/60 W coiled-coil filament lamps by fluctuations of the supply voltage. For systems with nominal voltage less than 220 V line to neutral and/or frequency of 60 Hz, the limits and reference circuit values are under consideration.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050(161):1990, *International Electrotechnical Vocabulary (IEV) – Chapter 161: Electromagnetic compatibility*

IEC/TR 60725, *Consideration of reference impedances and public supply impedances for use in determining disturbance characteristics of electrical equipment having a rated current ≤ 75 A per phase*

IEC 60974-1, *Arc welding equipment – Part 1: Welding power sources*

IEC 61000-3-2:2005, *Electromagnetic compatibility (EMC) – Part 3-2: Limits – Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)*

IEC 61000-3-11, *Electromagnetic compatibility (EMC) – Part 3-11: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems – Equipment with rated current ≤ 75 A and subject to conditional connection*

IEC 61000-4-15, *Electromagnetic compatibility (EMC) – Part 4: Testing and measurement techniques – Section 15: Flickermeter – Functional and design specifications*

3 Definitions

For the purpose of this part of IEC 61000-3, the following definitions apply.

3.1

r.m.s. voltage shape, $U(t)$

the time function of r.m.s. voltage, evaluated as a single value for each successive half period between zero-crossings of the source voltage (see Figure 2)

3.2

voltage change characteristic, $\Delta U(t)$

the time function of the r.m.s. voltage change evaluated as a single value for each successive half period between zero-crossings of the source voltage between time intervals in which the voltage is in a steady-state condition for at least 1 s (see Figure 2)

NOTE Since this characteristic is only used for assessments using calculations, the voltage in the steady-state condition is assumed to be constant within the measurement accuracy (see 6.2).

3.3

maximum voltage change characteristic, ΔU_{\max}

the difference between maximum and minimum r.m.s. values of a voltage change characteristic (see Figure 2)

3.4

steady-state voltage change, ΔU_c

the difference between two adjacent steady-state voltages separated by at least one voltage change characteristic (see Figure 2)

NOTE Definitions 3.2 to 3.4 relate to absolute phase-to-neutral voltages. The ratios of these magnitudes to the phase-to-neutral value of the nominal voltage (U_n) of the reference network in Figure 1 are called:

- relative voltage change characteristic: $d(t)$ (definition 3.2);
- maximum relative voltage change: d_{\max} (definition 3.3);
- relative steady-state voltage change: d_c (definition 3.4).

These definitions are explained by the example in Figure 3.

3.5

voltage fluctuation

series of changes of r.m.s. voltage evaluated as a single value for each successive half-period between zero-crossings of the source voltage

3.6

flicker

impression of unsteadiness of visual sensation induced by a light stimulus whose luminance or spectral distribution fluctuates with time. [IEV 161-08-13]

3.7

short-term flicker indicator, P_{st}

the flicker severity evaluated over a short period (in minutes); $P_{st} = 1$ is the conventional threshold of irritability

3.8

long-term flicker indicator, P_{lt}

the flicker severity evaluated over a long period (a few hours) using successive P_{st} values

3.9

flickermeter:

an instrument designed to measure any quantity representative of flicker

NOTE Measurements are normally P_{st} and P_{lt} . [IEV 161-08-14]

3.10

flicker impression time, t_f

value with a time dimension which describes the flicker impression of a voltage change characteristic

3.11

conditional connection

connection of equipment requiring the user's supply at the interface point to have an impedance lower than the reference impedance Z_{ref} in order that the equipment emissions comply with the limits in this part.

NOTE Meeting the voltage change limits may not be the only condition for connection; emission limits for other phenomena such as harmonics, may also have to be satisfied.

3.12

interface point

interface between a public supply network and a user's installation

4 Assessment of voltage changes, voltage fluctuations and flicker

4.1 Assessment of a relative voltage change, "d"

The basis for flicker evaluation is the voltage change characteristic at the terminals of the equipment under test, that is the difference ΔU of any two successive values of the phase-to-neutral voltages $U(t_1)$ and $U(t_2)$:

$$\Delta U = U(t_1) - U(t_2) \quad (1)$$

The r.m.s. values $U(t_1)$, $U(t_2)$ of the voltage shall be measured or calculated. When deducing r.m.s. values from oscillographic waveform, account should be taken of any waveform distortion that may be present. The voltage change ΔU is due to the change of the voltage drop across the complex reference impedance \underline{Z} , caused by the complex fundamental input current change, $\Delta \underline{I}$, of the equipment under test. ΔI_p and ΔI_q are the active and reactive parts respectively of the current change, $\Delta \underline{I}$.

$$\Delta \underline{I} = \Delta I_p - j \cdot \Delta I_q = \underline{I}(t_1) - \underline{I}(t_2) \quad (2)$$

NOTE 1 I_q is positive for lagging currents and negative for leading currents.

NOTE 2 If the harmonic distortion of the currents $\underline{I}(t_1)$ and $\underline{I}(t_2)$ is less than 10 %, the total r.m.s. value may be applied instead of the r.m.s. values of their fundamental currents.

NOTE 3 For single-phase and symmetrical three-phase equipment the voltage change can, provided X is positive (inductive), be approximated to:

$$\Delta U = | \Delta I_p \cdot R + \Delta I_q \cdot X | \quad (3)$$

where

ΔI_p and ΔI_q are the active and reactive parts respectively of the current change $\Delta \underline{I}$;

R and X are the elements of the complex reference impedance \underline{Z} (see Figure 1).

The relative voltage change is given by:

$$"d" = \Delta U / U_n \quad (4)$$

4.2 Assessment of the short-term flicker value, P_{st}

The short-term flicker value P_{st} is defined in IEC 61000-4-15.

Table 1 shows alternative methods for evaluating P_{st} , due to voltage fluctuations of different types:

Table 1 – Assessment method

Types of voltage fluctuations	Methods of evaluation P_{st}
All voltage fluctuations (on-line evaluation)	Direct measurement
All voltage fluctuations where $U(t)$ is defined	Simulation Direct measurement
Voltage change characteristics according to Figures 5 to 7 with an occurrence rate less than 1 per second	Analytical method Simulation Direct measurement
Rectangular voltage change at equal intervals	Use of the $P_{st} = 1$ curve of Figure 4

4.2.1 Flickermeter

All types of voltage fluctuations may be assessed by direct measurement using a flickermeter which complies with the specification given in IEC 61000-4-15, and is connected as described in Clause 6 of this part. This is the reference method for application of the limits.

4.2.2 Simulation method

In the case where the relative voltage change characteristic $d(t)$ is known, P_{st} can be evaluated using a computer simulation.

4.2.3 Analytical method

For voltage change characteristics of the types shown in Figures 5, 6 and 7, the P_{st} value can be evaluated by an analytical method using equations (5) and (6).

NOTE 1 The value of P_{st} obtained using this method is expected to be within $\pm 10\%$ of the result which would be obtained by direct measurement (reference method).

NOTE 2 This method is not recommended if the time duration between the end of one voltage change and the start of the next is less than 1 s.

4.2.3.1 Description of the analytical method

Each relative voltage change characteristic shall be expressed by a flicker impression time, t_f , in seconds:

$$t_f = 2,3 (F \cdot d_{\max})^{3,2} \quad (5)$$

- the maximum relative voltage change d_{\max} is expressed as a percentage of the nominal voltage;
- the shape factor, F , is associated with the shape of the voltage change characteristic (see 4.2.3.2).

The sum of the flicker impression times, Σt_f , of all evaluation periods within a total interval of the length T_p , in seconds, is the basis for the P_{st} evaluation. If the total time interval T_p is chosen according to 6.5, it is an "observation period", and:

$$P_{st} = (\Sigma t_f / T_p)^{1/3,2} \quad (6)$$

4.2.3.2 Shape factor

The shape factor, F , converts a relative voltage change characteristic $d(t)$ into a flicker equivalent relative step voltage change ($F \cdot d_{\max}$).

NOTE 1 The shape factor, F , is equal to 1,0 for step voltage changes.

NOTE 2 The relative voltage change characteristic may be measured directly (see Figure 1) or calculated from the r.m.s. current of the equipment under test (see equations (1) to (4)).

The relative voltage change characteristic shall be obtained from a histogram of $U(t)$ (see Figure 3).

The shape factor may be deduced from Figures 5, 6 and 7, provided that the relative voltage change characteristic matches a characteristic shown in the Figures. If the characteristics match, proceed as follows:

- find the maximum relative voltage change d_{\max} (according to Figure 3); and
- find the time T (ms) appropriate to the voltage change characteristic as shown in Figures 5, 6 and 7 and, using this value, obtain the required shape factor, F .

NOTE 3 Extrapolation outside the range of the Figures may lead to unacceptable errors.

4.2.4 Use of $P_{st} = 1$ curve

In the case of rectangular voltage changes of the same amplitude " d " separated by equal time intervals, the curve of Figure 4 may be used to deduce the amplitude corresponding to $P_{st} = 1$ for a particular rate of repetition; this amplitude is called d_{lim} . The P_{st} value corresponding to the voltage change " d " is then given by $P_{st} = d/d_{lim}$.

4.3 Assessment of long-term flicker value, P_{lt}

The long-term flicker value P_{lt} is defined in IEC 61000-4-15 and shall be applied with the value of $N = 12$ (see 6.5).

It is generally necessary to assess the value of P_{lt} for equipment which is normally operated for more than 30 min at a time.

5 Limits

The limits shall be applicable to voltage fluctuations and flicker at the supply terminals of the equipment under test, measured or calculated according to Clause 4 under test conditions described in Clause 6 and Annex A. Tests made to prove compliance with the limits are considered to be type tests.

The following limits apply:

- the value of P_{st} shall not be greater than 1,0;
- the value of P_{lt} shall not be greater than 0,65;
- the value of $d(t)$ during a voltage change shall not exceed 3,3 % for more than 500 ms;
- the relative steady-state voltage change, d_c , shall not exceed 3,3 %;
- the maximum relative voltage change d_{\max} , shall not exceed
 - a) 4 % without additional conditions;
 - b) 6 % for equipment which is:
 - switched manually, or
 - switched automatically more frequently than twice per day, and also has either a delayed restart (the delay being not less than a few tens of seconds), or manual restart, after a power supply interruption.