

TECHNICAL REPORT



**Multicore and symmetrical pair/quad cables for digital communications –
Part 1-2: Electrical transmission characteristics and test methods of
Symmetrical pair/quad cables**

IEC TR 61156-1-2:2009

<https://standards.iteh.ai/cou/standards/iec/27/d6af8-ad7c-4197-9ada-183c0a50c982/iec-tr-61156-1-2-2009>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2014 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 14 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 55 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

IEC TR 61156-1-2:2009

<https://standards.iteh.ai/catalog/standards/iec/27746af8-ad7c-4197-9ada-183c0a50c982/iec-tr-61156-1-2-2009>

TECHNICAL REPORT



**Multicore and symmetrical pair/quad cables for digital communications –
Part 1-2: Electrical transmission characteristics and test methods of
Symmetrical pair/quad cables**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.120.20

ISBN 978-2-8322-1857-0

Warning! Make sure that you obtained this publication from an authorized distributor.

Withdrawn

iTech Standards
(<https://standards.itech.ai>)
Document Preview

[IEC TR 61156-1-2:2009](https://standards.itech.ai/iec-tr-61156-1-2-2009)

<https://standards.itech.ai/iec-tr-61156-1-2-2009>

REDLINE VERSION



**Multicore and symmetrical pair/quad cables for digital communications –
Part 1-2: Electrical transmission characteristics and test methods of
Symmetrical pair/quad cables**

IEC TR 61156-1-2:2009

<https://standards.iteh.ai/cou/standards/iec/27/d6af8-ad7c-4197-9ada-183c0a50c982/iec-tr-61156-1-2-2009>

CONTENTS

FOREWORD.....	5
1 Scope.....	7
2 Normative references	7
3 Terms, definitions, symbols, units and abbreviated terms	7
3.1 Terms and definitions	7
3.2 Symbols, units and abbreviated terms	8
4 Basic transmission line equations.....	11
4.1 Introduction	11
4.2 Characteristic impedance and propagation coefficient equations.....	11
4.2.1 General	11
4.2.2 Propagation coefficient.....	11
4.2.3 Characteristic impedance	12
4.2.4 Phase and group velocity	13
4.3 High frequency representation of secondary parameters.....	14
4.4 Frequency dependence of the primary and secondary parameters	15
4.4.1 Resistance	15
4.4.2 Inductance.....	16
4.4.3 Characteristic impedance.....	16
4.4.4 Attenuation coefficient.....	16
4.4.5 Phase delay and group delay.....	17
5 Measurement of characteristic impedance.....	18
5.1 General.....	18
5.2 Open/short circuit single-ended impedance measurement made with a balun (reference method).....	19
5.2.1 Principle.....	19
5.2.2 Test equipment.....	20
5.2.3 Procedure.....	20
5.2.4 Expression of results	21
5.3 Function fitting the impedance magnitude and angle	21
5.3.1 General.....	21
5.3.2 Impedance magnitude	21
5.3.3 Function fitting the angle of the characteristic impedance.....	23
5.4 Characteristic impedance determined from measured phase coefficient and capacitance.....	23
5.4.1 General	23
5.4.2 Equations for all frequencies case and for high frequencies.....	24
5.4.3 Procedure for the measurement of the phase coefficient	24
5.4.4 Phase delay	26
5.4.5 Phase velocity.....	26
5.4.6 Procedure for the measurement of the capacitance	26
5.5 Determination of characteristic impedance using the terminated measurement method.....	26
5.6 Extended open/short circuit method using a balun but excluding the balun performance.....	27
5.6.1 Test equipment and cable-end preparation	27
5.6.2 Basic equations	27

5.6.3	Measurement principle	27
5.7	Extended open/short circuit method without using a balun	29
5.7.1	Basic equations and circuit diagrams	29
5.7.2	Measurement principle	31
5.8	Open/short impedance measurements at low frequencies with a balun	32
5.9	Characteristic impedance and propagation coefficient obtained from modal decomposition technique	33
5.9.1	General	33
5.9.2	Procedure	34
5.9.3	Measurement principle	34
5.9.4	Scattering matrix to impedance matrix	36
5.9.5	Expression of results	38
6	Measurement of return loss and structural return loss	38
6.1	General	38
6.2	Principle	38
7	Propagation coefficient effects due to periodic structural variation related to the effects appearing in the structural return loss	39
7.1	General	39
7.2	Equation for the forward echoes caused by periodic structural inhomogeneities	39
8	Unbalance attenuation	40
8.1	General	40
8.2	Unbalance attenuation near end and far end	41
8.3	Theoretical background	43
9	Balunless test method	46
9.1	Overall test arrangement	46
9.1.1	Test instrumentation	46
9.1.2	Measurement precautions	47
9.1.3	Mixed mode S-parameter nomenclature	47
9.1.4	Coaxial cables and interconnect for network analysers	48
9.1.5	Reference loads for calibration	49
9.1.6	Calibration	49
9.1.7	Termination loads for termination of conductor pairs	50
9.1.8	Termination of screens	51
9.2	Cabling and cable measurements	52
9.2.1	Insertion loss and EL TCTL	52
9.2.2	NEXT	53
9.2.3	ACR-F	55
9.2.4	Return loss and TCL	57
9.2.5	PS alien near-end crosstalk (PS ANEXT-Exogenous crosstalk)	59
9.2.6	PS attenuation to alien crosstalk ratio, far-end crosstalk (PS AACR-F-Exogenous crosstalk)	62
Annex A (informative) Example derivation of mixed mode parameters using the modal decomposition technique		66
Bibliography		69
Figure 1 – Secondary parameters extending from 1 kHz to 1 GHz		18
Figure 2 – Diagram of cable pair measurement circuit		20

Figure 3 – Determining the multiplier of 2π radians to add to the phase measurement	25
Figure 4 – Measurement configurations	28
Figure 5 – Measurement principle with four terminal network theory	28
Figure 6 – Admittance measurement configurations	31
Figure 7 – Admittance measurement principle	31
Figure 8 – Transmission line system	35
Figure 9 – Differential-mode transmission in a symmetric pair	41
Figure 10 – Common-mode transmission in a symmetric pair	41
Figure 11 – Circuit of an infinitesimal element of a symmetric pair	43
Figure 12 – Calculated coupling transfer function for a capacitive coupling of 0,4 pF/m and random $\pm 0,4$ pF/m ($\ell = 100$ m; $\varepsilon_{r1} = \varepsilon_{r2} = 2,3$)	45
Figure 13 – Measured coupling transfer function of 100 m Twinax 105 Ω	46
Figure 14 – Diagram of a single-ended 4-port device	47
Figure 15 – Diagram of a balanced 2-port device	48
Figure 16 – Possible solution for calibration of reference loads	49
Figure 17 – Resistor termination networks	50
Figure 18 – Insertion loss and EL TCTL measurement	53
Figure 19 – NEXT measurement	55
Figure 20 – FEXT measurement	57
Figure 21 – Return loss and TCL measurement	59
Figure 22 – Alien NEXT measurement	61
Figure 23 – Alien FEXT	64
Figure A.1 – Voltage and current on balanced DUT	66
Figure A.2 – Voltage and current on unbalanced DUT	67
Table 1 – Unbalance attenuation at near end	42
Table 2 – Unbalance attenuation at far end	42
Table 3 – Measurement set-up	42
Table 4 – Mixed mode S-parameter nomenclature	48
Table 5 – Requirements for terminations at calibration plane	51

INTERNATIONAL ELECTROTECHNICAL COMMISSION

MULTICORE AND SYMMETRICAL PAIR/QUAD CABLES FOR DIGITAL COMMUNICATIONS –

Part 1-2: Electrical transmission characteristics and test methods of symmetrical pair/quad cables

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.

IEC TR 61156-1-2 edition 1.1 contains the first edition (2009-05) [documents 46C/853/DTR and 46C/889/RVC] and its amendment 1 (2014-09) [documents 46C/993/DTR and 46C/1000/RVC].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions and deletions are displayed in red, with deletions being struck through. A separate Final version with all changes accepted is available in this publication.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC 61156-1-2, which is a technical report, has been prepared by subcommittee 46C: Wires and symmetric cables, of IEC technical committee 46: Cables, wires, waveguides, R.F. connectors, R.F. and microwave passive components and accessories.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the IEC 61156 series, under the general title: *Multicore and symmetrical pair/quad cables for digital communications*, can be found on the IEC website.

The committee has decided that the contents of the base publication and its amendment will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IMPORTANT – The “colour inside” logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

MULTICORE AND SYMMETRICAL PAIR/QUAD CABLES FOR DIGITAL COMMUNICATIONS –

Part 1-2: Electrical transmission characteristics and test methods of symmetrical pair/quad cables

1 Scope

This technical report is a revision of the symmetrical pair/quad electrical transmission characteristics present in IEC 61156-1:2002 (Edition 2) and not carried into IEC 61156-1:2007 (Edition 3).

This technical report includes the following topics from IEC 61156-1:2002:

- the characteristic impedance test methods and function fitting procedures of 3.3.6;
- Annex A covering basic transmission line equations and test methods;
- Annex B covering the open/short-circuit method;
- Annex C covering unbalance attenuation.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-726, *International Electrotechnical Vocabulary – Part 726: Transmission lines and waveguides*

IEC 60169-15, *Radio-frequency connectors – Part 15: R.F. coaxial connectors with inner diameter of outer conductor 4,13 mm (0,163 in) with screw coupling – Characteristic impedance 50 ohms (Type SMA)*

IEC 61156-1:2007, *Multicore and symmetrical pair/quad cables for digital communications – Part 1: Generic specification*

IEC 61169-16, *Radio-frequency connectors – Part 16: Sectional specification – RF coaxial connectors with inner diameter of outer conductor 7 mm (0,276 in) with screw coupling – Characteristics impedance 50 ohms (75 ohms) (type N)*

IEC/TR 62152, *Background of terms and definitions of cascaded two-ports*

3 Terms, definitions, symbols, units and abbreviated terms

3.1 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-726 ~~and~~, IEC TR 62152 ~~and the following~~ apply:

3.1.1

single-ended

measurement with respect to a fixed potential, usually ground

3.2 Symbols, units and abbreviated terms

For the purposes of this document, the following symbols, units and abbreviated terms apply.

Transmission line equation electrical symbols and related terms and symbols:

R	pair resistance (Ω/m)
L	pair inductance (H/m)
G	pair conductance (S/m)
C	pair capacitance (F/m)
α	attenuation coefficient (Np/m)
β	phase coefficient (rad/m)
γ	propagation coefficient (Np/m , rad/m)
v_P	phase velocity of cable (m/s)
v_G	group velocity of cable (m/s)
τ_P	phase delay time (s/m)
τ_G	group delay time (s/m)
Z_C	complex characteristic impedance, or mean characteristic impedance if the pair is homogeneous or free of structure (also used to represent a function fitted result) (Ω)
$\angle Z_C$	angle of the characteristic impedance in radians
Z_∞	high frequency asymptotic value of the characteristic impedance (Ω)
l	length (m)
j	imaginary denominator
Re	real part operator for a complex variable
Im	imaginary part operator for a complex variable
ω	radian frequency (rad/s)
f	frequency (Hz)
R'	first derivative of R with respect to ω
C'	first derivative of C with respect to ω
L'	first derivative of L with respect to ω
R_0	d.c. resistance of a round solid wire with radius r (Ω/m)
R_C	constant with frequency component of resistance which is about 1/4 of the d.c. resistance (Ω/m)
R_S	square-root of frequency component of resistance (Ω/m)
L_E	external (free space) inductance (H/m)
L_I	internal inductance whose reactance equals the surface resistance at high frequencies (H/m)
σ	specific conductivity of the wire material (S/m)
ρ	resistivity of the wire material (Ω/m^2)
μ	permeability of the wire material (H/m)
r	radius of the wire (m)
δ	skin depth (not to be confused with the dissipation factor $\tan \delta$) (m)

$$\delta = \frac{1}{\sqrt{\pi f \mu \sigma}}$$

$\tan \delta$ dissipation factor

$$\tan \delta = G/(\omega C)$$

q forward echo coefficient at the far end of the cable at a resonant frequency

p reflection coefficient measured from the near end of the cable at a

$$\text{resonant frequency, } p = 10^{-PSRL/20} = \left| \frac{Z_{CM} - Z_C}{Z_{CM} + Z_C} \right|$$

A_Q forward echo attenuation at a resonant frequency (dB)

$$A_Q = -20 \log |q|$$

$PSRL$ structural return loss at a resonant frequency (dB)

$$PSRL = -20 \log |p|$$

K = $2\alpha l - 1$ when $2\alpha l \gg 1$ (Np)

A_Q = $2 \times PSRL - 20 \log(2\alpha l - 1)$ (dB) where $2\alpha l$ is in Np

Z_{OC} complex measured open circuit impedance (Ω)

Z_{SC} complex measured short circuit impedance (Ω)

Z_{CM} characteristic impedance as measured (with structure) (Ω)

$$Z_{CM} = \sqrt{Z_{SC} Z_{OC}}$$

Z_{MEAS} complex measured impedance (open or short) (Ω)

Z_{IN} input impedance of the cable when it is terminated by Z_L (Ω)

Z_{OUT} output impedance of the cable when the input of the cable is terminated by Z_G (Ω)

Z_{CN} nominal characteristic impedance of a cable and is the specified Z_C value at a given frequency with tolerance and the structural return loss SRL limits in dB in a frequency range (Ω)

Z_N nominal (reference) impedance of the link and/or terminals (the system) between which the cable is operating (Ω)

Z_R (nominal) reference impedance that is used in measurement. Normally (for actual return loss results), $Z_R = Z_N$. When using a return loss measurement to approximate SRL , it is practical to choose Z_R to give the best balance in the given frequency range (Ω)

Z_T terminated impedance measurement made with the opposite end of the cable pair terminated in the reference impedance Z_R (Ω)

ζ reflection coefficient measured in the terminated measurement method

$$\zeta = \frac{Z_R - Z_C}{Z_R + Z_C}$$

Z_G termination at the cable input when defining the output impedance of the cable Z_{OUT} (Ω)

Z_L	termination at the cable output when defining the input impedance of the cable Z_{IN} (Ω)
L_0, L_1, L_2, L_3	least squares fit coefficients for angle of the characteristic impedance
K_0, K_1, K_2, K_3	least squares fit coefficients of the characteristic impedance
$ Z_C $	fitted magnitude of the characteristic impedance (Ω)
$ Z_{CM} $	measured magnitude of the characteristic impedance (Ω)
$\angle(V_{1N})$	input angle relative to a reference angle in radians
$\angle(V_{1F})$	output angle relative to the same reference angle in radians
k	multiple of 2π radians
S_{11}	reflection coefficient measured with an S parameter test set
RL	return loss (dB)
SRL	structural return loss (dB)

Attenuation unbalance electrical symbols:

TA	transverse asymmetry
LA	longitudinal asymmetry
R_1, R_2	resistance of one conductor per unit length (Ω)
L_1, L_2	inductance of one conductor per unit length (H)
C_1, C_2	capacitance of one conductor to earth (F)
G_1, G_2	conductance of one conductor to earth (S)
α_u	unbalance attenuation (dB)
T_u	unbalance coupling transfer function
Z_{com}	characteristic impedance of the common-mode circuit (Ω)
Z_{diff}	characteristic impedance of the differential-mode circuit (Ω)
Z_{unbal}	unbalance impedance (Ω)
ℓ	length of transmission line (m)
x	length coordinate (m)
γ_{com}	propagation factor of the common-mode circuit (Np/m, rad/m)
γ_{diff}	propagation factor of the differential-mode circuit (Np/m, rad/m)
α_{diff}	operational differential-mode attenuation of the cable (dB)
α_{com}	operational common-mode attenuation of the cable (dB)
ΔR	resistance unbalance of the sample length (Ω)
ΔL	inductance unbalance of the sample length (H)
ΔC	capacitance unbalance to earth (F)
ΔG	conductance unbalance to earth (S)
S	summing function
U_{diff}	voltage in the differential-mode circuit (V)
U_{com}	voltage in the common-mode circuit (V)
n, f	index to designate the near end and far end, respectively