

INTERNATIONAL STANDARD



Tap-changers –
Part 1: Performance requirements and test methods

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60214-1:2014](#)

<https://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6dbda64f46a4/iec-60214-1-2014>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2014 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 14 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 55 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

[IEC 60214-1:2014](http://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6bdba64f46a4/iec-60214-1-2014)

<https://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6bdba64f46a4/iec-60214-1-2014>



IEC 60214-1

Edition 2.0 2014-05

INTERNATIONAL STANDARD



Tap-changers –
Part 1: Performance requirements and test methods

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60214-1:2014](#)

<https://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6dbda64f46a4/iec-60214-1-2014>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE **XC**

ICS 29.180

ISBN 978-2-8322-1621-7

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	6
1 Scope.....	8
2 Normative references	8
3 Terms and definitions	9
4 Service conditions	15
4.1 Temperature of tap-changer environment.....	15
4.2 Temperature of motor-drive mechanism environment.....	16
4.3 Overload conditions	16
5 Requirements for on-load tap-changers	16
5.1 General requirements	16
5.1.1 Rating.....	16
5.1.2 Compartments for diverter and selector switches	17
5.1.3 Liquid-level gauges and gas monitoring devices	17
5.1.4 Safety requirements for protection against internal failure.....	17
5.1.5 Limiting devices for the protection against transient overvoltages	18
5.1.6 Change-over selector recovery voltages	18
5.1.7 Leakage inductance in coarse fine regulation arrangements	18
5.2 Type tests.....	18
5.2.1 General	18
5.2.2 Temperature rise of contacts	19
5.2.3 Switching tests	20
5.2.4 Short-circuit current test	25
5.2.5 Transition impedance test.....	26
5.2.6 Mechanical tests.....	27
5.2.7 Tightness test.....	29
5.2.8 Dielectric tests.....	30
5.2.9 Type-test certificate	35
5.3 Routine tests	35
5.3.1 General	35
5.3.2 Mechanical test	35
5.3.3 Sequence test	35
5.3.4 Auxiliary circuits insulation test.....	35
5.3.5 Pressure and vacuum tests.....	35
6 Requirements for motor-drive mechanisms for on-load tap-changers	35
6.1 General requirements	35
6.1.1 Compliance of component parts.....	35
6.1.2 Permissible variation of auxiliary supply	36
6.1.3 Step-by-step control	36
6.1.4 Tap position indicator	36
6.1.5 Tap-change in progress indication	36
6.1.6 Limiting devices.....	36
6.1.7 Parallel control devices.....	36
6.1.8 Direction of rotation protection.....	36
6.1.9 Overcurrent blocking device	36
6.1.10 Restarting device.....	37
6.1.11 Operation counter.....	37

6.1.12	Manual operation of the motor-drive mechanism	37
6.1.13	Motor-drive cubicle	37
6.1.14	Protective device against running-through	37
6.1.15	Protection against access to hazardous parts	37
6.2	Type tests	37
6.2.1	Mechanical load test	37
6.2.2	Overrun test	38
6.2.3	Degree of protection of motor-drive cubicle	38
6.3	Routine tests	38
6.3.1	Mechanical tests	38
6.3.2	Auxiliary circuits insulation test	38
7	Requirements for de-energized tap-changers	38
7.1	General requirements	38
7.1.1	Rated characteristics	38
7.1.2	Types	39
7.1.3	Handles and drives	39
7.1.4	Glands	39
7.1.5	Interlocks	39
7.1.6	Mechanical end stops	39
7.2	Type tests	40
7.2.1	General	40
7.2.2	Temperature rise of contacts	40
7.2.3	Short-circuit current test	41
7.2.4	Mechanical tests	41
7.2.5	Dielectric tests	42
7.2.6	Type test certificate	47
7.3	Routine tests	47
7.3.1	Mechanical tests	47
7.3.2	Pressure and vacuum tests	47
8	Requirements for motor-drive mechanisms for de-energized tap-changers	47
8.1	General requirements	47
8.1.1	General	47
8.1.2	Compliance of component parts	47
8.1.3	Permissible variation of auxiliary supply	47
8.1.4	Tap position indicator	47
8.1.5	Limiting devices	48
8.1.6	Operation counter	48
8.1.7	Manual operation of the motor-drive mechanism	48
8.1.8	Motor-drive cubicle	48
8.1.9	Protection against access to hazardous parts	48
8.2	Type tests	48
8.2.1	Mechanical load test	48
8.2.2	Overrun test	49
8.2.3	Degree of protection of motor-drive cubicle	49
8.3	Routine tests	49
8.3.1	Mechanical tests	49
8.3.2	Auxiliary circuits insulation test	49
9	Nameplate	49
9.1	Tap-changers (on-load and de-energized)	49

9.2	Motor-drive mechanisms	50
10	De-energized tap-changer warning label.....	50
11	Manufacturers operating instructions	51
Annex A (normative) Supplementary information on switching duty on main and transition contacts relating to resistor type tap-changers.....		52
Annex B (normative) Supplementary information on switching duty relating to reactor type tap-changers		58
B.1	Additional test parameters	58
B.1.1	Service duty test.....	58
B.1.2	Breaking capacity test	58
B.2	Duty of switching contacts	58
Annex C (normative) Method for determining the equivalent temperature of the transition resistor using power pulse current		69
Annex D (informative) Simulated a.c. circuits for service duty and breaking capacity tests		70
D.1	General.....	70
D.2	Transformer method.....	70
D.3	Resistance method	71
Annex E (informative) Example of a synthetic test circuit for service duty test of vacuum type tap-changers		73
E.1	Definitions with relevance to the synthetic test circuit.....	73
E.1.1	Synthetic test circuit	73
E.1.2	Simulated a.c. test circuit.....	73
E.1.3	Pre-arc	73
E.1.4	Making voltage	73
E.2	Example for the test setup of a synthetic test circuit.....	73
E.3	Example for the breaking/making condition during a switching operation.....	74
Bibliography.....		76

Figure 1	– Short-circuit test current (r.m.s. value) as a multiple of the maximum rated through-current (on-load tap-changer)	25
Figure 2	– Time sequence for the application of test voltage (on-load tap-changer).....	34
Figure 3	– Short-circuit test current (r.m.s. value) as a multiple of the maximum rated through-current (de-energized tap-changer).....	41
Figure 4	– Time sequence for the application of test voltage (de-energized tap-changer)	46
Figure 5	– Warning label (example)	50
Figure A.1	– Examples of current and voltage vectors for resistor type tap-changers	53
Figure B.1	– Operating sequence of reactor type tap-changers with selector switch.....	59
Figure B.2	– Current and voltage vectors for reactor type tap-changers with selector switch	60
Figure B.3	– Operating sequence of reactor type tap-changers with selector switch and equalizer windings	61
Figure B.4	– Current and voltage vectors for reactor type tap-changers with selector switch and equalizer windings.....	62
Figure B.5	– Operating sequence of a reactor type tap-changer with diverter switch and tap selector	64
Figure B.6	– Current and voltage vectors for reactor type tap-changers with diverter switch and tap selector	65

Figure B.7 – Operating sequence of a reactor type tap-changer with vacuum interrupter and tap selector	67
Figure B.8 – Current and voltage vectors for reactor type tap-changers with vacuum interrupter and tap selector	68
Figure D.1 – Simulated test circuit – Transformer method	70
Figure D.2 – Simulated test circuit – Resistance method	71
Figure E.1 – Synthetic test circuit for service duty test of vacuum type tap-changers	73
Figure E.2 – Currents of the synthetic test circuit	74
Figure E.3 – Example of the synthetic test for a switching operation with equal voltages for breaking and making duty	74
Table 1 – Temperature of tap-changer environment	16
Table 2 – Contact temperature-rise limits for on-load tap-changers	19
Table 3 – Test voltage levels for on-load tap-changers	30
Table 4 – Contact temperature-rise limits for de-energized tap-changers	40
Table 5 – Test voltage levels for de-energized tap-changers	43
Table A.1 – Duty of main and transition contacts for resistor type tap-changers (non-vacuum type)	54
Table A.2 – Effect of load power-factor on circuit-breaking duty for resistor type tap-changers (non-vacuum type)	55
Table A.3 – Duty of main and transition contacts for resistor type tap-changers (vacuum type) (1 of 2)	56
Table B.1 – Duty of switching contacts for reactor type tap-changers with selector switch – Switching direction from P1 to P5	59
Table B.2 – Duty of switching contacts for reactor type tap-changers with selector switch and equalizer windings – Switching direction from P1 to P5	61
Table B.3 – Duty of switching contacts for reactor type tap-changers with diverter switch and tap selector – Switching direction from P1 to P7	63
Table B.4 – Duty of switching contacts for reactor type tap-changers with vacuum interrupter and tap selector – Switching direction from P1 to P11	66

INTERNATIONAL ELECTROTECHNICAL COMMISSION

TAP-CHANGERS –

Part 1: Performance requirements and test methods

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60214-1 has been prepared by IEC technical committee 14: Power transformers.

This second edition cancels and replaces the first edition published in 2003. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- incorporation of requirements on vacuum type on-load tap-changers,
- incorporation of requirements on gas insulated tap-changers,
- changes in the type tests to fit with the service conditions,
- reference to the newest edition of IEC 60076-3:2013.

The text of this standard is based on the following documents:

CDV	Report on voting
14/746/CDV	14/767A/RVC

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 60214 series, published under the general title *Tap-changers*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

IEC 60214-1:2014

<https://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6dbda64f46a4/iec-60214-1-2014>

TAP-CHANGERS –

Part 1: Performance requirements and test methods

1 Scope

This part of IEC 60214 applies to on-load tap-changers of both resistor and reactor types, de-energized tap-changers, and their motor-drive mechanisms.

It applies mainly to tap-changers immersed in mineral insulating oil according to IEC 60296 but may also be used for tap-changers with air or gas insulation or immersed in other insulating liquids insofar as conditions are applicable.

It applies mainly to tap-changers with arcing contacts but may also be used for arcing-free on-load tap-changers (such as electronic switching) insofar as conditions are applicable.

This part of IEC 60214 applies to power and distribution transformers of all types and also to reactors.

It does not apply to transformers and reactors mounted on railway rolling stock.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050 (all parts), *International Electrotechnical Vocabulary* (available at <http://www.electropedia.org>)

IEC 60050-421, *International Electrotechnical Vocabulary – Chapter 421: Power transformers and reactors*

IEC 60060-1, *High voltage test techniques – Part 1: General definitions and test requirements*

IEC 60076-3:2013, *Power transformers – Part 3: Insulation levels, dielectric tests and external clearances in air*

IEC 60076-7:2005, *Power transformers – Part 7: Loading guide for oil-immersed power transformers*

IEC 60076-21:2011, *Power transformers – Part 21: Standard requirements, terminology, and test code for step-voltage regulators*

IEC 60137:2008, *Insulated bushings for alternating voltages above 1 000 V*

IEC 60214-2:2004, *Tap-changers – Part 2: Application guide*

IEC 60270, *High-voltage test techniques – Partial discharge measurements*

IEC 60296, *Fluids for electrotechnical applications – Unused mineral insulating oils for transformers and switchgear*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-421 as well as the following apply.

3.1

on-load tap-changer

OLTC

device for changing the tap connections of a winding, suitable for operation while the transformer is energized or on load

Note 1 to entry: On-load tap-changers are sometimes called load tap-changers (LTC).

3.2

non-vacuum type on-load tap-changer

on-load tap-changer with contacts that break and make the load and circulating currents and where the arcing takes place in a liquid or gas, the tap-changer itself being placed in liquid or gas

Note 1 to entry: This definition does not apply to arcing-free on-load tap-changers.

3.3

vacuum type on-load tap-changer

on-load tap-changer where vacuum interrupters (VI) break and make the load and circulating currents, the tap-changer itself being placed in a different medium such as liquid or gas

3.4

tap selector

device designed to carry, but not to make or break, current, used in conjunction with a diverter switch to select tap connections

3.5

diverter switch

switching device used in conjunction with a tap selector to carry, make and break currents in circuits which have already been selected

Note 1 to entry: Diverter switches are sometimes called arcing switches.

3.6

selector switch

switching device capable of carrying, making and breaking current, combining the duties of a tap selector and a diverter switch

Note 1 to entry: Selector switches are sometimes called arcing tap switches.

Note 2 to entry: In non-vacuum type selector switches the selection of tap connections (tap selector duty) and the diversion of the through-current (diverter switch duty) are carried out by the same contacts.

Note 3 to entry: In vacuum type selector switches the selection of tap connections (tap selector duty) and the diversion of the through-current (diverter switch duty) are carried out by different contacts.

3.7**de-energized tap-changer****DETC**

device for changing the tap connections of a winding, suitable for operation only while the transformer is de-energized (isolated from the system)

Note 1 to entry: De-energized tap-changers are sometimes called off-circuit tap-changers.

Note 2 to entry: De-energized tap-changers are sometimes abbreviated as DTC.

3.8**change-over selector**

device designed to carry, but not to make or break, through-current, used in conjunction with the tap selector or selector switch to enable its contacts and the connected taps to be used more than once when moving from one extreme position to the other

3.9**coarse change-over selector**

change-over selector connecting the tap winding to either the main winding or the coarse winding or parts thereof

3.10**reversing change-over selector**

change-over selector connecting either end of the tap winding to the main winding

3.11**transition impedance**

resistor or reactor consisting of one or more units bridging the tap in use and the tap next to be used, for the purpose of transferring load from one tap to the other without interruption or appreciable change in the load current, at the same time limiting the circulating current for the period that both taps are used

Note 1 to entry: For reactor type tap-changers, the transition impedance (reactor) is commonly called a preventive auto transformer. Reactor type tap-changers normally use the bridging position as a service position (mid-point or centre tapped reactor tap-changers) and, therefore, the reactor is designed for continuous operation.

3.12**preventive auto transformer**

auto transformer (or centre tapped reactor) used in on-load tap-changing and regulating transformers, or step voltage regulators to limit the circulating current when operating on a position in which two adjacent taps are bridged, or during the change of tap between adjacent positions

3.13**equalizer winding**

winding on the same magnetic circuit (core) as the excitation and tap winding of a reactor type regulating transformer with approximately half the number of turns of each tap section

3.14**drive mechanism**

means by which the drive to the tap-changer is actuated

Note 1 to entry: The mechanism may include an independent means of storing energy to control the operation.

3.15**set of contacts**

pair of individual fixed and moving contacts or a combination of such pairs operating substantially simultaneously

3.16

diverter switch and selector switch main contacts <of a resistor type tap-changer>
set of through-current carrying contacts which usually by-passes the main switching contact and only commutates any current (sparking often occurs)

3.17

diverter switch and selector switch main switching contacts <of a resistor type tap-changer>
set of contacts which has no transition resistor between the transformer winding and the contacts and makes and breaks current (arcing will occur)

Note 1 to entry: In case of vacuum type tap-changers, these contact systems are replaced by vacuum interrupters.

3.18

diverter switch and selector switch transition contacts, <of a resistor type tap-changer>
set of contacts which is connected in series with a transition resistor and makes or breaks current (arcing will occur)

Note 1 to entry: In case of vacuum type tap-changers, these contact systems are replaced by vacuum interrupters.

3.19

transfer contacts <of a reactor type tap-changer>
set of contacts that makes or breaks current

Note 1 to entry: Where by-pass contacts are not provided, the transfer contact is a continuous current-carrying contact.

3.20

by-pass contacts <of a reactor type tap-changer>
set of through-current carrying contacts that commutates the current to the transfer contacts without any arc (sparking may occur)

<https://standards.iteh.ai/>

<http://standards.iteh.ai/catalog/standards/iec/eb0e50cf-4150-4b77-ba1f-6dbda64f46a4/iec-60214-1-2014>

3.21
bridging position

position of a reactor type tap-changer with the selector and transfer contacts being on two adjacent taps and with the output terminal being electrically in the middle between two adjacent taps

3.22**non-bridging position**

position of a reactor type tap-changer with the selector and transfer contacts being on the same tap

3.23**circulating current**

that part of the current that flows through the transition impedance at the time when two taps are momentarily bridged during a tap-change operation for a resistor type tap-changer or when bridged in an operating position for a reactor type tap-changer

Note 1 to entry: The circulating current is due to the voltage difference between the taps.

3.24**switched current**

prospective current to be broken during switching operation by each set of main switching or transition contacts (resistor type tap-changer) or transfer contacts (reactor type tap-changer) incorporated in the diverter switch or the selector switch

3.25**recovery voltage**

power-frequency voltage which appears across each set of main switching or transition contacts (resistor type tap-changer) or transfer contacts (reactor type tap-changer) of the diverter switch or selector switch after these contacts have broken the switched current

3.26**tap-change operation**

complete sequence of events from the initiation to the completion of a tap-change from one service tap position to an adjacent position

3.27**cycle of operation**

movement of the tap-changer from one end of its range to the other end and the return to its original position

3.28**rated insulation level**

withstand values of the impulse and applied voltages to earth, and where appropriate between phases, and between those parts where insulation is required

3.29**rated through-current** I_r

current flowing through an on-load tap-changer towards the external circuit, which the apparatus is capable of transferring from one tap to the other at the relevant rated step voltage and which can be carried continuously while meeting the requirements of this standard

3.30**maximum rated through-current** I_{rm}

highest rated through-current for which the tap-changer is designed for and all the current related tests are based on

3.31**rated step voltage** U_{ir}

for each value of rated through-current, the highest permissible voltage between terminals which are intended to be connected to successive taps of the transformer

3.32**relevant rated step voltage**

highest step voltage permitted in connection with a given rated through-current

3.33**maximum rated step voltage** U_{irm}

highest value of the rated step voltage for which the tap-changer is designed

3.34**rated frequency**

frequency of the alternating current for which the tap-changer is designed

3.35**number of inherent tap positions**

highest number of tap positions for half a cycle of operation for which a tap-changer can be used according to its design