

TECHNICAL REPORT



INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE

**Radio interference characteristics of overhead power lines and high-voltage equipment –
Part 1: Description of phenomena**

[CISPR TR 18-1:2017](https://standards.iteh.ai/)

<https://standards.iteh.ai/catalog/standards/iec/c44a3f08-6b2d-46d9-8215-21f4b1f1092f/cispr-tr-18-1-2017>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2017 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing 21 000 terms and definitions in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

[CISPR TR 18-1:2017](https://standards.iteh.ai/CISPR/TR/18-1-2017)

<https://standards.iteh.ai/catalog/standards/iec/c44a3f08-6b2d-46d9-8215-21f4b1f1092f/cispr-tr-18-1-2017>



TECHNICAL REPORT



INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE

**Radio interference characteristics of overhead power lines and high-voltage equipment –
Part 1: Description of phenomena**

Document Preview

[CISPR TR 18-1:2017](https://standards.iteh.ai/CISPR-TR-18-1-2017)

<https://standards.iteh.ai/catalog/standards/iec/c44a3f08-6b2d-46d9-8215-21f4b1f1092f/cispr-tr-18-1-2017>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.100.01

ISBN 978-2-8322-4998-7

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	2
1 Scope.....	9
2 Normative references	9
3 Terms and definitions	9
4 Radio noise from HV AC overhead power lines.....	10
4.1 General.....	10
4.2 Physical aspects of radio noise	11
4.2.1 Mechanism of formation of a noise field.....	11
4.2.2 Definition of noise.....	13
4.2.3 Influence of external parameters.....	14
4.3 Main characteristics of the noise field resulting from conductor corona	14
4.3.1 General	14
4.3.2 Frequency spectrum	14
4.3.3 Lateral profile	15
4.3.4 Statistical distribution with varying seasons and weather conditions	17
5 Effects of corona from conductors	18
5.1 Physical aspects of corona from conductors	18
5.1.1 General.....	18
5.1.2 Factors in corona generation	19
5.2 Methods of investigation of corona by cages and test lines	20
5.2.1 General	20
5.2.2 Test cages.....	20
5.2.3 Test lines.....	21
5.3 Methods of predetermination.....	22
5.3.1 General	22
5.3.2 Analytical methods	22
5.3.3 CIGRÉ method	22
5.4 Catalogue of standard profiles	23
5.4.1 General	23
5.4.2 Principle of catalogue presentation	23
6 Radio noise levels due to insulators, hardware and substation equipment (excluding bad contacts).....	25
6.1 Physical aspects of radio noise sources.....	25
6.1.1 General	25
6.1.2 Radio noise due to corona discharges at hardware.....	25
6.1.3 Radio noise due to insulators.....	25
6.2 Correlation between radio noise voltage and the corresponding field strength for distributed and individual sources	27
6.2.1 General	27
6.2.2 Semi-empirical approach and equation	27
6.2.3 Analytical methods	29
6.2.4 Example of application.....	30
6.3 Influence of ambient conditions.....	30
7 Sparking due to bad contacts	30
7.1 Physical aspects of the radio noise phenomenon	30

7.2	Example of gap sources.....	32
8	Special d.c. effects Radio noise from HVDC overhead power lines	32
8.1	General [56, 57].....	32
8.1.1	Description of electric field physical phenomena of HVDC transmission systems.....	32
8.1.2	Description of radio interference phenomena of HVDC transmission system.....	33
8.2	Effects of corona from conductors Physical aspects of DC corona	34
8.3	Formation mechanism of a noise field from a DC line.....	34
8.4	Characteristics of the radio noise from DC lines.....	35
8.4.1	General	35
8.4.2	Frequency spectrum	35
8.4.3	Lateral profile	35
8.4.4	Statistical distribution	35
8.5	Factors influencing the radio noise from DC lines	36
8.5.1	General	36
8.5.2	Conductor surface conditions.....	36
8.5.3	Conductor surface gradient.....	37
8.5.4	Polarity.....	37
8.5.5	Weather conditions.....	37
8.5.6	Subjective effects.....	39
8.6	Calculation of the radio noise level due to conductor corona.....	39
8.7	Radio noise due to insulators, hardware and substation equipment.....	41
8.8	Valve firing effects	41
9	Figures.....	32
	Annex A (informative) Calculation of the voltage gradient at the surface of a conductor of an overhead line	55
	Annex B (informative) Catalogue of profiles of radio noise field due to conductor corona for certain types of power line	59
	Annex C (informative) Summary of the catalogue of radio noise profiles according to the recommendations of the CISPR	75
	Bibliography.....	77
	Figure 1 – Typical lateral attenuation curves for high voltage lines, normalized to a lateral distance of $y_0 = 15$ m, distance in linear scale	43
	Figure 2 – Typical lateral attenuation curves for high voltage lines, normalized to a direct distance of $D_0 = 20$ m, distance in logarithmic scale	44
	Figure 3 – Examples of statistical yearly distributions of radio-noise levels recorded continuously under various overhead lines.....	45
	Figure 4 – Examples of statistical yearly distributions of radio-noise levels recorded continuously under various overhead lines.....	46
	Figure 5 – Example of statistical yearly distributions of radio-noise levels recorded continuously under various overhead lines.....	47
	Figure 6 – Examples of statistical yearly distributions of radio-noise levels recorded continuously under various overhead lines.....	48
	Figure 7 – Equipotential lines for clean and dry insulation units	49
	Figure 8 – Determination of the magnetic field strength from a perpendicular to a section of a line, at a distance x from the point of injection of noise current I	49
	Figure 9 – Longitudinal noise attenuation versus distance from noise source (from test results of various experiments frequencies around 0,5 MHz).....	50

Figure 10 – Lateral profile of the radio noise field strength produced by distributed discrete sources on a 420 kV line of infinite length.....	51
Figure 11 – Impulsive radio-noise train of gap-type discharges	52
Figure 12 – Example of relative strength of radio noise field as a function of frequency below 1 GHz using QP detector	52
Figure 13 – Example of relative strength of radio noise field due to gap discharge as a function of frequency 200 MHz to 3 GHz using peak detector	53
Figure 14 – Example of relative strength of radio noise field as a function of the distance from the line.....	53
Figure 15 – Unipolar and bipolar space charge regions of a HVDC transmission line	54
Figure 16 – The corona current and radio interference field	54
Figure B.1 – Triangular formation (1)	60
Figure B.2 – Triangular formation (2)	61
Figure B.3 – Flat formation	62
Figure B.4 – Arched formation	63
Figure B.5 – Flat wide formation	64
Figure B.6 – Vertical formation (480 (Rail) X 4B)	65
Figure B.7 – Flat formation	66
Figure B.8 – Flat formation	67
Figure B.9 – Arched formation	68
Figure B.10 – Flat formation	69
Figure B.11 – Arched formation	70
Figure B.12 – Flat formation	71
Figure B.13 – Vertical formation (480 (Cardinal) X 6B).....	72
Figure B.14 – Typical frequency spectra for the radio noise fields of high voltage power lines	73
Figure B.15 – Prediction of radio noise level of a transmission line for various types of weather	74
Figure C.1 – Examples of transformations of the profiles of Figures B.1 to B.13 using the direct distance of 20 m as reference	76
Table B.1 – List of profiles	59
Table C.1 – Radio noise profiles	75

INTERNATIONAL ELECTROTECHNICAL COMMISSION
INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE

**RADIO INTERFERENCE CHARACTERISTICS
OF OVERHEAD POWER LINES AND
HIGH-VOLTAGE EQUIPMENT –**

Part 1: Description of phenomena

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

CISPR 18-1, which is a technical report, has been prepared by CISPR subcommittee B: Interference relating to industrial, scientific and medical radio-frequency apparatus, to other (heavy) industrial equipment, to overhead power lines, to high voltage equipment and to electric traction.

This third edition cancels and replaces the second edition published in 2010. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) updated description of the RF characteristics of spark discharges which might contain spectral radio noise components up to the GHz frequency range;
- b) addition of state of the art in HVDC converter technology

The text of this technical report is based on the following documents:

DTR	Report on voting
CIS/B/653/DTR	CIS/B/674/RVDTR

Full information on the voting for the approval of this technical report can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the CISPR 18 series can be found, under the general title *Radio interference characteristics of overhead power lines and high-voltage equipment*, on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

This Technical Report is the first of a three-part series dealing with radio noise generated by electrical power transmission and distribution facilities (overhead lines and substations). It contains information in relation of the physical phenomena involved in the generation of electromagnetic noise fields. It also includes a description of the main properties of such fields and their numerical values. Its content was adjusted such as to allow for use of the lateral distance y for the establishment of standard profiles for the lateral radio noise field emanating from HV overhead power lines.

The technical data given in this Part 1 of the CISPR 18 series are intended to be a useful aid to overhead line designers and also to anyone concerned with checking the radio noise performance of a line to ensure satisfactory protection of wanted radio signals. The data should facilitate the use of the recommendations given in its Parts 2 and 3 dealing with

- methods of measurement and procedures for determining limits, and a
- code of practice for minimizing the generation of radio noise.

The CISPR 18 series does not deal with biological effects on living matter or any issues related to exposure to electromagnetic fields.

This document has been prepared in order to provide information on the many factors involved in protecting the reception of radio, especially (but not limited to) analogue television, and digital terrestrial television broadcasting, hereafter denominated as digital television broadcasting, from interference due to background noise generated by AC and DC high voltage overhead power lines, distribution lines, and associated equipment. The information given should be of assistance when means of avoiding or abating radio noise are being considered.

Information is mainly given on the generation and characteristics of radio noise from AC power lines and equipment operating at 1 kV and above, in the frequency ranges 0,15 MHz to 30 MHz (a.m. sound broadcasting), 30 MHz to 300 MHz (f.m. sound broadcasting, analogue television broadcasting) and in the range 470 MHz to 950 MHz (digital television broadcasting). The special aspect of spark discharges due to bad contacts or defects is taken into account. Information is also given on interference due to DC overhead power lines for which corona and interference conditions are different from those of AC power lines. The radio broadcast services mentioned above are examples only and the information in this document relates, in a technology-neutral way, to protection of radio reception in general, for the given frequency ranges.

The general procedure for establishing the limits of the radio noise from overhead power lines and associated equipment is given, together with typical values as examples, and methods of measurement.

The clause on limits for conductor corona, which may occur in normal operation of power lines, concentrates on the low frequency and medium frequency bands as it is only in these bands where ample evidence, based on established practice, is available. Examples of limits to protect radio reception in the frequency band 30 MHz to 300 MHz are not given, as measuring methods and certain other aspects of the problems in this band have not yet been fully resolved. Site measurements and service experience have shown that levels of noise from power lines generated by conductor corona at frequencies higher than 300 MHz are so low that interference is unlikely to be caused to analogue television reception.

Presently, there are no limits for radio noise due to spark discharges, which may occur at bad contacts or on the surface of polluted insulators, to protect radio reception in the UHF band (around 470 MHz to 950 MHz) for digital television broadcasting. The characteristics of spark discharges in the UHF band are not fully understood yet. Furthermore, digital television systems employ error-correction functions, and the true effects of spark discharges to image quality are consequently not quite known.

The values of limits given as examples are calculated to provide a reasonable degree of protection to the reception of e.g. radio broadcasting at the edges of the recognized service areas of the appropriate transmitters in the a.m. radio frequency bands, in the least favourable conditions likely to be generally encountered. These limits are intended to provide guidance at the planning stage of the line and national standards or other specifications against which the performance of the line may be checked after construction and during its useful life.

Recommendations are made on the design, routing, construction and maintenance of the lines and equipment forming part of the power distribution system to minimize interference and it is hoped that this document will aid other radio services in the consideration of the problems of interference.

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[CISPR TR 18-1:2017](#)

<https://standards.iteh.ai/catalog/standards/iec/c44a3f08-6b2d-46d9-8215-21f4b1f1092f/cispr-tr-18-1-2017>

RADIO INTERFERENCE CHARACTERISTICS OF OVERHEAD POWER LINES AND HIGH-VOLTAGE EQUIPMENT –

Part 1: Description of phenomena

1 Scope

This part of CISPR 18, which is a Technical Report, applies to radio noise from overhead power lines, **associated equipment**, and high-voltage equipment which may cause interference to radio reception. The scope of this document includes the causes, measurement and effects of radio interference, design aspects in relation to this interference, methods and examples for establishing limits and prediction of tolerable levels of interference from high voltage overhead power lines and associated equipment, to the reception of radio ~~broadcast~~ **signals and services**.

The frequency range covered is 0,15 MHz to ~~300 MHz~~ **3 GHz**.

Radio frequency interference caused by the pantograph of overhead railway traction systems is not considered in this document.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-161, *International Electrotechnical Vocabulary (IEV) – Chapter 161: Electromagnetic compatibility*

CISPR 16-1-1, *Specification for radio disturbance and immunity measuring apparatus and methods – Part 1-1: Radio disturbance and immunity measuring apparatus – Measuring apparatus*

CISPR TR 18-2:~~2010~~¹, *Radio interference characteristics of overhead power lines and high-voltage equipment – Part 2: Methods of measurement and procedure for determining limits*

ISO IEC Guide 99, *International vocabulary of metrology – Basic and general concepts and associated terms (VIM)*

NOTE Informative references are listed in the Bibliography.

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-161 and the ISO IEC Guide 99 apply.

¹ Under preparation. Stage at the time of publication: CISPR/RPUB 18-2:2017.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

4 Radio noise from HV AC overhead power lines

4.1 General

Radio noise from high voltage alternating current (HVAC), which is to say above 1 kV, overhead power lines may be generated over a wide band of frequencies by

- a) corona discharges in the air at the surfaces of conductors, insulator assemblies and hardware;
- b) discharges and sparking at highly stressed areas of insulators;
- c) sparking at loose or imperfect contacts ~~of~~ and at defects in hardware (cracks, rust).

The sources of a) and b) are usually distributed along the length of the line, but source c) is usually local. For lines operating above about 100 kV, the electric stress in the air at the surface of conductors and hardware can cause corona discharges. Sparking at bad contacts or broken or cracked insulators can give rise to local sources of radio noise. High voltage apparatus in substations may also generate radio noise which can be propagated along the overhead lines.

If the field strength of the radio noise at the antennas used for ~~receiving broadcast sound and television services~~ radio reception is too high, it can cause degradation of the ~~sound output and, in the case of television, the picture also~~ quality and performance of the respective radio communication or broadcast service and application.

The generation of radio noise is affected by weather conditions, for example, conductor corona is more likely to occur in wet weather because of the water droplets which form on the conductors whereas, under these conditions, bad contacts can become bridged with water droplets and the generation of radio noise, by this process, ceases. Consequently, loose or imperfect contacts are more likely to spark in dry weather conditions. Dry, clean insulators may cause interference in fair weather, but prolonged sparking on the surfaces of insulators is more likely to occur when they are polluted, particularly during wet, foggy or icy conditions.

For interference-free reception of radio ~~and television~~ signals, it is important that a sufficiently high ratio is available at the input to the receiver between the level of the wanted signal and the level of the unwanted radio noise. Interference may therefore be experienced when the signal strength is low and the weather conditions are conducive to the generation of radio noise.

Unlike analogue radio reception, to realize interference-free reception of digital signals, it is important to keep the bit error rate (BER, BER used to evaluate digital communication quality) below a certain value, for example, below around 10^{-2} in the front of Viterbi decoder in case of a ISDB-T system. In this regard, a BER of around 10^{-2} in the front of Viterbi decoder assures a BER below 10^{-8} at the input of a display by error-correction function, which is commonly employed in modern digital communication systems.

When investigating radio noise it should be borne in mind that the local field may be caused by a distant source or sources as the noise may propagate along the line without substantial losses, over a considerable distance.

4.2 Physical aspects of radio noise

4.2.1 Mechanism of formation of a noise field

4.2.1.1 General

Corona discharges on conductors, insulators or line hardware or sparking at bad contacts can be the source of radio noise as they inject current pulses into the line conductors. These propagate along the conductors in both directions from the injection point. The various components of the frequency spectrum of these pulses have different effects.

In the frequency range 0,15 MHz to a few megahertz, the noise is largely the result of the effect of propagation along the line. Direct electromagnetic radiation from the pulse sources themselves does not materially contribute to the noise level. In this case, the wavelength is long in comparison with the clearances of the conductors and thus the line is not an efficient radiator. However, associated with each spectral voltage and current component, an electric and a magnetic field propagate along the line. In view of the relatively low attenuation of this propagation, the noise field is determined by the aggregation of the effects of all the discharges spread over many kilometres along the line on either side of the reception point. It should be noted that close to the line the guided field predominates, whereas further from the line the radiated field predominates. The changeover is not abrupt and the phenomenon is not well known. This effect is not important at low frequencies but is apparent at medium frequencies.

However, for spectral components above 30 MHz where the wavelengths are close to or less than the clearance of the line conductors, the noise effects can be largely explained by antenna radiation theory applied to the source of noise, as there is no material propagation along the line.

It should be appreciated, however, that 30 MHz does not represent a clear dividing line between the two different mechanisms producing noise fields.

4.2.1.2 Longitudinal propagation

In the case of a single conductor line mounted above the ground, there is a simultaneous propagation of a voltage wave $U(t)$ and a current wave $I(t)$.

For a given frequency, the two quantities are related by the expression $U(\omega) = Z(\omega) \times I(\omega)$ where Z , also a function of ω , is the surge impedance of the line.

During propagation the waves are attenuated by a common coefficient α where:

$$U_x = U_0 e^{-\alpha x}$$

$$I_x = I_0 e^{-\alpha x}$$

where

U_0 and I_0 are the amplitudes at the source, and

x is the distance of propagation along the line.

In case of multi-phase lines, experience shows that any system of voltages or currents becomes distorted in propagation, that is to say, the attenuation varies with the distance propagated and it differs for each conductor. Theory of propagation and actual measurements on power lines have shown that noise voltages on the phase conductors can be considered as being made up of a number of "modes", each one having components on every conductor. One mode propagates between all conductors in parallel and earth. The others propagate

between conductors. Each mode has its own different propagation attenuation. The complete theory of modal propagation is complex and involves matrix equations outside the scope of this document. Reference is made here to CIGRÉ and other published works. It is important to note that the attenuation of the conductor-to-earth mode propagation is fairly high, that is to say 2 dB/km to 4 dB/km, while the attenuation of the various conductor-to-conductor modes is a small fraction of 1 dB/km at a frequency of 0,5 MHz.

4.2.1.3 Electromagnetic field

The radio noise voltages and currents propagating along the line produce an associated propagating electromagnetic field near the line.

It should be noted here that in free space the electric and magnetic components of the field associated with radiated electromagnetic waves are at right angles both to each other and to the direction of propagation. The ratio of their amplitudes represents a constant value:

$$\frac{E_{(V/m)}}{H_{(A/m)}} = 377 \Omega$$

and is called the intrinsic impedance or impedance of free space.

On the other hand, the fields near the line are related to the radio frequency voltages and currents propagating along the line and their ratio depends on the surge impedance of the line for the various modes. Furthermore, the directions of the electric and magnetic field components differ from those for radiated fields in free space as they are largely determined by the geometrical arrangements of the line conductors. The matter is further complicated by the fact that soil conditions affect differently the mirror image in the ground of the electric and magnetic field components, respectively.

The electric field strength $E(y)$ at ground level of a single conductor line, which is the vertical component of the total electric field strength, can be predicted by the following empirical equation that has, in a lot of cases, proven to give a good approximation:

$$E(y) = 120 I \frac{h}{h^2 + y^2}$$

where

I is the radio noise current, in A, propagating in the conductor;

h is the height above ground, in m, of the conductor;

y is the lateral distance, in m, from a point at ground level directly under the conductor to the measuring point; and

E is the electric field strength, in V/m.

Furthermore, for an infinitely long single conductor line, the induction zone, or near field, has the same simple ratio of electric and magnetic field strength as the far field from a radio transmitter, that is to say 377Ω , and this is approximately true for all values of ground conductivity.

In the case of a multi-phase line, the total electric field strength is the vector sum of the individual field strength components associated with each phase conductor. A more comprehensive treatment, together with practical methods of assessing the electromagnetic field, is discussed in 5.3 of CISPR TR 18-2: ². The equation given above is a simplified version accurate for a distance of $D = 20$ m and $f = 0,5$ MHz where D is the direct distance, in

² Under preparation. Stage at the time of publication: CISPR/RPUB 18-2:2017.