



**SLOVENSKI STANDARD**  
**SIST EN 302 769 V1.2.1:2011**  
**01-junij-2011**

---

**Digitalna videoradiodifuzija (DVB) - Struktura okvirov pri kanalskem kodiranju in modulacija za drugo generacijo prenosnega sistema za kabelske sisteme (DVB-C2)**

Digital Video Broadcasting (DVB) - Frame structure channel coding and modulation for a second generation digital transmission system for cable systems (DVB-C2)

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

Ta slovenski standard je istoveten z: **EN 302 769 Version 1.2.1**  
<https://standards.iteh.ai/catalog/standards/sist/81a16c4b-d455-41cc-b612-1be883f61371/sist-en-302-769-v1-2-1-2011>

---

**ICS:**

33.170	Televizijska in radijska difuzija	Television and radio broadcasting
--------	-----------------------------------	-----------------------------------

**SIST EN 302 769 V1.2.1:2011**                      **en**

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

SIST EN 302 769 V1.2.1:2011

<https://standards.iteh.ai/catalog/standards/sist/8fa16e4b-d453-41ce-bb12-1be883f61371/sist-en-302-769-v1-2-1-2011>

# ETSI EN 302 769 V1.2.1 (2011-04)

European Standard

## Digital Video Broadcasting (DVB); Frame structure channel coding and modulation for a second generation digital transmission system for cable systems (DVB-C2)



iTeh STANDARD PREVIEW  
(standards.iteh.ai)

<https://standards.iteh.ai/catalog/standards/sist/8fa16e4b-d453-41ce-bb12-1be883f61371/sist-en-302-769-v1-2-1-2011>



---

**Reference**

REN/JTC-DVB-288

---

**Keywords**audio, broadcasting, cable, data, digital, DVB,  
MPEG, TV, video**ETSI**650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**SIST EN 302 769 V1.2.1:2011<https://standards.iteh.ai/catalog/standards/sist/8fa16e4b-d453-41ce-bb12-1be883f6197884e13d24072-v1-2-1-2011>  
**Important notice**

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

[http://portal.etsi.org/chaicor/ETSI\\_support.asp](http://portal.etsi.org/chaicor/ETSI_support.asp)

---

**Copyright Notification**

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2011.

© European Broadcasting Union 2011.

All rights reserved.

**DECT**<sup>™</sup>, **PLUGTESTS**<sup>™</sup>, **UMTS**<sup>™</sup>, **TIPHON**<sup>™</sup>, the TIPHON logo and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.

**3GPP**<sup>™</sup> is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

**LTE**<sup>™</sup> is a Trade Mark of ETSI currently being registered for the benefit of its Members and of the 3GPP Organizational Partners.

**GSM**<sup>®</sup> and the GSM logo are Trade Marks registered and owned by the GSM Association.

# Contents

Intellectual Property Rights .....	6
Foreword.....	6
1 Scope .....	7
2 References .....	8
2.1 Normative references .....	8
2.2 Informative references.....	8
3 Definitions, symbols and abbreviations .....	9
3.1 Definitions.....	9
3.2 Symbols.....	11
3.3 Abbreviations .....	14
4 DVB-C2 System architecture .....	16
4.1 System overview .....	16
4.2 System architecture .....	16
4.3 Target performance .....	19
5 Input processing .....	19
5.1 Mode adaptation.....	19
5.1.1 Input Formats.....	20
5.1.2 Input Interface.....	20
5.1.3 Input Stream Synchronization (Optional).....	21
5.1.4 Null Packet Deletion (optional, for TS only, NM and HEM).....	21
5.1.5 CRC-8 encoding (for GFPS and TS, NM only).....	22
5.1.6 Baseband Header (BBHeader) insertion.....	22
5.1.7 Mode adaptation sub-system output stream formats.....	24
5.2 Stream adaptation.....	27
5.2.1 Scheduler.....	27
5.2.2 Padding .....	27
5.2.3 BB scrambling .....	27
6 Bit-interleaved coding and modulation .....	28
6.1 FEC encoding.....	28
6.1.1 Outer encoding (BCH).....	29
6.1.2 Inner encoding (LDPC) .....	30
6.1.2.1 Inner coding for normal FECFrame .....	30
6.1.2.2 Inner coding for short FECFrame .....	32
6.1.3 Bit Interleaver .....	32
6.2 Mapping bits onto constellations.....	34
6.2.1 Bit to cell word demultiplexer .....	35
6.2.2 Cell word mapping into I/Q constellations .....	38
7 Data Slice Packet Generation.....	45
7.1 Data Slice Packets for Data Slice Type 1.....	45
7.2 Data Slice Packets for Data Slice Type 2.....	45
7.2.1 FECFrame header signalling data.....	46
7.2.2 Coding of the FECFrame header .....	47
7.2.2.1 Error Coding .....	48
7.2.2.2 Cyclic Delay.....	48
7.2.2.3 Scrambling of the lower branch .....	48
7.2.3 Mapping onto QAM constellations.....	49
7.2.3.1 Robust FECFrame header .....	49
7.2.3.2 High efficiency FECFrame header.....	49
7.2.4 Mapping of the XFECFrame cells .....	49
7.2.5 Length of the Data Slice Packet for Data Slice Type 2.....	49
7.2.6 Stuffing Data Slice Packets.....	50

8	Generation, coding and modulation of Layer 1 part 2 signalling.....	51
8.1	Overview .....	51
8.2	Preamble Header .....	51
8.3	L1 signalling part 2 data.....	53
8.3.1	L1 block padding .....	58
8.3.2	CRC for the L1 signalling part 2.....	58
8.3.3	L1 padding .....	58
8.4	Modulation and error correction coding of the L1 part 2 data.....	58
8.4.1	Overview .....	58
8.4.2	Parameters for FEC encoding of L1 part 2 data.....	60
8.4.3	FEC Encoding.....	62
8.4.3.1	Zero padding of BCH information bits .....	62
8.4.3.2	BCH encoding.....	64
8.4.3.3	LDPC encoding.....	64
8.4.3.4	Puncturing of LDPC parity bits.....	64
8.4.3.5	Removal of zero padding bits.....	65
8.4.3.6	Bit interleaving for L1 signalling part 2.....	65
8.4.4	Mapping bits onto constellations .....	66
8.4.4.1	Demultiplexing of L1 signalling part 2 .....	66
8.4.4.2	Mapping onto QAM constellations .....	66
8.5	Time interleaving of L1 signalling part 2 data .....	67
9	Frame Builder.....	69
9.1	C2 Frame structure .....	69
9.1.1	Duration of the C2 Frame .....	69
9.2	Pilot Reference Sequence .....	70
9.2.1	Data Scrambling Sequence .....	70
9.2.2	Pilot Scrambling Sequence .....	70
9.2.3	Pilot Reference Sequence .....	71
9.3	Preamble Symbol .....	71
9.3.1	Preamble Symbol overview .....	71
9.3.2	Frequency Interleaving .....	71
9.3.3	Pilot insertion.....	72
9.3.3.1	Locations of the preamble pilots .....	72
9.3.3.2	Amplitude and modulation of the preamble pilots .....	72
9.3.4	Mapping and scrambling of the signalling data .....	73
9.3.5	Notches within Preamble Symbols .....	73
9.3.5.1	Narrowband Notches.....	73
9.3.5.2	Broadband Notches .....	74
9.4	Data Slice generation.....	74
9.4.1	Location of Data Slices .....	74
9.4.1.1	Start and end OFDM carrier of Data Slices .....	74
9.4.1.2	Maximum width of Data Slices.....	74
9.4.1.3	Minimum width of Data Slices .....	75
9.4.1.4	Notches within Data Slices .....	75
9.4.2	Number of payload cells in Data Slice.....	75
9.4.3	Mapping of the Data Slice Packets .....	75
9.4.4	Time Interleaving.....	76
9.4.5	Frequency Interleaving .....	80
9.5	Stuffing Data Slices .....	81
9.6	Pilot Insertion .....	81
9.6.1	Introduction.....	81
9.6.2	Scattered pilot insertion .....	82
9.6.2.1	Locations of the scattered pilots.....	82
9.6.2.2	Amplitudes of the scattered pilots .....	82
9.6.2.3	Modulation of the scattered pilots .....	82
9.6.3	Continual pilot insertion .....	82
9.6.3.1	Locations of the continual pilots .....	83
9.6.3.2	Amplitudes of the Continual Pilots .....	83
9.6.3.3	Modulation of the Continual Pilots .....	83
9.6.4	Edge pilot insertion .....	83
9.6.4.1	Locations of the edge pilots .....	83

9.6.4.2	Amplitudes of the Edge Pilots.....	84
9.6.4.3	Modulation of the Edge Pilots.....	84
9.7	Dummy carrier reservation.....	85
10	OFDM generation .....	85
10.1	IFFT - OFDM Modulation .....	85
10.2	Guard interval insertion.....	87
10.3	Spectrum characteristics.....	87
<b>Annex A (normative):</b>	<b>Addresses of parity bit accumulators for Nldpc = 64 800 .....</b>	<b>89</b>
<b>Annex B (normative):</b>	<b>Addresses of parity bit accumulators for Nldpc = 16 200 .....</b>	<b>95</b>
<b>Annex C (normative):</b>	<b>Input stream synchronizer .....</b>	<b>97</b>
<b>Annex D (normative):</b>	<b>Input Remultiplexing Subsystem: Splitting of input MPEG-2 Transport Streams into Data PLPs, generation of a Common PLP of a group of PLPs and insertion of Null Packets into Transport Streams .....</b>	<b>99</b>
D.1	Overview .....	99
D.2	Splitting of a group of input TSs into TSPSS streams and a TSPSC stream .....	100
D.2.1	General .....	100
D.2.2	Extraction of the Common PLP from a group of TS.....	100
D.2.3	Insertion of additional Null Packets into TSPSS.....	101
D.3	Receiver Implementation Considerations.....	102
D.3.1	Recombination of TSPSS and TSPSC in a receiver.....	102
<b>Annex E (normative):</b>	<b>Calculation of the CRC word .....</b>	<b>104</b>
<b>Annex F (normative):</b>	<b>Bundling of PLPs .....</b>	<b>105</b>
<b>Annex G (informative):</b>	<b>Transport Stream regeneration and clock recovery using ISCR.....</b>	<b>106</b>
<b>Annex H (informative):</b>	<b>Pilot patterns .....</b>	<b>107</b>
<b>Annex I (informative):</b>	<b>Bibliography.....</b>	<b>110</b>
History	.....	111

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Foreword

This European Standard (EN) has been produced by Joint Technical Committee (JTC) Broadcast of the European Broadcasting Union (EBU), Comité Européen de Normalisation ELECTrotechnique (CENELEC) and the European Telecommunications Standards Institute (ETSI).

**NOTE:** The EBU/ETSI JTC Broadcast was established in 1990 to co-ordinate the drafting of standards in the specific field of broadcasting and related fields. Since 1995 the JTC Broadcast became a tripartite body by including in the Memorandum of Understanding also CENELEC, which is responsible for the standardization of radio and television receivers. The EBU is a professional association of broadcasting organizations whose work includes the co-ordination of its members' activities in the technical, legal, programme-making and programme-exchange domains. The EBU has active members in about 60 countries in the European broadcasting area; its headquarters is in Geneva.

European Broadcasting Union  
 CH-1218 GRAND SACONNEX (Geneva)  
 Switzerland  
 Tel: +41 22 717 21 11  
 Fax: +41 22 717 24 81

[standards.iteh.ai](http://standards.iteh.ai/catalog/standards/sist/8fa16e4b-d453-41ce-bb12-1be883f61371/sist-en-302-769-v1-2-1-2011)

The Digital Video Broadcasting Project (DVB) is an industry-led consortium of broadcasters, manufacturers, network operators, software developers, regulatory bodies, content owners and others committed to designing global standards for the delivery of digital television and data services. DVB fosters market driven solutions that meet the needs and economic circumstances of broadcast industry stakeholders and consumers. DVB standards cover all aspects of digital television from transmission through interfacing, conditional access and interactivity for digital video, audio and data. The consortium came together in 1993 to provide global standardisation, interoperability and future proof specifications.

### National transposition dates

Date of adoption of this EN:	18 April 2011
Date of latest announcement of this EN (doa):	31 July 2011
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	31 January 2012
Date of withdrawal of any conflicting National Standard (dow):	31 January 2012

# 1 Scope

The present document describes a second generation baseline transmission system for digital television broadcasting via Hybrid Fibre Coax (HFC) cable networks and Master Antenna Television (MATV) installations. It specifies the channel coding, modulation and lower layer signalling protocol system intended for the provision of digital television services and generic data streams.

The scope is as follows:

- it gives a general description of the Baseline System for digital cable TV;
- it specifies the digital signal processing in order to establish compatibility between pieces of equipment developed by different manufacturers. This is achieved by describing in detail the signal processing at the transmitting side, while the processing at the receiving side is left open to individual implementations. However, for the purpose of securing interoperability it is necessary in this text to refer to certain implementation aspects of the receiving end.

DVB-C [i.4] was introduced as a European Norm in 1994. It specifies single carrier QAM modulation and Reed-Solomon channel coding and is used today by many cable operators worldwide for television and data broadcasting as well as for forward channel transmission of the Data Over Cable System defined in [i.7].

Since 1994 enhanced digital transmission technologies have evolved somewhat:

- New channel coding schemes, combined with higher order modulation, promise more powerful alternatives to the DVB-C coding and modulation schemes. The result is a capacity gain in the order of 30 % at a given cable channel bandwidth and CATV network performance.
- Variable Coding and Modulation (VCM) may be applied to provide different levels of error protection to different services (e.g. SDTV and HDTV, audio, multimedia).
- In the case of interactive and point-to-point applications, the VCM functionality may be combined with the use of return channels, to achieve Adaptive Coding and Modulation (ACM). This technique provides more exact channel protection and dynamic link adaptation to propagation conditions, targeting each individual receiving terminal.
- DVB-C is strictly focused on a unique data format, the MPEG Transport Stream (ISO/IEC 13818-1 [i.1] or a reference to it). Extended flexibility to cope with other input data formats (such as multiple Transport Streams, or generic data formats) is now possible without significant complexity increase.

The present document defines a "second generation" modulation and channel coding system (denoted the "C2 System" or "DVB-C2" for the purposes of the present document) to make use of the improvements listed above. DVB-C2 is a single, very flexible standard, covering a variety of applications by cable, as described below. It is characterized by:

- a flexible input stream adapter, suitable for operation with single and multiple input streams of various formats (packetized or continuous);
- a powerful FEC system based on LDPC (Low-Density Parity Check) codes concatenated with BCH (Bose Chaudhuri Hocquenghem) codes, allowing Quasi Error Free operation close to the Shannon limit, depending on the transmission mode (AWGN channel, modulation constrained Shannon limit);
- a wide range of code rates (from 2/3 up to 9/10); 5 constellations, ranging in spectrum efficiency from 1 to 10,8 bit/s/Hz, optimized for operation in cable networks;
- Adaptive Coding and Modulation (ACM) functionality, optimizing channel coding and modulation on a frame-by-frame basis.

---

## 2 References

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the reference document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <http://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication ETSI cannot guarantee their long term validity.

### 2.1 Normative references

The following referenced documents are necessary for the application of the present document.

- [1] ETSI TS 101 162: "Digital Video Broadcasting (DVB); Allocation of Service Information (SI) and Data Broadcasting Codes for Digital Video Broadcasting (DVB) systems".

### 2.2 Informative references

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] ISO/IEC 13818-1: "Information technology - Generic coding of moving pictures and associated audio information: Systems".
- [i.2] ETSI TS 102 606: "Digital Video Broadcasting (DVB); Generic Stream Encapsulation (GSE) Protocol".
- [i.3] ETSI EN 302 307: "Digital Video Broadcasting (DVB); Second generation framing structure, channel coding and modulation systems for Broadcasting, Interactive Services, News Gathering and other broadband satellite applications (DVB-S2)".
- [i.4] ETSI EN 300 468: "Digital Video Broadcasting (DVB); Specification for Service Information (SI) in DVB systems".
- [i.5] ETSI EN 300 429: "Digital Video Broadcasting (DVB); Framing structure, channel coding and modulation for cable systems".
- [i.6] ETSI EN 302 755: "Digital Video Broadcasting (DVB); Frame structure channel coding and modulation for a second generation digital terrestrial television broadcasting system (DVB-T2)".
- [i.7] CENELEC EN 50083-2:2006: "Cable networks for television signals, sound signals and interactive services - Part 2: Electromagnetic compatibility for equipment".
- [i.8] ETSI EN 300 421: "Digital Video Broadcasting (DVB); Framing structure, channel coding and modulation for 11/12 GHz satellite services".

## 3 Definitions, symbols and abbreviations

### 3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

⊕: Exclusive OR / modulo-2 addition operation

**0xkk**: digits 'kk' should be interpreted as a hexadecimal number

**active cell**: OFDM Cell carrying a constellation point for L1 signalling or a PLP

**auxiliary data**: sequence of cells carrying data of as yet undefined modulation and coding, which may be used for stuffing Data Slices or stuffing Data Slice Packets

**BBFrame**: signal format of an input signal after mode and stream adaptation

**BBHeader**: header in front of a baseband data field

NOTE: See clause 5.1.

**BUFS**: maximum size of the requested receiver buffer to compensate delay variations

**BUFSTAT**: actual status of the receiver buffer

**C2 frame**: fixed physical layer TDM frame that is further divided into variable size Data Slices

NOTE: C2 Frame starts with one or more Preamble Symbol.

**C2 system**: complete transmitted DVB-C2 Signal, as described in the L1-part2 block of the related Preamble

**common PLP**: special PLP, which contains data shared by multiple PLPs (Transport Stream)

**data cell**: OFDM Cell which is not a pilot or tone reservation cell

**data PLP**: PLP carrying payload data

**data slice**: group of OFDM Cells carrying one or multiple PLPs in a certain frequency sub-band

NOTE: This set consists of OFDM Cells within a fixed range of consecutive cell addresses within each Data Symbol and spans over the complete C2 Frame, except the Preamble Symbols.

**data slice packet**: XFECFrame including the related FECFrame Header

**data symbol**: OFDM Symbol in a C2 Frame which is not a Preamble Symbol

**div**: integer division operator, defined as:

$$x \text{ div } y = \left\lfloor \frac{x}{y} \right\rfloor$$

**dummy cell**: OFDM Cell carrying a pseudo-random value used to fill the remaining capacity not used for L1 signalling, PLPs or Auxiliary Data

**elementary period**: time period which depends on the channel raster and is used to define the other time periods in the C2 System

**FECFrame**: set of  $N_{\text{LDPC}}$  (16 200 or 64 800) bits of one LDPC encoding operation

NOTE: In case of Data Slices carrying a single PLP and constant modulation and encoding is applied, FECFrame Header information may be carried in Layer1 part2 and the Data Slice Packet is identical with the XFECFrame.

**FFT size:** nominal FFT size for a DVB-C2 receiver is 4K

NOTE: Further details are discussed in clause 10.1.

**for i=0..xxx-1:** when used with the signalling loops, this means that the corresponding signalling loop is repeated as many times as there are elements of the loop

NOTE: If there are no elements, the whole loop is omitted.

**Im(x):** Imaginary part of x

**Layer 1 (L1):** name of the first layer of the DVB-C2 signalling scheme (signalling of physical layer parameters)

**L1 block:** set of L1-part2 COFDM Cells, cyclically repeated in the frequency domain

NOTE: L1 Blocks are transmitted in the Preamble.

**L1-part1:** signalling carried in the header of the Data Slice Packets carrying modulation and coding parameters of the related XFECFrame

NOTE: L1-part1 parameters may change per XFECFrame.

**L1-part2:** Layer 1 Signalling cyclically transmitted in the preamble carrying more detailed L1 information about the C2 System, Data Slices, Notches and the PLPs

NOTE: L1-part2 parameters may change per C2 Frame.

**Layer 2 (L2):** name of the second layer of the DVB-C2 signalling scheme (signalling of transport layer parameters)

**mod:** modulo operator, defined as:

$$x \bmod y = x - y \left\lfloor \frac{x}{y} \right\rfloor$$

**mode adapter:** input signal processing block, delivering BBFrames at its output

**nn<sub>D</sub>:** digits 'nn' should be interpreted as a decimal number

**notch:** set of adjacent OFDM Cells within each OFDM Symbol without transmitted energy

**null packet:** MPEG Packet with the Packet\_ID 0x1FFF, carrying no payload data and intended for padding

**OFDM cell:** modulation value for one OFDM carrier during one OFDM Symbol, e.g. a single constellation point

**OFDM symbol:** waveform Ts in duration comprising all the active carriers modulated with their corresponding modulation values and including the guard interval

**Physical Layer Pipe (PLP):** logical channel carried within one or multiple Data Slice(s)

NOTE 1: All signal components within a PLP share the same transmission parameters such as robustness, latency.

NOTE 2: A PLP may carry one or multiple services. In case of PLP Bundling a PLP may be carried in several Data Slices. Transmission parameters may change each XFECFrame.

**PLP bundling:** transmission of one PLP via multiple Data Slices

**PLP\_ID:** this 8-bit field identifies uniquely a PLP within a C2 transmission signal

**preamble header:** fixed size signalling transmitted in the first part of the Preamble, carrying the length and Interleaving parameters of Layer 1 part 2 data

**preamble symbol:** one or multiple OFDM Symbols, transmitted at the beginning of each C2 Frame, carrying Layer 1 part 2 signalling data

**Re(x):** Real part of x

**reserved for future use:** value of any field indicated as "reserved for future use" shall be set to "0" unless otherwise defined

**START\_FREQUENCY:** index of lowest used OFDM subcarrier of a C2 System. The value of START\_FREQUENCY shall be a multiple of  $D_x$

**x\*:** Complex conjugate of  $x$

**XFECFrame:** FECFrame mapped onto QAM constellations:

- $\lfloor x \rfloor$ : round towards minus infinity: the most positive integer less than or equal to  $x$ .
- $\lceil x \rceil$ : round towards plus infinity: the most negative integer greater than or equal to  $x$ .

## 3.2 Symbols

For the purposes of the present document, the following symbols apply:

$\Delta$	Absolute guard interval duration
$A$	LDPC codeword of size $N_{ldpc}$
$\lambda_i$	LDPC codeword bits
$\lambda^{RM}$	32 output bits of Reed-Muller encoder
$\lambda_i^{RM}$	Bit number of index $i$ of 32 bit long output bits of Reed-Muller encoder
$\eta_{MOD}, \eta_{MOD}(i)$	Number of transmitted bits per constellation symbol (for PLP $i$ )
$\pi_p$	Permutation operator defining parity bit groups to be punctured for L1 signalling
$\pi_s$	Permutation operator defining bit-groups to be padded for L1 signalling
$A_{m,l}$	Output vector of the frequency interleaver of OFDM Symbol $l$ and C2 Frame $m$
$A_{CP}$	Amplitude of the continual pilot cells
$A_{SP}$	Amplitude of the scattered pilot cells
$a_{m,l,q}$	Frequency-Interleaved cell value, cell index $q$ of symbol $l$ of C2 Frame $m$
$B(n)$	Location of the first Data Cell of symbol $l$ allocated to Data Slice $n$ in the frequency interleaver
$b$	16 bit long FECFrame signalling data vector
$b_{e,d_i}$	Output from the demultiplexer, depending on the demultiplexed bit sub-stream number $e$ and the input bit number $d_i$ of the bit interleaver demultiplexer
$b_i$	Bit number of index $i$ of 16 bit long FECFrame signalling data vector
$C/N$	Carrier-to-noise power ratio
$C/N+I$	Carrier-to-(Noise+Interference) ratio
$C_i$	Column of index $i$ of time interleaver
$c_i$	Column of index $i$ of bit interleaver
$c(x)$	Equivalent BCH codeword polynomial
$c_{m,l,k}$	Cell value for carrier $k$ of symbol $l$ of C2 Frame $m$
$DFL$	Data field length
$D_p$	Difference in carrier index between adjacent preamble-pilot-bearing carriers
$D_x$	Difference in carrier index between adjacent scattered-pilot-bearing carriers
$D_y$	Difference in symbol number between successive scattered pilots on a given carrier
$d(x)$	Remainder of dividing message polynomial by the generator polynomial $g(x)$ during BCH encoding
$d_i$	Input bit number $d_i$ of the bit interleaver demultiplexer
$d_o$	Bit number of a given stream at the output of the demultiplexer of the bit interleaver
$e$	Demultiplexed bit sub stream number ( $0 \leq e < N_{substreams}$ ), depending on input bit number $d_i$ of the bit interleaver demultiplexer
$f_q$	Constellation point normalized to mean energy of 1
$G$	Reed-Muller encoder matrix
$g(x)$	BCH generator polynomial

$g_1(x), g_2(x), \dots, g_{12}(x)$	Polynomials to obtain BCH code generator polynomial
$s_q$	Complex cell of index $q$ of a Data Slice Packet
$H(q)$	Frequency interleaver permutation function, element $q$
$I$	Output codeword of BCH encoder
$i_j$	BCH codeword bits which form the LDPC information bits
$j$	$\sqrt{-1}$
$K_{bch}$	Number of bits of BCH uncoded Block
$K_i$	L1 signalling part 2 parameter selected as $N_{L1part2}(K_i) \leq N_{L1part2\_Cells} \times \eta_{MOD}$
$K_{ldpc}$	Number of bits of LDPC uncoded Block
$K_{L1\_PADDING}$	Length of L1_PADDING field
$K_{L1part2}$	Length of L1-part2 signalling field including the padding field
$K_{L1part2\_ex\_pad}$	Number of information bits in L1-part2 signalling excluding the padding field
$K_{N,min}$	Lowest frequency carrier index of a frequency Notch
$K_{N,max}$	Highest frequency carrier index of a frequency Notch
$K_{sig}$	Number of signalling bits per FEC block for L1 signalling part 2
$K_{min}$	Lowest frequency carrier index of a C2 signal, shall be identical to the START_FREQUENCY and shall be multiple of $D_X$
$K_{max}$	Highest frequency carrier index of a C2 signal, shall be multiple of $D_X$
$K_{total}$	Number of OFDM carriers per OFDM symbol
$k$	Absolute OFDM carrier index
$L_{data}$	Number of data OFDM Symbols per C2 Frame (excluding Preamble)
$L_F$	Number of OFDM Symbols per C2 Frame including excluding preamble
$L_P$	Number of preamble OFDM Symbols within the C2 Frame
$l$	Index of OFDM Symbol within the C2 Frame (excluding preamble)
$l_P$	Index of preamble OFDM Symbol in C2 Frame
$m$	C2 Frame number
$m(x)$	Message polynomial within BCH encoding
$m_i$	Input bit of index $i$ from uncoded bit vector $M$ before BCH encoder
$M$	Uncoded bit vector before BCH encoder
$M_{max}$	Maximum Sequence length for the frequency interleaver
$N_{bch}$	Number of bits of BCH coded Block
$N_{bch\_parity}$	Number of BCH parity bits
$N_c$	Number of columns of bit or time interleaver
$N_{data}$	Number of Data Cells in a Data Slice in frequency interleaver
$N_{DP}$	Number of complex cells per Data Slice Packet
$N_{group}$	Number of bit-groups for BCH shortening
$N_{L1part2}$	Length of punctured and shortened LDPC codeword for L1-part2 signalling
$N_{L1part2\_Cells}$	Number of available cells for L1 signalling part 2 in one OFDM Symbol
$N_{L1part2\_FEC\_Block}$	Number of LDPC blocks for the L1 signalling part 2
$N_{L1part2\_max\_per\_Symbol}$	Maximum number of L1 information bits for transmitting the encoded L1 signalling part 2 through one OFDM Symbol
$N_{L1\_TI\_Depth}$	Time interleaving depth for L1 signalling part 2
$N_{L1part2\_temp}$	Intermediate value used in L1 puncturing calculation
$N_{ldpc}$	Number of bits of LDPC coded Block
$N_{MOD\_per\_Block}$	Number of modulated cells per FEC block for the L1-part2 signalling
$N_{MOD\_Total}$	Total number of modulated cells for the L1-part2 signalling
$N_{pad}$	Number of BCH bit-groups in which all bits will be padded for L1-part2 signalling
$N_{punc}$	Number of LDPC parity bits to be punctured
$N_{punc\_groups}$	Number of parity groups in which all parity bits are punctured for L1 signalling
$N_{punc\_temp}$	Intermediate value used in L1 puncturing calculation
$N_r$	Number of bits in Frequency Interleaver sequence
$N_r$	Number of rows of bit or time interleaver

$N_{RT}$	Number of reserved carriers
$N_{substreams}$	Number of substreams produced by the bit-to-sub-stream demultiplexer
$n$	Data slice number
$P_k(f)$	Power spectral density
$p_i$	LDPC parity bits
$Q_{ldpc}$	Code-rate dependent LDPC constant
$q$	Data Cell index within the OFDM Symbol prior to frequency interleaving and pilot insertion
$R_{eff\_16K\_LDPC\_1\_2}$	Effective code rate of 16K LDPC with nominal rate $\frac{1}{2}$
$R_{eff\_L1part2}$	Effective code rate of L1-part2 signalling
$R_i$	Row of index $i$ of time interleaver
$R_i$	Value of element $i$ of the frequency interleaver sequence following bit permutations
$R'_i$	Value of element $i$ of the frequency interleaver sequence prior to bit permutations
$r_i$	Row of index $i$ of bit interleaver
$r_k$	DBPSK modulated pilot reference sequence
$S_0$	List of reserved carriers
$T$	Elementary period
$T_{Ci}$	Column-twist value for column $C$ of time interleaver
$T_{CH}$	Component set of carrier indices for reserved carriers
$T_F$	Duration of one C2 Frame
$T_P$	Time interleaving period
$T_S$	Total OFDM Symbol duration
$T_U$	Useful OFDM Symbol duration
$t$	BCH error correction capability
$t_c$	Column-twist value for column $c$ of bit interleaver
$U$	Parity interleaver output
$UPL$	User Packet Length
$u_i$	Parity-interleaver output bits
$u^{RM}$	32 bit output vector of the cyclic delay block in the FECFrame header encoding
$u_{(i+2)mod32}^{RM}$	Output of the cyclic delay block for input bit $i$ in the FECFrame header encoding
$V$	Column-twist interleaver output
$v_i$	Column-twist interleaver output bits
$v_{m,l,i}$	Output vector of frequency interleaver, starting at carrier index $i$ (= Data slice start carrier) of the current OFDM Symbol $l$ and C2 Frame $m$
$v^{RM}$	Scrambled output sequence in the lower branch of the FECFrame header encoder
$v_i^{RM}$	Bit $i$ of scrambled output sequence in the lower branch of the FECFrame header encoder
$w_i$	Bit $i$ of the data scrambling sequence
$w^{RM}$	32 bit scrambling sequence in the lower branch of the FECFrame header encoder
$w_i^{RM}$	Bit $i$ of scrambling sequence in the lower branch of the FECFrame header encoder
$w^P$	Pilot synchronization sequence, build out of $w_i$ and $w'$
$w_k^P$	Bit of index $k$ of pilot synchronization sequence
$w'$	L1 block specific pilot synchronization sequence
$w'_i$	Bit of index $k$ of L1 block specific pilot synchronization sequence
$X_j$	The set of bits in group $j$ of BCH information bits for L1 shortening
$X_{m,l}$	Frequency interleaver input Data Cells of the OFDM Symbol $l$ and the C2 Frame $m$
$x$	Address of the parity bit accumulator according to $i_{360}$ in LDPC encoder
$y_{i,q}$	Bit $i$ of cell word $q$ from the bit-to-cell-word demultiplexer
$z_q$	Constellation point prior to normalization

The symbols  $s$ ,  $t$ ,  $i$ ,  $j$ ,  $k$  are also used as dummy variables and indices within the context of some clauses or equations.