

First edition
2007-02-15

Corrected version
2007-11-01

**Resistance welding — Transformer-
rectifier for welding guns with integrated
transformers — Transformer-rectifier
units operating at 1 000 Hz frequency**

*Soudage par résistance — Transformateurs-redresseurs pour pistolets
de soudage à transformateur incorporé — Transformateurs-redresseurs
alimentés sous une fréquence de 1 000 Hz*

iTeh STANDARD PREVIEW
(standards.iteh.ai)

ISO 22829:2007

<https://standards.iteh.ai/catalog/standards/sist/30c3fd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007>



Reference number
ISO 22829:2007(E)

© ISO 2007

PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[ISO 22829:2007](https://standards.iteh.ai/catalog/standards/sist/30c3fd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007)

<https://standards.iteh.ai/catalog/standards/sist/30c3fd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007>

© ISO 2007

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Contents

Page

Foreword.....	iv
1 Scope	1
2 Normative references	1
3 Terms and definitions.....	1
4 Power supply to the transformer-rectifier unit	3
5 Transformer types	3
6 Dimensions.....	4
7 Construction and additional equipment.....	5
8 Marking	6
9 Shipping.....	6
10 Designation	6
11 Tests.....	7
Annex A (informative) Relationship between output current and duty factor	13
Annex B (normative) Input voltage timing characteristics	14
Annex C (normative) Dimensions of transformers.....	15
Annex D (normative) Rating plate	24
Bibliography	26

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of technical committees is to prepare International Standards. Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the member bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights.

ISO 22829 was prepared by Technical Committee ISO/TC 44, *Welding and allied processes*, Subcommittee SC 6, *Resistance welding*.

Requests for official interpretations of any aspect of this International Standard should be directed to the Secretariat of ISO/TC 44/SC 6 via your national standards body. A complete listing of these bodies can be found at www.iso.org.

This corrected version incorporates an updated second paragraph in 11.3.9.

ISO 22829:2007
<https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007>

Resistance welding — Transformer-rectifier for welding guns with integrated transformers — Transformer-rectifier units operating at 1 000 Hz frequency

1 Scope

This International Standard is applicable to transformer-rectifier units as used in electric resistance welding machines operating from a power supply with a frequency of 1 000 Hz, and of a rated value of the input voltage equal to or higher than 500 V. These transformer-rectifier units are primarily used in welding guns with an integrated transformer.

For these transformer units, this International Standard supplements the requirements given in ISO 5826 and ISO 10656, which remain applicable except where amended by this International Standard.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 5826:1999, *Resistance welding equipment — Transformers — General specifications applicable to all transformers*

ISO 17657-3, *Resistance welding — Welding current measurement for resistance welding — Part 3: Current sensing coil*

ISO 17657-4, *Resistance welding — Welding current measurement for resistance welding — Part 4: Calibration system*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1

transformer-rectifier unit

transformer incorporating a full-wave rectifier in its secondary circuit

3.2

input voltage

U_1

root-mean-square (RMS) value of the voltage applied to the primary terminals of the transformer-rectifier unit

3.3

rated supply voltage

U_{1N}

RMS value of the supply voltage (applied to the primary terminals) for which the transformer-rectifier unit is constructed

**3.4
rectified voltage**

U_{2d}
RMS value of the voltage at the output of the transformer-rectifier unit when a load resistance is connected across the output terminals

**3.5
input current**

I_1
RMS value of the current at the input terminals of the transformer-rectifier unit

**3.6
open circuit input current**

I_{10}
RMS value of the current at the input terminals of the transformer-rectifier unit with the output terminals open circuit

**3.7
permanent input current**

I_{1P}
maximum RMS value of the current at the input terminals of the transformer-rectifier unit with 100 % duty factor ($X = 100\%$), without exceeding the specified temperature limits

NOTE For calculation related to this International Standard, $I_{1P} = I_{2P} / (N1/N2)$, where $(N1/N2)$ is the transformer turns ratio.

**iTeh STANDARD PREVIEW
(standards.iteh.ai)**

**3.8
output d.c.**

I_{2d}
RMS value of the direct current at the output terminals of the transformer-rectifier unit

[ISO 22829:2007](https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007)

**3.9
permanent output current**

<https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007>

I_{2P}
maximum RMS value of the output current delivered by the transformer-rectifier unit at 100 % duty factor ($X = 100\%$), without exceeding the specified temperature limits

**3.10
output current on load condition**

I_{2R}
RMS value of the output current delivered by the transformer-rectifier unit with a load resistance R

**3.11
apparent input power**

S_1
power measured at the input terminals of the transformer-rectifier unit, or calculated by $U_1 \times I_1$

**3.12
rated permanent input apparent power**

S_{1P}
rated permanent apparent power calculated by $U_{1N} \times I_{1P}$

3.13 conduction interval

 t_{st}

time span within one half-wave of a period of the alternating current of the inverter, in which a voltage has a measured value that is greater than or equal to $\frac{\hat{u}}{2}$, where \hat{u} expresses the amplitude of voltage measured at the output of inverter

NOTE See Annex B.

3.14 non-conduction interval

 t_{pt}

time span within one half-wave of a period of the alternating current of the inverter, in which the voltage has a measured value that is less than $\frac{\hat{u}}{2}$

NOTE See Annex B.

3.15 on time

 t_s

time during which the current is applied

3.16 off time

 t_p

time during which the current is not applied

iTeh STANDARD PREVIEW
(standards.iteh.ai)

4 Power supply to the transformer-rectifier unit

<https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7->

The rated voltage supply shall be delivered by an inverter. This inverter shall deliver the rated voltage at a frequency of 1 000 Hz in a waveform to suit the transformer-rectifier unit characteristics.

5 Transformer types

The minimum principal electrical characteristics of a transformer-rectifier unit shall conform to Table 1.

Table 1 — Electrical characteristics

Type	Nominal value of the rectified voltage U_{2d} V	Minimum value of S_{1P} kVA	Minimum permanent output current I_{2P} kA	Minimum output current on load condition I_{2R}^a kA
H1	6,3	36,0	5,0	11
H2	8,4	45,0	5,0	14
J1	6,3	45,0	6,3	18
J2	10,0	68,0	6,3	28
J3	9,3	63,0	6,3	25
J4	12,5	83,0	6,3	32
N1	10,4	64,0	5,7	20
P1	12,2	75,0	5,7	27
S1	8,2	71,0	6,3	25

NOTE Indicated values are RMS values and are given for a cooling liquid flow rate of 6 l/min for types J1, J2, H, N and P, and of 8 l/min for types J3, J4 and S, with a maximum temperature of the cooling liquid at transformer input of 30 °C.

^a $R = 200 \mu\Omega \pm 5\%$ = load resistance.

iTech STANDARD PREVIEW

The manufacturer of transformer-rectifier units shall provide a set of curves showing the maximum output current relative to duty factor and welding time at the rated supply voltage. An example of a set of curves is given in Annex A.

[ISO 22829:2007](https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007)

<https://standards.iteh.ai/catalog/standards/sist/30c3fcd8-a802-4d32-9ca7-e946719a3b78/iso-22829-2007>

6 Dimensions

The dimensions of the transformer-rectifier unit shall be as given in Table 2 and as illustrated in Annex C.

NOTE According to ISO 10656, there are basically two transformer types:

- H (106 mm × 150 mm × variable length), and
- J (125 mm × 160 mm × variable length).

Table 2 — Dimensions

Dimensions in millimetres

Type	Maximum length L_1	Length between mounting holes L_2	Overall width	Overall height	Output terminals dimensions
H1	270	170	106	150	32 × 32
H2	270	170	106	150	32 × 32
J1	300	190	125	160	32 × 32
J2	300	190	125	160	32 × 32
J3	300	190	125	160	40 × 50
J4	360	250	125	160	40 × 50
N1	400	115	130	190	45 × 50
P1	400	128	125	200	50 × 50
S1	370	279	127	171	51 × 67

7 Construction and additional equipment

7.1 Grounding

The centre point of the secondary coil shall be earthed by a removable link.

7.2 Thermal protection

The transformer and the rectifier shall be equipped with thermostats that each have a normally closed contact. The insulation shall be suitable for the test conditions prescribed in this International Standard. The position of the wiring of these thermostats shall be in accordance with Figures C.1 to C.6. The wiring of primary thermostats shall be sky blue, the wiring of secondary thermostats shall be black and the wiring of rectifier thermostats shall be yellow.

7.3 Protection of the rectifier

The rectifier should be protected against the accumulation of welding spatter and other contamination.

7.4 Output current sensing coil

If the transformer-rectifier unit is equipped with an output current sensing coil, it shall comply with the conditions below.

- The degree of protection of an externally mounted coil shall be IP 55.
- The output shall be $150 \text{ mV/kA} \pm 1,5 \%$ at a load resistor of $1\,000 \Omega \pm 1 \%$ under full sine wave with a 50 Hz frequency, up to $80 \text{ }^\circ\text{C}$. The tolerance after mounting in the transformer-rectifier unit shall be $\pm 3 \%$.

The detector shall be a Rogowski type coil. The internal resistance of the detector shall be 10Ω to 50Ω . White and brown colour coding shall be used for the wiring.

7.5 Output voltage sensing wires

If the transformer-rectifier unit is equipped with output voltage sensing wires, red and dark blue colour coding shall be used for the wiring. The red wire shall be connected to the “+” output terminal, and the dark blue wire to the “-” output terminal.

The wiring shall be protected from short-circuit currents by suitable means, e.g. by fuses, resistors or positive temperature coefficient thermistors.

If a resistor or a positive temperature coefficient thermistor is used, a value of 100 Ω is recommended.

7.6 Mechanical strength

After being tested in accordance with 11.3.6 and 11.3.8, the transformer shall exhibit no visible mechanical damage.

8 Marking

8.1 Primary

The earth and two primary voltage connections shall be clearly identified by means of “U”, “V” and the symbol \oplus (see IEC 60417). The connection to the mid-point of the transformer shall be marked with “MP”.

8.2 Output terminals

The polarity of the output terminals shall be marked on the transformer and on the data sheet with the symbols “+” and “-”, in accordance with Figures C.1 to C.6.

8.3 Rating plate

The rating plate shall conform to Annex D.

9 Shipping

The cooling system shall be drained and the ends plugged. The terminals shall be protected to avoid damage during shipment and storage.

10 Designation

The designation of a transformer-rectifier unit, principally used for welding guns with integrated transformer (robot guns) and complying with the requirements of this International Standard, shall provide the following information, in the order given:

- complete designation (i.e. “Transformer-rectifier unit”);
- reference to this International Standard;
- type of transformer-rectifier unit (e.g. “H1”);
- rectified voltage U_{2d} ;
- minimum permanent output current I_{2P} (see Table 1);

- rated supply voltage U_{1N} and frequency;
- indication of thermal protection T;
- indication of current sensing coil M;
- indication of voltage detector U.

EXAMPLE Transformer-rectifier unit ISO 22829 — H1 — 6,3 — 5,4 — 500/1000 — TMU.

11 Tests

11.1 Type tests

Type testing shall be in compliance with ISO 5826, except where amended by this International Standard.

The following type tests shall be carried out, in the following order:

- general visual examination (preliminary);
- insulation test (preliminary test);
- rectified voltage (U_{2d}), open-circuit input current (I_{10});
- minimum output current under load condition;
- temperature-rise test;
- dynamic behaviour;
- calibration of the current sensing coil, if appropriate;
- insulation test;
- mechanical strength;
- dielectric test of the transformer-rectifier unit;
- cooling circuit;
- general visual examination (final).

The bandwidth of the reference measuring current and voltage systems shall be at least 100 kHz (–3 dB) and the accuracy class rating shall be 0,5 % of the upper limit of the full scale.

For temperature meters, the accuracy class rating shall be 0,5 % of the full scale.

11.2 Routine tests

The routine tests shall comprise only a reduced set of tests:

- general visual examination;
- dielectric tests;
- rectified voltage (U_{2d});
- cooling circuit.

11.3 Test procedures

11.3.1 General visual examination

Visual examination shall be undertaken to assess visible imperfections. The visual examination performed at the end of the type test procedure shall include the measurement of the dimensions of the transformer-rectifier unit. The dimensions measured shall be reported.

11.3.2 Insulation test

The insulation resistance shall not be less than 50 MΩ.

The conformity shall be checked by applying a direct voltage of 500 V between:

- the input and output connections, and
- the connections and the cover(s).

The output terminals shall be short-circuited during testing to protect the diodes.

11.3.3 Open-circuit tests

The input voltage waveform supplying the test object shall comply with the requirements outlined in Annex B.

The time characteristic shall be chosen such that the period, T , is 1 ms. The conduction time, t_{st} , for the power supply shall be $450 \mu s \pm 1 \%$.

NOTE During the no-load test (when the transformer is connected to the inverter instead of the load resistor), the input voltage waveform is observed with a full conduction time.

During the test, the input voltage shall correspond to $U_{1N} \pm 5 \%$ (rating plate). A load resistor of $R = 10 \Omega \pm 10 \%$ shall be connected across the output connections of the transformer-rectifier unit.

The RMS values of rectified voltage, U_{2d} , at the output connections, and the open circuit input current, I_{10} , shall be measured using an integration time of 60 ms.

The rectified voltage, U_{2d} , shall not deviate by more than $\pm 5 \%$ from the value specified on the rating plate.

At the rated supply voltage, U_{1N} , the open-circuit input current, I_{10} , shall meet the following condition:

$$I_{10} \leq \frac{0,04 \cdot S_{1P}}{U_{1N}} \quad (1)$$

11.3.4 Minimum output current under load condition

The test shall only be started when the temperature difference between the cooling liquid inlet and the cooling liquid outlet is less than 1 K.

The input voltage waveform supplying the test object shall comply with the requirements outlined in Annex B.

The time characteristic shall be chosen such that the period, T , is 1 ms. The conduction time, t_{st} , for the power supply shall be $450 \mu s \pm 1 \%$.

The input voltage, U_1 , shall correspond to $U_{1N} \pm 5 \%$. The input voltage, U_1 , shall be recorded and a correction formulae shall be used if the input voltage, U_1 , is different from U_{1N} . A load resistor of $R = 200 \mu\Omega \pm 5 \%$ shall be connected across the output connections of the transformer-rectifier unit.