

ETSI TS 136 213 V12.3.0 (2014-10)



LTE; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures (3GPP TS 36.213 version 12.3.0 Release 12)



ReferenceRTS/TSGR-0136213vc30

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaicor/ETSI_support.asp

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2014.

All rights reserved.

DECTTM, PLUGTESTSTM, UMTSTM and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members. 3GPPTM and LTETM are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. GSM[®] and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**may not**", "**need**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Foreword.....	2
Modal verbs terminology.....	2
Foreword.....	6
1 Scope	7
2 References	7
3 Symbols and abbreviations.....	8
3.1 Symbols.....	8
3.2 Abbreviations	8
4 Synchronization procedures	10
4.1 Cell search	10
4.2 Timing synchronization.....	10
4.2.1 Radio link monitoring.....	10
4.2.2 Inter-cell synchronization	10
4.2.3 Transmission timing adjustments	10
4.3 Timing for Secondary Cell Activation / Deactivation	11
5 Power control	12
5.1 Uplink power control.....	12
5.1.1 Physical uplink shared channel	12
5.1.1.1 UE behaviour	12
5.1.1.2 Power headroom	19
5.1.2 Physical uplink control channel	21
5.1.2.1 UE behaviour	21
5.1.3 Sounding Reference Symbol (SRS).....	24
5.1.3.1 UE behaviour	24
5.2 Downlink power allocation	25
5.2.1 eNodeB Relative Narrowband TX Power (RNTP) restrictions	26
6 Random access procedure	28
6.1 Physical non-synchronized random access procedure.....	28
6.1.1 Timing	28
6.2 Random Access Response Grant.....	29
7 Physical downlink shared channel related procedures	31
7.1 UE procedure for receiving the physical downlink shared channel	31
7.1.1 Single-antenna port scheme	39
7.1.2 Transmit diversity scheme	40
7.1.3 Large delay CDD scheme	40
7.1.4 Closed-loop spatial multiplexing scheme	40
7.1.5 Multi-user MIMO scheme	40
7.1.5A Dual layer scheme.....	40
7.1.5B Up to 8 layer transmission scheme	40
7.1.6 Resource allocation.....	40
7.1.6.1 Resource allocation type 0	41
7.1.6.2 Resource allocation type 1	41
7.1.6.3 Resource allocation type 2	42
7.1.6.4 PDSCH starting position	43
7.1.6.5 Physical Resource Block (PRB) bundling.....	45
7.1.7 Modulation order and transport block size determination	46
7.1.7.1 Modulation order determination.....	46
7.1.7.2 Transport block size determination	48
7.1.7.2.1 Transport blocks not mapped to two or more layer spatial multiplexing	49
7.1.7.2.2 Transport blocks mapped to two-layer spatial multiplexing.....	56

7.1.7.2.3	Transport blocks mapped for DCI Format 1C	56
7.1.7.2.4	Transport blocks mapped to three-layer spatial multiplexing.....	57
7.1.7.2.5	Transport blocks mapped to four-layer spatial multiplexing.....	58
7.1.7.3	Redundancy Version determination for Format 1C	58
7.1.8	Storing soft channel bits	59
7.1.9	PDSCH resource mapping parameters.....	59
7.1.10	Antenna ports quasi co-location for PDSCH	60
7.2	UE procedure for reporting Channel State Information (CSI)	61
7.2.1	Aperiodic CSI Reporting using PUSCH.....	64
7.2.2	Periodic CSI Reporting using PUCCH	72
7.2.3	Channel Quality Indicator (CQI) definition.....	89
7.2.4	Precoding Matrix Indicator (PMI) definition.....	95
7.2.5	Channel-State Information – Reference Signal (CSI-RS) definition	100
7.2.6	Channel-State Information – Interference Measurement (CSI-IM) Resource definition.....	101
7.2.7	Zero Power CSI-RS Resource definition	101
7.3	UE procedure for reporting HARQ-ACK	102
7.3.1	FDD HARQ-ACK reporting procedure.....	102
7.3.2	TDD HARQ-ACK reporting procedure.....	102
7.3.2.1	TDD HARQ-ACK reporting procedure for same UL/DL configuration	103
7.3.2.2	TDD HARQ-ACK reporting procedure for different UL/DL configurations	109
7.3.3	FDD-TDD HARQ-ACK reporting procedure for primary cell frame structure type 1.....	113
7.3.4	FDD-TDD HARQ-ACK reporting procedure for primary cell frame structure type 2.....	113
8	Physical uplink shared channel related procedures.....	114
8.0	UE procedure for transmitting the physical uplink shared channel.....	114
8.0.1	Single-antenna port scheme	120
8.0.2	Closed-loop spatial multiplexing scheme	120
8.1	Resource allocation for PDCCH/EPDCCH with uplink DCI format	121
8.1.1	Uplink resource allocation type 0.....	121
8.1.2	Uplink resource allocation type 1.....	121
8.2	UE sounding procedure	122
8.3	UE HARQ-ACK procedure.....	128
8.4	UE PUSCH hopping procedure.....	130
8.4.1	Type 1 PUSCH hopping	131
8.4.2	Type 2 PUSCH hopping	131
8.5	UE Reference Symbol (RS) procedure.....	131
8.6	Modulation order, redundancy version and transport block size determination.....	132
8.6.1	Modulation order and redundancy version determination	132
8.6.2	Transport block size determination.....	133
8.6.3	Control information MCS offset determination.....	135
8.7	UE transmit antenna selection	138
9	Physical downlink control channel procedures.....	139
9.1	UE procedure for determining physical downlink control channel assignment.....	139
9.1.1	PDCCH assignment procedure	139
9.1.2	PHICH assignment procedure.....	141
9.1.3	Control Format Indicator (CFI) assignment procedure.....	143
9.1.4	EPDCCH assignment procedure.....	143
9.1.4.1	EPDCCH starting position	149
9.1.4.2	Antenna ports quasi co-location for EPDCCH.....	149
9.1.4.3	Resource mapping parameters for EPDCCH	150
9.1.4.4	PRB-pair indication for EPDCCH	150
9.2	PDCCH/EPDCCH validation for semi-persistent scheduling.....	151
9.3	PDCCH/EPDCCH control information procedure	152
10	Physical uplink control channel procedures.....	153
10.1	UE procedure for determining physical uplink control channel assignment.....	153
10.1.1	PUCCH format information.....	155
10.1.2	FDD HARQ-ACK feedback procedures.....	157
10.1.2.1	FDD HARQ-ACK procedure for one configured serving cell.....	157
10.1.2.2	FDD HARQ-ACK procedures for more than one configured serving cell	158
10.1.2.2.1	PUCCH format 1b with channel selection HARQ-ACK procedure.....	159
10.1.2.2.2	PUCCH format 3 HARQ-ACK procedure	162

10.1.3	TDD HARQ-ACK feedback procedures	164
10.1.3.1	TDD HARQ-ACK procedure for one configured serving cell.....	165
10.1.3.2	TDD HARQ-ACK procedure for more than one configured serving cell.....	175
10.1.3.2.1	PUCCH format 1b with channel selection HARQ-ACK procedure.....	175
10.1.3.2.2	PUCCH format 3 HARQ-ACK procedure	190
10.1.3A	FDD-TDD HARQ-ACK feedback procedures for primary cell frame structure type 2	196
10.1.4	HARQ-ACK Repetition procedure.....	197
10.1.5	Scheduling Request (SR) procedure	199
10.2	Uplink HARQ-ACK timing	200
11	Physical Multicast Channel (PMCH) related procedures.....	203
11.1	UE procedure for receiving the PMCH	203
11.2	UE procedure for receiving MCCH change notification	203
12	Assumptions independent of physical channel.....	203
13	Uplink/Downlink configuration determination procedure for Frame Structure Type 2.....	203
Annex A (informative):	Change history	206
History		213

iTeh STANDARD PREVIEW
 (standards.iteh.ai)
 Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b52382cc-70b7-4a29-b6df-838173f6e840/etsi-ts-136-213-v12.3.0-2014-10>

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of this present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b2-382cc-70b7-4a29-b6df-838173f6e840/etsi-ts-136-213-v12-3-0-2014-10>

1 Scope

The present document specifies and establishes the characteristics of the physical layer procedures in the FDD and TDD modes of E-UTRA.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 36.201: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Layer – General Description".
- [3] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation".
- [4] 3GPP TS 36.212: "Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding".
- [5] 3GPP TS 36.214: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer – Measurements".
- [6] 3GPP TS 36.101: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception".
- [7] 3GPP TS 36.104: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) radio transmission and reception".
- [8] 3GPP TS 36.321, "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification".
- [9] 3GPP TS 36.423, "Evolved Universal Terrestrial Radio Access (E-UTRA); X2 Application Protocol (X2AP)".
- [10] 3GPP TS 36.133, "Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management".
- [11] 3GPP TS 36.331, "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) protocol specification".
- [12] 3GPP TS 36.306: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio access capabilities".

3 Symbols and abbreviations

3.1 Symbols

For the purposes of the present document, the following symbols apply:

n_f	System frame number as defined in [3]
n_s	Slot number within a radio frame as defined in [3]
N_{cells}^{DL}	Number of configured cells
N_{RB}^{DL}	Downlink bandwidth configuration, expressed in units of N_{sc}^{RB} as defined in [3]
N_{RB}^{UL}	Uplink bandwidth configuration, expressed in units of N_{sc}^{RB} as defined in [3]
N_{symb}^{UL}	Number of SC-FDMA symbols in an uplink slot as defined in [3]
N_{sc}^{RB}	Resource block size in the frequency domain, expressed as a number of subcarriers as defined in [3]
T_s	Basic time unit as defined in [3]

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ACK	Acknowledgement
BCH	Broadcast Channel
CCE	Control Channel Element
CDD	Cyclic Delay Diversity
CIF	Carrier Indicator Field
CQI	Channel Quality Indicator
CRC	Cyclic Redundancy Check
CSI	Channel State Information
CSI-IM	CSI-interference measurement
DAI	Downlink Assignment Index
DCI	Downlink Control Information
DL	Downlink
DL-SCH	Downlink Shared Channel
DTX	Discontinuous Transmission
EPDCCH	Enhanced Physical Downlink Control Channel
EPRE	Energy Per Resource Element
MCS	Modulation and Coding Scheme
NACK	Negative Acknowledgement
PBCH	Physical Broadcast Channel
PCFICH	Physical Control Format Indicator Channel
PDCCH	Physical Downlink Control Channel
PDSCH	Physical Downlink Shared Channel
PHICH	Physical Hybrid ARQ Indicator Channel
PMCH	Physical Multicast Channel
PMI	Precoding Matrix Indicator
PRACH	Physical Random Access Channel
PRS	Positioning Reference Signal
PRB	Physical Resource Block
PUCCH	Physical Uplink Control Channel
PUSCH	Physical Uplink Shared Channel
PTI	Precoding Type Indicator
RBG	Resource Block Group

RE	Resource Element
RI	Rank Indication
RS	Reference Signal
SINR	Signal to Interference plus Noise Ratio
SPS C-RNTI	Semi-Persistent Scheduling C-RNTI
SR	Scheduling Request
SRS	Sounding Reference Symbol
TAG	Timing Advance Group
TBS	Transport Block Size
UCI	Uplink Control Information
UE	User Equipment
UL	Uplink
UL-SCH	Uplink Shared Channel
VRB	Virtual Resource Block

iTeh STANDARD PREVIEW
(standards.iteh.ai)

Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b52382cc-70b7-4a29-b6df-838173f6e840/etsi-ts-136-213-v12.3.0-2014-10>

4 Synchronization procedures

4.1 Cell search

Cell search is the procedure by which a UE acquires time and frequency synchronization with a cell and detects the physical layer Cell ID of that cell. E-UTRA cell search supports a scalable overall transmission bandwidth corresponding to 6 resource blocks and upwards.

The following signals are transmitted in the downlink to facilitate cell search: the primary and secondary synchronization signals.

A UE may assume the antenna ports 0 – 3 and the antenna port for the primary/secondary synchronization signals of a serving cell are quasi co-located (as defined in [3]) with respect to Doppler shift and average delay.

4.2 Timing synchronization

4.2.1 Radio link monitoring

The downlink radio link quality of the primary cell shall be monitored by the UE for the purpose of indicating out-of-sync/in-sync status to higher layers.

In non-DRX mode operation, the physical layer in the UE shall every radio frame assess the radio link quality, evaluated over the previous time period defined in [10], against thresholds (Q_{out} and Q_{in}) defined by relevant tests in [10].

In DRX mode operation, the physical layer in the UE shall at least once every DRX period assess the radio link quality, evaluated over the previous time period defined in [10], against thresholds (Q_{out} and Q_{in}) defined by relevant tests in [10].

If higher-layer signalling indicates certain subframes for restricted radio link monitoring, the radio link quality shall not be monitored in any subframe other than those indicated.

The physical layer in the UE shall in radio frames where the radio link quality is assessed indicate out-of-sync to higher layers when the radio link quality is worse than the threshold Q_{out} . When the radio link quality is better than the threshold Q_{in} , the physical layer in the UE shall in radio frames where the radio link quality is assessed indicate in-sync to higher layers.

4.2.2 Inter-cell synchronization

No functionality is specified in this subclause in this release.

4.2.3 Transmission timing adjustments

Upon reception of a timing advance command for a TAG containing the primary cell, the UE shall adjust uplink transmission timing for PUCCH/PUSCH/SRS of the primary cell based on the received timing advance command. The UL transmission timing for PUSCH/SRS of a secondary cell is the same as the primary cell if the secondary cell and the primary cell belong to the same TAG.

Upon reception of a timing advance command for a TAG not containing the primary cell, if all the serving cells in the TAG have the same frame structure type, the UE shall adjust uplink transmission timing for PUSCH/SRS of all the secondary cells in the TAG based on the received timing advance command where the UL transmission timing for PUSCH /SRS is the same for all the secondary cells in the TAG.

Upon reception of a timing advance command for a TAG not containing the primary cell, if a serving cell in the TAG has a different frame structure type compared to the frame structure type of another serving cell in the same TAG, the UE shall adjust uplink transmission timing for PUSCH/SRS of all the secondary cells in the TAG by using $N_{TAoffset} = 624$ regardless of the frame structure type of the serving cells and based on the received timing advance command

where the UL transmission timing for PUSCH /SRS is the same for all the secondary cells in the TAG. $N_{TAoffset}$ is described in [3].

The timing advance command for a TAG indicates the change of the uplink timing relative to the current uplink timing for the TAG as multiples of $16 T_s$. The start timing of the random access preamble is specified in [3].

In case of random access response, an 11-bit timing advance command [8], T_A , for a TAG indicates N_{TA} values by index values of $T_A = 0, 1, 2, \dots, 1282$, where an amount of the time alignment for the TAG is given by $N_{TA} = T_A \times 16$. N_{TA} is defined in [3].

In other cases, a 6-bit timing advance command [8], T_A , for a TAG indicates adjustment of the current N_{TA} value, $N_{TA,old}$, to the new N_{TA} value, $N_{TA,new}$, by index values of $T_A = 0, 1, 2, \dots, 63$, where $N_{TA,new} = N_{TA,old} + (T_A - 31) \times 16$. Here, adjustment of N_{TA} value by a positive or a negative amount indicates advancing or delaying the uplink transmission timing for the TAG by a given amount respectively.

For a timing advance command received on subframe n , the corresponding adjustment of the uplink transmission timing shall apply from the beginning of subframe $n+6$. For serving cells in the same TAG, when the UE's uplink PUCCH/PUSCH/SRS transmissions in subframe n and subframe $n+1$ are overlapped due to the timing adjustment, the UE shall complete transmission of subframe n and not transmit the overlapped part of subframe $n+1$.

If the received downlink timing changes and is not compensated or is only partly compensated by the uplink timing adjustment without timing advance command as specified in [10], the UE changes N_{TA} accordingly.

4.3 Timing for Secondary Cell Activation / Deactivation

When a UE receives an activation command [8] for a secondary cell in subframe n , the corresponding actions in [8] shall be applied no later than the minimum requirement defined in [10] and no earlier than subframe $n+8$, except for the following:

- the actions related to CSI reporting
- the actions related to the *sCellDeactivationTimer* associated with the secondary cell [8]

which shall be applied in subframe $n+8$.

When a UE receives a deactivation command [8] for a secondary cell or the *sCellDeactivationTimer* associated with the secondary cell expires in subframe n , the corresponding actions in [8] shall apply no later than the minimum requirement defined in [10], except for the actions related to CSI reporting which shall be applied in subframe $n+8$.

5 Power control

Downlink power control determines the Energy Per Resource Element (EPRE). The term Resource Element Energy denotes the energy prior to CP insertion. The term resource element energy also denotes the average energy taken over all constellation points for the modulation scheme applied. Uplink power control determines the average power over a SC-FDMA symbol in which the physical channel is transmitted.

5.1 Uplink power control

Uplink power control controls the transmit power of the different uplink physical channels.

For PUSCH, the transmit power $\hat{P}_{\text{PUSCH},c}(i)$ defined in subclause 5.1.1, is first scaled by the ratio of the number of antennas ports with a non-zero PUSCH transmission to the number of configured antenna ports for the transmission scheme. The resulting scaled power is then split equally across the antenna ports on which the non-zero PUSCH is transmitted.

For PUCCH or SRS, the transmit power $\hat{P}_{\text{PUCCH}}(i)$, defined in subclause 5.1.1.1, or $\hat{P}_{\text{SRS},c}(i)$ is split equally across the configured antenna ports for PUCCH or SRS. $\hat{P}_{\text{SRS},c}(i)$ is the linear value of $P_{\text{SRS},c}(i)$ defined in subclause 5.1.3.

A cell wide overload indicator (OI) and a High Interference Indicator (HII) to control UL interference are defined in [9].

5.1.1 Physical uplink shared channel

5.1.1.1 UE behaviour

The setting of the UE Transmit power for a Physical Uplink Shared Channel (PUSCH) transmission is defined as follows.

If the UE transmits PUSCH without a simultaneous PUCCH for the serving cell c , then the UE transmit power $P_{\text{PUSCH},c}(i)$ for PUSCH transmission in subframe i for the serving cell c is given by

$$P_{\text{PUSCH},c}(i) = \min \left\{ P_{\text{CMAX},c}(i), 10 \log_{10}(M_{\text{PUSCH},c}(i)) + P_{\text{O_PUSCH},c}(j) + \alpha_c(j) \cdot PL_c + \Delta_{\text{TF},c}(i) + f_c(i) \right\} \quad [\text{dBm}]$$

If the UE transmits PUSCH simultaneous with PUCCH for the serving cell c , then the UE transmit power $P_{\text{PUSCH},c}(i)$ for the PUSCH transmission in subframe i for the serving cell c is given by

$$P_{\text{PUSCH},c}(i) = \min \left\{ 10 \log_{10}(\hat{P}_{\text{CMAX},c}(i) - \hat{P}_{\text{PUCCH}}(i)), 10 \log_{10}(M_{\text{PUSCH},c}(i)) + P_{\text{O_PUSCH},c}(j) + \alpha_c(j) \cdot PL_c + \Delta_{\text{TF},c}(i) + f_c(i) \right\} \quad [\text{dBm}]$$

If the UE is not transmitting PUSCH for the serving cell c , for the accumulation of TPC command received with DCI format 3/3A for PUSCH, the UE shall assume that the UE transmit power $P_{\text{PUSCH},c}(i)$ for the PUSCH transmission in subframe i for the serving cell c is computed by

$$P_{\text{PUSCH},c}(i) = \min \{ P_{\text{CMAX},c}(i), P_{\text{O_PUSCH},c}(1) + \alpha_c(1) \cdot PL_c + f_c(i) \} \quad [\text{dBm}]$$

where,

- $P_{\text{CMAX},c}(i)$ is the configured UE transmit power defined in [6] in subframe i for serving cell c and $\hat{P}_{\text{CMAX},c}(i)$ is the linear value of $P_{\text{CMAX},c}(i)$. If the UE transmits PUCCH without PUSCH in subframe i for the serving cell c , for the accumulation of TPC command received with DCI format 3/3A for PUSCH, the UE shall assume $P_{\text{CMAX},c}(i)$ as given by subclause 5.1.2.1. If the UE does not transmit PUCCH and PUSCH in subframe i for the serving cell c , for the accumulation of TPC command received with DCI format 3/3A for