



SLOVENSKI STANDARD
SIST ETS 300 938 E1:2003

01-december-2003

8][JhUb]`WY] b]`hYY_ca i b]_UWg]`g]ghYa `E`AcV]`bUdcgjhU`U`E`Ja Ygb]`g]ghYa U
VUnbY`dcgjhU`Y`fA G!6 GGŁ`E`GdYWZ]_UW`UdcXUh_cj bY`dcj Yncj UbY`d`Ugl`f` GA
\$("\$* žfUh]]WU) \$"%L

Digital cellular telecommunications system; Mobile Station - Base Station System (MS - BSS) interface; Data Link (DL) layer specification (GSM 04.06 version 5.0.1)

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 938 E1:2003](#)

Ta slovenski standard je istoveten z: <https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-b8c7d89a/e8/sist-ets-300-938-e1-2003> **ETS 300 938 Edition 1**

ICS:

33.070.50	Globalni sistem za mobilno telekomunikacijo (GSM)	Global System for Mobile Communication (GSM)
-----------	---	--

SIST ETS 300 938 E1:2003

en

**iTeh STANDARD PREVIEW
(standards.iteh.ai)**

[SIST ETS 300 938 E1:2003](#)

<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-f5be7d89a7e8/sist-ets-300-938-e1-2003>



EUROPEAN TELECOMMUNICATION STANDARD

ETS 300 938

April 1997

Source: ETSI TC-SMG

Reference: DE/SMG-030406Q

ICS: 33.020

Key words: Digital cellular telecommunications system, Global System for Mobile communications (GSM)

iTeh STANDARD REVIEW
GSM[®]
 (standards.iteh.ai)
 GLOBAL SYSTEM FOR
 MOBILE COMMUNICATIONS
SIST ETS 300 938 E1:2003
<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-000000000000>
Digital cellular telecommunications system;
Mobile Station - Base Station System (MS - BSS) interface;
Data Link (DL) layer specification
(GSM 04.06 version 5.0.1)

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1997. All rights reserved.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 938 E1:2003](#)
<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-f5be7d89a7e8/sist-ets-300-938-e1-2003>

Contents

Foreword	7
0 Scope	9
0.1 Normative references	9
0.2 Abbreviations	9
1 General.....	10
2 Frame structure for peer-to-peer communication	11
2.1 General	11
2.2 Frame delimitation and fill bits	13
2.3 Address field	13
2.4 Control field.....	13
2.5 Length indicator field.....	13
2.6 Information field	13
2.7 Transparency	14
2.8 Format convention	14
2.8.1 Numbering convention	14
2.8.2 Order of bit transmission	14
2.8.3 Field mapping convention	14
3 Elements of procedures and formats of fields for Data Link Layer peer-to-peer communication.....	15
3.1 General	15
3.2 Address field format	15
3.3 Address field variables	15
3.3.1 Address field extension bit (EA)	15
3.3.2 Command/response field bit (C/R).....	15
3.3.3 Service access point Identifier (SAPI).....	16
3.4 Control field formats.....	16
3.4.1 Information transfer format - I	16
3.4.2 Supervisory format - S.....	16
3.4.3 Unnumbered format - U	16
3.5 Control field parameters and associated state variables	17
3.5.1 Poll/Final bit.....	17
3.5.2 Multiple frame operation - variables and sequence numbers	17
3.5.2.1 Modulus	17
3.5.2.2 Send state variable V(S).....	17
3.5.2.3 Acknowledge state variable V(A).....	18
3.5.2.4 Send sequence number N(S)	18
3.5.2.5 Receive state variable V(R)	18
3.5.2.6 Receive sequence number N(R)	18
3.5.2.7 Other parameters and variables	18
3.5.3 Unacknowledged operation variables and parameters	18
3.6 Length indicator field format	19
3.7 Length indicator field variables	19
3.7.1 Length indicator field extension bit (EL)	19
3.7.2 More data bit (M)	19
3.7.3 Length indicator (L)	19
3.8 Commands and responses.....	19
3.8.1 Information (I) commands	20
3.8.2 Set asynchronous balanced mode (SABM) command	20
3.8.3 Disconnect (DISC) command.....	21
3.8.4 Unnumbered information (UI) command.....	21
3.8.5 Receive ready (RR) command/response	21
3.8.6 Reject (REJ) command/response	22
3.8.7 Receive not ready (RNR) command/response	22
3.8.8 Unnumbered acknowledgement (UA) response	22

3.8.9	Disconnected mode (DM) response	22
4	Elements for layer-to-layer communication	23
4.1	Definition of primitives and parameters.....	23
4.1.1	Generic names	23
4.1.1.1	DL-ESTABLISH.....	23
4.1.1.2	DL-RELEASE.....	23
4.1.1.3	DL-DATA.....	23
4.1.1.4	DL-UNIT DATA	23
4.1.1.5	DL-SUSPEND	23
4.1.1.6	DL-RESUME	23
4.1.1.7	DL-RECONNECT	24
4.1.1.8	DL-RANDOM ACCESS.....	24
4.1.1.9	MDL-RELEASE	24
4.1.1.10	MDL-ERROR	24
4.1.1.11	PH-DATA	24
4.1.1.12	PH-RANDOM ACCESS	24
4.1.1.13	PH-CONNECT	24
4.1.1.14	PH-READY-TO-SEND	24
4.1.1.15	PH-EMPTY-FRAME.....	24
4.1.2	Primitives types.....	24
4.1.2.1	REQUEST.....	24
4.1.2.2	INDICATION	25
4.1.2.3	RESPONSE	25
4.1.2.4	CONFIRM	25
4.1.3	Parameter definition.....	25
4.1.3.1	Message unit.....	25
4.1.3.2	Channel type.....	26
4.1.3.3	Service Access Point.....	26
4.1.3.4	Release mode	26
4.1.3.5	Error cause	26
4.1.3.6	Establish mode	26
4.2	Primitive procedures	30
5	Definition of the peer-to-peer protocol LAPDm..... https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-5be/d89a/cb/sist-ets-300-938-e1-2003	31
5.1	General.....	31
5.2	General Protocol Procedures.....	32
5.2.1	Unacknowledged information transfer	32
5.2.2	Acknowledged multiple frame information transfer	32
5.3	Procedures for unacknowledged information transfer	32
5.3.1	General	32
5.3.2	Transmission of unacknowledged information	32
5.3.3	Receipt of unacknowledged information	32
5.4	Procedures for establishment and release of multiple frame operation.....	33
5.4.1	Establishment of multiple frame operation	33
5.4.1.1	General	33
5.4.1.2	Normal establishment procedures	33
5.4.1.3	Procedure on expiry of timer T200: Normal establishment.	34
5.4.1.4	Contention resolution establishment procedure.....	34
5.4.1.5	Procedure on expiry of timer T200: contention resolution (MS only)	36
5.4.2	Information transfer	36
5.4.2.1	General requirements	36
5.4.2.2	Error conditions	37
5.4.2.3	Fill frames	37
5.4.3	Suspension and resumption of multiple frame operation	38
5.4.3.1	General	38
5.4.3.2	Suspension	39
5.4.3.3	Resumption.....	39
5.4.3.3.1	Procedure after channel change	39
5.4.3.3.2	Procedure after returning to the old channel (MS only)	40
5.4.4	Termination of multiple frame operation	40

5.4.4.1	General	40
5.4.4.2	Normal release procedure	41
5.4.4.3	Procedure on expiry of timer T200 for normal release	41
5.4.4.4	Local end release procedure	41
5.4.5	Idle state	42
5.4.6	Collision of unnumbered commands and responses	42
5.4.6.1	Identical transmitted and received commands	42
5.4.6.2	Different transmitted and received commands	42
5.4.6.3	Unsolicited DM response and SABM or DISC command	42
5.5	Procedures for information transfer in multiple frame operation	43
5.5.1	Transmitting I frames	43
5.5.2	Receiving I frames	43
5.5.2.1	P bit of the received I frame set to "1"	44
5.5.2.2	P bit of the received I frame set to "0"	44
5.5.3	Receiving acknowledgement	44
5.5.3.1	On receipt of a valid I frame	44
5.5.3.2	Receiving supervisory command frames with the P bit set to "1"	45
5.5.4	Receiving REJ frames	45
5.5.4.1	Receipt of a valid REJ frame	45
5.5.4.2	Transmitting frames	46
5.5.5	Receiving RNR frame	46
5.5.6	Data link layer own receiver busy condition	47
5.5.7	Waiting acknowledgement	48
5.6	Abnormal release and re-establishment of multiple frame operation	49
5.6.1	Criteria for re-establishment	49
5.6.2	Criteria for abnormal release	49
5.6.3	Procedures for re-establishment	49
5.6.4	Procedures for abnormal release	49
5.7	Exception condition reporting and recovery for multiple frame operation	49
5.7.1	N(S) sequence error	50
5.7.2	Timer recovery	50
5.7.3	Invalid frame condition	50
5.7.4	N(R) sequence error	51
5.8	List of system parameters	51
5.8.1	Timer T200	51
5.8.1.1	For SAPI=0 and SAPI=3	51
5.8.1.2	For SAPIs other than 0 or 3	51
5.8.2	Maximum number of retransmissions (N200)	52
5.8.2.1	For SAPI=0 and 3	52
5.8.2.2	For SAPIs other than 0 or 3	52
5.8.3	Maximum number of octets in an I, UI, SABM and UA frame information field (N201)	52
5.8.4	Maximum number of outstanding I frames (k)	52
5.8.5	Maximum number of octets in a Layer 3 message	52
5.9	System performance requirements	52
6	Special protocol operation on SAPI=0 and SAPI=3	53
Annex A (normative): Random access procedures		55
A.1	Description of the procedure	55
A.1.1	Procedure in the MS	55
A.1.2	Procedure in the BS	55
A.2	Format	55
Annex G (normative): Handling of frames with parameter errors in the address, control and length indicator fields		56
G.1	General	56
G.2	Parameter errors in the address field	56

G.2.1	Unallocated SAPI	56
G.2.2	Wrong value of the C/R bit.....	56
G.2.3	EA bit set to "0"	56
G.3	Parameter errors in the control field	57
G.3.1	Supervisory frames	57
G.3.2	Unnumbered frames	57
G.4	Parameter errors in the length indicator field.....	57
G.4.1	EL bit error.....	57
G.4.2	Information frames	57
G.4.3	Supervisory frames	58
G.4.4	DISC and DM frames	58
G.4.5	SABM UA and UI frames	58
	History	59

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 938 E1:2003](#)
<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-f5be7d89a7e8/sist-ets-300-938-e1-2003>

Foreword

This European Telecommunication Standard (ETS) has been produced by the Special Mobile Group (SMG) Technical Committee (TC) of the European Telecommunications Standards Institute (ETSI).

This ETS defines the data link layer protocol of the Mobile Station - Base Station System (MS - BSS) interface within the digital cellular telecommunications system.

The ETS from which this ETS has evolved is Phase 2 GSM ETS 300 555 (GSM 04.06 version 4.4.0).

The contents of this ETS is subject to continuing work within TC-SMG and may change following formal TC-SMG approval. Should TC-SMG modify the contents of this ETS, it will be resubmitted for OAP by ETSI with an identifying change of release date and an increase in version number as follows:

Version 5.x.y

where:

- y the third digit is incremented when editorial only changes have been incorporated in the specification;
- x the second digit is incremented for all other types of changes, i.e. technical enhancements, corrections, updates, etc.

The specification from which this ETS has been derived was originally based on CEPT documentation, hence the presentation of this ETS may not be entirely in accordance with the ETSI drafting rules.

Annexes B to F were deleted from the original specification, however, for referencing purposes the annex numbering has been maintained.

ITEH STANDARD PREVIEW

(standards.iteh.ai)

Transposition dates

Date of adoption:	SIST ETS 300 938 E1:2003	28 March 1997
Date of latest announcement of this ETS (doa):	Doa/sist-ets-300-938-e1-2003	31 July 1997
Date of latest publication of new National Standard or endorsement of this ETS (dop/e):		31 January 1998
Date of withdrawal of any conflicting National Standard (dow):		31 January 1998

Blank page

**iTeh STANDARD PREVIEW
(standards.iteh.ai)**

SIST ETS 300 938 E1:2003
<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-f5be7d89a7e8/sist-ets-300-938-e1-2003>

0 Scope

This European Telecommunication Standard (ETS) defines a data link layer protocol to be used for signalling, and possibly also for other applications, on the MS-BS interface.

0.1 Normative references

This ETS incorporates by dated and undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references, the latest edition of the publication referred to applies.

- [1] GSM 01.04 (ETR 350): "Digital cellular telecommunications system (Phase 2+); Abbreviations and acronyms".
- [2] GSM 04.01: "Digital cellular telecommunications system; Mobile Station - Base Station System (MS - BSS) interface; General aspects and principles".
- [3] GSM 04.03: "Digital cellular telecommunications system (Phase 2+); Mobile Station - Base Station System (MS - BSS) interface Channel structures and access capabilities".
- [4] GSM 04.04 (ETS 300 936): "Digital cellular telecommunications system; Layer 1 General requirements".
- [5] GSM 04.05 (ETS 300 937): "Digital cellular telecommunications system; Data Link (DL) layer General aspects".
- [6] GSM 04.07 (ETS 300 939): "Digital cellular telecommunications system (Phase 2+); Mobile radio interface signalling layer 3; General aspects".
- [7] GSM 04.08 (ETS 300 940): "Digital cellular telecommunications system (Phase 2+), Mobile radio interface layer 3 specification".
<https://standards.itelektura.com/ets-300-940-digital-cellular-telecommunications-system-phase-2--mobile-radio-interface-layer-3-specification-5bc7d89a7e8/sist-ets-300-938-e1-2003>
- [8] GSM 04.10 (ETS 300 941): "Digital cellular telecommunications system; Mobile radio interface layer 3 Supplementary services specification; General aspects".
- [9] GSM 04.12 (ETS 300 943): "Digital cellular telecommunications system (Phase 2+); Short Message Service Cell Broadcast (SMSCB) support on the mobile radio interface".
- [10] GSM 05.02 (ETS 300 908): "Digital cellular telecommunications system (Phase 2+); Multiplexing and multiple access on the radio path".
- [11] GSM 08.56: "Digital cellular telecommunications system; Base Station Controller - Base Transceiver Station (BSC - BTS) interface; Layer 2 specification".
- [12] GSM 08.58: "Digital cellular telecommunications system (Phase 2+); Base Station Controller - Base Transceiver Station (BSC - BTS) interface; Layer 3 specification".
- [13] CCITT Recommendation Z.100: "Specification and description language (SDL)".

0.2 Abbreviations

Abbreviations used in this ETS are listed in GSM 01.04.

1 General

This ETS describes the frame structure, elements of procedure, format of fields and procedures for the proper operation of the Link Access Procedure on the Dm channel, LAPDm.

NOTE 1: The term Dm channel is used for convenience to designate the collection of all the various signalling channels required in the GSM system. See also GSM 04.03.

The concepts, terminology, overview description of LAPDm functions and procedures, and the relationship with other Technical Specifications are described in general terms in GSM 04.05.

The frame formats defined for LAPDm are based on those defined for LAPD. However, there are important differences between LAPDm and LAPD, in particular with regard to frame delimitation methods and transparency mechanisms. These differences are necessary for operation within the constraints set by the radio path.

LAPDm supports two modes of operation:

- unacknowledged operation using UI frames;
- acknowledged operation using the multiple frame procedure.

As a choice of implementation, the two modes of operation may be implemented independently of each other. This is possible since there is no interactions between the two modes, other than queuing at the transmitter, even when they coexist on the same physical channel. For BCCHs and CCCHs only the unacknowledged mode of operation needs to be implemented.

LAPDm is used for information sent on the control channels BCCH, AGCH, PCH, FACCH, SACCH and SDCCH as defined in GSM 04.03.

iTeh STANDARD PREVIEW

NOTE 2: AGCH and PCH are sometimes referred to by the collective name CCCH and FACCH, SACCH and SDCCH are, similarly, referred to by the collective name DCCH.

LAPDm may also be used on other types of channel:

<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-5e748947e8/sist-ets-300-038-e1-2003>

NOTE 3: As stated in GSM 04.05, the term "data link layer" is used in the main text of this ETS. However, mainly in figures and tables, the terms "layer 2" and "L2" are used as abbreviations. Furthermore, in accordance with GSM 04.07 and GSM 04.08, the term "layer 3" is used to indicate the layer above the data link layer.

This ETS is organized as follows:

The frame structure for peer-to-peer communication is given in clause 2. The elements of procedure and formats of fields are given in clause 3. The elements of layer-to-layer communication are contained in clause 4. The details of the peer-to-peer procedures are given in clause 5. Clause 6 summarizes the special protocol operations used mandatorily with SAPI=0 and SAPI=3.

The specification for the random access channel is contained in annex A, even though it is not a LAPDm function. This part of the ETS is descriptive and does not constrain the implementation of the random access function. The procedure is used for CHANNEL REQUEST on the RACH and HANDOVER ACCESS on the main DCCH.

(Annexes B to F are deleted.)

Annex G gives an overview of actions taken on frames containing parameter errors.

2 Frame structure for peer-to-peer communication

2.1 General

All data link layer peer-to-peer exchanges are in frames conforming to one of the formats shown in figure 1. Several format types are shown in the figure: format A is used on DCCHs for frames where there is no information field, Format B is used on DCCHs for frames containing an information field, and format Bbis is used only on BCCH, PCH, and AGCH. In addition there is a Format C for transmission of random access signals.

Format C frames are described in annex A. Format A and B/Bbis frames are described in the remainder of this ETS.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

SIST ETS 300 938 E1:2003
<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d-f5be7d89a7e8/sist-ets-300-938-e1-2003>






Figure 1/GSM 04.06 (sheet 1 of 2): General frame formats

**Figure 1/GSM 04.06 (sheet 2 of 2): General frame formats**

The parameter N201 takes a fixed value for each type of channel, see subclause 5.8.3, and determines the maximum number of octets in the information field of a frame.

2.2 Frame delimitation and fill bits

Frame delimitation is provided by the physical layer:

- in format type A and B frames at the beginning of the frame for determining the start of the first octet in the address field and in format type Bbis frames for determining the start of the first octet for the information field;
- at the end of the frame for determining the last bit of the frame.

The end of the useful part of the frame, i.e. the end of the length indicator field in type A frames and the end of the information field in type B frames, is determined by a length indicator contained in the length indicator field; the useful part of a Bbis frames takes all N201 octets of that frame.

If a frame contains a length indicator has a value less than N201, the frame contains fill bits. Octets containing fill bits shall take the binary value "00101011", when sent by the network. Octets containing fill bits shall take the value "00101011" or "11111111", when sent by the mobile station.

<https://standards.iteh.ai/catalog/standards/sist/b0302cb0-d0ea-4b6c-832d>

NOTE: The value "00101011" is chosen due to the modulation and interleaving scheme used in the GSM system.

2.3 Address field

The address field may consist of a variable number of octets. However, for applications on control channels the field consists of only one octet. The address field identifies the SAP for which a command frame is intended and the SAP transmitting a response frame. The format of the address field is defined in subclause 3.2.

2.4 Control field

The control field consists of one octet. The format of the control field is defined in subclause 3.4.

2.5 Length indicator field

The length indicator field may consist of a variable number of octets. However, for applications on control channels the field consists of only one octet. The format of the field is defined in subclause 3.6.

2.6 Information field

The information field of a frame, when present, follows the length indicator field (see subclause 2.5).

The maximum number of octets in the information field (N201) is defined in subclause 5.8.3.