

ETSI TS 136 211 V13.13.0 (2020-01)



LTE;
Evolved Universal Terrestrial Radio Access (E-UTRA);
Physical channels and modulation
(3GPP TS 36.211 version 13.13.0 Release 13)

iTeh Standards (standards.it-eh.com)
Full standards catalog: <https://standards.it-eh.com/catalog/standards/sls/6451deb-982-41e7-8ab2-4b0609c19520/etsi-ts-136-211-v13-13-0-2020-01>



ReferenceRTS/TSGR-0136211vdd0

KeywordsLTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	9
1 Scope	10
2 References	10
3 Symbols and abbreviations.....	10
3.1 Symbols.....	10
3.2 Abbreviations	14
4 Frame structure.....	15
4.1 Frame structure type 1	15
4.2 Frame structure type 2	16
4.3 Frame structure type 3	17
5 Uplink.....	18
5.1 Overview	18
5.1.1 Physical channels.....	18
5.1.2 Physical signals.....	18
5.2 Slot structure and physical resources.....	18
5.2.1 Resource grid	18
5.2.2 Resource elements	20
5.2.3 Resource blocks	20
5.2.4 Narrowbands.....	20
5.2.5 Guard period for narrowband retuning	21
5.3 Physical uplink shared channel.....	22
5.3.1 Scrambling	22
5.3.2 Modulation.....	23
5.3.2A Layer mapping	24
5.3.2A.1 Layer mapping for transmission on a single antenna port.....	24
5.3.2A.2 Layer mapping for spatial multiplexing	24
5.3.3 Transform precoding.....	25
5.3.3A Precoding	25
5.3.3A.1 Precoding for transmission on a single antenna port.....	25
5.3.3A.2 Precoding for spatial multiplexing	25
5.3.4 Mapping to physical resources.....	28
5.4 Physical uplink control channel.....	30
5.4.1 PUCCH formats 1, 1a and 1b	31
5.4.2 PUCCH formats 2, 2a and 2b	34
5.4.2A PUCCH format 3	35
5.4.2B PUCCH format 4	37
5.4.2C PUCCH format 5	37
5.4.3 Mapping to physical resources.....	38
5.5 Reference signals.....	41
5.5.1 Generation of the reference signal sequence.....	41
5.5.1.1 Base sequences of length $3N_{sc}^{RB}$ or larger	41
5.5.1.2 Base sequences of length less than $3N_{sc}^{RB}$	42
5.5.1.3 Group hopping	44
5.5.1.4 Sequence hopping	45
5.5.1.5 Determining virtual cell identity for sequence generation	45
5.5.2 Demodulation reference signal	46
5.5.2.1 Demodulation reference signal for PUSCH	46
5.5.2.1.1 Reference signal sequence.....	46
5.5.2.1.2 Mapping to physical resources	48

5.5.2.2	Demodulation reference signal for PUCCH.....	48
5.5.2.2.1	Reference signal sequence.....	48
5.5.2.2.2	Mapping to physical resources	50
5.5.3	Sounding reference signal.....	51
5.5.3.1	Sequence generation.....	51
5.5.3.2	Mapping to physical resources	51
5.5.3.3	Sounding reference signal subframe configuration	54
5.6	SC-FDMA baseband signal generation	55
5.7	Physical random access channel.....	56
5.7.1	Time and frequency structure	56
5.7.2	Preamble sequence generation.....	63
5.7.3	Baseband signal generation.....	66
5.8	Modulation and upconversion	67
6	Downlink.....	68
6.1	Overview	68
6.1.1	Physical channels.....	68
6.1.2	Physical signals.....	68
6.2	Slot structure and physical resource elements	69
6.2.1	Resource grid.....	69
6.2.2	Resource elements	70
6.2.3	Resource blocks	71
6.2.3.1	Virtual resource blocks of localized type	71
6.2.3.2	Virtual resource blocks of distributed type	71
6.2.4	Resource-element groups.....	73
6.2.4A	Enhanced Resource-Element Groups (EREGs).....	73
6.2.5	Guard period for half-duplex FDD operation	74
6.2.6	Guard Period for TDD Operation	74
6.2.7	Narrowbands.....	74
6.2.8	Guard period for narrowband retuning	74
6.3	General structure for downlink physical channels.....	75
6.3.1	Scrambling.....	75
6.3.2	Modulation.....	76
6.3.3	Layer mapping	76
6.3.3.1	Layer mapping for transmission on a single antenna port.....	77
6.3.3.2	Layer mapping for spatial multiplexing	77
6.3.3.3	Layer mapping for transmit diversity	80
6.3.4	Precoding.....	80
6.3.4.1	Precoding for transmission on a single antenna port.....	80
6.3.4.2	Precoding for spatial multiplexing using antenna ports with cell-specific reference signals	80
6.3.4.2.1	Precoding without CDD	80
6.3.4.2.2	Precoding for large delay CDD	81
6.3.4.2.3	Codebook for precoding and CSI reporting.....	82
6.3.4.3	Precoding for transmit diversity	83
6.3.4.4	Precoding for spatial multiplexing using antenna ports with UE-specific reference signals.....	84
6.3.5	Mapping to resource elements	84
6.4	Physical downlink shared channel.....	85
6.4.1	Physical downlink shared channel for BL/CE UEs	86
6.5	Physical multicast channel	88
6.6	Physical broadcast channel.....	88
6.6.1	Scrambling.....	88
6.6.2	Modulation.....	89
6.6.3	Layer mapping and precoding	89
6.6.4	Mapping to resource elements	89
6.7	Physical control format indicator channel.....	90
6.7.1	Scrambling.....	91
6.7.2	Modulation.....	91
6.7.3	Layer mapping and precoding	91
6.7.4	Mapping to resource elements	91
6.8	Physical downlink control channel.....	92
6.8.1	PDCCH formats.....	92
6.8.2	PDCCH multiplexing and scrambling	92

6.8.3	Modulation.....	92
6.8.4	Layer mapping and precoding	93
6.8.5	Mapping to resource elements	93
6.8A	Enhanced physical downlink control channel	94
6.8A.1	EPDCCH formats	94
6.8A.2	Scrambling	95
6.8A.3	Modulation.....	95
6.8A.4	Layer mapping and precoding	96
6.8A.5	Mapping to resource elements	96
6.8B	MTC physical downlink control channel	97
6.8B.1	MPDCCH formats	97
6.8B.2	Scrambling	98
6.8B.3	Modulation.....	99
6.8B.4	Layer mapping and precoding	99
6.8B.5	Mapping to resource elements	99
6.9	Physical hybrid ARQ indicator channel	101
6.9.1	Modulation.....	101
6.9.2	Resource group alignment, layer mapping and precoding	102
6.9.3	Mapping to resource elements	104
6.10	Reference signals.....	106
6.10.1	Cell-specific Reference Signal (CRS).....	106
6.10.1.1	Sequence generation.....	106
6.10.1.2	Mapping to resource elements.....	107
6.10.2	MBSFN reference signals.....	109
6.10.2.1	Sequence generation.....	109
6.10.2.2	Mapping to resource elements.....	109
6.10.3	UE-specific reference signals associated with PDSCH	111
6.10.3.1	Sequence generation.....	112
6.10.3.2	Mapping to resource elements.....	113
6.10.3A	Demodulation reference signals associated with EPDCCH or MPDCCH.....	118
6.10.3A.1	Sequence generation.....	118
6.10.3A.2	Mapping to resource elements.....	119
6.10.4	Positioning reference signals	120
6.10.4.1	Sequence generation.....	121
6.10.4.2	Mapping to resource elements.....	121
6.10.4.3	Positioning reference signal subframe configuration	122
6.10.5	CSI reference signals	123
6.10.5.1	Sequence generation.....	123
6.10.5.2	Mapping to resource elements.....	124
6.10.5.3	CSI reference signal subframe configuration	129
6.11	Synchronization signals.....	129
6.11.1	Primary synchronization signal (PSS)	129
6.11.1.1	Sequence generation.....	129
6.11.1.2	Mapping to resource elements.....	130
6.11.2	Secondary synchronization signal (SSS)	130
6.11.2.1	Sequence generation.....	130
6.11.2.2	Mapping to resource elements.....	132
6.11A	Discovery signal	133
6.12	OFDM baseband signal generation	133
6.13	Modulation and upconversion	134
7	Generic functions	135
7.1	Modulation mapper	135
7.1.1	BPSK	135
7.1.2	QPSK	135
7.1.3	16QAM.....	135
7.1.4	64QAM.....	136
7.1.5	256QAM.....	137
7.2	Pseudo-random sequence generation.....	140
8	Timing.....	140
8.1	Uplink-downlink frame timing.....	140

9	Sidelink.....	141
9.1	Overview	141
9.1.1	Physical channels.....	141
9.1.2	Physical signals.....	141
9.1.3	Handling of simultaneous sidelink and uplink/downlink transmissions	141
9.2	Slot structure and physical resources.....	142
9.2.1	Resource grid.....	142
9.2.2	Resource elements	142
9.2.3	Resource blocks	143
9.2.4	Resource pool	143
9.2.5	Guard period	143
9.3	Physical Sidelink Shared Channel.....	143
9.3.1	Scrambling.....	143
9.3.2	Modulation.....	143
9.3.3	Layer mapping.....	144
9.3.4	Transform precoding.....	144
9.3.5	Precoding	144
9.3.6	Mapping to physical resources.....	144
9.4	Physical Sidelink Control Channel.....	145
9.4.1	Scrambling	145
9.4.2	Modulation.....	145
9.4.3	Layer mapping	145
9.4.4	Transform precoding.....	145
9.4.5	Precoding	145
9.4.6	Mapping to physical resources.....	145
9.5	Physical Sidelink Discovery Channel.....	146
9.5.1	Scrambling	146
9.5.2	Modulation.....	146
9.5.3	Layer mapping	146
9.5.4	Transform precoding.....	146
9.5.5	Precoding	146
9.5.6	Mapping to physical resources.....	146
9.6	Physical Sidelink Broadcast Channel.....	146
9.6.1	Scrambling	146
9.6.2	Modulation.....	147
9.6.3	Layer mapping	147
9.6.4	Transform precoding.....	147
9.6.5	Precoding	147
9.6.6	Mapping to physical resources.....	147
9.7	Sidelink Synchronization Signals.....	147
9.7.1	Primary sidelink synchronization signal	147
9.7.1.1	Sequence generation.....	147
9.7.1.2	Mapping to resource elements.....	148
9.7.2	Secondary sidelink synchronization signal	148
9.7.2.1	Sequence generation.....	148
9.7.2.2	Mapping to resource elements.....	148
9.8	Demodulation reference signals	148
9.9	SC-FDMA baseband signal generation	149
9.10	Timing	149
10	Narrowband IoT	150
10.1	Uplink.....	150
10.1.1	Overview	150
10.1.1.1	Physical channels	150
10.1.1.2	Physical signals	150
10.1.2	Slot structure and physical resources	151
10.1.2.1	Resource grid	151
10.1.2.2	Resource elements.....	151
10.1.2.3	Resource unit.....	152
10.1.3	Narrowband physical uplink shared channel	152
10.1.3.1	Scrambling	152
10.1.3.2	Modulation	152

10.1.3.3	Layer mapping	152
10.1.3.4	Transform precoding	152
10.1.3.5	Precoding	153
10.1.3.6	Mapping to physical resources	153
10.1.4	Demodulation reference signal	153
10.1.4.1	Reference signal sequence	153
10.1.4.1.1	Reference signal sequence for $N_{sc}^{RU} = 1$	153
10.1.4.1.2	Reference signal sequence for $N_{sc}^{RU} > 1$	154
10.1.4.1.3	Group hopping	156
10.1.4.2	Mapping to physical resources	156
10.1.5	SC-FDMA baseband signal generation	157
10.1.6	Narrowband physical random access channel	158
10.1.6.1	Time and frequency structure	158
10.1.6.2	Baseband signal generation	159
10.1.7	Modulation and upconversion	159
10.2	Downlink	160
10.2.1	Overview	160
10.2.1.1	Physical channels	160
10.2.1.2	Physical signals	160
10.2.2	Slot structure and physical resource elements	160
10.2.2.1	Resource grid	160
10.2.2.2	Resource elements	160
10.2.2.3	Guard period for half-duplex FDD operation	160
10.2.3	Narrowband physical downlink shared channel	160
10.2.3.1	Scrambling	160
10.2.3.2	Modulation	161
10.2.3.3	Layer mapping and precoding	161
10.2.3.4	Mapping to resource elements	161
10.2.4	Narrowband physical broadcast channel	162
10.2.4.1	Scrambling	162
10.2.4.2	Modulation	162
10.2.4.3	Layer mapping and precoding	162
10.2.4.4	Mapping to resource elements	162
10.2.5	Narrowband physical downlink control channel	163
10.2.5.1	NPDCCH formats	163
10.2.5.2	Scrambling	163
10.2.5.3	Modulation	163
10.2.5.4	Layer mapping and precoding	163
10.2.5.5	Mapping to resource elements	163
10.2.6	Narrowband reference signal (NRS)	164
10.2.6.1	Sequence generation	164
10.2.6.2	Mapping to resource elements	164
10.2.7	Synchronization signals	166
10.2.7.1	Narrowband primary synchronization signal (NPSS)	166
10.2.7.1.1	Sequence generation	166
10.2.7.1.2	Mapping to resource elements	166
10.2.7.2	Narrowband secondary synchronization signal (NSSS)	167
10.2.7.2.1	Sequence generation	167
10.2.7.2.2	Mapping to resource elements	168
10.2.8	OFDM baseband signal generation	168
10.2.9	Modulation and upconversion	169
Annex A (informative):	Change history	170
History		178

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

PREVIEW
iTech STANDARD
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/f6451deb-9882-41e7-8ab2-4b0609c19520/etsi-ts-136-211-v13.13.0-2020-01>

1 Scope

The present document describes the physical channels for evolved UTRA.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

•

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 36.201: "Evolved Universal Terrestrial Radio Access (E-UTRA); LTE physical layer; General description".
- [3] 3GPP TS 36.212: "Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding".
- [4] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures".
- [5] 3GPP TS 36.214: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer; Measurements".
- [6] 3GPP TS 36.104: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) radio transmission and reception".
- [7] 3GPP TS 36.101: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception".
- [8] 3GPP TS 36.321, "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification".
- [9] 3GPP TS 36.331, "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) Protocol specification"
- [10] 3GPP TS 36.304, "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) procedures in idle mode"

3 Symbols and abbreviations

3.1 Symbols

For the purposes of the present document, the following symbols apply:

- (k, l) Resource element with frequency-domain index k and time-domain index l

$a_{k,l}^{(p)}$	Value of resource element (k,l) [for antenna port p]
D	Matrix for supporting cyclic delay diversity
D_{RA}	Density of random access opportunities per radio frame
f_0	Carrier frequency
f_{RA}	PRACH resource frequency index within the considered time-domain location
$f_{PRB,hop}^{PRACH}$	PRACH frequency hopping offset, expressed as a number of resource blocks
$l_{NPDCCHstart}$	Start symbol in slot 0 for NPDCCH
$l_{NPDSCHstart}$	Start symbol in slot 0 for NPDSCH
M_{sc}^{PSBCH}	Bandwidth for PSBCH transmission, expressed as a number of subcarriers
M_{RB}^{PSBCH}	Bandwidth for PSBCH transmission, expressed as a number of resource blocks
M_{sc}^{PSCCH}	Bandwidth for PSCCH transmission, expressed as a number of subcarriers
M_{RB}^{PSCCH}	Bandwidth for PSCCH transmission, expressed as a number of resource blocks
M_{sc}^{PSDCH}	Bandwidth for PSDCH transmission, expressed as a number of subcarriers
M_{RB}^{PSDCH}	Bandwidth for PSDCH transmission, expressed as a number of resource blocks
M_{sc}^{PSSCH}	Scheduled bandwidth for PSSCH transmission, expressed as a number of subcarriers
M_{RB}^{PSSCH}	Scheduled bandwidth for PSSCH transmission, expressed as a number of resource blocks
M_{sc}^{PUSCH}	Scheduled bandwidth for uplink transmission, expressed as a number of subcarriers
M_{RB}^{PUSCH}	Scheduled bandwidth for uplink transmission, expressed as a number of resource blocks
M_{rep}^{NPUSCH}	Scheduled number of repetitions of a NPUSCH transmission
M_{rep}^{NPDSCH}	Scheduled number of repetitions of a NPDSCH transmission
M_{sc}^{NPUSCH}	Scheduled bandwidth for uplink NPUSCH transmission, expressed as a number of subcarriers
$M_{identical}^{NPUSCH}$	Number of repetitions of identical slots for NPUSCH
$M_{bit}^{(q)}$	Number of coded bits to transmit on a physical channel [for codeword q]
$M_{symb}^{(q)}$	Number of modulation symbols to transmit on a physical channel [for codeword q]
M_{symb}^{layer}	Number of modulation symbols to transmit per layer for a physical channel
M_{symb}^{ap}	Number of modulation symbols to transmit per antenna port for a physical channel
N	A constant equal to 2048 for $\Delta f = 15$ kHz, 4096 for $\Delta f = 7.5$ kHz and 8192 for $\Delta f = 3.75$ kHz
$N_{CP,l}$	Downlink cyclic prefix length for OFDM symbol l in a slot
N_{CS}	Cyclic shift value used for random access preamble generation
$N_{cs}^{(1)}$	Number of cyclic shifts used for PUCCH formats 1/1a/1b in a resource block with a mix of formats 1/1a/1b and 2/2a/2b
$N_{RB}^{(2)}$	Bandwidth available for use by PUCCH formats 2/2a/2b, expressed in multiples of N_{sc}^{RB}
N_{RB}^{HO}	The offset used for PUSCH frequency hopping, expressed in number of resource blocks (set by higher layers)
N_{ID}^{cell}	Physical layer cell identity
N_{ID}^{Ncell}	Narrowband physical layer cell identity
N_{ID}^{MBSFN}	MBSFN area identity
N_{ID}^{SL}	Physical layer sidelink synchronization identity
N_{RB}^{DL}	Downlink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
$N_{RB}^{min,DL}$	Smallest downlink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
$N_{RB}^{max,DL}$	Largest downlink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
N_{RB}^{UL}	Uplink bandwidth configuration, expressed in multiples of N_{sc}^{RB}

$N_{RB}^{\min,UL}$	Smallest uplink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
$N_{RB}^{\max,UL}$	Largest uplink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
N_{RB}^{SL}	Sidelink bandwidth configuration, expressed in multiples of N_{sc}^{RB}
N_{SF}	Number of scheduled subframes for NPDSCH transmission
N_{symb}^{NPSS}	Number of symbols for NPSS in a subframe
N_{symb}^{NSSS}	Number of symbols for NSSS in a subframe
N_{sc}^{RU}	Number of consecutive subcarriers in an UL resource unit for NB-IoT
N_{seq}^{RU}	Number of reference signal sequences available for the UL resource unit size
N_{RU}	Number of scheduled UL resource units for NB-IoT
N_{NB}^{UL}	Total number of uplink narrowbands
N_{sc}^{UL}	Number of subcarriers in the frequency domain for NB-IoT
N_{acc}	Number of consecutive absolute subframes over which the scrambling sequence stays the same
N_{abs}^{PUSCH}	Total number of absolute subframes a PUSCH with repetition spans, expressed as a number of absolute subframes
N_{rep}^{PUSCH}	Number of repetitions of a PUSCH transmission
$N_{NB}^{ch,UL}$	Number of consecutive absolute subframes over which PUCCH or PUSCH stays at the same narrowband before hopping to another narrowband, expressed as a number of absolute subframes
$f_{NB,hop}^{PUSCH}$	Narrowband offset between one narrowband and the next narrowband a PUSCH hops to, expressed as a number of uplink narrowbands
N_{abs}^{PUCCH}	Total number of absolute subframes a PUCCH with repetition spans, expressed as a number of absolute subframes
N_{rep}^{PUCCH}	Number of repetitions of a PUCCH transmission
N_{rep}^{PRACH}	Number of PRACH repetitions per preamble transmission attempt
N_{sf}^{RA}	Number of subframes allowed for preamble transmission within a 1024-frame interval
N_{start}^{PRACH}	PRACH starting subframe periodicity
N_{rep}^{NPRACH}	Number of NPRACH repetitions per preamble transmission attempt
N_{period}^{NPRACH}	NPRACH resource periodicity
$N_{scoffset}^{NPRACH}$	Frequency location of the first sub-carrier allocated to NPRACH
N_{sc}^{NPRACH}	Number of sub-carriers allocated to NPRACH
$N_{sc,cont}^{NPRACH}$	Number of starting sub-carriers allocated for UE initiated random access
N_{start}^{NPRACH}	NPRACH starting subframe
N_{MSG3}^{NPRACH}	Fraction for starting subcarrier index for UE support for multi-tone msg3 transmission
$N_{gap,period}$	Periodicity for NPDSCH/NPDCCH gaps
$N_{gap,duration}$	Duration for NPDSCH/NPDCCH gaps
$N_{gap,threshold}$	Threshold for applying NPDDCH/NPDCCH gaps
N_{NB}^{DL}	Total number of downlink narrowbands
N_{abs}^{PDSCH}	Total number of absolute subframes a PDSCH with repetition spans, expressed as a number of absolute subframes
N_{rep}^{PDSCH}	Number of repetitions of a PDSCH transmission
$N_{NB}^{ch,DL}$	Number of consecutive absolute subframes over which MPDCCH or PDSCH stays at the same narrowband before hopping to another narrowband, expressed as a number of absolute subframes
$N_{NB,hop}^{ch,DL}$	Number of narrowbands over which MPDCCH or PDSCH frequency hops

$f_{\text{NB,hop}}^{\text{DL}}$	Narrowband offset between one narrowband and the next narrowband an MPDCCH or PDSCH hops to, expressed as a number of downlink narrowbands
$N_{\text{PDSCH}}^{\text{SIB1-BR}}$	Number of times a PDSCH carrying SIB1-BR is transmitted over 8 radio frames
$N_{\text{abs}}^{\text{MPDCCH}}$	Total number of absolute subframes a MPDCCH with repetition spans , expressed as a number of absolute subframes
$N_{\text{rep}}^{\text{MPDCCH}}$	Number of repetitions of a MPDCCH transmission
$N_{\text{abs,ss}}^{\text{MPDCCH}}$	Total number of absolute subframes a MPDCCH search space with maximum repetition level spans, expressed as a number of absolute subframes
$N_{\text{rep,ss}}^{\text{MPDCCH}}$	Maximum repetition level of a MPDCCH search space
$N_{\text{ECCE}}^{\text{MPDCCH}}$	Number of ECCEs in a subframe for one MPDCCH
$N_{\text{symb}}^{\text{DL}}$	Number of OFDM symbols in a downlink slot
$N_{\text{symb}}^{\text{UL}}$	Number of SC-FDMA symbols in an uplink slot
$N_{\text{slots}}^{\text{UL}}$	Number of consecutive slots in an UL resource unit for NB-IoT
$N_{\text{symb}}^{\text{SL}}$	Number of SC-FDMA symbols in a sidelink slot
$N_{\text{sc}}^{\text{RB}}$	Resource block size in the frequency domain, expressed as a number of subcarriers
N_{sb}	Number of sub-bands for PUSCH frequency-hopping with predefined hopping pattern
$N_{\text{RB}}^{\text{sb}}$	Size of each sub-band for PUSCH frequency-hopping with predefined hopping pattern, expressed as a number of resource blocks
$N_{\text{sc}}^{\text{RA}}$	Size of narrow-band random-access resource in number of subcarriers
N_{SP}	Number of downlink to uplink switch points within the radio frame
$N_{\text{RS}}^{\text{PUCCH}}$	Number of reference symbols per slot for PUCCH
N_{TA}	Timing offset between uplink and downlink radio frames at the UE, expressed in units of T_s
$N_{\text{TA offset}}$	Fixed timing advance offset, expressed in units of T_s
$N_{\text{TA,SL}}$	Timing offset between sidelink and timing reference frames at the UE, expressed in units of T_s
$n_{\text{PUCCH}}^{(1,\tilde{p})}$	Resource index for PUCCH formats 1/1a/1b
$n_{\text{PUCCH}}^{(2,\tilde{p})}$	Resource index for PUCCH formats 2/2a/2b
$n_{\text{PUCCH}}^{(3,\tilde{p})}$	Resource index for PUCCH formats 3
n_{PDCCH}	Number of PDCCHs present in a subframe
n_{PRB}	Physical resource block number
$n_{\text{PRB}}^{\text{RA}}$	First physical resource block occupied by PRACH resource considered
$n_{\text{PRB offset}}^{\text{RA}}$	First physical resource block available for PRACH
$n_{\text{sc}}^{\text{RA}}$	Subcarrier occupied by NPRACH resource considered
n_{VRB}	Virtual resource block number
n_{RNTI}	Radio network temporary identifier
$n_{\text{ID}}^{\text{SA}}$	Sidelink group destination identity
n_{f}	System frame number
n_{s}	Slot number within a radio frame
$n_{\text{sf}}^{\text{abs}}$	Absolute subframe number
$n_{\text{sf}}^{\text{RA}}$	Index for subframes allowed for preamble transmission
P	Number of antenna ports used for transmission of a channel
p	Antenna port number
q	Codeword number
r_{RA}	Index for PRACH versions with same preamble format and PRACH density
Q_m	Modulation order: 2 for QPSK, 4 for 16QAM, 6 for 64QAM and 8 for 256QAM transmissions