

ETSI TS 136 213 V13.15.0 (2020-02)



LTE;
Evolved Universal Terrestrial Radio Access (E-UTRA);
Physical layer procedures
(3GPP TS 36.213 version 13.15.0 Release 13)

*iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standards text
https://standards.iteh.ai/catalog/standards/sist/136213-13-2020/etsi-ts-136213-13-2020-02
4ae0-a440-dcf66e7527d4*



ReferenceRTS/TSGR-0136213vdf0

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal notice

This Technical Specification (TS) has been produced by the ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal notice	2
Modal verbs terminology.....	2
Foreword.....	7
1 Scope	8
2 References	8
3 Symbols and abbreviations.....	8
3.1 Symbols.....	8
3.2 Abbreviations	9
4 Synchronization procedures	11
4.1 Cell search	11
4.2 Timing synchronization.....	11
4.2.1 Radio link monitoring.....	11
4.2.2 Inter-cell synchronization	11
4.2.3 Transmission timing adjustments	11
4.3 Timing for Secondary Cell Activation / Deactivation.....	12
5 Power control	13
5.1 Uplink power control.....	13
5.1.1 Physical uplink shared channel.....	13
5.1.1.1 UE behaviour	13
5.1.1.2 Power headroom	21
5.1.2 Physical uplink control channel.....	23
5.1.2.1 UE behaviour	24
5.1.3 Sounding Reference Symbol (SRS).....	28
5.1.3.1 UE behaviour	28
5.1.4 Power allocation for dual connectivity.....	29
5.1.4.1 Dual connectivity power control Mode 1.....	29
5.1.4.2 Dual connectivity power control Mode 2.....	36
5.1.5 Power allocation for PUCCH-SCell.....	41
5.2 Downlink power allocation	41
5.2.1 eNodeB Relative Narrowband TX Power (RNTP) restrictions	43
6 Random access procedure	45
6.1 Physical non-synchronized random access procedure.....	45
6.1.1 Timing	46
6.2 Random Access Response Grant.....	47
7 Physical downlink shared channel related procedures	50
7.1 UE procedure for receiving the physical downlink shared channel	52
7.1.1 Single-antenna port scheme	62
7.1.2 Transmit diversity scheme	62
7.1.3 Large delay CDD scheme	62
7.1.4 Closed-loop spatial multiplexing scheme	62
7.1.5 Multi-user MIMO scheme	62
7.1.5A Dual layer scheme.....	63
7.1.5B Up to 8 layer transmission scheme	63
7.1.6 Resource allocation.....	63
7.1.6.1 Resource allocation type 0	64
7.1.6.2 Resource allocation type 1	64
7.1.6.3 Resource allocation type 2	65
7.1.6.4 PDSCH starting position	66
7.1.6.4A PDSCH starting position for BL/CE UEs	68
7.1.6.5 Physical Resource Block (PRB) bundling.....	69
7.1.7 Modulation order and transport block size determination	70

7.1.7.1	Modulation order and redundancy version determination.....	71
7.1.7.2	Transport block size determination.....	74
7.1.7.2.1	Transport blocks not mapped to two or more layer spatial multiplexing	75
7.1.7.2.2	Transport blocks mapped to two-layer spatial multiplexing.....	83
7.1.7.2.3	Transport blocks mapped for DCI Format 1C and DCI Format 6-2.....	83
7.1.7.2.4	Transport blocks mapped to three-layer spatial multiplexing.....	84
7.1.7.2.5	Transport blocks mapped to four-layer spatial multiplexing.....	85
7.1.7.2.6	Transport blocks mapped for BL/CE UEs configured with CEModeB.....	85
7.1.7.2.7	Transport blocks mapped for BL/CE UEs <i>SystemInformationBlockType1-BR</i>	86
7.1.7.3	Redundancy Version determination for Format 1C.....	86
7.1.8	Storing soft channel bits	86
7.1.9	PDSCH resource mapping parameters.....	86
7.1.10	Antenna ports quasi co-location for PDSCH.....	87
7.1.11	PDSCH subframe assignment for BL/CE UE.....	88
7.2	UE procedure for reporting Channel State Information (CSI)	90
7.2.1	Aperiodic CSI Reporting using PUSCH.....	96
7.2.2	Periodic CSI Reporting using PUCCH.....	110
7.2.3	Channel Quality Indicator (CQI) definition.....	146
7.2.4	Precoding Matrix Indicator (PMI) definition.....	154
7.2.5	Channel-State Information – Reference Signal (CSI-RS) definition	179
7.2.6	Channel-State Information – Interference Measurement (CSI-IM) Resource definition.....	181
7.2.7	Zero Power CSI-RS Resource definition	181
7.3	UE procedure for reporting HARQ-ACK	181
7.3.1	FDD HARQ-ACK reporting procedure.....	182
7.3.2	TDD HARQ-ACK reporting procedure.....	185
7.3.2.1	TDD HARQ-ACK reporting procedure for same UL/DL configuration	185
7.3.2.2	TDD HARQ-ACK reporting procedure for different UL/DL configurations	197
7.3.3	FDD-TDD HARQ-ACK reporting procedure for primary cell frame structure type 1.....	204
7.3.4	FDD-TDD HARQ-ACK reporting procedure for primary cell frame structure type 2.....	205
8	Physical uplink shared channel related procedures.....	206
8.0	UE procedure for transmitting the physical uplink shared channel.....	206
8.0.1	Single-antenna port scheme.....	215
8.0.2	Closed-loop spatial multiplexing scheme	215
8.1	Resource allocation for PDCCH/EPDCCH with uplink DCI format.....	216
8.1.1	Uplink resource allocation type 0.....	216
8.1.2	Uplink resource allocation type 1.....	216
8.1.3	Uplink resource allocation type 2.....	217
8.2	UE sounding procedure	218
8.3	UE HARQ-ACK procedure.....	225
8.4	UE PUSCH hopping procedure.....	227
8.4.1	Type 1 PUSCH hopping	228
8.4.2	Type 2 PUSCH hopping	228
8.5	UE Reference Symbol (RS) procedure.....	228
8.6	Modulation order, redundancy version and transport block size determination.....	229
8.6.1	Modulation order and redundancy version determination	229
8.6.2	Transport block size determination.....	231
8.6.3	Control information MCS offset determination.....	233
8.7	UE transmit antenna selection.....	237
9	Physical downlink control channel procedures	237
9.1	UE procedure for determining physical downlink control channel assignment	237
9.1.1	PDCCH assignment procedure	237
9.1.2	PHICH assignment procedure.....	240
9.1.3	Control Format Indicator (CFI) assignment procedure.....	242
9.1.4	EPDCCH assignment procedure.....	242
9.1.4.1	EPDCCH starting position	249
9.1.4.2	Antenna ports quasi co-location for EPDCCH.....	249
9.1.4.3	Resource mapping parameters for EPDCCH	250
9.1.4.4	PRB-pair indication for EPDCCH	250
9.1.5	MPDCCH assignment procedure.....	251
9.1.5.1	MPDCCH starting position.....	257

9.1.5.2	Antenna ports quasi co-location for MPDCCH	257
9.2	PDCCCH/EPDCCH/MPDCCH validation for semi-persistent scheduling	258
9.3	PDCCCH/EPDCCH/MPDCCH control information procedure	259
10	Physical uplink control channel procedures	260
10.1	UE procedure for determining physical uplink control channel assignment	260
10.1.1	PUCCH format information	263
10.1.2	FDD HARQ-ACK feedback procedures	268
10.1.2.1	FDD HARQ-ACK procedure for one configured serving cell	268
10.1.2.2	FDD HARQ-ACK procedures for more than one configured serving cell	270
10.1.2.2.1	PUCCH format 1b with channel selection HARQ-ACK procedure	270
10.1.2.2.2	PUCCH format 3 HARQ-ACK procedure	274
10.1.2.2.3	PUCCH format 4 HARQ-ACK procedure	276
10.1.2.2.4	PUCCH format 5 HARQ-ACK procedure	277
10.1.2A	FDD-TDD HARQ-ACK feedback procedures for primary cell frame structure type 1	277
10.1.3	TDD HARQ-ACK feedback procedures	278
10.1.3.1	TDD HARQ-ACK procedure for one configured serving cell	280
10.1.3.2	TDD HARQ-ACK procedure for more than one configured serving cell	292
10.1.3.2.1	PUCCH format 1b with channel selection HARQ-ACK procedure	292
10.1.3.2.2	PUCCH format 3 HARQ-ACK procedure	308
10.1.3.2.3	PUCCH format 4 HARQ-ACK procedure	315
10.1.3.2.4	PUCCH format 5 HARQ-ACK procedure	332
10.1.3A	FDD-TDD HARQ-ACK feedback procedures for primary cell frame structure type 2	332
10.1.4	HARQ-ACK Repetition procedure	334
10.1.5	Scheduling Request (SR) procedure	335
10.2	Uplink HARQ-ACK timing	336
11	Physical Multicast Channel (PMCH) related procedures	340
11.1	UE procedure for receiving the PMCH	340
11.2	UE procedure for receiving MCCH change notification	340
12	Assumptions independent of physical channel	340
13	Uplink/Downlink configuration determination procedure for Frame Structure Type 2	341
13.1	UE procedure for determining eIMTA-uplink/downlink configuration	341
13A	Subframe configuration for Frame Structure Type 3	342
14	UE procedures related to Sidelink	344
14.1	Physical Sidelink Shared Channel related procedures	344
14.1.1	UE procedure for transmitting the PSSCH	344
14.1.1.1	UE procedure for determining subframes for transmitting PSSCH for sidelink transmission mode 1	345
14.1.1.1.1	Determination of subframe indicator bitmap	345
14.1.1.2	UE procedure for determining resource blocks for transmitting PSSCH for sidelink transmission mode 1	348
14.1.1.2.1	PSSCH resource allocation for sidelink transmission mode 1	348
14.1.1.2.2	PSSCH frequency hopping for sidelink transmission mode 1	349
14.1.1.3	UE procedure for determining subframes for transmitting PSSCH for sidelink transmission mode 2	349
14.1.1.4	UE procedure for determining resource blocks for transmitting PSSCH for sidelink transmission mode 2	350
14.1.1.5	UE procedure for PSSCH power control	350
14.1.2	UE procedure for receiving the PSSCH	351
14.1.3	UE procedure for determining resource block pool and subframe pool for sidelink transmission mode 2	351
14.2	Physical Sidelink Control Channel related procedures	352
14.2.1	UE procedure for transmitting the PSCCH	352
14.2.1.1	UE procedure for determining subframes and resource blocks for transmitting PSCCH for sidelink transmission mode 1	353
14.2.1.2	UE procedure for determining subframes and resource blocks for transmitting PSCCH for sidelink transmission mode 2	353
14.2.1.3	UE procedure for PSCCH power control	353
14.2.2	UE procedure for receiving the PSCCH	354

14.2.3	UE procedure for determining resource block pool and subframe pool for PSCCH	354
15	Channel access procedures for LAA	358
15.1	Downlink channel access procedures	358
15.1.1	Channel access procedure for transmission(s) including PDSCH	358
15.1.2	Channel access procedure for transmissions including discovery signal transmission(s) and not including PDSCH	359
15.1.3	Contention window adjustment procedure	360
15.1.4	Energy detection threshold adaptation procedure	360
15.1.5	Channel access procedure for transmission(s) on multiple carriers	361
15.1.5.1	Type A multi-carrier access procedures	361
15.1.5.1.1	Type A1	361
15.1.5.1.2	Type A2	362
15.1.5.2	Type B multi-carrier access procedure	362
15.1.5.2.1	Type B1	362
15.1.5.2.2	Type B2	363
16	UE Procedures related to narrowband IoT	363
16.1	Synchronization procedures	363
16.1.1	Cell search	363
16.1.2	Timing synchronization	363
16.2	Power control	363
16.2.1	Uplink power control	363
16.2.1.1	Narrowband physical uplink shared channel	364
16.2.1.1.1	UE behaviour	364
16.2.1.1.2	Power headroom	364
16.2.2	Downlink power allocation	364
16.3	Random access procedure	365
16.3.1	Physical non-synchronized random access procedure	365
16.3.2	Timing	366
16.3.3	Narrowband random access response grant	366
16.4	Narrowband physical downlink shared channel related procedures	367
16.4.1	UE procedure for receiving the narrowband physical downlink shared channel	367
16.4.1.1	Single-antenna port scheme	369
16.4.1.2	Transmit diversity scheme	369
16.4.1.3	Resource allocation	369
16.4.1.4	NPDSCH starting position	371
16.4.1.5	Modulation order and transport block size determination	371
16.4.1.5.1	Transport blocks not mapped for <i>SystemInformationBlockType1-NB</i>	372
16.4.1.5.2	Transport blocks mapped for <i>SystemInformationBlockType1-NB</i>	372
16.4.2	UE procedure for reporting ACK/NACK	372
16.5	Narrowband physical uplink shared channel related procedures	373
16.5.1	UE procedure for transmitting format 1 narrowband physical uplink shared channel	373
16.5.1.1	Resource allocation	375
16.5.1.2	Modulation order, redundancy version and transport block size determination	376
16.5.2	UE procedure for NPUSCH retransmission	377
16.6	Narrowband physical downlink control channel related procedures	377
16.6.1	NPDCCH starting position	380
16.6.2	NPDCCH control information procedure	381
16.7	Assumptions independent of physical channel related to narrowband IoT	381
16.8	UE procedure for acquiring cell-specific reference signal sequence and raster offset	381
Annex A (informative):	Change history	382
History		396

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of this present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

ITeH STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/d22dc60e-195f-4ae0-a440-dcf66e7527d4/etsi-ts-136-213-v13.15.0-2020-02>

1 Scope

The present document specifies and establishes the characteristics of the physical layer procedures in the FDD and TDD modes of E-UTRA.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 36.201: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Layer – General Description".
- [3] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation".
- [4] 3GPP TS 36.212: "Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding".
- [5] 3GPP TS 36.214: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer – Measurements".
- [6] 3GPP TS 36.101: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception".
- [7] 3GPP TS 36.104: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) radio transmission and reception".
- [8] 3GPP TS 36.321, "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification".
- [9] 3GPP TS 36.423, "Evolved Universal Terrestrial Radio Access (E-UTRA); X2 Application Protocol (X2AP)".
- [10] 3GPP TS 36.133, "Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management".
- [11] 3GPP TS 36.331, "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) protocol specification".
- [12] 3GPP TS 36.306: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio access capabilities".

3 Symbols and abbreviations

3.1 Symbols

For the purposes of the present document, the following symbols apply:

n_f System frame number as defined in [3]

n_s	Slot number within a radio frame as defined in [3]
N_{cells}^{DL}	Number of configured cells
N_{RB}^{DL}	Downlink bandwidth configuration, expressed in units of N_{sc}^{RB} as defined in [3]
N_{RB}^{UL}	Uplink bandwidth configuration, expressed in units of N_{sc}^{RB} as defined in [3]
N_{symb}^{UL}	Number of SC-FDMA symbols in an uplink slot as defined in [3]
N_{sc}^{RB}	Resource block size in the frequency domain, expressed as a number of subcarriers as defined in [3]
T_s	Basic time unit as defined in [3]

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ACK	Acknowledgement
BCH	Broadcast Channel
CCE	Control Channel Element
CDD	Cyclic Delay Diversity
CG	Cell Group
CIF	Carrier Indicator Field
CQI	Channel Quality Indicator
CRC	Cyclic Redundancy Check
CRI	CSI-RS Resource Indicator
CSI	Channel State Information
CSI-IM	CSI-interference measurement
DAI	Downlink Assignment Index
DCI	Downlink Control Information
DL	Downlink
DL-SCH	Downlink Shared Channel
DTX	Discontinuous Transmission
EPDCCH	Enhanced Physical Downlink Control Channel
EPRE	Energy Per Resource Element
MCG	Master Cell Group
MCS	Modulation and Coding Scheme
NACK	Negative Acknowledgement
NPBCH	Narrowband Physical Broadcast Channel
NPDCCH	Narrowband Physical Downlink Control Channel
NPDSCH	Narrowband Physical Downlink Shared Channel
NPRACH	Narrowband Physical Random Access Channel
NPUSCH	Narrowband Physical Uplink Shared Channel
NPSS	Narrowband Primary Synchronization Signal
NSSS	Narrowband Secondary Synchronization Signal
NRS	Narrowband Reference Signal
PBCH	Physical Broadcast Channel
PCFICH	Physical Control Format Indicator Channel
PDCCH	Physical Downlink Control Channel
PDSCH	Physical Downlink Shared Channel
PHICH	Physical Hybrid ARQ Indicator Channel
PMCH	Physical Multicast Channel
PMI	Precoding Matrix Indicator
PRACH	Physical Random Access Channel
PRS	Positioning Reference Signal
PRB	Physical Resource Block
PSBCH	Physical Sidelink Broadcast Channel
PSCCH	Physical Sidelink Control Channel
PSCell	Primary Secondary cell

PSDCH	Physical Sidelink Discovery Channel
PSSCH	Physical Sidelink Shared Channel
PSSS	Primary Sidelink Synchronisation Signal
PUCCH	Physical Uplink Control Channel
PUCCH-SCell	PUCCH SCell
PUSCH	Physical Uplink Shared Channel
PTI	Precoding Type Indicator
RBG	Resource Block Group
RE	Resource Element
RI	Rank Indication
RS	Reference Signal
SCG	Secondary Cell Group
SINR	Signal to Interference plus Noise Ratio
SPS C-RNTI	Semi-Persistent Scheduling C-RNTI
SR	Scheduling Request
SRS	Sounding Reference Symbol
SSSS	Secondary Sidelink Synchronisation Signal
TAG	Timing Advance Group
TBS	Transport Block Size
UCI	Uplink Control Information
UE	User Equipment
UL	Uplink
UL-SCH	Uplink Shared Channel
VRB	Virtual Resource Block

iTeh STANDARD PREVIEW
(standards.iteh.ai)

Full standard:
<https://standards.iteh.ai/catalog/standards/sist/d22dc0e-f0bc-4ae0-a440-dcf66e7527d4/etsi-ts-136-213-v13.15.0-2020-02>

4 Synchronization procedures

4.1 Cell search

Cell search is the procedure by which a UE acquires time and frequency synchronization with a cell and detects the physical layer Cell ID of that cell. E-UTRA cell search supports a scalable overall transmission bandwidth corresponding to 6 resource blocks and upwards.

The following signals are transmitted in the downlink to facilitate cell search: the primary and secondary synchronization signals.

A UE may assume the antenna ports 0 – 3 and the antenna port for the primary/secondary synchronization signals of a serving cell are quasi co-located (as defined in [3]) with respect to Doppler shift and average delay.

4.2 Timing synchronization

4.2.1 Radio link monitoring

The downlink radio link quality of the primary cell shall be monitored by the UE for the purpose of indicating out-of-sync/in-sync status to higher layers.

If the UE is configured with a SCG [11] and the parameter *rlf-TimersAndConstantsSCG* is provided by the higher layers and is not set to release, the downlink radio link quality of the PSCell [11] of the SCG shall be monitored by the UE for the purpose of indicating out-of-sync/in-sync status to higher layers.

In non-DRX mode operation, the physical layer in the UE shall every radio frame assess the radio link quality, evaluated over the previous time period defined in [10], against thresholds (Q_{out} and Q_{in}) defined by relevant tests in [10].

In DRX mode operation, the physical layer in the UE shall at least once every DRX period assess the radio link quality, evaluated over the previous time period defined in [10], against thresholds (Q_{out} and Q_{in}) defined by relevant tests in [10].

If higher-layer signalling indicates certain subframes for restricted radio link monitoring, the radio link quality shall not be monitored in any subframe other than those indicated.

The physical layer in the UE shall in radio frames where the radio link quality is assessed indicate out-of-sync to higher layers when the radio link quality is worse than the threshold Q_{out} . When the radio link quality is better than the threshold Q_{in} , the physical layer in the UE shall in radio frames where the radio link quality is assessed indicate in-sync to higher layers.

4.2.2 Inter-cell synchronization

No functionality is specified in this subclause in this release.

4.2.3 Transmission timing adjustments

Upon reception of a timing advance command for a TAG containing the primary cell or PSCell, the UE shall adjust uplink transmission timing for PUCCH/PUSCH/SRS of the primary cell or PSCell based on the received timing advance command.

The UL transmission timing for PUSCH/SRS of a secondary cell is the same as the primary cell if the secondary cell and the primary cell belong to the same TAG. If the primary cell in a TAG has a frame structure type 1 and a secondary cell in the same TAG has a frame structure type 2, UE may assume that $N_{TA} \geq 624$.

If the UE is configured with a SCG, the UL transmission timing for PUSCH/SRS of a secondary cell other than the PSCell is the same as the PSCell if the secondary cell and the PSCell belong to the same TAG.

Upon reception of a timing advance command for a TAG not containing the primary cell or PSCell, if all the serving cells in the TAG have the same frame structure type, the UE shall adjust uplink transmission timing for PUSCH/SRS of all the secondary cells in the TAG based on the received timing advance command where the UL transmission timing for PUSCH /SRS is the same for all the secondary cells in the TAG.

Upon reception of a timing advance command for a TAG not containing the primary cell or PSCell, if a serving cell in the TAG has a different frame structure type compared to the frame structure type of another serving cell in the same TAG, the UE shall adjust uplink transmission timing for PUSCH/SRS of all the secondary cells in the TAG by using $N_{TAoffset} = 624$ regardless of the frame structure type of the serving cells and based on the received timing advance command where the UL transmission timing for PUSCH/SRS is the same for all the secondary cells in the TAG. $N_{TAoffset}$ is described in [3].

The timing advance command for a TAG indicates the change of the uplink timing relative to the current uplink timing for the TAG as multiples of $16 T_s$. The start timing of the random access preamble is specified in [3].

In case of random access response, an 11-bit timing advance command [8], T_A , for a TAG indicates N_{TA} values by index values of $T_A = 0, 1, 2, \dots, 256$ if the UE is configured with a SCG, and $T_A = 0, 1, 2, \dots, 1282$ otherwise, where an amount of the time alignment for the TAG is given by $N_{TA} = T_A \times 16$. N_{TA} is defined in [3].

In other cases, a 6-bit timing advance command [8], T_A , for a TAG indicates adjustment of the current N_{TA} value, $N_{TA,old}$, to the new N_{TA} value, $N_{TA,new}$, by index values of $T_A = 0, 1, 2, \dots, 63$, where $N_{TA,new} = N_{TA,old} + (T_A - 31) \times 16$. Here, adjustment of N_{TA} value by a positive or a negative amount indicates advancing or delaying the uplink transmission timing for the TAG by a given amount respectively.

For a non-BL/CE UE, for a timing advance command received on subframe n , the corresponding adjustment of the uplink transmission timing shall apply from the beginning of subframe $n+6$. For serving cells in the same TAG, when the UE's uplink PUCCH/PUSCH/SRS transmissions in subframe n and subframe $n+1$ are overlapped due to the timing adjustment, the UE shall complete transmission of subframe n and not transmit the overlapped part of subframe $n+1$.

For a BL/CE UE, for a timing advance command received on subframe n , the corresponding adjustment of the uplink transmission timing shall apply for the uplink PUCCH/PUSCH/SRS transmissions in subframe $n+6$. When the BL/CE UE's uplink PUCCH/PUSCH/SRS transmissions in subframe n and subframe $n+1$ are on the same narrowband and are overlapped due to the timing adjustment, the UE shall complete transmission of subframe n and not transmit in subframe $n+1$ until the first available symbol that has no overlapping portion with subframe n . When the BL/CE UE's uplink PUCCH/PUSCH/SRS transmissions in subframe n and subframe $n+1$ are on different narrowbands, and the timing adjustment occurs in the guard period for narrowband retuning, the UE shall not transmit in subframe $n+1$ until the first available symbol that has no overlapping portion with subframe n and which does not reduce the guard period.

If the received downlink timing changes and is not compensated or is only partly compensated by the uplink timing adjustment without timing advance command as specified in [10], the UE changes N_{TA} accordingly.

4.3 Timing for Secondary Cell Activation / Deactivation

When a UE receives an activation command [8] for a secondary cell in subframe n , the corresponding actions in [8] shall be applied no later than the minimum requirement defined in [10] and no earlier than subframe $n+8$, except for the following:

- the actions related to CSI reporting on a serving cell which is active in subframe $n+8$
- the actions related to the *sCellDeactivationTimer* associated with the secondary cell [8]

which shall be applied in subframe $n+8$.

- the actions related to CSI reporting on a serving cell which is not active in subframe $n+8$

which shall be applied in the earliest subframe after $n+8$ in which the serving cell is active.

When a UE receives a deactivation command [8] for a secondary cell or the *sCellDeactivationTimer* associated with the secondary cell expires in subframe n , the corresponding actions in [8] shall apply no later than the minimum requirement defined in [10], except for the actions related to CSI reporting on a serving cell which is active which shall be applied in subframe $n+8$.