



ETSI STANDARD

**Digital Radio Mondiale (DRM);
System Specification**

iTeh STANDARD PREVIEW
(Standards.iTech.ai)
Full standard:
<https://standards.itech.ai/catalog/standards/standard/129981c-4e98-a365-226e56582b36/etsi-es-201-980-v4.2.1-2020-11>

EBU

Reference

RES/JTC-DRM-35

Keywords

broadcasting, digital, DRM, radio

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.
Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:
<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.
© European Broadcasting Union 2020.
All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and
of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and
of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Contents

Intellectual Property Rights	8
Foreword.....	8
Modal verbs terminology.....	8
Introduction	9
1 Scope	10
2 References	10
2.1 Normative references	10
2.2 Informative references.....	11
3 Definition of terms, symbols, abbreviations and conventions.....	11
3.1 Terms.....	11
3.2 Symbols	12
3.3 Abbreviations	13
3.4 Conventions.....	14
4 General characteristics	15
4.1 System overview	15
4.2 System architecture	15
4.3 Audio source coding.....	17
4.4 Transmission modes	18
4.4.1 Signal bandwidth related parameters	18
4.4.2 Transmission efficiency related parameters.....	18
4.4.2.0 General	18
4.4.2.1 Coding rates and constellations.....	18
4.4.2.2 OFDM parameter set.....	18
5 Source coding modes.....	19
5.1 Overview	19
5.1.0 Introduction.....	19
5.1.1 Extended HE-AAC audio coding (xHE-AAC).....	20
5.1.2 AAC audio coding	20
5.1.3 MPEG Surround coding.....	22
5.2 Audio super framing.....	22
5.3 xHE-AAC coding.....	23
5.3.1 xHE-AAC	23
5.3.1.0 Introduction	23
5.3.1.1 xHE-AAC audio super frame	24
5.3.1.2 xHE-AAC audio frame	25
5.3.1.3 Transport of xHE-AAC audio frames within the payload section	25
5.3.2 xHE-AAC decoder configuration	27
5.3.3 xHE-AAC error concealment	30
5.3.3.0 Introduction	30
5.3.3.1 Frequency Domain coding (AAC based coding and TCX).....	30
5.3.3.2 ACELP	31
5.3.3.3 SBR	31
5.3.3.4 MPS212 parametric stereo	34
5.3.3.5 MDCT based Complex Prediction	34
5.3.3.6 Forward Aliasing Cancellation.....	34
5.3.4 xHE-AAC + MPS	34
5.4 AAC coding.....	35
5.4.1 AAC	35
5.4.2 AAC + SBR	37
5.4.3 Parametric Stereo coding	38
5.4.4 AAC error concealment	39
5.4.4.0 Introduction	39
5.4.4.1 Interpolation of one corrupt frame	39

5.4.4.2	Fade-out and fade-in	40
5.4.4.3	Concealment granularity	40
5.4.4.4	SBR error concealment	40
5.4.4.5	Parametric Stereo concealment	43
5.4.5	AAC + MPS	43
6	Multiplex definition	45
6.1	Introduction	45
6.2	Main Service Channel (MSC)	45
6.2.1	Introduction	45
6.2.2	Structure	45
6.2.3	Building the MSC	45
6.2.4	Reconfiguration	46
6.3	Fast Access Channel (FAC)	46
6.3.1	Introduction	46
6.3.2	Structure	46
6.3.3	Channel parameters	46
6.3.4	Service parameters	49
6.3.5	CRC	51
6.3.6	FAC repetition	51
6.4	Service Description Channel (SDC)	52
6.4.1	Introduction	52
6.4.2	Structure	52
6.4.3	Data entities	53
6.4.3.0	Introduction	53
6.4.3.1	Multiplex description data entity - type 0	54
6.4.3.2	Label data entity - type 1	54
6.4.3.3	Conditional access parameters data entity - type 2	55
6.4.3.4	Alternative frequency signalling: Multiple frequency network information data entity - type 3	56
6.4.3.5	Alternative frequency signalling: Schedule definition data entity - type 4	58
6.4.3.6	Application information data entity - type 5	58
6.4.3.7	Announcement support and switching data entity - type 6	60
6.4.3.8	Alternative frequency signalling: Region definition data entity - type 7	62
6.4.3.9	Time and date information data entity - type 8	63
6.4.3.10	Audio information data entity - type 9	63
6.4.3.11	FAC channel parameters data entity - type 10	66
6.4.3.12	Alternative frequency signalling: Other services data entity - type 11	67
6.4.3.13	Language and country data entity - type 12	71
6.4.3.14	Alternative frequency signalling: detailed region definition data entity - type 13	71
6.4.3.15	Packet stream FEC parameters data entity - type 14	72
6.4.3.16	Extension data entity - type 15	73
6.4.3.16.0	General	73
6.4.3.16.1	Service linking information data entity - type 15, extension 0	73
6.4.3.16.2	Other data entity type 15 extensions	74
6.4.4	Summary of data entity characteristics	75
6.4.5	Changing the content of the SDC	76
6.4.6	Signalling of reconfigurations	77
6.4.6.0	Introduction	77
6.4.6.1	Service reconfigurations	77
6.4.6.2	Channel reconfigurations	78
6.5	Text message application	78
6.6	Packet mode	80
6.6.0	Introduction	80
6.6.1	Packet structure	80
6.6.1.0	Introduction	80
6.6.1.1	Header	81
6.6.1.2	Data field	81
6.6.2	Asynchronous streams	82
6.6.3	Files	82
6.6.4	Choosing the packet length	82
6.6.5	Forward Error Correction (FEC) for packet mode streams	82
6.6.5.0	Introduction	82

6.6.5.1	Encoding of FEC Packets.....	83
6.6.5.2	Transport of FEC packets.....	85
6.6.5.3	Receiver considerations	86
6.7	Presentation of service labels and text messages.....	86
6.7.1	Introduction.....	86
6.7.2	Encoding of the text control field	87
6.7.3	Transport of the text control field	88
6.7.3.1	SDC data entity type 1 labels	88
6.7.3.2	Text messages	89
6.7.4	Display of RTL and bidirectional text	89
6.7.4.1	Introduction.....	89
6.7.4.2	Minimum RTL implementation	89
6.7.4.3	Simplified bidirectional algorithm	90
7	Channel coding and modulation.....	91
7.1	Introduction	91
7.2	Transport multiplex adaptation and energy dispersal	92
7.2.1	Transport multiplex adaptation	92
7.2.1.0	General	92
7.2.1.1	MSC	92
7.2.1.2	FAC	93
7.2.1.3	SDC	93
7.2.2	Energy dispersal.....	94
7.3	Coding	95
7.3.1	Multilevel coding.....	95
7.3.1.0	Introduction	95
7.3.1.1	Partitioning of the bitstream.....	96
7.3.2	Component code	97
7.3.3	Bit interleaving	103
7.3.3.0	Introduction	103
7.3.3.1	FAC	103
7.3.3.2	SDC	104
7.3.3.3	MSC	104
7.4	Signal constellations and mapping	105
7.5	Application of coding to the channels	107
7.5.1	Coding the MSC	107
7.5.1.0	Introduction	107
7.5.1.1	Coding	107
7.5.2	Coding the SDC	108
7.5.3	Coding the FAC	109
7.6	MSC cell interleaving.....	109
7.7	Mapping of MSC cells on the transmission super frame structure	111
8	Transmission structure	112
8.1	Transmission frame structure and robustness modes	112
8.2	Propagation-related OFDM parameters.....	114
8.3	Signal bandwidth related parameters.....	114
8.3.1	Parameter definition.....	114
8.3.2	Simulcast transmission	116
8.4	Pilot cells	116
8.4.1	Functions and derivation.....	116
8.4.2	Frequency references	116
8.4.2.0	Introduction	116
8.4.2.1	Cell positions.....	117
8.4.2.2	Cell gains and phases	117
8.4.3	Time references	118
8.4.3.0	Introduction	118
8.4.3.1	Cell positions and phases	118
8.4.3.2	Cell gains	121
8.4.4	Gain references	121
8.4.4.0	Introduction	121
8.4.4.1	Cell positions.....	121

8.4.4.2	Cell gains	121
8.4.4.3	Cell phases	122
8.4.4.3.0	Introduction	122
8.4.4.3.1	Procedure for calculation of cell phases	122
8.4.4.3.2	Robustness mode A	123
8.4.4.3.3	Robustness mode B	123
8.4.4.3.4	Robustness mode C	123
8.4.4.3.5	Robustness mode D	124
8.4.4.3.6	Robustness mode E.....	124
8.4.5	AFS references.....	124
8.4.5.0	Introduction.....	124
8.4.5.1	Cell positions and phases	125
8.4.5.2	Cell gains	126
8.5	Control cells	126
8.5.1	General.....	126
8.5.2	FAC cells	127
8.5.2.1	Cell positions.....	127
8.5.2.2	Cell gains and phases	129
8.5.3	SDC cells	129
8.5.3.1	Cell positions.....	129
8.5.3.2	Cell gains and phases	130
8.6	Data cells	130
8.6.1	Cell positions	130
8.6.2	Cell gains and phases.....	130
Annex A (informative):	Simulated system performance.....	131
Annex B (informative):	Definition of channel profiles.....	132
B.1	Robustness modes A, B, C and D	132
B.2	Robustness mode E	134
Annex C (informative):	Example of mapping of logical frames to multiplex frames.....	137
Annex D (normative):	Calculation of the CRC word	139
Annex E (informative):	RF protection ratios.....	141
Annex F (informative):	Alternative Frequency and announcement signalling	142
F.0	Introduction	142
F.1	Possibilities of the Alternative Frequency Signalling feature	142
F.2	Possibilities of the announcement feature	143
F.3	SDC data entities overview for Alternative Frequency and announcement signalling	145
F.4	SDC data entities and setup for alternative frequency signalling.....	146
F.5	SDC data entities and setup for announcement.....	146
F.6	Alternative frequency and announcement signalling - coding example.....	148
Annex G (informative):	Guidelines for receiver implementation.....	151
G.0	Introduction	151
G.1	Alternative frequency checking and switching (AFS)	151
G.2	Station buttons for DRM services	152
G.3	Seamless Alternative Frequency checking and Switching (AFS)	153
Annex H (informative):	Service capacity and bit rates	156
Annex I:	Void	157

Annex J (informative):	Numbers of input bits	158
Annex K (informative):	Simulcast transmission, alternate sources and enhancement signalling.....	160
Annex L (informative):	Pilot reference illustrations	163
Annex M (informative):	MSC configuration examples.....	169
Annex N (informative):	Signalling Warning/Alarm announcements	172
Annex O (normative):	Interpretation of schedules for Alternative Frequency Signalling.....	173
Annex P (informative):	Transmit diversity.....	175
Annex Q (informative):	Seamless reconfiguration	176
Annex R (informative):	Seamless receiver switching between DRM, DAB, AM and FM broadcasts.....	178
R.1	Overview	178
R.2	General network timing considerations.....	178
R.3	Network synchronization rules.....	179
R.4	Receiver implementation rules.....	180
R.5	Definition of broadcast signal time references.....	181
Annex S (informative):	Combined transmission of DRM and FM	182
Annex T (informative):	Assignment of Service identifiers	183
T.0	Introduction	183
T.1	Domestic services.....	183
T.2	International services.....	183
History		184

*iTeh STANDARD REVIEW
Full standard:
<https://standards.iteh.ae/4e98-a365-226e5652b36/etsi-es-201-980-v4.2.1-2020-11>*

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Foreword

This final draft ETSI Standard (ES) has been produced by Joint Technical Committee (JTC) Broadcast of the European Broadcasting Union (EBU), Comité Européen de Normalisation ELECtrotechnique (CENELEC) and the European Telecommunications Standards Institute (ETSI), and is now submitted for the ETSI standards Membership Approval Procedure.

NOTE: The EBU/ETSI JTC Broadcast was established in 1990 to co-ordinate the drafting of standards in the specific field of broadcasting and related fields. Since 1995 the JTC Broadcast became a tripartite body by including in the Memorandum of Understanding also CENELEC, which is responsible for the standardization of radio and television receivers. The EBU is a professional association of broadcasting organizations whose work includes the co-ordination of its members' activities in the technical, legal, programme-making and programme-exchange domains. The EBU has active members in about 60 countries in the European broadcasting area; its headquarters is in Geneva.

European Broadcasting Union
CH-1218 GRAND SACONNEX (Geneva)
Switzerland
Tel: +41 22 717 21 11
Fax: +41 22 717 24 81

Modal verbs terminology

In the present document "shall", "shall not", "should", "should not", "may", "need not", "will", "will not", "can" and "cannot" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and "must not" are NOT allowed in ETSI deliverables except when used in direct citation.

Introduction

The frequency bands used for broadcasting below 30 MHz are:

- Low Frequency (LF) band: from 148,5 kHz to 283,5 kHz, in ITU Region 1 [1] only;
- Medium Frequency (MF) band: from 526,5 kHz to 1 606,5 kHz, in ITU Regions 1 [1] and 3 [1] and from 525 kHz to 1 705 kHz in ITU Region 2 [1];
- High Frequency (HF) band: a set of individual broadcasting bands in the frequency range 2,3 MHz to 27 MHz, generally available on a Worldwide basis.

These bands offer unique propagation capabilities that permit the achievement of:

- large coverage areas, whose size and location may be dependent upon the time of day, season of the year or period in the (approximately) 11 year sunspot cycle;
- portable and mobile reception with relatively little impairment caused by the environment surrounding the receiver.

There is thus a desire to continue broadcasting in these bands, perhaps especially in the case of international broadcasting where the HF bands offer the only reception possibilities which do not also involve the use of local repeater stations.

However, broadcasting services in these bands:

- use analogue techniques;
- are subject to limited quality;
- are subject to considerable interference as a result of the long-distance propagation mechanisms which prevail in this part of the frequency spectrum and the large number of users.

As a direct result of the above considerations, there is a desire to effect a transfer to digital transmission and reception techniques in order to provide the increase in quality which is needed to retain listeners who, increasingly, have a wide variety of other programme reception media possibilities, usually already offering higher quality and reliability.

In order to meet the need for a digital transmission system suitable for use in all of the bands below 30 MHz, the Digital Radio Mondiale (DRM) consortium was formed in early 1998. The DRM consortium is a non-profit making body which seeks to develop and promote the use of the DRM system worldwide. Its members include broadcasters, network providers, receiver and transmitter manufacturers and research institutes. More information is available from their website (<http://www.drm.org/>).

In March 2005, the DRM Consortium voted at its General Assembly to embark on extending the capability of the DRM system to provide digital radio services at higher transmission frequencies. This range includes:

- 47 MHz to 68 MHz (Band I) allocated to analogue television broadcasting;
- 65,8 MHz to 74 MHz (OIRT FM band);
- 76 MHz to 90 MHz (Japanese FM band);
- 87,5 MHz to 107,9 MHz (Band II) allocated to FM radio broadcasting;
- 174 MHz to 240 MHz (Band III) allocated to digital broadcasting.

This extension completes the family of digital standards for radio broadcasting.

1 Scope

The present document gives the specification for the Digital Radio Mondiale (DRM) system for digital transmissions in the broadcasting bands below 300 MHz.

With respect to the previous published version, the present document removes unused modulation features and defines additional text handling features.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] ITU Radio Regulations.
- [2] ISO/IEC 14496-3: "Information technology - Coding of audio-visual objects - Part 3: Audio".
- [3] ETSI EN 300 401: "Radio Broadcasting Systems; Digital Audio Broadcasting (DAB) to mobile, portable and fixed receivers".
- [4] ISO/IEC 10646: "Information technology -- Universal Coded Character Set (UCS)".
- [5] ISO 639-2: "Codes for the representation of names of languages - Part 2: Alpha-3 code".
- [6] ISO 3166 (all parts): "Codes for the representation of names of countries and their subdivisions".
- [7] ISO/IEC 8859-1: "Information technology - 8-bit single-byte coded graphic character sets - Part 1: Latin alphabet No. 1".
- [8] ETSI TS 101 968: "Digital Radio Mondiale (DRM); Data applications directory".
- [9] Void.
- [10] ISO/IEC 23003-1: "Information technology - MPEG audio technologies - Part 1: MPEG Surround".
- [11] ISO/IEC 23003-3: "Information technology - MPEG audio technologies - Part 3: Unified speech and audio coding".
- [12] ETSI TS 126 290: "Digital cellular telecommunications system (Phase 2+) (GSM); Universal Mobile Telecommunications System (UMTS); LTE; Audio codec processing functions; Extended Adaptive Multi-Rate - Wideband (AMR-WB+) codec; Transcoding functions (3GPP TS 26.290)".
- [13] IEC 62106: "Specification of the Radio Data System (RDS) for VHF/FM sound broadcasting in the frequency range from 87,5 MHz to 108,0 MHz".
- [14] ETSI TS 102 386: "Digital Radio Mondiale (DRM); AM signalling system (AMSS)".
- [15] ETSI TS 103 176: "Digital Audio Broadcasting (DAB); Rules of implementation; Service information features".

[16] ETSI TS 102 980: "Digital Audio Broadcasting (DAB); Dynamic Label Plus (DL Plus); Application specification".

[17] ETSI TS 103 771: "Digital Radio Mondiale (DRM); Regional profiles".

[18] Unicode® standard.

NOTE: Available at <https://www.unicode.org/versions/latest>.

[19] Unicode® bidirectional algorithm, UAX#9.

NOTE: Available at <http://www.unicode.org/reports/tr9/>.

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

[i.1] Recommendation ITU-R BS.1615: "Planning parameters" for digital sound broadcasting at frequencies below 30 MHz".

[i.2] Recommendation ITU-R BS.1660: "Technical basis for planning of terrestrial digital sound broadcasting in the VHF band".

3 Definition of terms, symbols, abbreviations and conventions

3.1 Terms

For the purposes of the present document, the following terms apply:

cell: sine wave portion of duration T_s , transmitted with a given amplitude and phase and corresponding to a carrier position

NOTE: Each OFDM symbol is the sum of K such sine wave portions equally spaced in frequency.

energy dispersal: operation involving deterministic selective complementing of bits in the logical frame, intended to reduce the possibility that systematic patterns result in unwanted regularity in the transmitted signal

Fast Access Channel (FAC): channel of the multiplex data stream which contains the information that is necessary to find services and begin to decode the multiplex

kbit/s: kilo bits per second (1 000 bits per second)

logical frame: data contained in one stream during 400 ms or 100 ms

Main Service Channel (MSC): channel of the multiplex data stream which occupies the major part of the transmission frame and which carries all the digital audio services, together with possible supporting and additional data services

mod: modulo operator

NOTE: $(x \bmod y) = z$, where $y > 0$, such that $x = qy + z$, q is an integer and $0 \leq z < y$.

multiplex frame: logical frames from all streams form a multiplex frame

NOTE: It is the relevant basis for coding and interleaving.

OFDM symbol: transmitted signal for that portion of time when the modulating amplitude and phase state is held constant on each of the equally-spaced carriers in the signal

reserved for future addition (rfa): bits with this designation are set to zero

NOTE: Receivers need not decode these bits.

reserved for future use (rfu): bits with this designation are set to zero

NOTE: Receivers need to check these bits in order to determine the valid status of the other fields in the same scope.

Service Description Channel (SDC): channel of the multiplex data stream which gives information to decode the services included in the multiplex

NOTE: The SDC also provides additional information to enable a receiver to find alternative sources of the same data.

Single Frequency Network (SFN): network of transmitters sharing the same radio frequency to achieve a large area coverage

transmission frame: number of consecutive OFDM symbols, whereby the first OFDM symbol contains the time reference cells

transmission super frame: set of consecutive transmission frames, whereby the first OFDM symbols contain the SDC block

UEP profile: combination of protection levels and lengths of higher protected parts for unequal error protection

3.2 Symbols

For the purposes of the present document, the following symbols apply:

$E[]$	expectation value of the expression in brackets
f_r	reference frequency of the emitted signal
K	number of active carriers in the OFDM symbol
K_{\max}	carrier index of the upper active carrier in the OFDM signal
K_{\min}	carrier index of the lower active carrier in the OFDM signal
L_{MUX}	number of input bits per multiplex frame for the multilevel encoding
N_{MUX}	number of MSC cells (QAM symbols) per multiplex frame
T	elementary time period, equal to $83^{1/3} \mu\text{s}$ (1/12 kHz)
T_f	duration of the transmission frame
T_g	duration of the guard interval
T_s	duration of an OFDM symbol
T_{sf}	duration of the transmission super-frame built from the set of transmission frames
T_u	duration of the useful (orthogonal) part of an OFDM symbol, excluding the guard interval
X^*	complex conjugate of value X
$\lceil \rceil$	round towards plus infinity
$\lfloor \rfloor$	round towards minus infinity

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

AAC	Advanced Audio Coding
ACELP	Algebraic Code Excited Linear Prediction
AF	Audio Frequency
AFS	Alternative Frequency Switching
AM	Amplitude Modulation
AMR-WB	Adaptive Multi-Rate WideBand
AMSS	Amplitude Modulation Signalling System
AWGN	Additive White Gaussian Noise
BER	Bit Error Rate
CA	Conditional Access
CC	Country Codes
CCIR	Comité Consultatif International des Radio-communications
CI	Continuity Index
CIRAF	Conferencia Internacional de Radiodifusión por Altas Frecuencias
CRC	Cyclic Redundancy Check
DAB	Digital Audio Broadcasting
DC	Direct Current
DL	Dynamic Label
DRM	Digital Radio Mondiale
DSB	Double SideBand
ECC	Extended Country Code
EEP	Equal Error Protection
EP	Error Protection
ER	Error Robust
EW	East West
FAC	Fast Access Channel
FEC	Forward Error Correction
FM	Frequency Modulation
HCR	Huffman Codeword Reordering
HE-AAC	High Efficiency AAC
HF	High Frequency
HFBC	High Frequency Broadcasting Committee
HFCC	High Frequency Coordination Committee
ID	Identification
IFFT	Inverse Fast Fourier Transform
ILS	International Linkage Set
ISO	International Organization for Standardization
LA	Linkage Actuator
LF	Low Frequency
LOS	Line-Of-Sight
LRI	Left-to-Right Isolate
LSb	Least Significant bit
LSN	Linkage Set Number
LTO	Local Time Offset
LTR	Left-To-Right
MDCT	Modified Discrete Cosine Transform
MDI	Multiplex Distribution Interface
MF	Medium Frequency
MJD	Modified Julian Date
MPEG	Moving Picture Experts Group
MPS	MPEG Surround
MSb	Most Significant bit
MSC	Main Service Channel
MW	Medium Wave
NS	North South
OFDM	Orthogonal Frequency Division Multiplexing