

ETSI TS 138 213 V17.3.0 (2022-09)



**5G;
NR;**

**Physical layer procedures for control
(3GPP TS 38.213 version 17.3.0 Release 17)**

[ETSI TS 138 213 V17.3.0 \(2022-09\)](https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09)

<https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09>



Reference

RTS/TSGR-0138213vh30

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://standards-portal.etsi.org/People/CommitteeSupportStaff.aspx> 4829-8360-

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2022.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

| | |
|--|----|
| Intellectual Property Rights | 2 |
| Legal Notice | 2 |
| Modal verbs terminology..... | 2 |
| Foreword..... | 6 |
| 1 Scope | 7 |
| 2 References | 7 |
| 3 Definitions, symbols and abbreviations | 8 |
| 3.1 Definitions | 8 |
| 3.2 Symbols..... | 8 |
| 3.3 Abbreviations | 8 |
| 4 Synchronization procedures | 10 |
| 4.1 Cell search | 10 |
| 4.2 Transmission timing adjustments | 13 |
| 4.3 Timing for secondary cell activation / deactivation..... | 14 |
| 5 Radio link monitoring | 15 |
| 6 Link recovery procedures | 16 |
| 7 Uplink Power control | 20 |
| 7.1 Physical uplink shared channel | 21 |
| 7.1.1 UE behaviour | 22 |
| 7.2 Physical uplink control channel | 34 |
| 7.2.1 UE behaviour | 34 |
| 7.3 Sounding reference signals..... | 40 |
| 7.3.1 UE behaviour | 40 |
| 7.4 Physical random access channel..... | 43 |
| 7.5 Prioritizations for transmission power reductions | 43 |
| 7.6 Dual connectivity | 44 |
| 7.6.1 EN-DC | 44 |
| 7.6.1A NE-DC | 45 |
| 7.6.2 NR-DC..... | 46 |
| 7.7 Power headroom report | 47 |
| 7.7.1 Type 1 PH report | 48 |
| 7.7.2 Type 2 PH report | 50 |
| 7.7.3 Type 3 PH report | 50 |
| 8 Random access procedure | 51 |
| 8.1 Random access preamble | 51 |
| 8.1A PUSCH for Type-2 random access procedure..... | 55 |
| 8.2 Random access response - Type-1 random access procedure | 57 |
| 8.2A Random access response - Type-2 random access procedure | 58 |
| 8.3 PUSCH scheduled by RAR UL grant..... | 60 |
| 8.4 PDSCH with UE contention resolution identity | 61 |
| 9 UE procedure for reporting control information | 62 |
| 9.A PUCCH cell switching | 70 |
| 9.1 HARQ-ACK codebook determination | 71 |
| 9.1.1 CBG-based HARQ-ACK codebook determination | 72 |
| 9.1.2 Type-1 HARQ-ACK codebook determination | 72 |
| 9.1.2.1 Type-1 HARQ-ACK codebook in physical uplink control channel..... | 74 |
| 9.1.2.2 Type-1 HARQ-ACK codebook in physical uplink shared channel..... | 86 |
| 9.1.3 Type-2 HARQ-ACK codebook determination | 87 |
| 9.1.3.1 Type-2 HARQ-ACK codebook in physical uplink control channel..... | 88 |
| 9.1.3.2 Type-2 HARQ-ACK codebook in physical uplink shared channel..... | 97 |
| 9.1.3.3 Type-2 HARQ-ACK codebook grouping and HARQ-ACK retransmission..... | 98 |

| | | |
|------------|---|-----|
| 9.1.4 | Type-3 HARQ-ACK codebook determination | 101 |
| 9.1.5 | HARQ-ACK codebook retransmission..... | 104 |
| 9.2 | UCI reporting in physical uplink control channel | 105 |
| 9.2.1 | PUCCH Resource Sets..... | 105 |
| 9.2.2 | PUCCH Formats for UCI transmission | 109 |
| 9.2.3 | UE procedure for reporting HARQ-ACK..... | 110 |
| 9.2.4 | UE procedure for reporting SR..... | 114 |
| 9.2.5 | UE procedure for reporting multiple UCI types | 115 |
| 9.2.5.0 | UE procedure for prioritization between SL HARQ-ACK information in a PUCCH and DL HARQ-ACK or SR or CSI in a PUCCH..... | 120 |
| 9.2.5.1 | UE procedure for multiplexing HARQ-ACK or CSI and SR in a PUCCH | 120 |
| 9.2.5.2 | UE procedure for multiplexing HARQ-ACK/SR/CSI in a PUCCH | 122 |
| 9.2.5.3 | UE procedure for reporting UCI of different priorities | 126 |
| 9.2.5.4 | UE procedure for deferring HARQ-ACK for SPS PDSCH | 127 |
| 9.2.6 | PUCCH repetition procedure..... | 128 |
| 9.3 | UCI reporting in physical uplink shared channel | 130 |
| 10 | UE procedure for receiving control information | 135 |
| 10.1 | UE procedure for determining physical downlink control channel assignment | 148 |
| 10.1.1 | Self-carrier and cross-carrier scheduling on the primary cell | 168 |
| 10.2 | PDCCH validation for DL SPS and UL grant Type 2..... | 168 |
| 10.2A | PDCCH validation for SL configured grant Type 2..... | 170 |
| 10.3 | PDCCH monitoring indication and dormancy/non-dormancy behaviour for SCells | 171 |
| 10.4 | Search space set group switching and skipping of PDCCH monitoring | 173 |
| 10.4A | PDCCH monitoring for early indication of paging | 178 |
| 10.4B | Indication of TRS resources | 178 |
| 10.5 | HARQ-ACK information for PUSCH transmissions | 178 |
| 11 | UE-group common signalling | 179 |
| 11.1 | Slot configuration..... | 179 |
| 11.1.1 | UE procedure for determining slot format..... | 185 |
| 11.2 | Interrupted transmission indication | 192 |
| 11.2A | Cancellation indication..... | 193 |
| 11.3 | Group TPC commands for PUCCH/PUSCH | 194 |
| 11.4 | SRS switching | 195 |
| 12 | Bandwidth part operation | 196 |
| 13 | UE procedure for monitoring Type0-PDCCH CSS sets | 198 |
| 14 | Integrated access-backhaul operation..... | 211 |
| 15 | Dual active protocol stack based handover | 217 |
| 16 | UE procedures for sidelink..... | 219 |
| 16.1 | Synchronization procedures | 219 |
| 16.2 | Power control | 221 |
| 16.2.0 | S-SS/PSBCH blocks | 221 |
| 16.2.1 | PSSCH | 222 |
| 16.2.2 | PSCCH..... | 223 |
| 16.2.3 | PSFCH | 223 |
| 16.2.4 | Prioritization of transmissions/receptions | 225 |
| 16.2.4.1 | Simultaneous NR and E-UTRA transmission/reception | 225 |
| 16.2.4.2 | Simultaneous PSFCH transmission/reception | 225 |
| 16.2.4.3 | Simultaneous SL and UL transmissions/receptions | 226 |
| 16.2.4.3.1 | Prioritizations for sidelink and uplink transmissions/receptions | 227 |
| 16.3 | UE procedure for reporting and obtaining control information in PSFCH..... | 228 |
| 16.3.0 | UE procedure for transmitting PSFCH with control information | 228 |
| 16.3.1 | UE procedure for receiving PSFCH with control information | 231 |
| 16.4 | UE procedure for transmitting PSCCH | 232 |
| 16.5 | UE procedure for reporting HARQ-ACK on uplink | 232 |
| 16.5.1 | Type-1 HARQ-ACK codebook determination | 235 |
| 16.5.1.1 | Type-1 HARQ-ACK codebook in physical uplink control channel..... | 235 |
| 16.5.1.2 | Type-1 HARQ-ACK codebook in physical uplink shared channel..... | 237 |

| | | |
|-----------------|--|------------|
| 16.5.2 | Type-2 HARQ-ACK codebook determination | 238 |
| 16.5.2.1 | Type-2 HARQ-ACK codebook in physical uplink control channel..... | 238 |
| 16.5.2.2 | Type-2 HARQ-ACK codebook in physical uplink shared channel..... | 240 |
| 16.6 | UE procedure for LTE sidelink transmission | 241 |
| 16.7 | Operation for in-device coexistence | 241 |
| 17 | UE with reduced capabilities..... | 241 |
| 17.1 | RedCap UE procedures | 241 |
| 17.2 | Half-Duplex UE in paired spectrum..... | 242 |
| 18 | Multicast Broadcast Services | 243 |
| 19 | PUSCH transmission in RRC_INACTIVE state..... | 247 |
| 19.1 | Configured-grant based PUSCH transmission | 247 |
| 19.2 | Random-access based PUSCH transmission | 249 |
| Annex A: | Change history | 250 |
| History | | 261 |

iTeh STANDARD PREVIEW (standards.iteh.ai)

[ETSI TS 138 213 V17.3.0 \(2022-09\)](https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09)

<https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[ETSI TS 138 213 V17.3.0 \(2022-09\)](https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09)

<https://standards.iteh.ai/catalog/standards/sist/1f2cd784-41c8-4829-83b0-fe55c2828f35/etsi-ts-138-213-v17-3-0-2022-09>

1 Scope

The present document specifies and establishes the characteristics of the physical layer procedures for control operations in 5G-NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications"
- [2] 3GPP TS 38.201: "NR; Physical Layer – General Description"
- [3] 3GPP TS 38.202: "NR; Services provided by the physical layer"
- [4] 3GPP TS 38.211: "NR; Physical channels and modulation"
- [5] 3GPP TS 38.212: "NR; Multiplexing and channel coding"
- [6] 3GPP TS 38.214: "NR; Physical layer procedures for data"
- [7] 3GPP TS 38.215: "NR; Physical layer measurements"
- [8-1] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone"
- [8-2] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone"
- [8-3] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios"
- [8-4] 3GPP TS 38.101-4: "NR; User Equipment (UE) radio transmission and reception; Part 4: Performance requirements"
- [9] 3GPP TS 38.104: "NR; Base Station (BS) radio transmission and reception"
- [10] 3GPP TS 38.133: "NR; Requirements for support of radio resource management"
- [11] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification"
- [12] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol specification"
- [13] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures"
- [14] 3GPP TS 36.321: "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification"
- [15] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access"
- [16] 3GPP TS 38.473: "F1 application protocol (F1AP)"
- [17] 3GPP TS 38.304: "NR; User Equipment (UE) procedures in Idle mode and RRC Inactive state"
- [18] 3GPP TS 38.306: "NR; User Equipment (UE) radio access capabilities"
- [19] 3GPP TS 38.300: "NR; NR and NG-RAN Overall Description"

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in [1, TR 21.905] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in [1, TR 21.905]. A parameter referenced in *italics* is provided by higher layers.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in [1, TR 21.905].

| | |
|-----------|--|
| BPRE | Bits per resource element |
| BWP | Bandwidth part |
| CB | Code block |
| CBG | Code block group |
| CBR | Channel busy ratio |
| CCE | Control channel element |
| CORESET | Control resource set |
| CP | Cyclic prefix |
| CRC | Cyclic redundancy check |
| C-RNTI | Cell RNTI |
| CS-RNTI | Configured scheduling RNTI |
| CSI | Channel state information |
| CSS | Common search space |
| DAI | Downlink assignment index |
| DAPS | Dual active protocol stack |
| DC | Dual connectivity |
| DCI | Downlink control information |
| DL | Downlink |
| DL-SCH | Downlink shared channel |
| EPRE | Energy per resource element |
| EN-DC | E-UTRA NR dual connectivity with MCG using E-UTRA and SCG using NR |
| FR1 | Frequency range 1 |
| FR2 | Frequency range 2 |
| G-CS-RNTI | Group configured scheduling RNTI |
| G-RNTI | Group RNTI |
| GSCN | Global synchronization channel number |
| HARQ-ACK | Hybrid automatic repeat request acknowledgement |
| MBS | Multicast broadcast services |
| MCG | Master cell group |
| MCS | Modulation and coding scheme |
| NDI | New Data Indicator |
| NE-DC | E-UTRA NR dual connectivity with MCG using NR and SCG using E-UTRA |
| NR-DC | NR NR dual connectivity |
| PBCH | Physical broadcast channel |
| PCell | Primary cell |
| PDCCH | Physical downlink control channel |
| PDSCH | Physical downlink shared channel |
| PO | Paging occasion |
| PRACH | Physical random access channel |
| PRB | Physical resource block |

| | |
|--------------|---------------------------------------|
| PRG | Physical resource block group |
| PSCell | Primary secondary cell |
| PSBCH | Physical sidelink broadcast channel |
| PSCCH | Physical sidelink control channel |
| PSFCH | Physical sidelink feedback channel |
| PSS | Primary synchronization signal |
| PSSCH | Physical sidelink shared channel |
| PUCCH | Physical uplink control channel |
| PUCCH-SCell | PUCCH SCell |
| PUCCH-sSCell | PUCCH switching SCell |
| PUSCH | Physical uplink shared channel |
| QCL | Quasi co-location |
| RB | Resource block |
| RE | Resource element |
| RLM | Radio link monitoring |
| RRM | Radio resource management |
| RS | Reference signal |
| RSRP | Reference signal received power |
| SCG | Secondary cell group |
| SCI | Sidelink control information |
| SCS | Subcarrier spacing |
| SFCI | Sidelink feedback control information |
| SFN | System frame number |
| SL | Sidelink |
| SLIV | Start and length indicator value |
| SPS | Semi-persistent scheduling |
| SR | Scheduling request |
| SRI | SRS resource indicator |
| SRS | Sounding reference signal |
| SSS | Secondary synchronization signal |
| SSSG | Search space set group |
| TA | Timing advance |
| TAG | Timing advance group |
| TB | Transport block |
| TBG | Transport block group |
| TCI | Transmission Configuration Indicator |
| UCI | Uplink control information |
| UE | User equipment |
| UL | Uplink |
| UL-SCH | Uplink shared channel |
| USS | UE-specific search space |

4 Synchronization procedures

4.1 Cell search

Cell search is the procedure for a UE to acquire time and frequency synchronization with a cell and to detect the physical layer Cell ID of the cell.

A UE receives the following synchronization signals (SS) in order to perform cell search: the primary synchronization signal (PSS) and secondary synchronization signal (SSS) as defined in [4, TS 38.211].

A UE assumes that reception occasions of a physical broadcast channel (PBCH), PSS, and SSS are in consecutive symbols, as defined in [4, TS 38.211], and form a SS/PBCH block. The UE assumes that SSS, PBCH DM-RS, and PBCH data have same EPRE. The UE may assume that the ratio of PSS EPRE to SSS EPRE in a SS/PBCH block is either 0 dB or 3 dB. If the UE has not been provided dedicated higher layer parameters, the UE may assume that the ratio of PDCCH DMRS EPRE to SSS EPRE is within -8 dB and 8 dB when the UE monitors PDCCHs for a DCI format 1_0 with CRC scrambled by SI-RNTI, P-RNTI, or RA-RNTI, or for a DCI format 2_7.

For a half frame with SS/PBCH blocks, the first symbol indexes for candidate SS/PBCH blocks are determined according to the SCS of SS/PBCH blocks as follows, where index 0 corresponds to the first symbol of the first slot in a half-frame.

- Case A - 15 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes of $\{2,8\} + 14 \cdot n$.
 - For operation without shared spectrum channel access:
 - For carrier frequencies smaller than or equal to 3 GHz, $n = 0,1$.
 - For carrier frequencies within FR1 larger than 3 GHz, $n = 0,1,2,3$.
 - For operation with shared spectrum channel access, as described in [15, TS 37.213], $n = 0, 1, 2, 3, 4$.
- Case B - 30 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{4,8,16,20\} + 28 \cdot n$. For carrier frequencies smaller than or equal to 3 GHz, $n = 0$. For carrier frequencies within FR1 larger than 3 GHz, $n = 0,1$.
- Case C - 30 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{2,8\} + 14 \cdot n$.
 - For operation without shared spectrum channel access
 - For paired spectrum operation
 - For carrier frequencies smaller than or equal to 3 GHz, $n = 0,1$. For carrier frequencies within FR1 larger than 3 GHz, $n = 0,1,2,3$.
 - For unpaired spectrum operation
 - For carrier frequencies smaller than 1.88 GHz, $n = 0,1$. For carrier frequencies within FR1 equal to or larger than 1.88 GHz, $n = 0,1,2,3$.
 - For operation with shared spectrum channel access, $n = 0, 1, 2, 3, 4, 5, 6, 7, 8, 9$.
- Case D - 120 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{4,8,16,20\} + 28 \cdot n$. For carrier frequencies within FR2, $n = 0, 1, 2, 3, 5, 6, 7, 8, 10, 11, 12, 13, 15, 16, 17, 18$.
- Case E - 240 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{8,12,16,20,32,36,40,44\} + 56 \cdot n$. For carrier frequencies within FR2-1, $n = 0, 1, 2, 3, 5, 6, 7, 8$.
- Case F – 480 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{2, 9\} + 14 \cdot n$. For carrier frequencies within FR2-2, $n = 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30, 31$.

- Case G – 960 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{2, 9\} + 14 \cdot n$. For carrier frequencies within FR2-2, $n = 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30, 31$.

From the above cases, if the SCS of SS/PBCH blocks is not provided by *ssbSubcarrierSpacing*, the applicable cases for a cell depend on a respective frequency band, as provided in [8-1, TS 38.101-1] and [8-2, TS 38.101-2]. A same case applies for all SS/PBCH blocks on the cell. If a 30 kHz SS/PBCH block SCS is indicated by *ssbSubcarrierSpacing*, Case B applies for frequency bands with only 15 kHz SS/PBCH block SCS as specified in [8-1, TS 38.101-1], and the case specified for 30 kHz SS/PBCH block SCS in [8-1, TS 38.101-1] applies for frequency bands with 30 kHz SS/PBCH block SCS or both 15 kHz and 30 kHz SS/PBCH block SCS as specified in [8-1, TS 38.101-1]. For a UE configured to operate with carrier aggregation over a set of cells in a frequency band of FR2 or with frequency-contiguous carrier aggregation over a set of cells in a frequency band of FR1, if the UE is provided SCS values by *ssbSubcarrierSpacing* for receptions of SS/PBCH blocks on any cells from the set of cells, the UE expects the SCS values to be same.

The candidate SS/PBCH blocks in a half frame are indexed in an ascending order in time from 0 to $\bar{L}_{max} - 1$, where \bar{L}_{max} is determined according to SS/PBCH block patterns for Cases A through G. L_{max} is a maximum number of SS/PBCH block indexes in a cell, and the maximum number of transmitted SS/PBCH blocks within a half frame is L_{max} .

- For operation without shared spectrum channel access in FR1 and FR2, and for operation with shared spectrum channel access in FR2-2, $L_{max} = \bar{L}_{max}$
- For operation with shared spectrum channel access in FR1, $L_{max} = 8$ for $\bar{L}_{max} = 10$ and 15 kHz SCS of SS/PBCH blocks and for $\bar{L}_{max} = 20$ and 30 kHz SCS of SS/PBCH blocks

For $\bar{L}_{max} = 4$, a UE determines the 2 LSB bits of a candidate SS/PBCH block index per half frame from a one-to-one mapping with an index of the DM-RS sequence transmitted in the PBCH as described in [4, TS 38.211].

For $\bar{L}_{max} > 4$, a UE determines the 3 LSB bits of a candidate SS/PBCH block index per half frame from a one-to-one mapping with an index of the DM-RS sequence transmitted in the PBCH as described in [4, TS 38.211]

- for $\bar{L}_{max} = 10$, the UE determines the 1 MSB bit of the candidate SS/PBCH block index from PBCH payload bit $\bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]
- for $\bar{L}_{max} = 20$, the UE determines the 2 MSB bits of the candidate SS/PBCH block index from PBCH payload bits $\bar{a}_{\bar{A}+6}, \bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]
- for $\bar{L}_{max} = 64$, the UE determines the 3 MSB bits of the candidate SS/PBCH block index from PBCH payload bits $\bar{a}_{\bar{A}+5}, \bar{a}_{\bar{A}+6}, \bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]

A UE can be provided per serving cell by *ssb-periodicityServingCell* a periodicity of the half frames for reception of the SS/PBCH blocks for the serving cell. If the UE is not configured a periodicity of the half frames for receptions of the SS/PBCH blocks, the UE assumes a periodicity of a half frame. A UE assumes that the periodicity is same for all SS/PBCH blocks in the serving cell.

For initial cell selection, a UE may assume that half frames with SS/PBCH blocks occur with a periodicity of 2 frames.

For operation without shared spectrum channel access, an SS/PBCH block index is same as a candidate SS/PBCH block index.

For operation with shared spectrum channel access, a UE assumes that transmission of SS/PBCH blocks in a half frame is within a discovery burst transmission window that starts from the first symbol of the first slot in a half-frame. The UE can be provided per serving cell by *discoveryBurstWindowLength* a duration of the discovery burst transmission window. If *discoveryBurstWindowLength* is not provided, the UE assumes that the duration of the discovery burst transmission window is a half frame. For a serving cell, the UE assumes that a periodicity of the discovery burst transmission window is same as a periodicity of half frames for receptions of SS/PBCH blocks in the serving cell. The UE assumes that one or more SS/PBCH blocks indicated by *ssb-PositionsInBurst* may be transmitted within the discovery burst transmission window and have candidate SS/PBCH blocks indexes corresponding to SS/PBCH block indexes provided by *ssb-PositionsInBurst*. If MSB $k, k \geq 1$, of *ssb-PositionsInBurst* is set to 1, the UE assumes that SS/PBCH block(s) within the discovery burst transmission window with candidate SS/PBCH block index(es)

corresponding to SS/PBCH block index equal to $k - 1$ may be transmitted; if MSB k is set to 0, the UE assumes that the SS/PBCH block(s) are not transmitted. If MSB k , $k \geq 1$, of *inOneGroup* is set to 1, and MSB m , $m \geq 1$, of *groupPresence* is set to 1, the UE assumes that SS/PBCH block(s) within the discovery burst transmission window with candidate SS/PBCH block index(es) corresponding to SS/PBCH block index determined by k and m may be transmitted; otherwise, the UE assumes that the SS/PBCH block(s) are not transmitted.

For operation with shared spectrum channel access in FR1, a UE assumes that SS/PBCH blocks in a serving cell that are within a same discovery burst transmission window or across discovery burst transmission windows are quasi co-located with respect to average gain, quasi co-location 'typeA' and 'typeD' properties, when applicable [6, TS 38.214], if a value of $(N_{DM-RS}^{PBCH} \bmod N_{SSB}^{QCL})$ is same among the SS/PBCH blocks. N_{DM-RS}^{PBCH} is an index of a DM-RS sequence transmitted in a PBCH of a corresponding SS/PBCH block, and N_{SSB}^{QCL} is either provided by *ssb-PositionQCL* or, if *ssb-PositionQCL* is not provided, obtained from a *MIB* provided by a SS/PBCH block according to Table 4.1-1 with $k_{SSB} < 24$ [4, TS 38.211]. The UE can determine an SS/PBCH block index according to $(N_{DM-RS}^{PBCH} \bmod N_{SSB}^{QCL})$, or according to $(\bar{i} \bmod N_{SSB}^{QCL})$ where \bar{i} is the candidate SS/PBCH block index. The UE assumes that within a discovery burst transmission window, a number of transmitted SS/PBCH blocks on a serving cell is not larger than N_{SSB}^{QCL} and a number of transmitted SS/PBCH blocks with a same SS/PBCH block index is not larger than one.

Table 4.1-1: Mapping between the combination of *subCarrierSpacingCommon* and LSB of *ssb-SubcarrierOffset* to N_{SSB}^{QCL} for operation with shared spectrum channel access in FR1

| <i>subCarrierSpacingCommon</i> | LSB of <i>ssb-SubcarrierOffset</i> | N_{SSB}^{QCL} |
|--------------------------------|------------------------------------|-----------------|
| scs15or60 | 0 | 1 |
| scs15or60 | 1 | 2 |
| scs30or120 | 0 | 4 |
| scs30or120 | 1 | 8 |

For operation with shared spectrum channel access in FR2-2, a UE assumes that SS/PBCH blocks in a serving cell that are within a same discovery burst transmission window or across discovery burst transmission windows are quasi co-located with respect to average gain, quasi co-location 'typeA' and 'typeD' properties, when applicable, if a value of $(\bar{i} \bmod N_{SSB}^{QCL})$ is same among the SS/PBCH blocks, where \bar{i} is the candidate SS/PBCH block index. N_{SSB}^{QCL} is either provided by *ssb-PositionQCL* or, if *ssb-PositionQCL* is not provided, obtained from a *MIB* provided by a SS/PBCH block according to Table 4.1-2. The UE can determine an SS/PBCH block index according to $(\bar{i} \bmod N_{SSB}^{QCL})$. The UE assumes that within a discovery burst transmission window, a number of transmitted SS/PBCH blocks on a serving cell is not larger than N_{SSB}^{QCL} and a number of transmitted SS/PBCH blocks with a same SS/PBCH block index is not larger than one.

Table 4.1-2: Mapping between *subCarrierSpacingCommon* to N_{SSB}^{QCL} for operation with shared spectrum channel access in FR2-2

| <i>subCarrierSpacingCommon</i> | N_{SSB}^{QCL} |
|--------------------------------|-----------------|
| scs15or60 | 32 |
| scs30or120 | 64 |

For operation without shared spectrum channel access in FR2-2, a UE expects a *MIB* in a SS/PBCH block to provide *subCarrierSpacingCommon* = 'scs30or120'.

Upon detection of a SS/PBCH block, the UE determines from *MIB* that a CORESET for Type0-PDCCH CSS set, as described in clause 13, is present if $k_{SSB} < 24$ [4, TS 38.211] for FR1 or if $k_{SSB} < 12$ for FR2. The UE determines from *MIB* that a CORESET for Type0-PDCCH CSS set is not present if $k_{SSB} > 23$ for FR1 or if $k_{SSB} > 11$ for FR2; the CORESET for Type0-PDCCH CSS set may be provided by *PDCCH-ConfigCommon*.

For a serving cell without transmission of SS/PBCH blocks, a UE acquires time and frequency synchronization with the serving cell based on receptions of SS/PBCH blocks on the PCell, or on the PSCell, or on an SCell if applicable as described in [10, TS 38.133], of the cell group for the serving cell.

4.2 Transmission timing adjustments

A UE can be provided a value $N_{TA,offset}$ of a timing advance offset for a serving cell by *n-TimingAdvanceOffset* for the serving cell. If the UE is not provided *n-TimingAdvanceOffset* for a serving cell, the UE determines a default value $N_{TA,offset}$ of the timing advance offset for the serving cell as described in [10, TS 38.133].

If a UE is configured with two UL carriers for a serving cell, a same timing advance offset value $N_{TA,offset}$ applies to both carriers.

Upon reception of a timing advance command for a TAG, the UE adjusts uplink timing for PUSCH/SRS/PUCCH transmission on all the serving cells in the TAG based on a value $N_{TA,offset}$ that the UE expects to be same for all the serving cells in the TAG and based on the received timing advance command where the uplink timing for PUSCH/SRS/PUCCH transmissions is the same for all the serving cells in the TAG.

For a band with synchronous contiguous intra-band EN-DC in a band combination with non-applicable maximum transmit timing difference requirements as described in Note 1 of Table 7.5.3-1 of [10, TS 38.133], if the UE indicates *ul-TimingAlignmentEUTRA-NR* as 'required' and uplink transmission timing based on timing adjustment indication for a TAG from MCG and a TAG from SCG are determined to be different by the UE, the UE adjusts the transmission timing for PUSCH/SRS/PUCCH transmission on all serving cells part of the band with the synchronous contiguous intra-band EN-DC based on timing adjustment indication for a TAG from a serving cell in MCG in the band. The UE is not expected to transmit a PUSCH/SRS/PUCCH in one CG when the PUSCH/SRS/PUCCH is overlapping in time, even partially, with random access preamble transmitted in another CG.

For a SCS of $2^\mu \cdot 15$ kHz, the timing advance command for a TAG indicates the change of the uplink timing relative to the current uplink timing for the TAG in multiples of $16 \cdot 64 \cdot T_c / 2^\mu$. The start timing of the random access preamble is described in [4, TS 38.211].

A timing advance command [11, TS 38.321] in case of random access response or in an absolute timing advance command MAC CE, T_A , for a TAG indicates N_{TA} values by index values of $T_A = 0, 1, 2, \dots, 3846$, where an amount of the time alignment for the TAG with SCS of $2^\mu \cdot 15$ kHz is $N_{TA} = T_A \cdot 16 \cdot 64 / 2^\mu$. N_{TA} is defined in [4, TS 38.211] and is relative to the SCS of the first uplink transmission from the UE after the reception of the random access response or absolute timing advance command MAC CE.

In other cases, a timing advance command [11, TS 38.321], T_A , for a TAG indicates adjustment of a current N_{TA} value, $N_{TA,old}$, to the new N_{TA} value, $N_{TA,new}$, by index values of $T_A = 0, 1, 2, \dots, 63$, where for a SCS of $2^\mu \cdot 15$ kHz, $N_{TA,new} = N_{TA,old} + (T_A - 31) \cdot 16 \cdot 64 / 2^\mu$.

If a UE has multiple active UL BWPs, as described in clause 12, in a same TAG, including UL BWPs in two UL carriers of a serving cell, the timing advance command value is relative to the largest SCS of the multiple active UL BWPs. The applicable $N_{TA,new}$ value for an UL BWP with lower SCS may be rounded to align with the timing advance granularity for the UL BWP with the lower SCS while satisfying the timing advance accuracy requirements in [10, TS 38.133].

Adjustment of an N_{TA} value by a positive or a negative amount indicates advancing or delaying the uplink transmission timing for the TAG by a corresponding amount, respectively.

For a timing advance command received on uplink slot n and for a transmission other than a PUSCH scheduled by a RAR UL grant or a fallbackRAR UL grant as described in clause 8.2A or 8.3, or a PUCCH with HARQ-ACK information in response to a successRAR as described in clause 8.2A, the corresponding adjustment of the uplink transmission timing applies from the beginning of uplink slot $n + k + 1 + 2^\mu \cdot K_{offset}$ where $k = \lceil N_{slot}^{subframe,\mu} \cdot (N_{T,1} + N_{T,2} + N_{TA,max} + 0.5) / T_{sf} \rceil$, $N_{T,1}$ is a time duration in msec of N_1 symbols corresponding to a PDSCH processing time for UE processing capability 1 when additional PDSCH DM-RS is configured, $N_{T,2}$ is a time duration in msec of N_2 symbols corresponding to a PUSCH preparation time for UE processing capability 1 [6, TS 38.214], $N_{TA,max}$ is the maximum timing advance value in msec that can be provided by a TA command field of 12 bits, $N_{slot}^{subframe,\mu}$ is the number of slots per subframe, T_{sf} is the subframe duration of 1 msec, and $K_{offset} = K_{cell,offset} - K_{UE,offset}$, where $K_{cell,offset}$ is provided by *CellSpecific_Koffset* and $K_{UE,offset}$ is provided by a Differential Koffset MAC CE command [11, TS 38.321]; otherwise, if not respectively provided, $K_{cell,offset} = 0$ or $K_{UE,offset} = 0$. N_1 and N_2 are determined with respect to the minimum SCS among the SCSs of all configured UL BWPs for all uplink carriers in the TAG and of all configured DL BWPs for the corresponding downlink carriers. For $\mu = 0$, the UE assumes $N_{1,0} = 14$ [6, TS 38.214]. Slot n and $N_{slot}^{subframe,\mu}$ are determined with respect to the minimum SCS among the SCSs of all configured UL BWPs for all uplink carriers in the TAG. $N_{TA,max}$ is determined with respect to the minimum SCS

among the SCSs of all configured UL BWPs for all uplink carriers in the TAG and for all configured initial UL BWPs provided by *initialUplinkBWP*. The uplink slot n is the last slot among uplink slot(s) overlapping with the slot(s) of PDSCH reception assuming $T_{TA} = 0$, where the PDSCH provides the timing advance command and T_{TA} is defined in [4, TS 38.211].

If a UE changes an active UL BWP between a time of a timing advance command reception and a time of applying a corresponding adjustment for the uplink transmission timing, the UE determines the timing advance command value based on the SCS of the new active UL BWP. If the UE changes an active UL BWP after applying an adjustment for the uplink transmission timing, the UE assumes a same absolute timing advance command value before and after the active UL BWP change.

If the received downlink timing changes and is not compensated or is only partly compensated by the uplink timing adjustment without timing advance command as described in [10, TS 38.133], the UE changes N_{TA} accordingly.

If two adjacent slots overlap due to a TA command, the latter slot is reduced in duration relative to the former slot. The UE does not change N_{TA} during an actual transmission time window for a PUSCH or a PUCCH transmission [6, TS 38.214].

Using higher-layer ephemeris parameters for a serving satellite, if provided, a UE pre-compensates the two-way transmission delay on the service link based on $N_{TA,adj}^{UE}$ that the UE determines using the serving satellite position and its own position. To pre-compensate the two-way transmission delay between the uplink time synchronization reference point and the serving satellite, the UE determines $N_{TA,adj}^{common}$ [4, TS 38.211] based on one-way propagation delay $Delay_{common}(t)$ that the UE determines as:

$$Delay_{common}(t) = \frac{TA_{Common}}{2} + \frac{TA_{CommonDrift}}{2} \times (t - t_{epoch}) + \frac{TA_{CommonDriftVariant}}{2} \times (t - t_{epoch})^2$$

where TA_{Common} , $TA_{CommonDrift}$, and $TA_{CommonDriftVariant}$ are respectively provided by *ta-Common*, *ta-CommonDrift*, and *ta-CommonDriftVariant* and t_{epoch} is the epoch time of TA_{Common} , $TA_{CommonDrift}$, and $TA_{CommonDriftVariant}$ [12, TS 38.331]. $Delay_{common}(t)$ provides a distance at time t between the serving satellite and the uplink time synchronization reference point divided by the speed of light. The uplink time synchronization reference point is the point where DL and UL are frame aligned with an offset given by $N_{TA,offset}$.

4.3 Timing for secondary cell activation / deactivation

With reference to slots for PUCCH transmissions, when a UE receives in a PDSCH an activation command [11, TS 38.321] for a secondary cell ending in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133] and no earlier than slot $n+k$, except for the following:

- the actions related to CSI reporting on a serving cell that is active in slot $n+k$
- the actions related to the *sCellDeactivationTimer* associated with the secondary cell [11, TS 38.321] that the UE applies in slot $n+k$
- the actions related to CSI reporting on a serving cell which is not active in slot $n+k$ that the UE applies in the earliest slot after $n+k$ in which the serving cell is active.

The value of k is $m + 3 N_{slot}^{subframe,\mu} + 1$ where slot $n+m$ is a slot indicated for PUCCH transmission with HARQ-ACK information for the PDSCH reception as described in clause 9.2.3 and $N_{slot}^{subframe,\mu}$ is a number of slots per subframe for the SCS configuration μ of the PUCCH transmission as defined in [4, TS 38.211].

With reference to slots for PUCCH transmissions, if a UE receives a deactivation command [11, TS 38.321] for a secondary cell ending in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133], except for the actions related to CSI reporting on an activated serving cell which the UE applies in slot $n+k$.

If the *sCellDeactivationTimer* associated with the secondary cell expires in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133], except for the actions