

ETSI TS 138 213 V16.14.0 (2023-07)



**5G;
NR;**

**Physical layer procedures for control
(3GPP TS 38.213 version 16.14.0 Release 16)**

ETSI TS 138 213 V16.14.0 (2023-07)

<https://standards.iteh.ai/catalog/standards/sist/337b586c-6a0a-4f25-af56-d86e1e8befc9/etsi-ts-138-213-v16-14-0-2023-07>



Reference

RTS/TSGR-0138213vge0

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<https://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://standards.iteh.ai/> <https://portal.etsi.org/People/CommitteeSupportStaff.aspx> 6-d86e1e8befe9/etsi-

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2023.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <https://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document **"shall"**, **"shall not"**, **"should"**, **"should not"**, **"may"**, **"need not"**, **"will"**, **"will not"**, **"can"** and **"cannot"** are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and **"must not"** are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	5
1 Scope	6
2 References	6
3 Definitions, symbols and abbreviations	7
3.1 Definitions	7
3.2 Symbols.....	7
3.3 Abbreviations	7
4 Synchronization procedures	9
4.1 Cell search	9
4.2 Transmission timing adjustments	11
4.3 Timing for secondary cell activation / deactivation.....	12
5 Radio link monitoring	13
6 Link recovery procedures.....	14
7 Uplink Power control	16
7.1 Physical uplink shared channel	17
7.1.1 UE behaviour	17
7.2 Physical uplink control channel.....	24
7.2.1 UE behaviour	24
7.3 Sounding reference signals.....	29
7.3.1 UE behaviour	29
7.4 Physical random access channel.....	33
7.5 Prioritizations for transmission power reductions	33
7.6 Dual connectivity	34
7.6.1 EN-DC	34
7.6.1A NE-DC	35
7.6.2 NR-DC.....	36
7.7 Power headroom report	37
7.7.1 Type 1 PH report	38
7.7.2 Type 2 PH report	39
7.7.3 Type 3 PH report	40
8 Random access procedure	40
8.1 Random access preamble	41
8.1A PUSCH for Type-2 random access procedure.....	44
8.2 Random access response - Type-1 random access procedure	46
8.2A Random access response - Type-2 random access procedure	47
8.3 PUSCH scheduled by RAR UL grant.....	49
8.4 PDSCH with UE contention resolution identity	50
9 UE procedure for reporting control information	51
9.1 HARQ-ACK codebook determination	56
9.1.1 CBG-based HARQ-ACK codebook determination	57
9.1.2 Type-1 HARQ-ACK codebook determination	58
9.1.2.1 Type-1 HARQ-ACK codebook in physical uplink control channel.....	59
9.1.2.2 Type-1 HARQ-ACK codebook in physical uplink shared channel.....	66
9.1.3 Type-2 HARQ-ACK codebook determination	67
9.1.3.1 Type-2 HARQ-ACK codebook in physical uplink control channel.....	68
9.1.3.2 Type-2 HARQ-ACK codebook in physical uplink shared channel.....	73
9.1.3.3 Type-2 HARQ-ACK codebook grouping and HARQ-ACK retransmission.....	74
9.1.4 Type-3 HARQ-ACK codebook determination	77

9.2	UCI reporting in physical uplink control channel	80
9.2.1	PUCCH Resource Sets.....	80
9.2.2	PUCCH Formats for UCI transmission	84
9.2.3	UE procedure for reporting HARQ-ACK.....	85
9.2.4	UE procedure for reporting SR.....	88
9.2.5	UE procedure for reporting multiple UCI types	89
9.2.5.0	UE procedure for prioritization between SL HARQ-ACK information in a PUCCH and DL HARQ-ACK or SR or CSI in a PUCCH.....	94
9.2.5.1	UE procedure for multiplexing HARQ-ACK or CSI and SR in a PUCCH	94
9.2.5.2	UE procedure for multiplexing HARQ-ACK/SR/CSI in a PUCCH	96
9.2.6	PUCCH repetition procedure.....	100
9.3	UCI reporting in physical uplink shared channel	102
10	UE procedure for receiving control information.....	106
10.1	UE procedure for determining physical downlink control channel assignment	111
10.2	PDCCH validation for DL SPS and UL grant Type 2.....	123
10.2A	PDCCH validation for SL configured grant Type 2.....	125
10.3	PDCCH monitoring indication and dormancy/non-dormancy behaviour for SCells	126
10.4	Search space set group switching	128
10.5	HARQ-ACK information for PUSCH transmissions	130
11	UE-group common signalling	130
11.1	Slot configuration.....	130
11.1.1	UE procedure for determining slot format.....	135
11.2	Interrupted transmission indication	143
11.2A	Cancellation indication.....	144
11.3	Group TPC commands for PUCCH/PUSCH	145
11.4	SRS switching	146
12	Bandwidth part operation	146
13	UE procedure for monitoring Type0-PDCCH CSS sets	149
14	Integrated access-backhaul operation.....	160
15	Dual active protocol stack based handover	164
16	UE procedures for sidelink.....	165
16.1	Synchronization procedures	165
16.2	Power control	168
16.2.0	S-SS/PSBCH blocks	168
16.2.1	PSSCH.....	168
16.2.2	PSCCH.....	169
16.2.3	PSFCH.....	170
16.2.4	Prioritization of transmissions/receptions.....	171
16.2.4.1	Simultaneous NR and E-UTRA transmission/reception	171
16.2.4.2	Simultaneous PSFCH transmission/reception.....	172
16.2.4.3	Simultaneous SL and UL transmissions/receptions	172
16.2.4.3.1	Prioritizations for sidelink and uplink transmissions/receptions	172
16.3	UE procedure for reporting HARQ-ACK on sidelink	174
16.3.1	UE procedure for receiving HARQ-ACK on sidelink	175
16.4	UE procedure for transmitting PSCCH	175
16.5	UE procedure for reporting HARQ-ACK on uplink	176
16.5.1	Type-1 HARQ-ACK codebook determination	179
16.5.1.1	Type-1 HARQ-ACK codebook in physical uplink control channel.....	179
16.5.1.2	Type-1 HARQ-ACK codebook in physical uplink shared channel.....	181
16.5.2	Type-2 HARQ-ACK codebook determination	181
16.5.2.1	Type-2 HARQ-ACK codebook in physical uplink control channel.....	182
16.5.2.2	Type-2 HARQ-ACK codebook in physical uplink shared channel.....	184
16.6	UE procedure for LTE sidelink transmission.....	185
16.7	Operation for in-device coexistence	185
Annex A: Change history.....		186
History		195

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

ETSI TS 138 213 V16.14.0 (2023-07)

<https://standards.iteh.ai/catalog/standards/sist/337b586c-6a0a-4f25-af56-d86e1e8bfc9/etsi-ts-138-213-v16-14-0-2023-07>

1 Scope

The present document specifies and establishes the characteristics of the physical layer procedures for control operations in 5G-NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications"
- [2] 3GPP TS 38.201: "NR; Physical Layer – General Description"
- [3] 3GPP TS 38.202: "NR; Services provided by the physical layer"
- [4] 3GPP TS 38.211: "NR; Physical channels and modulation"
- [5] 3GPP TS 38.212: "NR; Multiplexing and channel coding"
- [6] 3GPP TS 38.214: "NR; Physical layer procedures for data"
- [7] 3GPP TS 38.215: "NR; Physical layer measurements"
- [8-1] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone"
- [8-2] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone"
- [8-3] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios"
- [8-4] 3GPP TS 38.101-4: "NR; User Equipment (UE) radio transmission and reception; Part 4: Performance requirements"
- [9] 3GPP TS 38.104: "NR; Base Station (BS) radio transmission and reception"
- [10] 3GPP TS 38.133: "NR; Requirements for support of radio resource management"
- [11] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification"
- [12] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol specification"
- [13] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures"
- [14] 3GPP TS 36.321: "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification"
- [15] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access"
- [16] 3GPP TS 38.473: "F1 application protocol (F1AP)"

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in [1, TR 21.905] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in [1, TR 21.905]. A parameter referenced in *italics* is provided by higher layers.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in [1, TR 21.905].

BPRE	Bits per resource element
BWP	Bandwidth part
CB	Code block
CBG	Code block group
CBR	Channel busy ratio
CCE	Control channel element
CORESET	Control resource set
CP	Cyclic prefix
CRC	Cyclic redundancy check
CSI	Channel state information
CSS	Common search space
DAI	Downlink assignment index
DAPS	Dual active protocol stack
DC	Dual connectivity
DCI	Downlink control information
DL	Downlink
DL-SCH	Downlink shared channel
EPRE	Energy per resource element
EN-DC	E-UTRA NR dual connectivity with MCG using E-UTRA and SCG using NR
FR1	Frequency range 1
FR2	Frequency range 2
GSCN	Global synchronization channel number
HARQ-ACK	Hybrid automatic repeat request acknowledgement
MCG	Master cell group
MCS	Modulation and coding scheme
NDI	New Data Indicator
NE-DC	E-UTRA NR dual connectivity with MCG using NR and SCG using E-UTRA
NR-DC	NR NR dual connectivity
PBCH	Physical broadcast channel
PCell	Primary cell
PDCCH	Physical downlink control channel
PDSCH	Physical downlink shared channel
PRACH	Physical random access channel
PRB	Physical resource block
PRG	Physical resource block group
PSCell	Primary secondary cell
PSBCH	Physical sidelink broadcast channel
PSCCH	Physical sidelink control channel
PSFCH	Physical sidelink feedback channel
PSS	Primary synchronization signal

PSSCH	Physical sidelink shared channel
PUCCH	Physical uplink control channel
PUCCH-SCell	PUCCH SCell
PUSCH	Physical uplink shared channel
QCL	Quasi co-location
RB	Resource block
RE	Resource element
RLM	Radio link monitoring
RRM	Radio resource management
RS	Reference signal
RSRP	Reference signal received power
SCG	Secondary cell group
SCI	Sidelink control information
SCS	Subcarrier spacing
SFCI	Sidelink feedback control information
SFN	System frame number
SL	Sidelink
SLIV	Start and length indicator value
SPS	Semi-persistent scheduling
SR	Scheduling request
SRI	SRS resource indicator
SRS	Sounding reference signal
SSS	Secondary synchronization signal
TA	Timing advance
TAG	Timing advance group
TCI	Transmission Configuration Indicator
UCI	Uplink control information
UE	User equipment
UL	Uplink
UL-SCH	Uplink shared channel
USS	UE-specific search space

ETSI TS 138 213 V16.14.0 (2023-07)

<https://standards.iteh.ai/catalog/standards/sist/337b586c-6a0a-4f25-af56-d86e1e8bfc9/etsi-ts-138-213-v16-14-0-2023-07>

4 Synchronization procedures

4.1 Cell search

Cell search is the procedure for a UE to acquire time and frequency synchronization with a cell and to detect the physical layer Cell ID of the cell.

A UE receives the following synchronization signals (SS) in order to perform cell search: the primary synchronization signal (PSS) and secondary synchronization signal (SSS) as defined in [4, TS 38.211].

A UE assumes that reception occasions of a physical broadcast channel (PBCH), PSS, and SSS are in consecutive symbols, as defined in [4, TS 38.211], and form a SS/PBCH block. The UE assumes that SSS, PBCH DM-RS, and PBCH data have same EPRE. The UE may assume that the ratio of PSS EPRE to SSS EPRE in a SS/PBCH block is either 0 dB or 3 dB. If the UE has not been provided dedicated higher layer parameters, the UE may assume that the ratio of PDCCH DMRS EPRE to SSS EPRE is within -8 dB and 8 dB when the UE monitors PDCCHs for a DCI format 1_0 with CRC scrambled by SI-RNTI, P-RNTI, or RA-RNTI.

For a half frame with SS/PBCH blocks, the first symbol indexes for candidate SS/PBCH blocks are determined according to the SCS of SS/PBCH blocks as follows, where index 0 corresponds to the first symbol of the first slot in a half-frame.

- Case A - 15 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes of $\{2, 8\} + 14 \cdot n$.
 - For operation without shared spectrum channel access:
 - For carrier frequencies smaller than or equal to 3 GHz, $n=0, 1$.
 - For carrier frequencies within FR1 larger than 3 GHz, $n=0, 1, 2, 3$.
 - For operation with shared spectrum channel access, as described in [15, TS 37.213], $n = 0, 1, 2, 3, 4$.
- Case B - 30 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{4, 8, 16, 20\} + 28 \cdot n$. For carrier frequencies smaller than or equal to 3 GHz, $n=0$. For carrier frequencies within FR1 larger than 3 GHz, $n=0, 1$.
- Case C - 30 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{2, 8\} + 14 \cdot n$.
 - For operation without shared spectrum channel access
 - For paired spectrum operation
 - For carrier frequencies smaller than or equal to 3 GHz, $n=0, 1$. For carrier frequencies within FR1 larger than 3 GHz, $n = 0, 1, 2, 3$.
 - For unpaired spectrum operation
 - For carrier frequencies smaller than 1.88 GHz, $n=0, 1$. For carrier frequencies within FR1 equal to or larger than 1.88 GHz, $n = 0, 1, 2, 3$.
 - For operation with shared spectrum channel access, $n = 0, 1, 2, 3, 4, 5, 6, 7, 8, 9$.
- Case D - 120 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{4, 8, 16, 20\} + 28 \cdot n$. For carrier frequencies within FR2, $n = 0, 1, 2, 3, 5, 6, 7, 8, 10, 11, 12, 13, 15, 16, 17, 18$.
- Case E - 240 kHz SCS: the first symbols of the candidate SS/PBCH blocks have indexes $\{8, 12, 16, 20, 32, 36, 40, 44\} + 56 \cdot n$. For carrier frequencies within FR2, $n = 0, 1, 2, 3, 5, 6, 7, 8$.

From the above cases, if the SCS of SS/PBCH blocks is not provided by *ssbSubcarrierSpacing*, the applicable cases for a cell depend on a respective frequency band, as provided in [8-1, TS 38.101-1] and [8-2, TS 38.101-2]. A same case applies for all SS/PBCH blocks on the cell. If a 30 kHz SS/PBCH block SCS is indicated by *ssbSubcarrierSpacing*,

Case B applies for frequency bands with only 15 kHz SS/PBCH block SCS as specified in [8-1, TS 38.101-1], and the case specified for 30 kHz SS/PBCH block SCS in [8-1, TS 38.101-1] applies for frequency bands with 30 kHz SS/PBCH block SCS or both 15 kHz and 30 kHz SS/PBCH block SCS as specified in [8-1, TS 38.101-1]. For a UE configured to operate with carrier aggregation over a set of cells in a frequency band of FR2 or with frequency-contiguous carrier aggregation over a set of cells in a frequency band of FR1, if the UE is provided SCS values by *ssbSubcarrierSpacing* for receptions of SS/PBCH blocks on any cells from the set of cells, the UE expects the SCS values to be same.

The candidate SS/PBCH blocks in a half frame are indexed in an ascending order in time from 0 to $\bar{L}_{max} - 1$, where \bar{L}_{max} is determined according to SS/PBCH block patterns for Cases A through E. L_{max} is a maximum number of SS/PBCH block indexes in a cell, and the maximum number of transmitted SS/PBCH blocks within a half frame is L_{max} .

- For operation without shared spectrum channel access, $L_{max} = \bar{L}_{max}$
- For operation with shared spectrum channel access, $L_{max} = 8$ for $\bar{L}_{max} = 10$ and 15 kHz SCS of SS/PBCH blocks and for $\bar{L}_{max} = 20$ and 30 kHz SCS of SS/PBCH blocks

For $\bar{L}_{max} = 4$, a UE determines the 2 LSB bits of a candidate SS/PBCH block index per half frame from a one-to-one mapping with an index of the DM-RS sequence transmitted in the PBCH as described in [4, TS 38.211].

For $\bar{L}_{max} > 4$, a UE determines the 3 LSB bits of a candidate SS/PBCH block index per half frame from a one-to-one mapping with an index of the DM-RS sequence transmitted in the PBCH as described in [4, TS 38.211]

- for $\bar{L}_{max} = 10$, the UE determines the 1 MSB bit of the candidate SS/PBCH block index from PBCH payload bit $\bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]
- for $\bar{L}_{max} = 20$, the UE determines the 2 MSB bits of the candidate SS/PBCH block index from PBCH payload bits $\bar{a}_{\bar{A}+6}$, $\bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]
- for $\bar{L}_{max} = 64$, the UE determines the 3 MSB bits of the candidate SS/PBCH block index from PBCH payload bits $\bar{a}_{\bar{A}+5}$, $\bar{a}_{\bar{A}+6}$, $\bar{a}_{\bar{A}+7}$ as described in [5, TS 38.212]

A UE can be provided per serving cell by *ssb-periodicityServingCell* a periodicity of the half frames for reception of the SS/PBCH blocks for the serving cell. If the UE is not configured a periodicity of the half frames for receptions of the SS/PBCH blocks, the UE assumes a periodicity of a half frame. A UE assumes that the periodicity is same for all SS/PBCH blocks in the serving cell.

For initial cell selection, a UE may assume that half frames with SS/PBCH blocks occur with a periodicity of 2 frames.

For operation without shared spectrum channel access, an SS/PBCH block index is same as a candidate SS/PBCH block index.

For operation with shared spectrum channel access, a UE assumes that transmission of SS/PBCH blocks in a half frame is within a discovery burst transmission window that starts from the first symbol of the first slot in a half-frame. The UE can be provided per serving cell by *discoveryBurstWindowLength* a duration of the discovery burst transmission window. If *discoveryBurstWindowLength* is not provided, the UE assumes that the duration of the discovery burst transmission window is a half frame. For a serving cell, the UE assumes that a periodicity of the discovery burst transmission window is same as a periodicity of half frames for receptions of SS/PBCH blocks in the serving cell. The UE assumes that one or more SS/PBCH blocks indicated by *ssb-PositionsInBurst* may be transmitted within the discovery burst transmission window and have candidate SS/PBCH blocks indexes corresponding to SS/PBCH block indexes provided by *ssb-PositionsInBurst*. If MSB k , $k \geq 1$, of *ssb-PositionsInBurst* is set to 1, the UE assumes that SS/PBCH block(s) within the discovery burst transmission window with candidate SS/PBCH block index(es) corresponding to SS/PBCH block index equal to $k - 1$ may be transmitted; if MSB k is set to 0, the UE assumes that the SS/PBCH block(s) are not transmitted.

For operation with shared spectrum channel access, a UE assumes that SS/PBCH blocks in a serving cell that are within a same discovery burst transmission window or across discovery burst transmission windows are quasi co-located with respect to average gain, quasi co-location 'typeA' and 'typeD' properties, when applicable [6, TS 38.214], if a value of $(N_{DM-RS}^{PBCH} \bmod N_{SSB}^{QCL})$ is same among the SS/PBCH blocks. N_{DM-RS}^{PBCH} is an index of a DM-RS sequence transmitted in a

PBCH of a corresponding SS/PBCH block, and N_{SSB}^{QCL} is either provided by *ssb-PositionQCL* or, if *ssb-PositionQCL* is not provided, obtained from a *MIB* provided by a SS/PBCH block according to Table 4.1-1 with $k_{SSB} < 24$ [4, TS 38.211]. *subCarrierSpacingCommon* indicates SCS of RMSI only for the case of operation without shared spectrum channel access. The UE can determine an SS/PBCH block index according to $(N_{DM-RS}^{PBCH} \bmod N_{SSB}^{QCL})$, or according to $(\bar{i} \bmod N_{SSB}^{QCL})$ where \bar{i} is the candidate SS/PBCH block index. The UE assumes that within a discovery burst transmission window, a number of transmitted SS/PBCH blocks on a serving cell is not larger than N_{SSB}^{QCL} and a number of transmitted SS/PBCH blocks with a same SS/PBCH block index is not larger than one.

Table 4.1-1: Mapping between the combination of *subCarrierSpacingCommon* and LSB of *ssb-SubcarrierOffset* to N_{SSB}^{QCL}

<i>subCarrierSpacingCommon</i>	LSB of <i>ssb-SubcarrierOffset</i>	N_{SSB}^{QCL}
scs15or60	0	1
scs15or60	1	2
scs30or120	0	4
scs30or120	1	8

Upon detection of a SS/PBCH block, the UE determines from *MIB* that a CORESET for Type0-PDCCH CSS set, as described in clause 13, is present if $k_{SSB} < 24$ [4, TS 38.211] for FR1 or if $k_{SSB} < 12$ for FR2. The UE determines from *MIB* that a CORESET for Type0-PDCCH CSS set is not present if $k_{SSB} > 23$ for FR1 or if $k_{SSB} > 11$ for FR2; the CORESET for Type0-PDCCH CSS set may be provided by *PDCCH-ConfigCommon*.

For a serving cell without transmission of SS/PBCH blocks, a UE acquires time and frequency synchronization with the serving cell based on receptions of SS/PBCH blocks on the PCell, or on the PSCell, or on an SCell if applicable as described in [10, TS 38.133], of the cell group for the serving cell.

4.2 Transmission timing adjustments

A UE can be provided a value $N_{TA,offset}$ of a timing advance offset for a serving cell by *n-TimingAdvanceOffset* for the serving cell. If the UE is not provided *n-TimingAdvanceOffset* for a serving cell, the UE determines a default value $N_{TA,offset}$ of the timing advance offset for the serving cell as described in [10, TS 38.133].

If a UE is configured with two UL carriers for a serving cell, a same timing advance offset value $N_{TA,offset}$ applies to both carriers.

Upon reception of a timing advance command for a TAG, the UE adjusts uplink timing for PUSCH/SRS/PUCCH transmission on all the serving cells in the TAG based on a value $N_{TA,offset}$ that the UE expects to be same for all the serving cells in the TAG and based on the received timing advance command where the uplink timing for PUSCH/SRS/PUCCH transmissions is the same for all the serving cells in the TAG.

For a band with synchronous contiguous intra-band EN-DC in a band combination with non-applicable maximum transmit timing difference requirements as described in Note 1 of Table 7.5.3-1 of [10, TS 38.133], if the UE indicates *ul-TimingAlignmentEUTRA-NR* as 'required' and uplink transmission timing based on timing adjustment indication for a TAG from MCG and a TAG from SCG are determined to be different by the UE, the UE adjusts the transmission timing for PUSCH/SRS/PUCCH transmission on all serving cells part of the band with the synchronous contiguous intra-band EN-DC based on timing adjustment indication for a TAG from a serving cell in MCG in the band. The UE is not expected to transmit a PUSCH/SRS/PUCCH in one CG when the PUSCH/SRS/PUCCH is overlapping in time, even partially, with random access preamble transmitted in another CG.

For a SCS of $2^\mu \cdot 15$ kHz, the timing advance command for a TAG indicates the change of the uplink timing relative to the current uplink timing for the TAG in multiples of $16 \cdot 64 \cdot T_c / 2^\mu$. The start timing of the random access preamble is described in [4, TS 38.211].

A timing advance command [11, TS 38.321] in case of random access response or in an absolute timing advance command MAC CE, T_A , for a TAG indicates N_{TA} values by index values of $T_A = 0, 1, 2, \dots, 3846$, where an amount

of the time alignment for the TAG with SCS of $2^\mu \cdot 15$ kHz is $N_{TA} = T_A \cdot 16 \cdot 64 / 2^\mu$. N_{TA} is defined in [4, TS 38.211] and is relative to the SCS of the first uplink transmission from the UE after the reception of the random access response or absolute timing advance command MAC CE.

In other cases, a timing advance command [11, TS 38.321], T_A , for a TAG indicates adjustment of a current N_{TA} value, N_{TA_old} , to the new N_{TA} value, N_{TA_new} , by index values of $T_A = 0, 1, 2, \dots, 63$, where for a SCS of $2^\mu \cdot 15$ kHz, $N_{TA_new} = N_{TA_old} + (T_A - 31) \cdot 16 \cdot 64 / 2^\mu$.

If a UE has multiple active UL BWPs, as described in clause 12, in a same TAG, including UL BWPs in two UL carriers of a serving cell, the timing advance command value is relative to the largest SCS of the multiple active UL BWPs. The applicable N_{TA_new} value for an UL BWP with lower SCS may be rounded to align with the timing advance granularity for the UL BWP with the lower SCS while satisfying the timing advance accuracy requirements in [10, TS 38.133].

Adjustment of an N_{TA} value by a positive or a negative amount indicates advancing or delaying the uplink transmission timing for the TAG by a corresponding amount, respectively.

For a timing advance command received on uplink slot n and for a transmission other than a PUSCH scheduled by a RAR UL grant or a fallback RAR UL grant as described in clause 8.2A or 8.3, or a PUCCH with HARQ-ACK information in response to a success RAR as described in clause 8.2A, the corresponding adjustment of the uplink transmission timing applies from the beginning of uplink slot $n+k+1$ where

$k = \left\lceil N_{slot}^{subframe, \mu} \cdot (N_{T,1} + N_{T,2} + N_{TA,max} + 0.5) / T_{sf} \right\rceil$, $N_{T,1}$ is a time duration in msec of N_1 symbols corresponding to a PDSCH processing time for UE processing capability 1 when additional PDSCH DM-RS is configured, $N_{T,2}$ is a time duration in msec of N_2 symbols corresponding to a PUSCH preparation time for UE processing capability 1 [6, TS 38.214], $N_{TA,max}$ is the maximum timing advance value in msec that can be provided by a TA command field of 12 bits, $N_{slot}^{subframe, \mu}$ is the number of slots per subframe, and T_{sf} is the subframe duration of 1 msec. N_1 and N_2 are determined with respect to the minimum SCS among the SCSs of all configured UL BWPs for all uplink carriers in the TAG and of all configured DL BWPs for the corresponding downlink carriers. For $\mu = 0$, the UE assumes $N_{1,0} = 14$ [6, TS 38.214]. Slot n and $N_{slot}^{subframe, \mu}$ are determined with respect to the minimum SCS among the SCSs of all configured UL BWPs for all uplink carriers in the TAG. $N_{TA,max}$ is determined with respect to the minimum SCS among the SCSs of all configured UL BWPs for all uplink carriers in the TAG and for all configured initial UL BWPs provided by *initialUplinkBWP*. The uplink slot n is the last slot among uplink slot(s) overlapping with the slot(s) of PDSCH reception assuming $T_{TA} = 0$, where the PDSCH provides the timing advance command and T_{TA} is defined in [4, TS 38.211].

If a UE changes an active UL BWP between a time of a timing advance command reception and a time of applying a corresponding adjustment for the uplink transmission timing, the UE determines the timing advance command value based on the SCS of the new active UL BWP. If the UE changes an active UL BWP after applying an adjustment for the uplink transmission timing, the UE assumes a same absolute timing advance command value before and after the active UL BWP change.

If the received downlink timing changes and is not compensated or is only partly compensated by the uplink timing adjustment without timing advance command as described in [10, TS 38.133], the UE changes N_{TA} accordingly.

If two adjacent slots overlap due to a TA command, the latter slot is reduced in duration relative to the former slot.

4.3 Timing for secondary cell activation / deactivation

With reference to slots for PUCCH transmissions, when a UE receives in a PDSCH an activation command [11, TS 38.321] for a secondary cell ending in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133] and no earlier than slot $n+k$, except for the following:

- the actions related to CSI reporting on a serving cell that is active in slot $n+k$
- the actions related to the *sCellDeactivationTimer* associated with the secondary cell [11, TS 38.321] that the UE applies in slot $n+k$

- the actions related to CSI reporting on a serving cell which is not active in slot $n+k$ that the UE applies in the earliest slot after $n+k$ in which the serving cell is active.

The value of k is $m + 3 N_{\text{slot}}^{\text{subframe},\mu} + 1$ where slot $n+m$ is a slot indicated for PUCCH transmission with HARQ-ACK information for the PDSCH reception as described in clause 9.2.3 and $N_{\text{slot}}^{\text{subframe},\mu}$ is a number of slots per subframe for the SCS configuration μ of the PUCCH transmission as defined in [4, TS 38.211].

With reference to slots for PUCCH transmissions, if a UE receives a deactivation command [11, TS 38.321] for a secondary cell ending in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133], except for the actions related to CSI reporting on an activated serving cell which the UE applies in slot $n+k$.

If the *sCellDeactivationTimer* associated with the secondary cell expires in slot n , the UE applies the corresponding actions in [11, TS 38.321] no later than the minimum requirement defined in [10, TS 38.133], except for the actions related to CSI reporting on an activated serving cell which the UE applies in the first slot that is after slot $n + 3 \cdot N_{\text{slot}}^{\text{subframe},\mu}$ where μ is the SCS configuration for PDSCH reception on the secondary cell.

5 Radio link monitoring

The downlink radio link quality of the primary cell is monitored by a UE for the purpose of indicating out-of-sync/in-sync status to higher layers. The UE is not required to monitor the downlink radio link quality in DL BWPs other than the active DL BWP, as described in clause 12, on the primary cell. If the active DL BWP is the initial DL BWP and for SS/PBCH block and CORESET multiplexing pattern 2 or 3, as described in clause 13, the UE is expected to perform RLM using the associated SS/PBCH block when the associated SS/PBCH block index is provided by *RadioLinkMonitoringRS*.

If the UE is configured with a SCG, as described in [12, TS 38.331], and the parameter *rlf-TimersAndConstants* is provided by higher layers and is not set to release, the downlink radio link quality of the PSCell of the SCG is monitored by the UE for the purpose of indicating out-of-sync/in-sync status to higher layers. The UE is not required to monitor the downlink radio link quality in DL BWPs other than the active DL BWP on the PSCell.

A UE can be configured for each DL BWP of a SpCell [11, TS 38.321] with a set of resource indexes, through a corresponding set of *RadioLinkMonitoringRS*, for radio link monitoring by *failureDetectionResources*. The UE is provided either a CSI-RS resource configuration index, by *csi-RS-Index*, or a SS/PBCH block index, by *ssb-Index*. The UE can be configured with up to $N_{\text{LR-RLM}}$ *RadioLinkMonitoringRS* for link recovery procedures, as described in clause 6, and for radio link monitoring. From the $N_{\text{LR-RLM}}$ *RadioLinkMonitoringRS*, up to N_{RLM} *RadioLinkMonitoringRS* can be used for radio link monitoring depending on L_{max} as described in Table 5-1, wherein L_{max} is as defined in clause 4.1, and up to two *RadioLinkMonitoringRS* can be used for link recovery procedures.

For operation with shared spectrum channel access, when a UE is provided a SS/PBCH block index by *ssb-Index*, the UE is expected to perform radio link monitoring using SS/PBCH block(s) in the discovery burst transmission window as described in clause 4.1, where the SS/PBCH block(s) have candidate SS/PBCH block index(es) corresponding to SS/PBCH block index provided by *ssb-Index*.

If the UE is not provided *RadioLinkMonitoringRS* and the UE is provided for PDCCH receptions TCI states that include one or more of a CSI-RS

- the UE uses for radio link monitoring the RS provided for the active TCI state for PDCCH reception if the active TCI state for PDCCH reception includes only one RS
- if the active TCI state for PDCCH reception includes two RS, the UE expects that one RS is configured with *qcl-Type* set to 'typeD' [6, TS 38.214] and the UE uses the RS configured with *qcl-Type* set to 'typeD' for radio link monitoring; the UE does not expect both RS to be configured with *qcl-Type* set to 'typeD'
- the UE is not required to use for radio link monitoring an aperiodic or semi-persistent RS
- For $L_{\text{max}} = 4$, the UE selects the N_{RLM} RS provided for active TCI states for PDCCH receptions in CORESETs associated with the search space sets in an order from the shortest monitoring periodicity. If more than one

CORESETs are associated with search space sets having same monitoring periodicity, the UE determines the order of the CORESET from the highest CORESET index as described in clause 10.1.

A UE does not expect to use more than N_{RLM} *RadioLinkMonitoringRS* for radio link monitoring when the UE is not provided *RadioLinkMonitoringRS*.

Values of $N_{\text{LR-RLM}}$ and N_{RLM} for different values of L_{max} are given in Table 5-1.

Table 5-1: $N_{\text{LR-RLM}}$ and N_{RLM} as a function of maximum number L_{max} of SS/PBCH blocks per half frame

L_{max}	$N_{\text{LR-RLM}}$	N_{RLM}
4	2	2
8	6	4
64	8	8

For a CSI-RS resource configuration, *powerControlOffsetSS* is not applicable and a UE expects to be provided only 'noCDM' from *cdm-Type*, only 'one' and 'three' from *density*, and only '1 port' from *nrofPorts* [6, TS 38.214].

If a UE is configured with multiple DL BWPs for a serving cell, the UE performs RLM using the RS(s) corresponding to resource indexes provided by *RadioLinkMonitoringRS* for the active DL BWP or, if *RadioLinkMonitoringRS* is not provided for the active DL BWP, using the RS(s) provided for the active TCI state for PDCCH receptions in CORESETs on the active DL BWP.

In non-DRX mode operation, the physical layer in the UE assesses once per indication period the radio link quality, evaluated over the previous time period defined in [10, TS 38.133] against thresholds (Q_{out} and Q_{in}) configured by *rlmInSyncOutOfSyncThreshold*. The UE determines the indication period as the maximum between the shortest periodicity for radio link monitoring resources and 10 msec.

In DRX mode operation, the physical layer in the UE assesses once per indication period the radio link quality, evaluated over the previous time period defined in [10, TS 38.133], against thresholds (Q_{out} and Q_{in}) provided by *rlmInSyncOutOfSyncThreshold*. The UE determines the indication period as the maximum between the shortest periodicity for radio link monitoring resources and the DRX period.

The physical layer in the UE indicates, in frames where the radio link quality is assessed, out-of-sync to higher layers when the radio link quality is worse than the threshold Q_{out} for all resources in the set of resources for radio link monitoring. When the radio link quality is better than the threshold Q_{in} for any resource in the set of resources for radio link monitoring, the physical layer in the UE indicates, in frames where the radio link quality is assessed, in-sync to higher layers.

6 Link recovery procedures

A UE can be provided, for each BWP of a serving cell, a set \bar{q}_0 of periodic CSI-RS resource configuration indexes by *failureDetectionResourcesToAddModList* and a set \bar{q}_1 of periodic CSI-RS resource configuration indexes and/or SS/PBCH block indexes by *candidateBeamRSList* or *candidateBeamRSListExt* or *candidateBeamRSSCellList* for radio link quality measurements on the BWP of the serving cell. If the UE is not provided \bar{q}_0 by *failureDetectionResourcesToAddModList* for a BWP of the serving cell, the UE determines the set \bar{q}_0 to include periodic CSI-RS resource configuration indexes with same values as the RS indexes in the RS sets indicated by *TCI-State* for respective CORESETs that the UE uses for monitoring PDCCH and, if there are two RS indexes in a TCI state, the set \bar{q}_0 includes RS indexes configured with *qcl-Type* set to 'typeD' for the corresponding TCI states. The UE expects the set \bar{q}_0 to include up to two RS indexes. The UE expects single port RS in the set \bar{q}_0 . The UE expects single-port or two-port CSI-RS with frequency density equal to 1 or 3 REs per RB in the set \bar{q}_1 .

The thresholds $Q_{\text{out,LR}}$ and $Q_{\text{in,LR}}$ correspond to the default value of *rlmInSyncOutOfSyncThreshold*, as described in [10, TS 38.133] for Q_{out} , and to the value provided by *rsrp-ThresholdSSB* or *rsrp-ThresholdBFR*, respectively.