

ETSI TS 138 321 V18.1.0 (2024-05)



**5G;
NR;
Medium Access Control (MAC) protocol specification
(3GPP TS 38.321 version 18.1.0 Release 18)**

[ETSI TS 138 321 V18.1.0 \(2024-05\)](https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05)

<https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05>



ReferenceRTS/TSGR-0238321v10

Keywords5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<https://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2024.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables. (2024-05)

The cross reference between 3GPP and ETSI identities can be found under <https://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	9
1 Scope	10
2 References	10
3 Definitions, symbols and abbreviations	11
3.1 Definitions	11
3.2 Abbreviations	13
4 General	15
4.1 Introduction	15
4.2 MAC architecture	15
4.2.1 General.....	15
4.2.2 MAC Entities	15
4.3 Services	17
4.3.1 Services provided to upper layers.....	17
4.3.2 Services expected from physical layer.....	17
4.4 Functions	17
4.5 Channel structure.....	18
4.5.1 General.....	18
4.5.2 Transport Channels	18
4.5.3 Logical Channels	18
4.5.4 Mapping of Transport Channels to Logical Channels	19
4.5.4.1 General	19
4.5.4.2 Uplink mapping.....	19
4.5.4.3 Downlink mapping.....	19
4.5.4.4 Sidelink mapping	19
5 MAC procedures	20
5.1 Random Access procedure	20
5.1.1 Random Access procedure initialization.....	20
5.1.1a Initialization of variables specific to Random Access type	25
5.1.1b Selection of the set of Random Access resources for the Random Access procedure.....	28
5.1.1c Availability of the set of Random Access resources.....	31
5.1.1d Selection of the set of Random Access resources based on feature prioritization	32
5.1.1e Selection of Msg1 repetition for SI request	32
5.1.2 Random Access Resource selection.....	32
5.1.2a Random Access Resource selection for 2-step RA type	36
5.1.3 Random Access Preamble transmission	37
5.1.3a MSGA transmission.....	39
5.1.4 Random Access Response reception.....	40
5.1.4a MSGB reception and contention resolution for 2-step RA type	44
5.1.5 Contention Resolution	47
5.1.6 Completion of the Random Access procedure.....	50
5.2 Maintenance of Uplink Time Alignment.....	50
5.2a Maintenance of UL Synchronization.....	54
5.3 DL-SCH data transfer.....	55
5.3.1 DL Assignment reception	55
5.3.2 HARQ operation.....	57
5.3.2.1 HARQ Entity.....	57
5.3.2.2 HARQ process	57
5.3.3 Disassembly and demultiplexing	59
5.4 UL-SCH data transfer.....	59
5.4.1 UL Grant reception	59

5.4.2	HARQ operation.....	65
5.4.2.1	HARQ Entity.....	65
5.4.2.2	HARQ process	69
5.4.3	Multiplexing and assembly.....	71
5.4.3.1	Logical Channel Prioritization	71
5.4.3.1.1	General	71
5.4.3.1.2	Selection of logical channels	71
5.4.3.1.3	Allocation of resources.....	72
5.4.3.2	Multiplexing of MAC Control Elements and MAC SDUs	74
5.4.4	Scheduling Request.....	74
5.4.5	Buffer Status Reporting	79
5.4.6	Power Headroom Reporting	82
5.4.7	Pre-emptive Buffer Status Reporting.....	88
5.4.8	Timing Advance Reporting	88
5.4.9	Delay status reporting	89
5.5	PCH reception	90
5.6	BCH reception.....	90
5.7	Discontinuous Reception (DRX).....	90
5.7a	Discontinuous Reception (DRX) for MBS Broadcast.....	98
5.7b	Discontinuous Reception (DRX) for MBS Multicast.....	99
5.8	Transmission and reception without dynamic scheduling.....	101
5.8.1	Downlink	101
5.8.1a	Downlink for Multicast.....	102
5.8.2	Uplink	102
5.8.3	Sidelink.....	107
5.9	Activation/Deactivation of SCells.....	109
5.10	Activation/Deactivation of PDCP duplication.....	111
5.11	MAC reconfiguration	112
5.12	MAC Reset.....	112
5.12a	Void.....	114
5.13	Handling of unknown, unforeseen and erroneous protocol data	114
5.14	Handling of measurement gaps	114
5.15	Bandwidth Part (BWP) operation.....	115
5.15.1	Downlink and Uplink.....	115
5.15.2	Sidelink.....	119
5.16	SUL operation	121
5.17	Beam Failure Detection and Recovery procedure.....	121
5.18	Handling of MAC CEs	125
5.18.1	General.....	125
5.18.2	Activation/Deactivation of Semi-persistent CSI-RS/CSI-IM resource set	126
5.18.3	Aperiodic CSI Trigger State Subselection	126
5.18.4	Activation/Deactivation of UE-specific PDSCH TCI state	126
5.18.5	Indication of TCI state for UE-specific PDCCH	127
5.18.6	Activation/Deactivation of Semi-persistent CSI reporting on PUCCH	127
5.18.7	Activation/Deactivation of Semi-persistent SRS and Indication of spatial relation of SP/AP SRS	127
5.18.8	Activation/Deactivation of spatial relation of PUCCH resource	128
5.18.9	Activation/Deactivation of semi-persistent ZP CSI-RS resource set.....	128
5.18.10	Recommended Bit Rate	129
5.18.11	Void	129
5.18.12	Void	129
5.18.13	Void	129
5.18.14	Update of Pathloss Reference RS of SRS.....	129
5.18.15	Update of Pathloss Reference RS of PUSCH	129
5.18.16	Indication of spatial relation of SRS resource for a Serving Cell set.....	130
5.18.17	Activation/Deactivation of Semi-Persistent Positioning SRS.....	130
5.18.18	Timing offset adjustments for IAB.....	130
5.18.19	Guard symbols for IAB.....	130
5.18.20	Positioning Measurement Gap Activation/Deactivation Command	131
5.18.21	PPW Activation/Deactivation Command	132
5.18.22	Update of PUCCH Power Control Set for multiple TRP PUCCH repetition	132
5.18.23	Unified TCI States Activation/Deactivation MAC CE	132
5.18.24	Update of Differential Koffset.....	133

5.18.25	BFD-RS Indication MAC CE	133
5.18.26	Restricted and recommended beam indication for IAB	133
5.18.27	DL TX power adjustment for IAB	133
5.18.28	UL PSD range adjustment for IAB	134
5.18.29	Timing case indication for IAB	134
5.18.30	Case-6 Timing Request	135
5.18.31	Backhaul Link Beam Indication for NCR	135
5.18.32	Access Link Beam Indication for NCR	135
5.18.33	Enhanced Unified TCI States Activation/Deactivation MAC CE	135
5.18.34	Activation/deactivation of PSI-based SDU discard	136
5.18.35	LTM Cell Switch Command	136
5.18.36	Candidate Cell TCI States Activation/Deactivation	136
5.19	Data inactivity monitoring	137
5.20	Void	137
5.21	LBT operation	137
5.21.1	General	137
5.21.2	LBT failure detection and recovery procedure	137
5.22	SL-SCH Data transfer and SL-PRS transmission	139
5.22.1	SL-SCH Data and SL-PRS transmission	139
5.22.1.1	SL Grant reception and SCI transmission	139
5.22.1.2	TX resource (re-)selection check	158
5.22.1.2a	Re-evaluation and Pre-emption	159
5.22.1.2b	Re-selection for using a received resource conflict indication	160
5.22.1.2c	Resource re-selection from SL LBT Failure indication	161
5.22.1.3	Sidelink HARQ operation and SL-PRS transmission	161
5.22.1.3.1	Sidelink HARQ Entity	161
5.22.1.3.1a	Sidelink process not associated with SL-PRS dedicated resource pool	164
5.22.1.3.2	PSFCH reception	166
5.22.1.3.3	HARQ-based Sidelink RLF detection	167
5.22.1.4	Multiplexing and assembly	169
5.22.1.4.0	General	169
5.22.1.4.1	Logical channel prioritization	169
5.22.1.4.1.1	General	169
5.22.1.4.1.2	Selection of logical channels and SL-PRS	170
5.22.1.4.1.3	Allocation of sidelink resources	173
5.22.1.4.2	Multiplexing of MAC Control Elements and MAC SDUs	174
5.22.1.5	Scheduling Request	174
5.22.1.6	Buffer Status Reporting	175
5.22.1.7	CSI Reporting	177
5.22.1.8	Void	178
5.22.1.9	IUC-Request transmission	178
5.22.1.10	IUC-Information Reporting	178
5.22.1.10.1	General	178
5.22.1.10.2	Reception of IUC-Information Reporting	179
5.22.1.11	TX carrier (re-)selection	179
5.22.1.12	SL-PRS Resource Request	180
5.22.2	SL-SCH Data and SL-PRS reception	181
5.22.2.1	SCI reception	181
5.22.2.2	Sidelink HARQ operation and SL-PRS reception on SL-PRS shared resource pool	182
5.22.2.2.1	Sidelink HARQ Entity	182
5.22.2.2.2	Sidelink process	182
5.22.2.3	Disassembly and demultiplexing	184
5.22.2.4	SL-PRS reception on SL-PRS dedicated resource pool	184
5.23	SL-BCH data transfer	185
5.23.1	SL-BCH data transmission	185
5.23.2	SL-BCH data reception	185
5.24	Handling of PRS Processing Window	185
5.25	Positioning Measurement Gap Activation/Deactivation Request	185
5.26	Positioning SRS transmission in RRC_INACTIVE	186
5.26.1	General	186
5.26.2	TA validation for SRS transmission in RRC_INACTIVE	186
5.27	Small Data Transmission	187

5.27.1	General.....	187
5.27.2	TA Validation for CG-SDT	189
5.28	Sidelink Discontinuous Reception (DRX)	189
5.28.1	General.....	189
5.28.2	Behaviour of UE receiving SL-SCH Data	190
5.28.3	Behaviour of UE transmitting SL-SCH Data.....	193
5.29	Activation/Deactivation of SCG.....	194
5.30	Handling of FR2 UL gap.....	195
5.31	Sidelink LBT operation	195
5.31.1	General.....	195
5.31.2	Sidelink LBT failure detection and recovery procedure	196
5.32	SRS for positioning Tx frequency hopping.....	197
5.33	RACH-less initial UL transmission.....	197
5.34	Cell-Level Energy Saving	198
5.34.1	General.....	198
5.34.2	Cell Discontinuous Transmission	198
5.34.3	Cell Discontinuous Reception.....	199
6	Protocol Data Units, formats and parameters.....	200
6.1	Protocol Data Units	200
6.1.1	General.....	200
6.1.2	MAC PDU (DL-SCH and UL-SCH except transparent MAC and Random Access Response).....	200
6.1.3	MAC Control Elements (CEs).....	203
6.1.3.1	Buffer Status Report MAC CEs	203
6.1.3.2	C-RNTI MAC CE	212
6.1.3.3	UE Contention Resolution Identity MAC CE	212
6.1.3.4	Timing Advance Command MAC CE	212
6.1.3.4a	Absolute Timing Advance Command MAC CE.....	213
6.1.3.5	DRX Command MAC CE	213
6.1.3.6	Long DRX Command MAC CE	213
6.1.3.7	Configured Grant Confirmation MAC CE.....	213
6.1.3.8	Single Entry PHR MAC CE.....	213
6.1.3.9	Multiple Entry PHR MAC CE	215
6.1.3.10	SCell Activation/Deactivation MAC CEs	218
6.1.3.11	Duplication Activation/Deactivation MAC CE.....	219
6.1.3.12	SP CSI-RS/CSI-IM Resource Set Activation/Deactivation MAC CE	219
6.1.3.13	Aperiodic CSI Trigger State Subselection MAC CE	220
6.1.3.14	TCI States Activation/Deactivation for UE-specific PDSCH MAC CE	221
6.1.3.15	TCI State Indication for UE-specific PDCCH MAC CE	222
6.1.3.16	SP CSI reporting on PUCCH Activation/Deactivation MAC CE	222
6.1.3.17	SP SRS Activation/Deactivation MAC CE.....	223
6.1.3.18	PUCCH spatial relation Activation/Deactivation MAC CE.....	224
6.1.3.19	SP ZP CSI-RS Resource Set Activation/Deactivation MAC CE	225
6.1.3.20	Recommended bit rate MAC CE	225
6.1.3.21	Timing Delta MAC CE	226
6.1.3.22	Guard Symbols MAC CEs	227
6.1.3.23	BFR MAC CEs	228
6.1.3.24	Enhanced TCI States Activation/Deactivation for UE-specific PDSCH MAC CE	229
6.1.3.25	Enhanced PUCCH Spatial Relation Activation/Deactivation MAC CE	230
6.1.3.26	Enhanced SP/AP SRS Spatial Relation Indication MAC CE.....	231
6.1.3.27	SRS Pathloss Reference RS Update MAC CE.....	232
6.1.3.28	PUSCH Pathloss Reference RS Update MAC CE	233
6.1.3.29	Serving Cell Set based SRS Spatial Relation Indication MAC CE.....	233
6.1.3.30	LBT failure MAC CEs	235
6.1.3.31	Multiple Entry Configured Grant Confirmation MAC CE	236
6.1.3.32	Duplication RLC Activation/Deactivation MAC CE.....	236
6.1.3.33	Sidelink Buffer Status Report MAC CEs.....	236
6.1.3.34	Sidelink Configured Grant Confirmation MAC CE.....	237
6.1.3.35	Sidelink CSI Reporting MAC CE	238
6.1.3.36	SP Positioning SRS Activation/Deactivation MAC CE.....	238
6.1.3.37	Guard Symbols MAC CEs for Case-6 and Case-7 timing modes	241
6.1.3.38	Case-7 Timing advance offset MAC CE.....	242

6.1.3.39	Case-6 Timing Request MAC CE	242
6.1.3.40	Positioning Measurement Gap Activation/Deactivation Request MAC CE	242
6.1.3.41	Positioning Measurement Gap Activation/Deactivation Command MAC CE	243
6.1.3.42	PPW Activation/Deactivation Command MAC CE.....	243
6.1.3.43	Enhanced BFR MAC CEs.....	244
6.1.3.44	Enhanced TCI States Indication for UE-specific PDCCH MAC CE	247
6.1.3.45	PUCCH spatial relation Activation/Deactivation for multiple TRP PUCCH repetition MAC CE	248
6.1.3.46	PUCCH Power Control Set Update for multiple TRP PUCCH repetition MAC CE	249
6.1.3.47	Unified TCI States Activation/Deactivation MAC CE	250
6.1.3.48	Enhanced Single Entry PHR MAC CE	251
6.1.3.49	Enhanced Multiple Entry PHR MAC CE.....	252
6.1.3.50	Enhanced Single Entry PHR for multiple TRP MAC CE	257
6.1.3.51	Enhanced Multiple Entry PHR for multiple TRP MAC CE	257
6.1.3.52	Sidelink DRX Command MAC CE	260
6.1.3.53	Inter-UE Coordination Information MAC CE	260
6.1.3.54	Inter-UE Coordination Request MAC CE.....	263
6.1.3.55	Enhanced SCell Activation/Deactivation MAC CEs	265
6.1.3.56	Timing Advance Report MAC CE.....	266
6.1.3.57	Differential Koffset MAC CE	266
6.1.3.58	BFD-RS Indication MAC CE	266
6.1.3.59	SP/AP SRS TCI State Indication MAC CE	267
6.1.3.60	Serving Cell Set based SRS TCI State Indication MAC CE.....	268
6.1.3.61	Child IAB-DU Restricted Beam Indication MAC CE	269
6.1.3.62	IAB-MT Recommended Beam Indication MAC CE	273
6.1.3.63	DL TX Power Adjustment and Desired DL TX Power Adjustment MAC CEs	276
6.1.3.64	Desired IAB-MT PSD range MAC CE.....	277
6.1.3.65	Timing Case Indication MAC CE	279
6.1.3.66	NCR Downlink Backhaul Link Beam Indication MAC CE.....	280
6.1.3.67	NCR Uplink Backhaul Link Beam Indication MAC CE	280
6.1.3.68	NCR Access Link Beam Indication MAC CE	281
6.1.3.69	SL LBT failure MAC CEs	281
6.1.3.70	Enhanced Unified TCI States Activation/Deactivation MAC CE for Joint TCI States	281
6.1.3.71	Enhanced Unified TCI States Activation/Deactivation MAC CE for Separate TCI States.....	282
6.1.3.72	Delay Status Report MAC CE	283
6.1.3.73	PSI-Based SDU Discard Activation/Deactivation MAC CE	284
6.1.3.74	SL-PRS Resource Request MAC CE	285
6.1.3.75	LTM Cell Switch Command MAC CE.....	285
6.1.3.76	Candidate Cell TCI States Activation/Deactivation MAC CE.....	287
6.1.3.77	Cross-RRH TCI State Indication for UE-specific PDCCH MAC CE.....	288
6.1.3.78	Single Entry PHR with assumed PUSCH MAC CE	289
6.1.3.79	Multiple Entry PHR with assumed PUSCH MAC CE.....	290
6.1.3.80	Enhanced SP CSI reporting on PUCCH Activation/Deactivation MAC CE	293
6.1.3.81	Enhanced Single Entry PHR for multiple TRP STx2P MAC CE	294
6.1.3.82	Enhanced Multiple Entry PHR for multiple TRP STx2P MAC CE.....	295
6.1.4	MAC PDU (transparent MAC).....	298
6.1.5	MAC PDU (Random Access Response).....	299
6.1.5a	MAC PDU (MSGB)	299
6.1.6	MAC PDU (SL-SCH).....	301
6.2	Formats and parameters.....	302
6.2.1	MAC subheader for DL-SCH and UL-SCH	302
6.2.2	MAC subheader for Random Access Response.....	307
6.2.2a	MAC subheader for MSGB	307
6.2.3	MAC payload for Random Access Response	308
6.2.3a	MAC payload for MSGB.....	309
6.2.4	MAC subheader for SL-SCH.....	311
7	Variables and constants.....	312
7.1	RNTI values	312
7.2	Backoff Parameter values.....	315
7.3	DELTA_PREAMBLE values	315
7.4	PRACH Mask Index values.....	316

Annex A (informative):

Change history

History

317

324

iTeh Standards

(<https://standards.iteh.ai>)

Document Preview

[ETSI TS 138 321 V18.1.0 \(2024-05\)](https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05)

<https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[ETSI TS 138 321 V18.1.0 \(2024-05\)](https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05)

<https://standards.iteh.ai/catalog/standards/etsi/bb4f4a8f-e6ec-4580-b333-93e3b34e99e9/etsi-ts-138-321-v18-1-0-2024-05>

1 Scope

The present document specifies the NR MAC protocol.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.300: "NR; Overall description; Stage 2".
- [3] 3GPP TS 38.322: "NR; Radio Link Control (RLC) protocol specification".
- [4] 3GPP TS 38.323: "NR; Packet Data Convergence Protocol (PDCP) protocol specification".
- [5] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol specification".
- [6] 3GPP TS 38.213: "NR; Physical Layer Procedures for control".
- [7] 3GPP TS 38.214: "NR; Physical Layer Procedures for data".
- [8] 3GPP TS 38.211: "NR; Physical channels and modulation".
- [9] 3GPP TS 38.212: "NR; Multiplexing and channel coding".
- [10] Void.
- [11] 3GPP TS 38.133: "NR; Requirements for support of radio resource management".
- [12] 3GPP TS 36.133: "Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management".
- [13] 3GPP TS 26.114: "Technical Specification Group Services and System Aspects; IP Multimedia Subsystem (IMS); Multimedia Telephony; Media handling and interaction".
- [14] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone".
- [15] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone".
- [16] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios".
- [17] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Layer Procedures".
- [18] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access".
- [19] 3GPP TS 23.287: "Architecture enhancements for 5G System (5GS) to support Vehicle-to-Everything (V2X) services".
- [20] 3GPP TS 23.285: "Architecture enhancements for V2X services".

- [21] 3GPP TS 36.331: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification".
- [22] 3GPP TS 36.321: "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC); Protocol specification".
- [23] 3GPP TS 37.355: "Evolved Universal Terrestrial Radio Access (E-UTRA); LTE Positioning Protocol (LPP)".
- [24] 3GPP TS 38.215: "NR; Physical layer measurements".
- [25] 3GPP TS 38.306: "NR; User Equipment (UE) radio access capabilities".
- [26] 3GPP TS 23.304: "Proximity based Services (ProSe) in the 5G System (5GS)".
- [27] 3GPP TS 38.473: "NG-RAN; F1 Application Protocol (F1AP)".
- [28] 3GPP TS 24.587: "Technical Specification Group Core Network and Terminals; Vehicle-to-Everything (V2X) services in 5G System (5GS)".
- [29] 3GPP TS 24.554: "Technical Specification Group Core Network and Terminals; Proximity-services (ProSe) in 5G System (5GS) protocol".
- [30] 3GPP TS 23.586: "Technical Specification Group Services and System Aspects; Architectural Enhancements to support Ranging based services and Sidelink Positioning".
- [31] 3GPP TS 23.256: "Support of Uncrewed Aerial Systems (UAS) connectivity, identification and tracking; Stage 2".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

A2X communication: A communication to support A2X services leveraging PC5 reference points, as defined in TS 23.256 [31]. A2X services are realized by various types of A2X applications, e.g., BRID or DAA.

Air to Ground network: An NG-RAN consisting of ground-based gNBs, which provide cell towers that send signals up to an aircraft's antenna(s) of onboard ATG terminal, with typical vertical altitude of around 10,000 m and take-off/landing altitudes down to 3000 m.

BWP for SRS for positioning Tx frequency hopping: For SRS for positioning Tx frequency hopping, separate BWP configuration outside BWP configuration for data transmission.

Dormant BWP: The dormant BWP is one of downlink BWPs configured by the network via dedicated RRC signaling. In the dormant BWP, the UE stop monitoring PDCCH on/for the SCell, but continues performing CSI measurements, Automatic Gain Control (AGC) and beam management, if configured.

DRX group: A group of Serving Cells that is configured by RRC and that have the same DRX Active Time.

eRedCap UE: A UE with enhanced reduced capabilities as specified in clause 4.2.22.1 of TS 38.306 [25].

HARQ information: HARQ information for DL-SCH, for UL-SCH, or for SL-SCH transmissions consists of New Data Indicator (NDI), Transport Block Size (TBS), Redundancy Version (RV), and HARQ process ID.

IAB-donor: gNB that provides network access to UEs via a network of backhaul and access links.

IAB-node: RAN node that supports NR access links to UEs and NR backhaul links to parent nodes and child nodes.

Listen Before Talk: A procedure according to which transmissions are not performed if the channel is identified as being occupied, see TS 37.213 [18].

LTM candidate cell: A candidate cell configured for LTM as defined in TS 38.331 [5].

Msg3: Message transmitted on UL-SCH containing a C-RNTI MAC CE or CCCH SDU, submitted from upper layer and associated with the UE Contention Resolution Identity, as part of a Random Access procedure.

Multi-path: Mode of operation of a UE in RRC_CONNECTED configured with one direct path on which the UE connects to gNB using NR Uu, and one indirect path on which the UE connects to the same gNB via another UE using PC5 unicast link or non-3GPP connection (N3C).

Multi-PUSCH configured grant: A configured grant configuration that includes multiple consecutive configured uplink grants within a single periodicity.

N3C indirect path: In Multi-path, the indirect path using Non-3GPP Connection between remote UE and relay UE.

NCR-Fwd: NCR-node function, which performs amplifying-and-forwarding of UL/DL RF signals between gNB and UE. The behavior of the NCR-Fwd is controlled according to the side control information received by the NCR-MT from a gNB.

NCR-MT: NCR-node entity which communicates with a gNB via a control link to receive side control information. The control link is based on NR Uu interface.

NCR-node: RAN node comprising NCR-MT and NCR-Fwd.

Non-terrestrial network: An NG-RAN consisting of gNBs, which provide non-terrestrial NR access to UEs by means of an NTN payload embarked on an airborne or space-borne NTN vehicle and an NTN Gateway.

NR backhaul link: NR link used for backhauling between an IAB-node and an IAB-donor, and between IAB-nodes in case of a multi-hop backhauling.

NR sidelink communication: AS functionality enabling at least V2X Communication as defined in TS 23.287 [19] and ProSe communication (including ProSe non-Relay, UE-to-Network Relay and UE-to-UE Relay communication (including ProSe UE-to-UE Relay communication with integrated discovery)) as defined in TS 23.304 [26], between two or more nearby UEs, using NR technology but not traversing any network node.

NR sidelink discovery: AS functionality enabling ProSe non-Relay discovery, ProSe UE-to-Network Relay discovery and ProSe UE-to-UE Relay discovery for Proximity based Services as defined in TS 23.304 [26], between two or more nearby UEs, using NR technology but not traversing any network node.

NR sidelink transmission: Any NR Sidelink-based transmission, including transmission for NR sidelink discovery, transmission for NR sidelink communication, transmission for Ranging/Sidelink Positioning, and transmission for A2X communication.

PDCCH occasion: A time duration (i.e. one or a consecutive number of symbols) during which the MAC entity is configured to monitor the PDCCH.

Positioning SRS Bandwidth Aggregation: Transmission of positioning SRS on multiple carriers in RRC_CONNECTED and RRC_INACTIVE where the positioning SRS resources are linked in RRC configuration as defined in TS 38.331 [5].

PRS Processing Window: A time window during which UE may perform PRS measurement inside the active DL BWP with the same numerology as the active DL BWP without measurement gap.

Ranging/Sidelink Positioning: AS functionality enabling ranging-based services and sidelink positioning as specified in TS 23.586 [30].

RB set: A RB set refers to a contiguous set of resource blocks (RBs) on which a channel access procedure is performed in shared spectrum as defined in TS 37.213 [18].

RedCap UE: A UE with reduced capabilities as specified in clause 4.2.21.1 in TS 38.306 [25].

Serving Cell: A PCell, a PSCell, or an SCell in TS 38.331 [5].

Sidelink transmission information: Sidelink transmission information included in an SCI for an SL-SCH transmission or SL-PRS transmission with or without SL-SCH transmission on SL-PRS shared resource pool as specified in clause 8.3 and 8.4 of TS 38.212 [9] consists of Sidelink HARQ information including NDI, RV, Sidelink process ID, HARQ feedback enabled/disabled indicator, Sidelink identification information including cast type indicator, Source Layer-1

ID and Destination Layer-1 ID, and Sidelink other information including CSI request, SL-PRS request, SL-PRS resource ID, a priority, a communication range requirement and Zone ID.

SL-PRS delay budget: Delay budget before which the SL-PRS is expected to be transmitted by the Tx UE.

SL-PRS dedicated resource pool: A sidelink resource pool which can be used for the transmission of SL-PRS and cannot be used for the transmission of PSSCH.

SL-PRS shared resource pool: A sidelink resource pool which can be used for the transmission of both SL-PRS and PSSCH.

SL-PRS transmission information on SL-PRS dedicated resource pool: SL-PRS transmission information on SL-PRS dedicated resource pool is included in an SCI for an SL-PRS transmission on SL-PRS dedicated resource pool, as specified in TS 38.212 [9], consisting of

- SL-PRS identification information, including cast type indicator, source ID and destination ID;
- SL-PRS transmission other information, including SL-PRS priority, SL-PRS request, SL-PRS resource ID and resource reservation period.

SRS for positioning Tx frequency hopping: Transmit frequency hopping of positioning SRS in RRC_INACTIVE and RRC_CONNECTED.

SRS positioning validity area: An area consisting of a list of cells within which the corresponding positioning SRS configuration is considered as valid.

Special Cell: For Dual Connectivity operation the term Special Cell refers to the PCell of the MCG or the PSCell of the SCG depending on if the MAC entity is associated to the MCG or the SCG, respectively. Otherwise the term Special Cell refers to the PCell. A Special Cell supports PUCCH transmission and contention-based Random Access, and is always activated.

Timing Advance Group: A group of Serving Cells that is configured by RRC and that, for the cells with a UL configured, using the same timing reference cell and the same Timing Advance value. A Timing Advance Group containing the SpCell of a MAC entity is referred to as Primary Timing Advance Group (PTAG), whereas the term Secondary Timing Advance Group (STAG) refers to other TAGs.

UE-gNB RTT: For non-terrestrial networks, the sum of the UE's Timing Advance value (see TS 38.211 [8] clause 4.3.1) and *kmac*.

V2X sidelink communication: AS functionality enabling V2X Communication as defined in TS 23.285 [20], between nearby UEs, using E-UTRA technology but not traversing any network node.

NOTE 1: A timer is running once it is started, until it is stopped or until it expires; otherwise it is not running. A timer can be started if it is not running or restarted if it is running. A Timer is always started or restarted from its initial value. The duration of a timer is not updated until it is stopped or expires (e.g. due to BWP switching). When the MAC entity applies zero value for a timer, the timer shall be started and immediately expire unless explicitly stated otherwise.

NOTE 2: In this version of the specification, the SRS in the procedural description includes Positioning SRS except for the Positioning SRS for transmission in RRC_INACTIVE as in clause 5.26. Positioning SRS except for the Positioning SRS for transmission in RRC_INACTIVE is treated the same as SRS by the UE unless explicitly stated otherwise.

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

A2X	Aircraft-to-Everything
AP	Aperiodic
BFR	Beam Failure Recovery
BRID	Broadcast Remote Identification
BSR	Buffer Status Report