

ETSI TS 138 211 V18.5.0 (2025-01)



**5G;
NR;
Physical channels and modulation
(3GPP TS 38.211 version 18.5.0 Release 18)**

ETSI TS 138 211 V18.5.0 (2025-01)

<https://standards.iteh.ai/catalog/standards/etsi/d9f7d06f-f6f0-40f3-8ef7-cb0ef6805e37/etsi-ts-138-211-v18-5-0-2025-01>



Reference

RTS/TSGR-0138211v150

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
[ETSI Search & Browse Standards application](#).

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver repository](#).

Users should be aware that the present document may be revised or have its status changed,
this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to
the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our
[Coordinated Vulnerability Disclosure \(CVD\)](#) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2025.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables. (2025-01)

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](https://standards.iteh.ai/catalog/standards/etsi/d9f7d06f-f6f0-40f3-8ef7-cb0ef6805e37/etsi-ts-138-211-v18-5-0-2025-01).

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	8
1 Scope	9
2 References	9
3 Definitions of terms, symbols and abbreviations	9
3.1 Terms.....	9
3.2 Symbols.....	9
3.3 Abbreviations	11
4 Frame structure and physical resources.....	12
4.1 General	12
4.2 Numerologies	12
4.3 Frame structure.....	12
4.3.1 Frames and subframes	12
4.3.2 Slots	13
4.4 Physical resources	14
4.4.1 Antenna ports.....	14
4.4.2 Resource grid.....	14
4.4.3 Resource elements	15
4.4.4 Resource blocks	15
4.4.4.1 General	15
4.4.4.2 Point A	15
4.4.4.3 Common resource blocks	15
4.4.4.4 Physical resource blocks	15
4.4.4.5 Virtual resource blocks	16
4.4.4.6 Interlaced resource blocks.....	16
4.4.5 Bandwidth part.....	16
4.4.6 Common MBS frequency resource.....	16
4.5 Carrier aggregation.....	17
5 Generic functions	17
5.1 Modulation mapper	17
5.1.1 $\pi/2$ -BPSK.....	17
5.1.2 BPSK	17
5.1.3 QPSK.....	18
5.1.4 16QAM.....	18
5.1.5 64QAM.....	18
5.1.6 256QAM.....	18
5.1.7 1024QAM.....	18
5.2 Sequence generation.....	18
5.2.1 Pseudo-random sequence generation.....	18
5.2.2 Low-PAPR sequence generation type 1.....	19
5.2.2.1 Base sequences of length 36 or larger	19
5.2.2.2 Base sequences of length less than 36.....	19
5.2.3 Low-PAPR sequence generation type 2.....	23
5.2.3.1 Sequences of length 30 or larger	23
5.2.3.2 Sequences of length less than 30.....	23
5.3 OFDM baseband signal generation	27
5.3.1 OFDM baseband signal generation for all channels except PRACH and RIM-RS	27
5.3.2 OFDM baseband signal generation for PRACH.....	29
5.3.3 OFDM baseband signal generation for RIM-RS	31
5.4 Modulation and upconversion	32

6	Uplink.....	32
6.1	Overview	32
6.1.1	Overview of physical channels	32
6.1.2	Overview of physical signals.....	32
6.2	Physical resources	33
6.3	Physical channels	33
6.3.1	Physical uplink shared channel.....	33
6.3.1.1	Scrambling	33
6.3.1.2	Modulation	34
6.3.1.3	Layer mapping	34
6.3.1.4	Transform precoding.....	35
6.3.1.5	Precoding	35
6.3.1.6	Mapping to virtual resource blocks	60
6.3.1.7	Mapping from virtual to physical resource blocks	61
6.3.2	Physical uplink control channel.....	61
6.3.2.1	General.....	61
6.3.2.2	Sequence and cyclic shift hopping	61
6.3.2.2.1	Group and sequence hopping	61
6.3.2.2.2	Cyclic shift hopping	62
6.3.2.3	PUCCH format 0.....	63
6.3.2.3.1	Sequence generation	63
6.3.2.3.2	Mapping to physical resources	63
6.3.2.4	PUCCH format 1.....	63
6.3.2.4.1	Sequence modulation.....	63
6.3.2.4.2	Mapping to physical resources	64
6.3.2.5	PUCCH format 2.....	65
6.3.2.5.1	Scrambling.....	65
6.3.2.5.2	Modulation	65
6.3.2.5.2A	Spreading.....	65
6.3.2.5.3	Mapping to physical resources	66
6.3.2.6	PUCCH formats 3 and 4	66
6.3.2.6.1	Scrambling.....	66
6.3.2.6.2	Modulation	67
6.3.2.6.3	Block-wise spreading	67
6.3.2.6.4	Transform precoding	68
6.3.2.6.5	Mapping to physical resources	68
6.3.3	Physical random-access channel.....	69
6.3.3.1	Sequence generation.....	69
6.3.3.2	Mapping to physical resources	75
6.4	Physical signals	95
6.4.1	Reference signals	95
6.4.1.1	Demodulation reference signal for PUSCH	95
6.4.1.1.1	Sequence generation	95
6.4.1.1.2	(void)	97
6.4.1.1.3	Precoding and mapping to physical resources	97
6.4.1.2	Phase-tracking reference signals for PUSCH.....	102
6.4.1.2.1	Sequence generation	102
6.4.1.2.1.1	Sequence generation if transform precoding is not enabled.....	102
6.4.1.2.1.2	Sequence generation if transform precoding is enabled.....	102
6.4.1.2.2	Mapping to physical resources	103
6.4.1.2.2.1	Precoding and mapping to physical resources if transform precoding is not enabled.....	103
6.4.1.2.2.2	Mapping to physical resources if transform precoding is enabled.....	105
6.4.1.3	Demodulation reference signal for PUCCH.....	106
6.4.1.3.1	Demodulation reference signal for PUCCH format 1.....	106
6.4.1.3.1.1	Sequence generation	106
6.4.1.3.1.2	Mapping to physical resources.....	107
6.4.1.3.2	Demodulation reference signal for PUCCH format 2.....	107
6.4.1.3.2.1	Sequence generation	107
6.4.1.3.2.2	Mapping to physical resources.....	108
6.4.1.3.3	Demodulation reference signal for PUCCH formats 3 and 4	108
6.4.1.3.3.1	Sequence generation	108
6.4.1.3.3.2	Mapping to physical resources.....	108

6.4.1.4	Sounding reference signal	109
6.4.1.4.1	SRS resource	109
6.4.1.4.2	Sequence generation	109
6.4.1.4.3	Mapping to physical resources	111
6.4.1.4.4	Sounding reference signal slot configuration	117
7	Downlink	117
7.1	Overview	117
7.1.1	Overview of physical channels	117
7.1.2	Overview of physical signals	118
7.2	Physical resources	118
7.3	Physical channels	119
7.3.1	Physical downlink shared channel	119
7.3.1.1	Scrambling	119
7.3.1.2	Modulation	119
7.3.1.3	Layer mapping	120
7.3.1.4	Antenna port mapping	121
7.3.1.5	Mapping to virtual resource blocks	122
7.3.1.6	Mapping from virtual to physical resource blocks	122
7.3.2	Physical downlink control channel (PDCCH)	124
7.3.2.1	Control-channel element (CCE)	124
7.3.2.2	Control-resource set (CORESET)	124
7.3.2.3	Scrambling	126
7.3.2.4	PDCCH modulation	126
7.3.2.5	Mapping to physical resources	127
7.3.3	Physical broadcast channel	127
7.3.3.1	Scrambling	127
7.3.3.2	Modulation	127
7.3.3.3	Mapping to physical resources	127
7.4	Physical signals	127
7.4.1	Reference signals	127
7.4.1.1	Demodulation reference signals for PDSCH	127
7.4.1.1.1	Sequence generation	127
7.4.1.1.2	Mapping to physical resources	128
7.4.1.2	Phase-tracking reference signals for PDSCH	133
7.4.1.2.1	Sequence generation	133
7.4.1.2.2	Mapping to physical resources	133
7.4.1.3	Demodulation reference signals for PDCCH	134
7.4.1.3.1	Sequence generation	134
7.4.1.3.2	Mapping to physical resources	135
7.4.1.4	Demodulation reference signals for PBCH	135
7.4.1.4.1	Sequence generation	135
7.4.1.4.2	Mapping to physical resources	136
7.4.1.5	CSI reference signals	136
7.4.1.5.1	General	136
7.4.1.5.2	Sequence generation	136
7.4.1.5.3	Mapping to physical resources	136
7.4.1.6	RIM reference signals	139
7.4.1.6.1	General	139
7.4.1.6.2	Sequence generation	139
7.4.1.6.3	Mapping to physical resources	140
7.4.1.6.4	RIM-RS configuration	140
7.4.1.6.4.1	General	140
7.4.1.6.4.2	Time-domain parameters and mapping from it to time-domain parameters	141
7.4.1.6.4.3	Frequency-domain parameters and mapping from it to frequency-domain parameters	141
7.4.1.6.4.4	Sequence parameters and mapping from it to sequence parameters	142
7.4.1.6.4.5	Mapping between resource triplet and set ID	142
7.4.1.7	Positioning reference signals	143
7.4.1.7.1	General	143
7.4.1.7.2	Sequence generation	143
7.4.1.7.3	Mapping to physical resources in a downlink PRS resource	143
7.4.1.7.4	Mapping to slots in a downlink PRS resource set	144

7.4.2	Synchronization signals	145
7.4.2.1	Physical-layer cell identities.....	145
7.4.2.2	Primary synchronization signal.....	145
7.4.2.2.1	Sequence generation	145
7.4.2.2.2	Mapping to physical resources	145
7.4.2.3	Secondary synchronization signal	145
7.4.2.3.1	Sequence generation	145
7.4.2.3.2	Mapping to physical resources	146
7.4.3	SS/PBCH block	146
7.4.3.1	Time-frequency structure of an SS/PBCH block	146
7.4.3.1.1	Mapping of PSS within an SS/PBCH block	147
7.4.3.1.2	Mapping of SSS within an SS/PBCH block	147
7.4.3.1.3	Mapping of PBCH and DM-RS within an SS/PBCH block	148
7.4.3.2	Time location of an SS/PBCH block.....	148
8	Sidelink.....	148
8.1	Overview	148
8.1.1	Overview of physical channels	148
8.1.2	Overview of physical signals.....	148
8.2	Physical resources	149
8.2.1	General.....	149
8.2.2	Numerologies.....	149
8.2.3	Frame structure	149
8.2.3.1	Frames and subframes.....	149
8.2.3.2	Slots.....	149
8.2.4	Antenna ports.....	149
8.2.5	Resource grid.....	150
8.2.6	Resource elements	150
8.2.7	Resource blocks	150
8.2.8	Bandwidth part.....	150
8.3	Physical channels	150
8.3.1	Physical sidelink shared channel	150
8.3.1.1	Scrambling	150
8.3.1.2	Modulation	151
8.3.1.3	Layer mapping	152
8.3.1.4	Precoding	152
8.3.1.5	Mapping to virtual resource blocks	152
8.3.1.6	Mapping from virtual to physical resource blocks	152
8.3.2	Physical sidelink control channel.....	152
8.3.2.1	Scrambling	152
8.3.2.2	Modulation	153
8.3.2.3	Mapping to physical resources	153
8.3.3	Physical sidelink broadcast channel.....	153
8.3.3.1	Scrambling	153
8.3.3.2	Modulation	153
8.3.3.3	Mapping to physical resources	153
8.3.4	Physical sidelink feedback channel.....	153
8.3.4.1	General	153
8.3.4.2	PSFCH format 0.....	153
8.3.4.2.1	Sequence generation	153
8.3.4.2.2	Mapping to physical resources	154
8.4	Physical signals	154
8.4.1	Reference signals	154
8.4.1.1	Demodulation reference signals for PSSCH	154
8.4.1.1.1	Sequence generation	154
8.4.1.1.2	Mapping to physical resources	155
8.4.1.2	Phase-tracking reference signals for PSSCH	156
8.4.1.2.1	Sequence generation	156
8.4.1.2.2	Mapping to physical resources	156
8.4.1.3	Demodulation reference signals for PSCCH	157
8.4.1.3.1	Sequence generation	157
8.4.1.3.2	Mapping to physical resources	158

8.4.1.4	Demodulation reference signals for PSBCH	158
8.4.1.4.1	Sequence generation	158
8.4.1.4.2	Mapping to physical resources	158
8.4.1.5	CSI reference signals.....	158
8.4.1.5.1	General	158
8.4.1.5.2	Sequence generation	158
8.4.1.5.3	Mapping to physical resources	159
8.4.1.6	Positioning reference signals.....	159
8.4.1.6.1	General	159
8.4.1.6.2	Sequence generation	159
8.4.1.6.3	Mapping to physical resources	159
8.4.2	Synchronization signals	160
8.4.2.1	Physical-layer sidelink synchronization identities	160
8.4.2.2	Sidelink primary synchronization signal	161
8.4.2.2.1	Sequence generation	161
8.4.2.2.2	Mapping to physical resources	161
8.4.2.3	Sidelink secondary synchronization signal	161
8.4.2.3.1	Sequence generation	161
8.4.2.3.2	Mapping to physical resources	161
8.4.3	S-SS/PSBCH block.....	161
8.4.3.1	Time-frequency structure of an S-SS/PSBCH block.....	161
8.4.3.1.1	Mapping of S-PSS within an S-SS/PSBCH block.....	162
8.4.3.1.2	Mapping of S-SSS within an S-SS/PSBCH block.....	162
8.4.3.1.3	Mapping of PSBCH and DM-RS within an S-SS/PSBCH block.....	162
8.4.3.2	Time location of an S-SS/PSBCH block.....	163
8.5	Timing	163
Annex A (informative): Change history		164
History		170

Annex A (informative):		Change history	164
History			170

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[ETSI TS 138 211 V18.5.0 \(2025-01\)](https://standards.iteh.ai/catalog/standards/etsi/d9f7d06f-f6f0-40f3-8ef7-cb0ef6805e37/etsi-ts-138-211-v18-5-0-2025-01)

<https://standards.iteh.ai/catalog/standards/etsi/d9f7d06f-f6f0-40f3-8ef7-cb0ef6805e37/etsi-ts-138-211-v18-5-0-2025-01>

1 Scope

The present document describes the physical channels and signals for 5G-NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.201: "NR; Physical Layer – General Description"
- [3] 3GPP TS 38.202: "NR; Services provided by the physical layer"
- [4] 3GPP TS 38.212: "NR; Multiplexing and channel coding"
- [5] 3GPP TS 38.213: "NR; Physical layer procedures for control "
- [6] 3GPP TS 38.214: "NR; Physical layer procedures for data "
- [7] 3GPP TS 38.215: "NR; Physical layer measurements"
- [8] 3GPP TS 38.104: "NR; Base Station (BS) radio transmission and reception"
- [9] void
- [10] 3GPP TS 38.306: "NR; User Equipment (UE) radio access capabilities"
- [11] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification"
- [12] 3GPP TS 38.133: "NR; Requirements for support of radio resource management"
- [13] 3GPP TS 38.304: "NR; User Equipment (UE) procedures in Idle mode and RRC Inactive state"
- [14] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone"
- [15] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone"
- [16] 3GPP TS 38.101-5: "NR; User Equipment (UE) radio transmission and reception; Part 5: Satellite access Radio Frequency (RF) and performance requirements"
- [17] 3GPP TS 38.108: "Satellite Access Node radio transmission and reception"

3 Definitions of terms, symbols and abbreviations

3.1 Terms

For the purposes of the present document, the following definitions apply:

3.2 Symbols

For the purposes of the present document, the following symbols apply:

$(k,l)_{p,\mu}$	Resource element with frequency-domain index k and time-domain index l for antenna port p and subcarrier spacing configuration μ ; see clause 4.4.3
$a_{k,l}^{(p,\mu)}$	Value of resource element (k,l) for antenna port p and subcarrier spacing configuration μ ; see clause 4.4.3
β	Amplitude scaling for a physical channel/signal
$c(n)$	PN sequence; see clause 5.2.1
Δf	Subcarrier spacing
Δf_{RA}	Subcarrier spacing for random-access preambles
κ	The ratio between T_s and T_c ; see clause 4.1
k	Subcarrier index relative to a reference
l	OFDM symbol index relative to a reference
μ	Subcarrier spacing configuration, $\Delta f = 2^\mu \cdot 15$ [kHz]
$M_{\text{bit}}^{(q)}$	Number of coded bits to transmit on a physical channel [for codeword q]
$M_{\text{symb}}^{(q)}$	Number of modulation symbols to transmit on a physical channel [for codeword q]
$M_{\text{symb}}^{\text{layer}}$	Number of modulation symbols to transmit per layer for a physical channel
$M_{\text{sc}}^{\text{PUSCH}}$	Scheduled bandwidth for uplink transmission, expressed as a number of subcarriers
$M_{\text{RB}}^{\text{PUSCH}}$	Scheduled bandwidth for uplink transmission, expressed as a number of resource blocks
$M_{\text{symb}}^{\text{ap}}$	Number of modulation symbols to transmit per antenna port for a physical channel
v	Number of transmission layers
$N_{\text{BWP},i}^{\text{size}}$	Size of bandwidth part i ; see clause 4.4.4.4
$N_{\text{BWP},i}^{\text{start}}$	Start of bandwidth part i ; see clause 4.4.4.4
$N_{\text{CP},i}^\mu$	Cyclic prefix length; see clause 5.3.1
$N_{\text{grid},x}^{\text{size},\mu}$	The size of the resource grid; see clauses 4.4.2 and 5.3
$N_{\text{grid},x}^{\text{start},\mu}$	The start of the resource grid; see clause 4.4.2
$N_{\text{group}}^{\text{PT-RS}}$	The number of PT-RS groups; see clause 6.3.1.4
$N_{\text{ID}}^{\text{cell}}$	Physical layer cell identity; see clause 7.4.2.1
$N_{\text{ID}}^{\text{SL}}$	Physical-layer sidelink identity; see clause 8.4.2.1
$N_{\text{RB}}^{\text{CORESET}}$	Frequency-domain size of a control resource set; see clause 7.3.2.2
$N_{\text{REG}}^{\text{CORESET}}$	Number of resource-element groups in a CORESET; see clause 7.3.2.2
$N_{\text{samp}}^{\text{group}}$	Number of samples per PT-RS group; see clause 6.3.1.4
$N_{\text{sc}}^{\text{RB}}$	Number of subcarriers per resource block, see clause 4.4.4.1
$N_{\text{slot}}^{\text{subframe},\mu}$	Number of slots per subframe for subcarrier spacing configuration μ , see clause 4.3.2
$N_{\text{slot}}^{\text{frame},\mu}$	Number of slots per frame for subcarrier spacing configuration μ , see clause 4.3.2
$N_{\text{symb}}^{\text{CORESET}}$	Time duration of a control resource set; see clause 7.3.2.2
$N_{\text{symb}}^{\text{PUCCH}}$	Length of the PUCCH transmission in OFDM symbols; see clause 6.3.2.1
$N_{\text{symb}}^{\text{subframe},\mu}$	Number of OFDM symbols per subframe for subcarrier spacing configuration μ ; see clause 4.3.1
$N_{\text{symb}}^{\text{slot}}$	Number of symbols per slot
N_{TA}	Timing advance between downlink and uplink; see clause 4.3.1
$N_{\text{TA,offset}}$	A fixed offset used to calculate the timing advance; see clause 4.3.1
$N_{\text{TA,adj}}^{\text{common}}$	Network-controlled timing correction; see clause 4.3.1
$N_{\text{TA,adj}}^{\text{UE}}$	UE-derived timing correction; see clause 4.3.1
$N_{\text{Rx-Tx}}$	Minimum time from reception to transmission for a half-duplex UE; see clause 4.3.2
n_f	System frame number (SFN)
n_{CRB}^μ	Common resource block number for subcarrier spacing configuration μ , see clause 4.4.4.3
n_{HFN}	Hyper-frame number
n_{PRB}	Physical resource block number; see clause 4.4.4.4
n_{RNTI}	Radio network temporary identifier
n_s^μ	Slot number within a subframe for subcarrier spacing configuration μ ; see clause 4.3.2
$n_{s,f}^\mu$	Slot number within a frame for subcarrier spacing configuration μ ; see clause 4.3.2
p	Antenna port number
Q_m	Modulation order

ρ	Number of antenna ports
$\bar{r}_{u,v}(n)$	Low-PAPR base sequence; see clause 5.2.2
$r_{u,v}^{(\alpha,\delta)}(n)$	Low-PAPR sequence; see clause 5.2.2
$s_l^{(p,\mu)}(t)$	The time-continuous signal on antenna port p and subcarrier spacing configuration μ for OFDM symbol l in a subframe; see clause 5.3.1
T_c	Basic time unit for NR; see clause 4.1
T_f	Radio frame duration; see clause 4.3.1
T_s	Basic time unit for LTE
T_{sf}	Subframe duration; see clause 4.3.1
T_{slot}	Slot duration; see clause 4.3.2
T_{TA}	Timing advance between downlink and uplink; see clause 4.3.1
W	Precoding matrix for spatial multiplexing

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

BWP	Bandwidth Part
CCE	Control Channel Element
CORESET	Control Resource Set
CRB	Common Resource Block
CSI	Channel-State Information
CSI-RS	CSI Reference Signal
DCI	Downlink Control Information
DM-RS	Demodulation Reference Signal
FR1	Frequency Range 1 as defined in TS 38.104 [8]
FR2	Frequency Range 2 as defined in TS 38.104 [8]
FR2-NTN	Frequency Range 2 for Non-terrestrial networks as defined in TS 38.101-5 [16]
IAB	Integrated Access and Backhaul
IAB-MT	IAB Mobile Termination
IE	Information Element
NCR	Network-Controlled repeater
NCR-MT	NCR Mobile Termination
PBCH	Physical Broadcast Channel
PDCCH	Physical Downlink Control Channel
PDSCH	Physical Downlink Shared Channel
PRACH	Physical Random-Access Channel
PRB	Physical Resource Block
PSS	Primary Synchronization Signal
PT-RS	Phase-tracking reference signal
PUCCH	Physical Uplink Control Channel
PUSCH	Physical Uplink Shared Channel
RAR	Random Access Response
REG	Resource-Element Group
RIM	Remote Interference Management
RIM-RS	Remote Interference Management Reference Signal
SRS	Sounding Reference Signal
SSS	Secondary Synchronization Signal
VRB	Virtual Resource Block

4 Frame structure and physical resources

4.1 General

Throughout this specification, unless otherwise noted, the size of various fields in the time domain is expressed in time units $T_c = 1/(\Delta f_{\max} \cdot N_f)$ where $\Delta f_{\max} = 480 \cdot 10^3$ Hz and $N_f = 4096$. The constant $\kappa = T_s/T_c = 64$ where $T_s = 1/(\Delta f_{\text{ref}} \cdot N_{f,\text{ref}})$, $\Delta f_{\text{ref}} = 15 \cdot 10^3$ Hz and $N_{f,\text{ref}} = 2048$.

Throughout this specification, unless otherwise noted, statements using the term "UE" in clauses 4, 5, 6, or 7 are equally applicable to the IAB-MT part of an IAB-node and the NCR-MT part of an NCR node.

4.2 Numerologies

Multiple OFDM numerologies are supported as given by Table 4.2-1 where μ and the cyclic prefix for a downlink or uplink bandwidth part are obtained from the higher-layer parameters *subcarrierSpacing* and *cyclicPrefix*, respectively.

Table 4.2-1: Supported transmission numerologies.

μ	$\Delta f = 2^\mu \cdot 15[\text{kHz}]$	Cyclic prefix
0	15	Normal
1	30	Normal
2	60	Normal, Extended
3	120	Normal
4	240	Normal
5	480	Normal
6	960	Normal

4.3 Frame structure

4.3.1 Frames and subframes

Downlink, uplink, and sidelink transmissions are organized into frames with $T_f = (\Delta f_{\max} N_f / 100) \cdot T_c = 10$ ms duration, each consisting of ten subframes of $T_{sf} = (\Delta f_{\max} N_f / 1000) \cdot T_c = 1$ ms duration. The number of consecutive OFDM symbols per subframe is $N_{\text{subframe},\mu}^{\text{subframe}} = N_{\text{symbol}}^{\text{slot}} N_{\text{slot}}^{\text{subframe},\mu}$. Each frame is divided into two equally-sized half-frames of five subframes each with half-frame 0 consisting of subframes 0 – 4 and half-frame 1 consisting of subframes 5 – 9.

There is one set of frames in the uplink and one set of frames in the downlink on a carrier.

Uplink frame number i for transmission from the UE shall start $T_{TA} = (N_{TA} + N_{TA,\text{offset}} + N_{TA,\text{adj}}^{\text{common}} + N_{TA,\text{adj}}^{\text{UE}}) T_c$ before the start of the corresponding downlink frame at the UE where

- N_{TA} and $N_{TA,\text{offset}}$ are given by clause 4.2 of [5, TS 38.213], except for msgA transmission on PUSCH where $N_{TA} = 0$ shall be used;
- $N_{TA,\text{adj}}^{\text{common}}$ given by clause 4.2 of [5, TS 38.213] is derived from the higher-layer parameters *ta-Common*, *ta-CommonDrift*, and *ta-CommonDriftVariant* if configured, otherwise $N_{TA,\text{adj}}^{\text{common}} = 0$;
- $N_{TA,\text{adj}}^{\text{UE}}$ given by clause 4.2 of [5, TS 38.213] is computed by the UE based on UE position and serving-satellite-ephemeris-related higher-layers parameters if configured, or is computed by the UE based on UE position and gNB location provided by *atg-gNB-Location* if configured, otherwise $N_{TA,\text{adj}}^{\text{UE}} = 0$.




Figure 4.3.1-1: Uplink-downlink timing relation.

4.3.2 Slots

For subcarrier spacing configuration μ , slots are numbered $n_s^\mu \in \{0, \dots, N_{\text{slot}}^{\text{subframe}, \mu} - 1\}$ in increasing order within a subframe and $n_{s,f}^\mu \in \{0, \dots, N_{\text{slot}}^{\text{frame}, \mu} - 1\}$ in increasing order within a frame. There are $N_{\text{sym}}^{\text{slot}}$ consecutive OFDM symbols in a slot where $N_{\text{sym}}^{\text{slot}}$ depends on the cyclic prefix as given by Tables 4.3.2-1 and 4.3.2-2. The start of slot n_s^μ in a subframe is aligned in time with the start of OFDM symbol $n_s^\mu N_{\text{sym}}^{\text{slot}}$ in the same subframe.

OFDM symbols in a slot in a downlink or uplink frame can be classified as 'downlink', 'flexible', or 'uplink'. Signaling of slot formats is described in clause 11.1 of [5, TS 38.213].

In a slot in a downlink frame, the UE shall assume that downlink transmissions only occur in 'downlink' or 'flexible' symbols.

In a slot in an uplink frame, the UE shall only transmit in 'uplink' or 'flexible' symbols.

A UE not capable of full-duplex communication and not supporting simultaneous transmission and reception as defined by parameter *simultaneousRxTxInterBandENDC*, *simultaneousRxTxInterBandCA* or *simultaneousRxTxSUL* [10, TS 38.306] among all cells within a group of cells is not expected to transmit in the uplink in one cell within the group of cells earlier than $N_{\text{Rx-Tx}} T_c$ after the end of the last received downlink symbol in the same or different cell within the group of cells where $N_{\text{Rx-Tx}}$ is given by Table 4.3.2-3.

A UE not capable of full-duplex communication and not supporting simultaneous transmission and reception as defined by parameter *simultaneousRxTxInterBandENDC*, *simultaneousRxTxInterBandCA* or *simultaneousRxTxSUL* [10, TS 38.306] among all cells within a group of cells is not expected to receive in the downlink in one cell within the group of cells earlier than $N_{\text{Tx-Rx}} T_c$ after the end of the last transmitted uplink symbol in the same or different cell within the group of cells where $N_{\text{Tx-Rx}}$ is given by Table 4.3.2-3.

For DAPS handover operation, a UE not capable of full-duplex communication is not expected to transmit in the uplink to a cell earlier than $N_{\text{Rx-Tx}} T_c$ after the end of the last received downlink symbol in the different cell where $N_{\text{Rx-Tx}}$ is given by Table 4.3.2-3.

For DAPS handover operation, a UE not capable of full-duplex communication is not expected to receive in the downlink from a cell earlier than $N_{\text{Tx-Rx}} T_c$ after the end of the last transmitted uplink symbol in the different cell where $N_{\text{Tx-Rx}}$ is given by Table 4.3.2-3.

A UE not capable of full-duplex communication is not expected to transmit in the uplink earlier than $N_{\text{Rx-Tx}} T_c$ after the end of the last received downlink symbol in the same cell where $N_{\text{Rx-Tx}}$ is given by Table 4.3.2-3.

A UE not capable of full-duplex communication is not expected to receive in the downlink earlier than $N_{\text{Tx-Rx}} T_c$ after the end of the last transmitted uplink symbol in the same cell where $N_{\text{Tx-Rx}}$ is given by Table 4.3.2-3.