

ETSI TS 138 212 V18.8.0 (2026-02)



TECHNICAL SPECIFICATION

5G;
NR;

**Multiplexing and channel coding
(3GPP TS 38.212 version 18.8.0 Release 18)**

get full document from standards.iteh.ai



Reference

RTS/TSGR-0138212vi80

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
[ETSI Search & Browse Standards](#) application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver](#) repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our [Coordinated Vulnerability Disclosure \(CVD\)](#) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	6
1 Scope	8
2 References	8
3 Definitions of terms, symbols and abbreviations	8
3.1 Terms.....	8
3.2 Symbols.....	8
3.3 Abbreviations	9
4 Mapping to physical channels	10
4.1 Uplink.....	10
4.2 Downlink	10
4.3 Sidelink	10
5 General procedures.....	11
5.1 CRC calculation	11
5.2 Code block segmentation and code block CRC attachment	12
5.2.1 Polar coding	12
5.2.2 Low density parity check coding	12
5.3 Channel coding.....	14
5.3.1 Polar coding.....	15
5.3.1.1 Interleaving	15
5.3.1.2 Polar encoding.....	16
5.3.2 Low density parity check coding	19
5.3.3 Channel coding of small block lengths	24
5.3.3.1 Encoding of 1-bit information.....	24
5.3.3.2 Encoding of 2-bit information.....	24
5.3.3.3 Encoding of other small block lengths	25
5.4 Rate matching.....	26
5.4.1 Rate matching for Polar code.....	26
5.4.1.1 Sub-block interleaving	26
5.4.1.2 Bit selection.....	27
5.4.1.3 Interleaving of coded bits.....	27
5.4.2 Rate matching for LDPC code.....	28
5.4.2.1 Bit selection.....	29
5.4.2.2 Bit interleaving.....	32
5.4.3 Rate matching for channel coding of small block lengths	32
5.5 Code block concatenation	32
6 Uplink transport channels and control information.....	33
6.1 Random access channel.....	33
6.2 Uplink shared channel	33
6.2.1 Transport block CRC attachment.....	33
6.2.2 LDPC base graph selection.....	33
6.2.3 Code block segmentation and code block CRC attachment	34
6.2.4 Channel coding of UL-SCH.....	34
6.2.5 Rate matching	34
6.2.6 Code block concatenation	34
6.2.7 Data and control multiplexing	35
6.3 Uplink control information.....	46
6.3.1 Uplink control information on PUCCH.....	46
6.3.1.1 UCI bit sequence generation	46
6.3.1.1.1 HARQ-ACK/SR only	46

6.3.1.1.2	CSI only.....	46
6.3.1.1.3	HARQ-ACK/SR and CSI	64
6.3.1.1.4	UCI with different priority indexes	65
6.3.1.2	Code block segmentation and CRC attachment	65
6.3.1.2.1	UCI encoded by Polar code.....	65
6.3.1.2.2	UCI encoded by channel coding of small block lengths.....	66
6.3.1.3	Channel coding of UCI	66
6.3.1.3.1	UCI encoded by Polar code.....	66
6.3.1.3.2	UCI encoded by channel coding of small block lengths.....	66
6.3.1.4	Rate matching	66
6.3.1.4.1	UCI encoded by Polar code.....	66
6.3.1.4.2	UCI encoded by channel coding of small block lengths.....	67
6.3.1.4.3	UCI with different priority indexes encoded by Polar code	68
6.3.1.4.4	UCI with different priority indexes encoded by channel coding of small block lengths.....	68
6.3.1.5	Code block concatenation	69
6.3.1.6	Multiplexing of coded UCI bits to PUCCH	69
6.3.2	Uplink control information on PUSCH	71
6.3.2.1	UCI bit sequence generation	72
6.3.2.1.1	HARQ-ACK.....	72
6.3.2.1.2	CSI.....	72
6.3.2.1.3	CG-UCI	94
6.3.2.1.3A	UTO-UCI.....	95
6.3.2.1.4	HARQ-ACK and CG-UCI/UTO-UCI	95
6.3.2.1.5	UCI with different priority indexes	96
6.3.2.2	Code block segmentation and CRC attachment	98
6.3.2.2.1	UCI encoded by Polar code.....	98
6.3.2.2.2	UCI encoded by channel coding of small block lengths.....	98
6.3.2.3	Channel coding of UCI	98
6.3.2.3.1	UCI encoded by Polar code.....	98
6.3.2.3.2	UCI encoded by channel coding of small block lengths.....	98
6.3.2.4	Rate matching	98
6.3.2.4.1	UCI encoded by Polar code.....	98
6.3.2.4.2	UCI encoded by channel coding of small block lengths.....	112
6.3.2.5	Code block concatenation	115
6.3.2.6	Multiplexing of coded UCI bits to PUSCH.....	115
6.3.2.7	Multiplexing of coded UCI bits with different priority indexes to PUSCH.....	115
7	Downlink transport channels and control information.....	116
7.1	Broadcast channel.....	116
7.1.1	PBCH payload generation	116
7.1.2	Scrambling	117
7.1.3	Transport block CRC attachment.....	118
7.1.4	Channel coding	118
7.1.5	Rate matching	119
7.2	Downlink shared channel and paging channel	119
7.2.1	Transport block CRC attachment.....	119
7.2.2	LDPC base graph selection.....	119
7.2.3	Code block segmentation and code block CRC attachment	119
7.2.4	Channel coding	119
7.2.5	Rate matching	120
7.2.6	Code block concatenation.....	120
7.3	Downlink control information.....	120
7.3.1	DCI formats	120
7.3.1.0	DCI size alignment.....	122
7.3.1.0.1	DCI size alignment for DCI formats for scheduling of sidelink.....	125
7.3.1.1	DCI formats for scheduling of PUSCH.....	125
7.3.1.1.1	Format 0_0	125
7.3.1.1.2	Format 0_1	129
7.3.1.1.3	Format 0_2	199
7.3.1.1.4	Format 0_3	213
7.3.1.2	DCI formats for scheduling of PDSCH.....	223
7.3.1.2.1	Format 1_0	223

7.3.1.2.2	Format 1_1	227
7.3.1.2.3	Format 1_2	254
7.3.1.2.4	Format 1_3	259
7.3.1.3	DCI formats for other purposes.....	268
7.3.1.3.1	Format 2_0	268
7.3.1.3.2	Format 2_1	268
7.3.1.3.3	Format 2_2	268
7.3.1.3.4	Format 2_3	269
7.3.1.3.5	Format 2_4	270
7.3.1.3.6	Format 2_5	270
7.3.1.3.7	Format 2_6	270
7.3.1.3.8	Format 2_7	270
7.3.1.3.9	Format 2_8	271
7.3.1.3.10	Format 2_9	271
7.3.1.4	DCI formats for scheduling of sidelink.....	272
7.3.1.4.1	Format 3_0	272
7.3.1.4.2	Format 3_1	273
7.3.1.4.3	Format 3_2	273
7.3.1.5	DCI formats for scheduling of MBS	274
7.3.1.5.1	Format 4_0	274
7.3.1.5.2	Format 4_1	274
7.3.1.5.3	Format 4_2	275
7.3.2	CRC attachment.....	277
7.3.3	Channel coding	277
7.3.4	Rate matching	277
8	Sidelink transport channels and control information.....	277
8.1	Sidelink broadcast channel	277
8.1.1	Void	278
8.2	Sidelink shared channel.....	278
8.2.1	Data and control multiplexing	278
8.3	Sidelink control information on PSCCH.....	279
8.3.1	1 st -stage SCI formats.....	279
8.3.1.1	SCI format 1-A.....	279
8.3.1.2	SCI format 1-B.....	281
8.3.2	CRC attachment.....	282
8.3.3	Channel coding	282
8.3.4	Rate Matching.....	282
8.4	Sidelink control information on PSSCH	282
8.4.1	2 nd -stage SCI formats.....	282
8.4.1.1	SCI format 2-A.....	282
8.4.1.2	SCI format 2-B.....	283
8.4.1.3	SCI format 2-C.....	284
8.4.1.4	SCI format 2-D.....	285
8.4.2	CRC attachment.....	286
8.4.3	Channel coding	286
8.4.4	Rate Matching.....	286
8.4.5	Multiplexing of coded 2 nd -stage SCI bits to PSSCH.....	287
Annex A (informative): Change history		288
History		295

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

In the present document, modal verbs have the following meanings:

shall indicates a mandatory requirement to do something

shall not indicates an interdiction (prohibition) to do something

The constructions "shall" and "shall not" are confined to the context of normative provisions, and do not appear in Technical Reports.

The constructions "must" and "must not" are not used as substitutes for "shall" and "shall not". Their use is avoided insofar as possible, and they are not used in a normative context except in a direct citation from an external, referenced, non-3GPP document, or so as to maintain continuity of style when extending or modifying the provisions of such a referenced document.

should indicates a recommendation to do something

should not indicates a recommendation not to do something

may indicates permission to do something

need not indicates permission not to do something

The construction "may not" is ambiguous and is not used in normative elements. The unambiguous constructions "might not" or "shall not" are used instead, depending upon the meaning intended.

can indicates that something is possible

cannot indicates that something is impossible

The constructions "can" and "cannot" are not substitutes for "may" and "need not".

will indicates that something is certain or expected to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

will not indicates that something is certain or expected not to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

might indicates a likelihood that something will happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

might not indicates a likelihood that something will not happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

In addition:

is (or any other verb in the indicative mood) indicates a statement of fact

is not (or any other negative verb in the indicative mood) indicates a statement of fact

The constructions "is" and "is not" do not indicate requirements.

Sample Document

get full document from standards.iteh.ai

1 Scope

The present document specifies the coding, multiplexing and mapping to physical channels for 5G NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] void.
- [3] void.
- [4] 3GPP TS 38.211: "NR; Physical channels and modulation".
- [5] 3GPP TS 38.213: "NR; Physical layer procedures for control".
- [6] 3GPP TS 38.214: "NR; Physical layer procedures for data".
- [7] void.
- [8] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification".
- [9] 3GPP TS 38.331: "NR; Radio Resource Control (RRC) protocol specification".
- [10] 3GPP TS 38.473: "NG-RAN; F1 Application Protocol (F1AP)".
- [11] 3GPP TS 36.212: "Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding".
- [12] 3GPP TS 23.287: "Architecture enhancements for 5G System (5GS) to support Vehicle-to-Everything (V2X) services".
- [13] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone".
- [14] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access".

3 Definitions of terms, symbols and abbreviations

3.1 Terms

For the purposes of the present document, the terms given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

3.2 Symbols

Void.

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

BCH	Broadcast Channel
CAPC	Channel Access Priority Class
CBG	Code Block Group
CBGTI	Code Block Group Transmission Information
CG	Configured Grant
CG-DFI	CG - Downlink Feedback Information
CG-UCI	CG - Uplink Control Information
CORESET	Control Resource Set
COT	Channel Occupancy Time
CQI	Channel Quality Indicator
CRC	Cyclic Redundancy Check
CRI	CSI-RS Resource Indicator
CSI	Channel State Information
CSI-RS	CSI - Reference Signal
DAI	Downlink Assignment Index
DCI	Downlink Control Information
DL	Downlink
DL-SCH	Downlink - Shared Channel
DMRS	Demodulation Reference Signal
HARQ	Hybrid Automatic repeat Request
HARQ-ACK	Hybrid Automatic repeat Request - Acknowledgement
LDPC	Low Density Parity Check
LI	Layer Indicator
MBS	Multicast Broadcast Services
MCS	Modulation and Coding Scheme
NCR	Network-controlled repeater
OFDM	Orthogonal Frequency Division Multiplex
PBCH	Physical Broadcast Channel
PCH	Paging Channel
PDCCH	Physical Downlink Control Channel
PDSCH	Physical Downlink Shared Channel
PMI	Precoding Matrix Indicator
PRB	Physical Resource Block
PRACH	Physical Random Access Channel
PSBCH	Physical Sidelink Broadcast Channel
PSCCH	Physical Sidelink Control Channel
PSFCH	Physical Sidelink Feedback Channel
PSSCH	Physical Sidelink Shared Channel
PTRS	Phase-Tracking Reference Signal
PUCCH	Physical Uplink Control Channel
PUSCH	Physical Uplink Shared Channel
RACH	Random Access Channel
RI	Rank Indicator
RSRP	Reference Signal Received Power
SCI	Sidelink Control Information
SFCI	Sidelink Feedback Control Information
SFN	System Frame Number
SL	Sidelink
SL-BCH	Sidelink - Broadcast Channel
SL PRS	Sidelink Positioning Reference Signal
SL-SCH	Sidelink - Shared Channel
SR	Scheduling Request
SRS	Sounding Reference Signal
SS	Synchronisation Signal
SUL	Supplementary Uplink

TCI	Transmission Configuration Indicator
TPC	Transmit Power Control
TrCH	Transport Channel
UCI	Uplink Control Information
UE	User Equipment
UL	Uplink
UL-SCH	Uplink Shared Channel
UTO-UCI	Unused Transmission Occasion - Uplink Control Information
VRB	Virtual Resource Block
ZP CSI-RS	Zero power CSI-RS

4 Mapping to physical channels

4.1 Uplink

Table 4.1-1 specifies the mapping of the uplink transport channels to their corresponding physical channels. Table 4.1-2 specifies the mapping of the uplink control channel information to its corresponding physical channel.

Table 4.1-1

TrCH	Physical Channel
UL-SCH	PUSCH
RACH	PRACH

Table 4.1-2

Control information	Physical Channel
UCI	PUCCH, PUSCH

4.2 Downlink

Table 4.2-1 specifies the mapping of the downlink transport channels to their corresponding physical channels. Table 4.2-2 specifies the mapping of the downlink control channel information to its corresponding physical channel.

Table 4.2-1

TrCH	Physical Channel
DL-SCH	PDSCH
BCH	PBCH
PCH	PDSCH

Table 4.2-2

Control information	Physical Channel
DCI	PDCCH

4.3 Sidelink

Table 4.3-1 specifies the mapping of the sidelink transport channels to their corresponding physical channels. Table 4.3-2 specifies the mapping of the sidelink control information and sidelink feedback control information to their corresponding physical channels.

Table 4.3-1

TrCH	Physical Channel
SL-SCH	PSSCH
SL-BCH	PSBCH

Table 4.3-2

Control information	Physical Channel
1 st -stage SCI	PSSCH
2 nd -stage SCI	PSSCH
SFCI	PSFCH

5 General procedures

Data and control streams from/to MAC layer are encoded /decoded to offer transport and control services over the radio transmission link. Channel coding scheme is a combination of error detection, error correcting, rate matching, interleaving and transport channel or control information mapping onto/splitting from physical channels.

5.1 CRC calculation

Denote the input bits to the CRC computation by $a_0, a_1, a_2, a_3, \dots, a_{A-1}$, and the parity bits by $p_0, p_1, p_2, p_3, \dots, p_{L-1}$, where A is the size of the input sequence and L is the number of parity bits. The parity bits are generated by one of the following cyclic generator polynomials:

- $g_{\text{CRC24A}}(D) = [D^{24} + D^{23} + D^{18} + D^{17} + D^{14} + D^{11} + D^{10} + D^7 + D^6 + D^5 + D^4 + D^3 + D + 1]$ for a CRC length $L = 24$;
- $g_{\text{CRC24B}}(D) = [D^{24} + D^{23} + D^6 + D^5 + D + 1]$ for a CRC length $L = 24$;
- $g_{\text{CRC24C}}(D) = [D^{24} + D^{23} + D^{21} + D^{20} + D^{17} + D^{15} + D^{13} + D^{12} + D^8 + D^4 + D^2 + D + 1]$ for a CRC length $L = 24$;
- $g_{\text{CRC16}}(D) = [D^{16} + D^{12} + D^5 + 1]$ for a CRC length $L = 16$;
- $g_{\text{CRC11}}(D) = [D^{11} + D^{10} + D^9 + D^5 + 1]$ for a CRC length $L = 11$;
- $g_{\text{CRC6}}(D) = [D^6 + D^5 + 1]$ for a CRC length $L = 6$.

The encoding is performed in a systematic form, which means that in GF(2), the polynomial:

$$a_0 D^{A+L-1} + a_1 D^{A+L-2} + \dots + a_{A-1} D^L + p_0 D^{L-1} + p_1 D^{L-2} + \dots + p_{L-2} D^1 + p_{L-1}$$

yields a remainder equal to 0 when divided by the corresponding CRC generator polynomial.

The bits after CRC attachment are denoted by $b_0, b_1, b_2, b_3, \dots, b_{B-1}$, where $B = A + L$. The relation between a_k and b_k is:

$$b_k = a_k \quad \text{for } k = 0, 1, 2, \dots, A-1$$

$$b_k = p_{k-A} \quad \text{for } k = A, A+1, A+2, \dots, A+L-1.$$

5.2 Code block segmentation and code block CRC attachment

5.2.1 Polar coding

The input bit sequence to the code block segmentation is denoted by $a_0, a_1, a_2, a_3, \dots, a_{A-1}$, where $A > 0$.

if $I_{seg} = 1$

Number of code blocks: $C = 2$;

else

Number of code blocks: $C = 1$

end if

$A' = \lceil A/C \rceil \cdot C$;

for $i = 0$ to $A' - A - 1$

$a'_i = 0$;

end for

for $i = A' - A$ to $A' - 1$

$a'_i = a_{i-(A'-A)}$;

end for

$s = 0$;

for $r = 0$ to $C - 1$

for $k = 0$ to $A'/C - 1$

$c_{rk} = a'_s$;

$s = s + 1$;

end for

The sequence $c_{r0}, c_{r1}, c_{r2}, c_{r3}, \dots, c_{r(A'/C-1)}$ is used to calculate the CRC parity bits $p_{r0}, p_{r1}, p_{r2}, \dots, p_{r(L-1)}$ according to Clause 5.1 with a generator polynomial of length L .

for $k = A'/C$ to $A'/C + L - 1$

$c_{rk} = p_{r(k-A'/C)}$;

end for

end for

The value of A is no larger than 1706.

5.2.2 Low density parity check coding

The input bit sequence to the code block segmentation is denoted by $b_0, b_1, b_2, b_3, \dots, b_{B-1}$, where $B > 0$. If B is larger than the maximum code block size K_{cb} , segmentation of the input bit sequence is performed and an additional CRC sequence of $L = 24$ bits is attached to each code block.

For LDPC base graph 1, the maximum code block size is:

$$- K_{cb} = 8448.$$

For LDPC base graph 2, the maximum code block size is:

$$- K_{cb} = 3840.$$

Total number of code blocks C is determined by:

if $B \leq K_{cb}$

$$L = 0$$

Number of code blocks: $C = 1$

$$B' = B$$

else

$$L = 24$$

Number of code blocks: $C = \lceil B / (K_{cb} - L) \rceil$.

$$B' = B + C \cdot L$$

end if

The bits output from code block segmentation are denoted by $c_{r0}, c_{r1}, c_{r2}, c_{r3}, \dots, c_{r(K_r-1)}$, where $0 \leq r < C$ is the code block number, and $K_r = K$ is the number of bits for the code block number r .

The number of bits K in each code block is calculated as:

$$K' = B' / C; \quad \text{get full document from standards.iteh.ai}$$

For LDPC base graph 1,

$$K_b = 22.$$

For LDPC base graph 2,

if $B > 640$

$$K_b = 10;$$

elseif $B > 560$

$$K_b = 9;$$

elseif $B > 192$

$$K_b = 8;$$

else

$$K_b = 6;$$

end if

find the minimum value of Z in all sets of lifting sizes in Table 5.3.2-1, denoted as Z_c , such that $K_b \cdot Z_c \geq K'$, and set $K = 22Z_c$ for LDPC base graph 1 and $K = 10Z_c$ for LDPC base graph 2;

The bit sequence c_{rk} is calculated as:

$s=0$;

for $r=0$ to $C-1$

for $k=0$ to $K'-L-1$

$c_{rk} = b_s$;

$s = s + 1$;

end for

if $C > 1$

The sequence $c_{r0}, c_{r1}, c_{r2}, c_{r3}, \dots, c_{r(K'-L-1)}$ is used to calculate the CRC parity bits $p_{r0}, p_{r1}, p_{r2}, \dots, p_{r(L-1)}$ according to Clause 5.1 with the generator polynomial $g_{\text{CRC24B}}(D)$.

for $k = K'-L$ to $K'-1$

$c_{rk} = p_{r(k+L-K')}$;

end for

end if

for $k = K'$ to $K-1$ -- Insertion of filler bits

$c_{rk} = \langle \text{NULL} \rangle$;

end for

end for

5.3 Channel coding

Usage of coding scheme for the different types of TrCH is shown in table 5.3-1. Usage of coding scheme for the different control information types is shown in table 5.3-2.

Table 5.3-1: Usage of channel coding scheme for TrCHs

TrCH	Coding scheme
UL-SCH	LDPC
DL-SCH	
PCH	
BCH	Polar code

Table 5.3-2: Usage of channel coding scheme for control information

Control Information	Coding scheme
DCI	Polar code
UCI	Block code
	Polar code