

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures –

Part 6: Effectiveness of residual current devices (RCD) in TT, TN and IT systems

[IEC 61557-6:2019](https://standards.iteh.ai/catalog/standards/sist/ba2a98c6-997d-4668-a95a-6330a86c-1521/iec-61557-6-2019)

Sécurité électrique dans les réseaux de distribution basse tension au plus égale à 1 000 V c.a. et 1 500 V c.c. – Dispositifs de contrôle, de mesure ou de surveillance de mesures de protection –

Partie 6: Efficacité des dispositifs à courant différentiel résiduel (DDR) dans les réseaux TT, TN et IT



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2019 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

67 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures –

Part 6: Effectiveness of residual current devices (RCD) in TT, TN and IT systems

<https://standards.iteh.ai/catalog/standards/sist/ba2a98c6-997d-4668-a95a-75482019701a-61557-6-2012>

Sécurité électrique dans les réseaux de distribution basse tension au plus égale à 1 000 V c.a. et 1 500 V c.c. – Dispositifs de contrôle, de mesure ou de surveillance de mesures de protection –

Partie 6: Efficacité des dispositifs à courant différentiel résiduel (DDR) dans les réseaux TT, TN et IT

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 17.220.20; 29.080.01; 29.240.01

ISBN 978-2-8322-7160-5

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	5
4 Requirements	6
4.1 General	6
4.2 Functions	7
4.2.1 Measurement of trip current	7
4.2.2 Non-tripping functions	7
4.2.3 Fault voltage indication	8
4.2.4 Measurement of trip time	8
4.3 Measurement with indicators	8
4.4 Test with rated residual operating current	9
4.5 Fault voltages exceeding U_L	9
4.6 Overvoltage	9
5 Marking and operating instructions	9
5.1 Marking	9
5.2 Explicit indication of the waveform of the testing current	9
5.3 Operating instructions	10
6 Tests	10
6.1 General	10
6.2 Operating uncertainty	11
6.3 Fault voltage	12
6.4 Testing the connection to voltages higher than nominal voltage	12
6.5 Overvoltage	12
Annex A (informative) Applicable tripping tests (time and current) for different types of RCDs	13
Bibliography	14
Table 1 – Calculation of operating uncertainty	11
Table A.1 – Tripping tests for different types of RCD	13

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ELECTRICAL SAFETY IN LOW VOLTAGE DISTRIBUTION SYSTEMS UP TO
1 000 V AC AND 1 500 V DC – EQUIPMENT FOR TESTING, MEASURING
OR MONITORING OF PROTECTIVE MEASURES –****Part 6: Effectiveness of residual current devices (RCD)
in TT, TN and IT systems**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61557-6 has been prepared by IEC technical committee 85: Measuring equipment for electrical and electromagnetic quantities.

This third edition cancels and replaces the second edition published in 2007. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) addition of requirements for testing a new type of RCD;
- b) addition of requirements for type B RCDs (former Annex B);
- c) addition of new Annex B on recommended tripping times;

d) alignment of the structure with that of the whole IEC 61557 series.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
85/ 684/FDIS	85/ 697/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

This International Standard is to be used in conjunction with IEC 61557-1:2019.

A list of all parts in the IEC 61557 series, published under the general title *Electrical safety in low voltage distribution systems up to 1 000 V AC and 1 500 V DC – Equipment for testing, measuring or monitoring of protective measures*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

IEC 61557-6:2019

<https://standards.iteh.ai/catalog/standards/sist/ba2a98c6-997d-4668-a95a-75bbfb693ff6/iec-61557-6-2019>

ELECTRICAL SAFETY IN LOW VOLTAGE DISTRIBUTION SYSTEMS UP TO 1 000 V AC AND 1 500 V DC – EQUIPMENT FOR TESTING, MEASURING OR MONITORING OF PROTECTIVE MEASURES –

Part 6: Effectiveness of residual current devices (RCD) in TT, TN and IT systems

1 Scope

This part of IEC 61557 specifies the requirements applicable to measuring equipment for testing the effectiveness of protective measures of residual current devices (RCD) installed in TT, TN and IT systems.

It is not the purpose of this document to verify the RCD according to their product standards.

NOTE Applicable tripping tests for time and current of RCD are listed in Annex A, Table A.1.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61010-1:2010, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 1: General requirements*
IEC 61010-1:2010/AMD1:2016¹

IEC 61010-2-030:2017, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 2-030: Particular requirements for equipment having testing or measuring circuits*

IEC 61010-031, *Safety requirements for electrical equipment for measurement, control and laboratory use – Part 031: Safety requirements for hand-held and hand-manipulated probe assemblies for electrical test and measurement*

IEC 61557-1:2019, *Electrical safety in low voltage distribution systems up to 1 000 V AC and 1 500 V DC – Equipment for testing, measuring or monitoring of protective measures – Part 1: General requirements*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 61557-1 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>

¹ A consolidated version of this publication exists, comprising IEC 61010-1:2010 and IEC 61010-1:2010/AMD1:2016.

- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1

earth fault current

current flowing to earth due to an insulation fault

[SOURCE: IEC 60050-442:1998, 442-01-23]

3.2

residual current

I_{Δ}

RMS value of the vector sum of the currents flowing through the main circuit of the residual current device

[SOURCE: IEC 60050-442:1998, 442-05-19, modified – in alignment with the use in this document. The symbol has been modified.]

3.3

rated residual operating current

$I_{\Delta n}$

fault current for which the residual current is designed

3.4

residual operating current

I_a

value of residual current which causes the residual current device to operate under specified conditions

[SOURCE: IEC 60050-442:1998, 442-05-20, modified – The symbol has been added.]

3.5

leakage current

electric current in an unwanted conductive path to earth under normal operating conditions

[SOURCE: IEC 60050-195:1998, 195-05-15, modified – "to earth" has been added and the deprecated term "earth current" omitted.]

3.6

test resistance

R_p

resistance by means of which a fault current for test purposes is produced

3.7

resistance to earth

resistance to ground, US

real part of the impedance to earth

[SOURCE: IEC 60050-195:1998, 195-01-18]

4 Requirements

4.1 General

In addition to the requirements of IEC 61557-1:2019, Clause 4, the requirements of Clause 4 of this document shall apply.

Test leads and test probes used with this measuring equipment shall fulfil the requirements of IEC 61010-031.

Equipment intended for making measurements on distribution systems shall, at the minimum, be rated for measurement category III in accordance with IEC 61010-2-030.

Equipment intended for making measurements on electrical equipment shall, at the minimum, be rated for measurement category II in accordance with IEC 61010-2-030.

4.2 Functions

4.2.1 Measurement of trip current

The measuring equipment shall be capable of indicating if and when the residual operating current of the protective device is less than or equal to the rated residual operating current.

The tests shall be carried out with a sinusoidal, or mains-derived quasi sinusoidal test current.

The operating uncertainty of the test currents, determined in accordance with Table 1, shall not exceed (the rated residual operating current) +10 %.

The operating uncertainty of measurement of the residual operating current, determined in accordance with Table 1, shall not exceed ± 10 % of the rated residual operating current.

If the measuring equipment is provided for the purpose of testing residual current devices (RCD) of 30 mA or below, installed for supplementary protection, the measuring equipment shall be capable of providing a test of 5 times the rated residual operating current. The test period shall be limited to 40 ms. When measuring the trip time, this limit of test period need not be applied so long as the fault voltage remains below the touch voltage limit.

If the measuring equipment is capable of producing half-wave test currents, testing of pulse current sensitive RCDs may alternatively be carried out using half-wave test currents. In this case, test equipment shall be able to test in both polarities.

If the measuring equipment includes a test intended to be applied to residual current devices (RCD) type B, the test current shall be an increasing smooth direct residual current.

NOTE A smooth direct current is a current with less than 10 % AC ripple (peak to peak).

If the test current increases linearly, the rate of increase shall not be greater than 2 times $I_{\Delta n}$ in 5 s. If the test current increases in steps, the increase per step shall not be more than 2 times $I_{\Delta n}/30$ and the rate of increase shall not be greater than 2 times $I_{\Delta n}$ in 5 s.

It shall be possible to test with both polarities of the test current. The operating uncertainty of the measurement of the residual current shall not exceed ± 10 % of the rated residual operating current and the operating uncertainty of the maximum value of the increasing test current shall not exceed (2 times the rated residual operating current) +10 %.

4.2.2 Non-tripping functions

When a test at 50 % or less of the rated residual operating current is included to test the immunity of the RCD to nuisance tripping, the minimum test period for general type RCDs shall be 0,3 s and for type S RCDs, it shall be 0,5 s. The protective device shall not operate.

When a non-trip test at 50 % or less of the rated residual operating current is included, the operating uncertainty of the calibrated test current shall be in the range between 0 % and –10 % of the specified non-tripping test current in accordance with Table 1.

If the purpose of the test is to evaluate other parameters (e.g. fault voltage) the minimum test period may be shorter but not less than one cycle of the rated frequency.

4.2.3 Fault voltage indication

The measuring equipment shall be capable of indicating whether the fault voltage at the rated residual operating current of the protective device is less than or equal to the conventional touch voltage limit. The test may be carried out with or without a probe.

Indication may be provided by displaying the value of the fault voltage or by the use of other clear indicators.

If the value of the fault voltage or the indication for the fault current (shown on a display or otherwise indicated) show the value for the residual current and not for the rated residual operating current, this shall be indicated on the display or on the measuring equipment. Otherwise the fault voltage shall be calculated according to Equation 1:

$$U_F \leq U_L \times \frac{I_a}{I_{\Delta n}} \quad (1)$$

where

U_F is the fault voltage;

U_L is the conventional touch voltage limit;

$I_{\Delta n}$ is the rated residual operating current;

I_a is the residual operating current.

The operating uncertainty of the fault voltage measurement, determined in accordance with Table 1, shall be in the range of 0 % and +20 % with the conventional touch voltage limit as fiducial value.

The internal resistance of the voltage measuring equipment should be at least 0,7 kΩ/V of the full-scale value of the measurement range. The influence of the voltage measurement on the measurement of the fault current should be taken into consideration.

4.2.4 Measurement of trip time

The measuring equipment shall be capable of measuring the trip time of residual current devices (RCD) at the rated residual operating current or shall be capable of indicating the compliance with the maximum permissible trip time. As a minimum, the test equipment shall include a test with a sinusoidal test current.

When measuring the trip time, the operating uncertainty shall not exceed ±10 % with the maximum permissible trip time as fiducial value and the influence quantities according to Table 1.

If trip times are measured with different waveforms, the manufacturer should provide guidance on the interpretation of the results in the operating instructions.

4.3 Measurement with indicators

On measuring equipment with indicators, the threshold value of the indicators shall be the value for the calculation of uncertainties.

4.4 Test with rated residual operating current

When testing with the rated residual operating current, the following conditions shall be met:

- the test current shall be switched on during a zero crossing;
- the starting phase of the test current shall be indicated to the user;
- the test period shall be limited to the maximum allowed trip time of the residual current device (RCD) under test. When measuring the trip time, these limits of the test periods need not be applied.

4.5 Fault voltages exceeding U_L

Prevention of danger due to fault voltages exceeding U_L within the system under test shall be ensured during measurements. This can be achieved as follows:

- automatic disconnection in accordance with IEC 61010-1:2010/AMD1:2016, Figure 2, when fault voltages $> U_L$ occur;
- use of test resistances R_p adjustable in steps, or continuously, in such a manner that the test is started with a resistance that permits a maximum current of 3,5 mA to flow when all parallel-connected circuits are included. An unambiguous detection shall be ensured, for example by means of a voltmeter, to determine whether this test resistance can be varied without producing a hazardous fault voltage.

If the measuring equipment indicates the value of the voltage at its measuring terminals, it shall also indicate if the system voltage exists and if the live conductor is exchanged with the protective conductor.

4.6 Overvoltage

The user shall not be exposed to danger and the equipment shall not be damaged when the measuring equipment is connected for at least 10 min to 120 % of the nominal voltage of the distribution system for which the measuring equipment has been designed. Protective devices shall not be activated.

The user shall not be exposed to danger and the measuring equipment shall not be damaged when the measuring equipment is accidentally connected for at least 1 min with up to 173 % of its rated voltage to earth. Protective devices may be activated.

5 Marking and operating instructions

5.1 Marking

In addition to IEC 61557-1:2019, 5.1 and 5.2, the following information shall be provided on the measuring equipment.

The rated residual operating current or rated residual operating currents of the residual current device (RCD) for which the measuring equipment has been designed shall be marked.

The maximum voltage to earth and the rated measuring category shall be marked.

5.2 Explicit indication of the waveform of the testing current

The measuring equipment shall contain the indication that in the case of a half wave testing current or DC testing current, the tripping test shall be carried out in both directions (see Annex A for tripping test for different types of RCD). Where there is insufficient space, the warning symbol according to IEC 61010-1:2010, Table 1 symbol 14 shall be marked adjacent to the RCD function or a warning shall be given on the display.

5.3 Operating instructions

In addition to IEC 61557-1:2019, 5.3, the operating instructions shall include the following information.

- Where the measuring circuit has no probe and a voltage present between the protective conductor and earth will influence the measurements, a warning shall be included.
- Where the measuring circuit uses the N-conductor as a probe, a warning shall be given to test the connection between the neutral point of the distribution system and earth before the test is started; a possible voltage between the N-conductor and the earth may influence the measurements.
- A warning that leakage currents in the circuit following the residual current device (RCD) may influence the measurements.
- Where the fault voltage is indicated by the test equipment, a clear statement shall be given as to whether the voltage relates to the rated residual operating current or to the residual operating current of the protective device. If applicable, a note to fulfil the conditions of 4.2.3 shall also be included.
- A statement that the earth electrode resistance of a measuring circuit with a probe shall not exceed a value to be stated by the manufacturer.
- A warning, that when using a probe, the potential fields of other earthing installations may influence the measurement.
- A warning that special conditions in residual current devices (RCD) of a particular design, for example of type S (selective and resistant to impulse currents) shall be taken into consideration.
- A warning that equipment in the circuit following the residual current device (RCD) may cause a considerable extension of the operating time. Examples of such equipment might be connected capacitors or running motors.

IEC 61557-6:2019
<https://standards.iteh.ai/catalog/standards/sist/ba2a98c6-997d-4668-a95a-75bbfb693ff6/iec-61557-6-2019>

6 Tests

6.1 General

In addition to IEC 61557-1:2019, Clause 6, the tests in Clause 6 of this document shall be performed.

These tests shall be performed at all rated residual operating currents and in addition at 50 % and 500 % of the rated residual operating current, if applicable.

The test circuit shall be adapted to test both at the limits of the fault voltage for which the equipment is designed and at the appropriate total earthing resistance $R_A = R_{Amax}$ for each range.

The test circuit shall be adapted to each test method employed. The manufacturer's data shall be observed.

NOTE The maximum earthing resistance is derived from:

$$R_{Amax} = \frac{U_L}{I_{\Delta n}}$$

where

U_L is the conventional touch voltage limit;

$I_{\Delta n}$ is the rated residual operating current.