

INTERNATIONAL STANDARD



**Fibre optics – Multimode launch conditions –
Part 1: Launch condition requirements for measuring multimode attenuation**
PREVIEW
(standards.iteh.ai)

[IEC 62614-1:2020](https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020)

<https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2020 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

[IEC 62614-1:2020](https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020)

<https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020>

INTERNATIONAL STANDARD



**Fibre optics – Multimode launch conditions –
Part 1: Launch condition requirements for measuring multimode attenuation**

STANDARD PREVIEW
(standards.iteh.ai)

IEC 62614-1:2020
<https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.01

ISBN 978-2-8322-8398-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	3
1 Scope.....	5
2 Normative references	5
3 Terms and definitions	5
4 Background on multimode launch conditions	6
5 Test source launch	7
5.1 General.....	7
5.2 Encircled flux	7
5.3 Encircled flux template illustration.....	7
5.4 Encircled flux target for attenuation measurement.....	8
5.5 Harmonization of multimode launch conditions to eliminate wavelength bias.....	9
5.6 Uncertainties expectations	10
5.7 Encircled flux limits	10
5.8 Practical limitations of multimode launch conditions	11
Bibliography.....	12
Figure 1 – EF template illustration for 50 µm core fibre cabling at 850 nm	8
Figure 2 – Wavelength comparison	9
Table 1 – EF target for 50 µm core fibre at 850 nm	8
Table 2 – EF target for 50 µm core fibre at 1 300 nm	8
Table 3 – EF target for 62,5 µm fibre at 850 nm	9
Table 4 – EF target for 62,5 µm fibre at 1 300 nm	9
Table 5 – Attenuation, threshold tolerance and confidence level	10

STANDARD PREVIEW

(standards.iteh.ai)

IEC 62614-1:2020
https://standards.iteh.ai/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTICS – MULTIMODE LAUNCH CONDITIONS –

Part 1: Launch condition requirements for
measuring multimode attenuation

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62614-1 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics.

This first edition cancels and replaces IEC 62614, published in 2010, and constitutes a technical revision.

This edition includes the following significant technical changes with respect to IEC 62614:

- a) increase of the value of the uncertainty attenuation variation coefficient Y for 50 μm core fibre at 1 300 nm, due to launch conditions, to twice the previous value;
- b) changes to 3.4, 5.6, including Table 5, and some references to remain consistent with IEC 61280-4-1:2019;
- c) changes to multimode fibre references to be consistent with IEC 60793-2-10:2019.

The text of this International Standard is based on the following documents:

CDV	Report on voting
86C/1625/CDV	86C/1654A/RVC

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 62614 series, published under the general title *Fibre optics – Multimode launch conditions*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

iTeh STANDARD PREVIEW

(standards.iteh.ai)

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

<https://standards.iteh.ai/catalog/standards/sist/bec9b8a1-065e-47e7-9cf7-ee4a4ec52ecd/iec-62614-1-2020>

FIBRE OPTICS – MULTIMODE LAUNCH CONDITIONS –

Part 1: Launch condition requirements for measuring multimode attenuation

1 Scope

This part of IEC 62614 describes the launch condition requirements used for measuring multimode attenuation in passive components and in installed cable plants.

In this document, the fibre types that are addressed include category A1-OM_x, where $x = 2, 3, 4$ and 5 ($50\ \mu\text{m}/125\ \mu\text{m}$), and A1-OM1 ($62,5\ \mu\text{m}/125\ \mu\text{m}$) multimode fibres, as specified in IEC 60793-2-10. The nominal test wavelengths detailed are $850\ \text{nm}$ and $1\ 300\ \text{nm}$. This document can be suitable for multimode attenuation measurements for other multimode categories and/or other wavelengths, but the source condition for other categories and wavelengths are not defined here.

The purpose of these requirements is as follows:

- to ensure consistency of field measurements when different types of test equipment are used;
- to ensure consistency of factory measurements when different types of test equipment are used;
- to ensure consistency of field measurements when compared with factory measurements.

This document describes launch condition requirements for optical attenuation using sources with a controlled encircled flux (EF).

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61280-1-4, *Fibre optic communication subsystem test procedures – Part 1-4: General communication subsystems – Light source encircled flux measurement method*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1 encircled flux

EF

fraction of cumulative near-field power to the total output power as a function of radial distance from the optical centre of the core

3.2 multimode attenuation

attenuation pertaining to multimode fibres and/or multimode fibre components, systems and subsystems

3.3 reference grade launch cord

launch cords constructed with a reference grade termination at the interface to the device under test

3.4 reference grade termination

connector and plug with tightened tolerances terminated onto an optical fibre with tightened tolerances such that the expected attenuation of a connection formed by mating two such assemblies is lower and more repeatable than a standard-grade termination

Note 1 to entry: An adapter, required to assure the reduced attenuation, may be considered part of the reference grade termination where required by the test configuration.

Note 2 to entry: IEC 61755-6-2 defines reference grade terminations for 50/125 µm fibre.

4 Background on multimode launch conditions

There have been a wide range of launch conditions used for testing multimode fibre components and systems. Light sources, typically used in measuring attenuation, can produce varying modal distributions when launched into multimode fibre. These differing modal distributions, combined with the differential mode attenuation (DMA) inherent in most multimode components, commonly cause measurement variations when measuring attenuation of multimode components. For example, attenuation measurement variations can occur when two similar light sources or different launch cords are used.

Legacy (LED based) applications had a wide power budget, which in most cases masked the variance in results between the factory and field measurement. As technology has evolved, the system requirements for attenuation have become more stringent. Demanding application requirements are driving the need for accurate and reproducible multimode attenuation measurements over a variety of field-test instruments. Attenuation measurement experiments, with different instruments having the same standards compliant set up, produce measurement variations that are induced by their differing launch conditions.

Experts have concluded that the launch condition should be expressed at the interface between the test instrument launch cord and the terminated fibre to be tested. That is, the launch condition should be based in part on the measured near field at the output of the launch cord. The key to making reproducible attenuation measurements across various sources is to narrowly constrain the range of power distribution at large radii so that all compliant sources produce closely agreeing attenuation measurement results. This is because the variation in the allowed power distribution at large radii across different sources translates directly into variability of attenuation measurements. Smaller power variations enable more reproducible attenuation measurements.

5 Test source launch

5.1 General

The source launch conditions are described at the output of the reference grade launch cord. It is expected that the source and launch cord, as supplied, have been verified by the test equipment manufacturer to produce the specified launch measured according to IEC 61280-1-4. For reference grade fibre, core diameter tolerances of $\pm 0,7 \mu\text{m}$ have been evaluated with some success. Variance of other parameters, such as numerical aperture and core concentricity, need more study.

5.2 Encircled flux

The EF shall be determined from the near field measurement of the light coming from the end of the reference grade launch cord in accordance with IEC 61280-1-4.

The measured near field result is a function of the near field profile, $I(r)$, of radius r , away from the optical centre of the core, and the edge of the near field profile, R , which is used to generate the EF function as shown in Formula (1):

$$EF(r) = \frac{\int_0^r xI(x) dx}{\int_0^R xI(x) dx} \quad (1)$$

iTeh STANDARD PREVIEW
(standards.iteh.ai)

5.3 Encircled flux template illustration

An illustration of an EF template is shown in Figure 1. A target EF value for a set of particular radial control points is defined. Upper and lower limit of EF values for a set of particular radial control points may also be defined. A compliant launch is a launch that falls within the template at the particular radial control points.