

INTERNATIONAL STANDARD



Low-voltage fuses –
Part 4: Supplementary requirements for fuse-links for the protection of
semiconductor devices

iTeh Standards
(<https://standards.itih.ai>)
Document Preview

[IEC 60269-4:2024](#)

<https://standards.itih.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

International
Standards
iteh.ai
Document Preview

[IEC 60269-4:2024](https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024)

<https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>



IEC 60269-4

Edition 6.0 2024-08
COMMENTED VERSION

INTERNATIONAL STANDARD



Low-voltage fuses –
Part 4: Supplementary requirements for fuse-links for the protection of
semiconductor devices

iTeh Standards
<https://standards.itih.ai>
Document Preview

[IEC 60269-4:2024](https://standards.itih.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024)

<https://standards.itih.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.120.50

ISBN 978-2-8322-9552-6

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	4
1 General Scope	7
2 Normative references	8
3 Terms and definitions	8
4 Conditions for operation in service	9
5 Classification	11
6 Characteristics of fuses	11
7 Markings	16
8 Standard conditions for construction	16
9 Tests	17
Annex AA (informative) Guidance for the coordination of fuse-links with semiconductor devices	29
Annex BB (normative) Survey on information to be supplied by the manufacturer in his literature (catalogue) or on request for a fuse designed for the protection of semiconductor devices	35
Annex CC (normative) Examples of standardized fuse-links for the protection of semiconductor devices	36
Bibliography	55
List of comments	56
<div style="color: red; font-size: 1.2em; font-weight: bold;"> <p>Figure 101 – Conventional overload curve (example) (X and Y are points of verified overload capability)</p> </div>	
Figure 101 – Example of a conventional test arrangement for bolted fuse-links	27
Figure 102 – Example of a conventional test arrangement for blade contact fuse-links	28
Figure CC.1 – Single body fuse-links	37
Figure CC.2 – Double body fuse-links	38
Figure CC.3 – Twin body fuse-links	39
Figure CC.4 – Striker fuse-links	39
Figure CC.5 – Fuse-links with bolted connections, type B, body sizes 000 and 00	42
Figure CC.6 – Fuse-links with bolted connections, type B, body sizes 0, 1, 2 and 3	44
Figure CC.7 – Bolted fuse-links, type C	46
Figure CC.8 – Flush end fuse-links, type A	48
Figure CC.9 – Flush end fuse-links, type B	50
Figure CC.10 – Fuse-links with cylindrical contact caps, type A	51
Figure CC.11 – Fuse-links with cylindrical contact caps, type B	53
Figure CC.12 – Fuse-links with cylindrical contact caps with striker, type B (additional dimensions for all sizes except 10 × 38)	54
Table 101 – Conventional time and current for "gR" and "gS" fuse-links	13
Table 102 – List of complete tests	18
Table 103 – Survey of tests on fuse-links of the smallest rated current of a homogeneous series	18
Table 107 – Cross-sectional area of copper conductors for high current ratings tests	19
Table 104 – Values for breaking-capacity tests on AC fuses	23

Table 105 – Values for breaking-capacity tests on DC fuses.....	24
Table 106 – Values for breaking-capacity tests on VSI fuse-links.....	24
Table CC.1 – Conventional time and current for "gR" and "gS" fuse links.....
Table CC.2 – Conventional time and current for "gR" and "gS" fuse links.....
Table CC.4 – Conventional time and current for "gR" and "gS" fuse links.....
Table CC.1 – Typical rated voltages and preferred maximum rated currents.....	52

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60269-4:2024](https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024)

<https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE FUSES –

**Part 4: Supplementary requirements for fuse-links
for the protection of semiconductor devices**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This commented version (CMV) of the official standard IEC 60269-4:2024 edition 6.0 allows the user to identify the changes made to the previous IEC 60269-4:2009+AMD1:2012+AMD2:2016 CSV edition 5.2. Furthermore, comments from IEC SC 32B experts are provided to explain the reasons of the most relevant changes, or to clarify any part of the content.

A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text. Experts' comments are identified by a blue-background number. Mouse over a number to display a pop-up note with the comment.

This publication contains the CMV and the official standard. The full list of comments is available at the end of the CMV.

IEC 60269-4 has been prepared by subcommittee 32B: Low-voltage fuses, of IEC technical committee 32: Fuses. It is an International Standard.

This sixth edition cancels and replaces the fifth edition published in 2009, Amendment 1:2012 and Amendment 2:2016. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) the introduction of voltage source inverter fuse-links, including test requirements.
- b) coverage of the tests on operating characteristics for AC. by the breaking capacity tests.
- c) the updating of examples of standardised fuse-links for the protection of semiconductor devices.

The text of this International Standard is based on the following documents:

Draft	Report on voting
32B/746/FDIS	32B/753/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

This part is to be used in conjunction with IEC 60269-1:2024, *Low-voltage fuses – Part 1: General requirements*.

This Part 4 supplements or modifies the corresponding clauses or subclauses of Part 1.

Where no change is necessary, this Part 4 indicates that the relevant clause or subclause applies.

Tables and figures which are additional to those in Part 1 are numbered starting from 101.

Additional annexes are lettered AA, BB, etc.

A list of all parts of the IEC 60269 series, under the general title: *Low-voltage fuses*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

iTeh Standards
(<https://standards.itih.ai>)
Document Preview

[IEC 60269-4:2024](#)

<https://standards.itih.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>

LOW-VOLTAGE FUSES –

Part 4: Supplementary requirements for fuse-links for the protection of semiconductor devices

1 ~~General Scope~~ 1

IEC 60269-1 applies with the following supplementary requirements.

Fuse-links for the protection of semiconductor devices shall comply with all requirements of IEC 60269-1, if not otherwise indicated hereinafter, and shall also comply with the supplementary requirements laid down below.

~~1.1 Scope and object~~

These supplementary requirements apply to fuse-links for application in equipment containing semiconductor devices for circuits of nominal voltages up to 1 000 V AC or 1 500 V DC ~~and also, in so far as they are applicable, for circuits of higher nominal voltages~~. For some fuse-links higher rated voltages can be used. 2

~~NOTE 1~~ Such fuse-links are commonly referred to as "semiconductor fuse-links".

~~NOTE 2~~ In most cases, a part of the associated equipment serves the purpose of a fuse base. Owing to the great variety of equipment, no general rules can be given; the suitability of the associated equipment to serve as a fuse base should be subject to agreement between the manufacturer and the user. However, if separate fuse bases or fuse holders are used, they should comply with the appropriate requirements of IEC 60269-1.

~~NOTE 3~~ IEC 60269-6 (Low-voltage fuses – Part 6: Supplementary requirements for fuse-links for the protection of solar photovoltaic energy systems) is dedicated to the protection of solar photovoltaic energy systems.

~~NOTE 4~~ These fuse links are intended for use on systems employing the standardized voltages and tolerances of IEC 60038. Tests carried out on fuse links in accordance with previous editions of this standard shall remain valid until such time as complementary equipment has evolved to the standardized voltages and tolerances of IEC 60038. 3

The object of these supplementary requirements is to establish the characteristics of semiconductor fuse-links in such a way that they can be replaced by other fuse-links having the same characteristics, provided that their dimensions are identical. For this purpose, this standard refers in particular to

- a) the following characteristics of fuses:
 - 1) their rated values
 - 2) their temperature rises in normal service
 - 3) their power dissipation
 - 4) their time-current characteristics
 - 5) their breaking capacity
 - 6) their cut-off current characteristics and their I^2t characteristics
 - 7) their arc voltage characteristics
- b) type tests for verification of the characteristics of fuses
- c) the markings on fuses
- d) availability and presentation of technical data (see Annex BB).

2 Normative references 4

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60269-1:2024, *Low-voltage fuses – Part 1: General requirements*

IEC 60269-2:2013, *Low-voltage fuses – Part 2: Supplementary requirements for fuses for use by authorized persons (fuses mainly for industrial application) – Examples of standardized systems of fuses A to K*

IEC 60269-2:2013/AMD1:2016

IEC 60269-2:2013/AMD2:2024

~~IEC 60269-3, *Low-voltage fuses – Supplementary requirements for fuses for use by unskilled persons (fuses mainly for household and similar applications) – Examples of standardized systems of fuses A to F*~~

IEC TR 60269-5:2014, *Low-voltage fuses – Part 5: Guidance for the application of low-voltage fuses*

IEC TR 60269-5:2014/AMD1:2020

~~IEC 60269-6, *Low-voltage fuses – Part 6: Supplementary requirements for fuse links for the protection of solar photovoltaic energy systems*~~

IEC 60417, *Graphical symbols for use on equipment*

~~IEC 60664-1:2000, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*~~

ISO 3, *Preferred numbers – Series of preferred numbers*

3 Terms and definitions

IEC 60269-1 applies with the following supplementary definitions.

3.2 General terms

3.2.101

semiconductor device

device whose essential characteristics are due to the flow of charge carriers within a semiconductor.

[SOURCE: IEC 60050-521:2002, 521-04-01]

3.2.102

semiconductor fuse-link

current-limiting fuse-link capable of breaking, under specific conditions, any current value within the breaking range (see 8.4)

3.2.103

signalling device

device forming part of the fuse and signalling the fuse operation to a remote place

Note 1 to entry: A signalling device consists of a striker and an auxiliary switch. Electronic devices may also be used.

3.2.104 voltage source inverter VSI a voltage stiff inverter

Note 1 to entry: Also referred to as a voltage stiff inverter i.e. an inverter that supplies current without any practical change in its output voltage.

[SOURCE: IEC 60050-551:1998, 551-12-11] **5**

3.2.105 voltage source inverter fuse-link VSI fuse-link

current-limiting fuse-link capable of breaking, under specified conditions, the short circuit current supplied by the discharge of a DC-link capacitor in a voltage source inverter

Note 1 to entry: The abbreviation "VSI fuse-link" is used in this document.

Note 2 to entry: A VSI fuse-link usually operates under a short circuit current supplied by the discharge of a DC-link capacitor through a very low inductance, in order to allow high frequency in normal operation. This short circuit condition leads to a very high rate of rise of current equivalent to a very low value of time constant, typically 3 ms or less. The supply voltage is DC, even though the applied voltage decreases as the current increases during the short circuit.

Note 3 to entry: In some multiple AC drive applications, individual output inverters may be remote from the main input rectifier. In these cases, the associated fault circuit impedances may influence the operation of the fuse-links. – the associated time constant and the size of the capacitors need to be considered when choosing the appropriate short circuit protection.

4 Conditions for operation in service

IEC 60269-1 applies with the following supplementary requirements.

Fuses must be only used according to their rated values. **6**

[IEC 60269-4:2024](https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024)

<https://standards.iteh.ai/catalog/standards/iec/2a40825a-c920-4c4f-9f0a-1b1ef464d810/iec-60269-4-2024>

4.5 Voltage

4.5.1 Rated voltage

For AC, the rated voltage of a fuse-link is related to the applied voltage; it is based on the RMS value of a sinusoidal AC voltage. It is further assumed that the applied voltage retains the same value throughout the operation of the fuse-link. All tests to verify the ratings are based on this assumption.

~~NOTE In many applications, the applied voltage will be sufficiently close to the sinusoidal form for the significant part of the operating time, but there are many cases where this condition is not satisfied.~~

~~The performance of a fuse-link subjected to a non-sinusoidal applied voltage can be evaluated by comparing, for the first approximation, the arithmetic mean values of the non-sinusoidal and sinusoidal applied voltages.~~ **7**

For DC and VSI fuse-links, the rated voltage of a fuse-link is related to the applied voltage. It is based on the mean value. When DC is obtained by rectifying AC, the ripple is assumed not to cause a variation of more than 5 % above or 9 % below the mean value.

4.5.2 Applied voltage in service

Under service conditions, the applied voltage is that voltage which, in the fault circuit, causes the current to increase to such proportions that the fuse-link will operate.

For AC, consequently, the value of the applied voltage in a single-phase AC circuit is usually identical to the power-frequency recovery voltage. For all cases other than the sinusoidal AC voltage, it is necessary to know the applied voltage as a function of time.

For a unidirectional voltage and for VSI fuse-links, the important values are:

- the average value over the entire period of the operation of the fuse-link;
- the instantaneous value near the end of the arcing period.

4.6 Current

The rated current of a semiconductor fuse-link is based on the RMS value of a sinusoidal AC current at rated frequency.

For DC, the RMS value of current is assumed not to exceed the RMS value based on a sinusoidal AC current at rated frequency.

NOTE The thermal response time of the fuse-element may be so short that it cannot be assumed that operation under conditions which deviate much from sinusoidal current can be estimated on the basis of the RMS current alone. This is so, in particular at lower frequency values and when the current presents salient peaks separated by appreciable intervals of insignificant current; for example, in the case of frequency converters and traction applications.

4.7 Frequency, power factor and time constant

4.7.1 Frequency

The rated frequency refers to the frequency of the sinusoidal current and voltage that form the basis of the type tests.

~~NOTE In particular, where service frequency deviates significantly from rated frequency the manufacturer should be consulted.~~

4.7.3 Time constant (τ)

For DC, the time constants expected in practice are considered to correspond to those in Table 105.

~~NOTE 1 Some service conditions may be found which exceed the specified performance shown in the table as regards time constant. In such a case, a design of fuse link which has been tested and marked accordingly should be used or the suitability of such a fuse link be subject to agreement between manufacturer and user. In some service conditions, the time constant is significantly lower than the values stated in the table. In such a case, the applied voltage can be higher than the rated voltage defined according to Table 105.~~ **8**

For VSI fuse-links, equivalent time constants expected in practice are considered to correspond to those in Table 106.

NOTE 2 The high rate of rise of short circuit current is due to the low inductance, which is considered to be equivalent to a low time constant.

NOTE 3 Instead of time constant di/dt can be used in case of short circuit condition.

$$di/dt = E/L.$$

E = voltage value of the DC power source,

L = total inductance of the capacitor discharge circuit.

~~3.10 Temperature inside an enclosure~~ **9**

~~Since the rated values of the fuse-links are based on specified conditions that do not always correspond to those prevailing at the point of installation, including the local air conditions, the user may have to consult the manufacturer concerning the possible need for re-rating.~~

5 Classification

IEC 60269-1 applies.

6 Characteristics of fuses

IEC 60269-1 applies with the following supplementary requirements.

6.1 Summary of characteristics

6.1.3 Fuse-links

- a) Rated voltage (see 6.2)
- b) Rated current (see 6.3 of IEC 60269-1:2024)
- c) Kind of current and frequency (see 6.4 of IEC 60269-1:2024)
- d) Rated power dissipation (see 6.5 of IEC 60269-1:2024)
- e) Time-current characteristics (see 6.6)
- f) Breaking range (see 6.7.1 of IEC 60269-1:2024)
- g) Rated breaking capacity (see 6.7.2 of IEC 60269-1:2024)
- h) Cut-off current characteristics (see 6.8.2)
- i) I^2t characteristics (see 6.8.3)
- j) Dimensions or size (if applicable)
- k) Arc voltage characteristics (see 6.9)
- l) Fuse-links may only be used with the fuse-base and/or fuse-holder assigned by the manufacturer and defined in the manufacturer's instructions **10**

6.2 Rated voltage

For rated AC voltages up to 690 V and DC voltages up to 750 V, IEC 60269-1 applies; for higher voltages, the values shall be selected from the R 5 series or, where not possible, from the R 10 series of ISO 3.

A fuse-link shall have an AC voltage rating or a DC voltage rating or a VSI voltage rating. It may have one or more of these voltage ratings.

6.4 Rated frequency

The rated frequency is that frequency to which the performance data are related.

6.5 Rated power dissipation of the fuse-link and rated acceptable power dissipation of a fuse-holder **11**

In addition to the requirements of IEC 60269-1, the manufacturer shall indicate the power dissipation as a function of current for the range 50 % to 100 % of the rated current ~~or for 50 %, 63 %, 80 % and 100 % of the rated current.~~ **12**

NOTE—In cases where the resistance of the fuse-link is of interest, this resistance should be determined from the functional relation between the power dissipation and the associated value of current.

6.6 Limits of time-current characteristics

6.6.2 Time-current characteristics, time-current zones

6.6.2.1 General requirements

The time-current characteristics depend on the design of the fuse-link, and, for a given fuse-link, on the ambient air temperature and the cooling conditions.

The manufacturer shall provide time-current characteristics based on an ambient temperature of 20 °C to 25 °C in accordance with the conditions specified in 9.3. The time-current characteristics of interest are the pre-arcing characteristic and operating characteristics.

For AC, the time-current characteristics are stated at rated frequency and for pre-arcing or operating times longer than 0,1 s.

For DC, they are stated for time constants according to Table 105 and for pre-arcing or operating times longer than 15τ .

For the higher values of prospective current (shorter times), the same information shall be presented in the form of I^2t characteristics (see 6.8.2).

6.6.2.2 Pre-arcing time-current characteristics

For AC, the pre-arcing time-current characteristic shall be based on a symmetrical AC current of a stated value of frequency (rated frequency).

For DC, the pre-arcing time-current characteristic is of particular significance for times exceeding 15τ for the relevant circuit, and is identical to the AC pre-arcing time-current characteristic in this zone.

NOTE 1 Because of the wide range of circuit time constants likely to be experienced in service, the information for times shorter than 15τ is conveniently expressed as a pre-arcing I^2t characteristic.

NOTE 2 The value of 15τ has been chosen to avoid the effects which different rates of rise of current have on the pre-arcing time-current characteristic at shorter times.

6.6.2.3 Operating time-current characteristics

For AC with times longer than 0,1 s and for DC with times longer than 15τ , the arcing period is negligible compared to the pre-arcing time. The operating time is then equivalent to the pre-arcing time.

6.6.3 Conventional times and currents

6.6.3.1 Conventional times and currents for "aR" fuse-links

See 8.4 and Table 101. **13**

6.6.3.2 Conventional times and currents for "gR" and "gS" fuse-links

The conventional times and currents are given in Table 101.