

INTERNATIONAL STANDARD



**Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –
Part 1: General and guidance**

Document Preview

[IEC 61300-1:2022](#)

<https://standards.iteh.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022>





THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2022 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

International Standards
standards.iteh.ai
Document Preview

[IEC 61300-1:2022](https://standards.iteh.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022)

<https://standards.iteh.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022>



IEC 61300-1

Edition 5.0 2022-04
REDLINE VERSION

INTERNATIONAL STANDARD



**Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –
Part 1: General and guidance**

Document Preview

[IEC 61300-1:2022](https://standards.iteh.ai/)

<https://standards.iteh.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.20

ISBN 978-2-8322-4943-7

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	4
INTRODUCTION	6
1 Scope	7
2 Normative references	7
3 Terms, definitions and abbreviated terms	8
3.1 Terms and definitions	8
3.2 Abbreviated terms	11
4 Requirements for IEC 61300-2 (all parts) and IEC 61300-3 (all parts)	11
4.1 Requirements for IEC 61300-2 (all parts) (tests)	11
4.2 Requirements for IEC 61300-3 (all parts) (examinations and measurement procedures)	12
4.2.1 General requirements	12
4.2.2 Requirements for attenuation variation	12
5 Standard atmospheric conditions	12
6 Significance of the numerical value of a quantity	13
6.1 General	13
6.2 Quantity expressed as nominal value with tolerance	13
6.3 Quantity expressed as a range of values	14
7 Graphical symbols and terminology	14
8 Safety	14
9 Calibration	15
9.1 General	15
9.2 Round robin calibration procedure	15
10 Launch conditions	15
10.1 General	15
10.2 Multimode launch conditions for A1b fibre A1 fibres	15
10.3 Multimode launch conditions for A3e fibre	16
10.4 Multimode launch conditions for the other multimode fibres	17
10.5 Single-mode launch conditions	17
10.6 Multimode planar waveguide launch conditions	17
Annex A (normative) Multimode launch condition requirement for measuring attenuation of components terminated on IEC 60793-2-10 type A1a and A1b A1 fibres	18
A.1 General	18
A.2 Technical background	18
A.3 EF template	18
A.3.1 Applicable types of optical fibres	18
A.3.2 Encircled flux	18
A.3.3 EF template example	18
A.4 Target launch and upper and lower tolerance bands for attenuation measurements of A1a A1-OM2 to A1-OM5 and A1b A1-OM1 optical fibre connections	19
A.4.1 General	19
A.4.2 Limits on EF	19
Annex B (normative) Multimode launch condition requirement for measuring attenuation of components terminated on IEC 60793-2-30 type A3e fibres	21

B.1	EAF template	21
B.1.1	Applicable types of optical fibres	21
B.1.2	Encircled angular flux	21
B.1.3	EAF template example.....	21
B.2	Target launch and upper and lower tolerance bands for attenuation measurements of A3e optical fibre connections.....	21
B.2.1	General	21
B.2.2	Limits on EAF	22
	Bibliography.....	23
	Figure A.1 – Encircled flux template example.....	19
	Figure B.1 – Encircled angular flux template example	21
	Table 1 – Standard atmospheric conditions.....	12
	Table 2 – Expected uncertainty for measured attenuation of single connections for A1b fibre variation of attenuation due to mode variation of single connections for A1-OM2, A1-OM3, A1-OM4 and A1-OM5 fibres	16
	Table 3 – Expected uncertainty for measured variation of attenuation due to mode variation of single connections for A3e fibre.....	16
	Table A.1 – EF requirements for 50 µm core fibre at 850 nm	19
	Table A.2 – EF requirements for 50 µm core fibre at 1 300 nm.....	20
	Table A.3 – EF requirements for 62,5 µm fibre at 850 nm	20
	Table A.4 – EF requirements for 62,5 µm fibre at 1 300 nm	20
	Table B.1 – EAF requirements for NA of 0,37 and 200 µm core fibre at 850 nm	22

IEC 61300-1:2022

<https://standards.itech.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**FIBRE OPTIC INTERCONNECTING
DEVICES AND PASSIVE COMPONENTS –
BASIC TEST AND MEASUREMENT PROCEDURES –****Part 1: General and guidance****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 61300-1:2022. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 61300-1 has been prepared by subcommittee 86B: Fibre optic interconnecting devices and passive components, of IEC technical committee 86: Fibre optics. It is an International Standard.

This fifth edition cancels and replaces the fourth edition published in 2016. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) addition of the information of measurement uncertainties in 4.2.1;
- b) change of the requirements for attenuation variation in 4.2.2;
- c) addition of the multimode launch conditions of other fibres than A1-OM2, A1-OM3, A1-OM4, A1-OM5 and A3e in 10.4;
- d) addition of the multimode launch conditions of the planar waveguide in 10.6;
- e) splitting Annex A for EF and Annex B for EAF;
- f) correction of errors in the definitions of encircled flux and encircled angular flux.

The text of this International Standard is based on the following documents:

Draft	Report on voting
86B/4582/FDIS	86B/4602/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61300 series, published under the general title, *Fibre optic interconnecting and passive components – Basic test and measurement procedures*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The publications in IEC 61300 series [1]¹ contain information on mechanical and environmental testing procedures and measurement procedures relating to fibre optic interconnecting devices and passive components. They are intended to be used to achieve uniformity and reproducibility in environmental testing procedures and measurement procedures.

The term "test procedure" refers to procedures commonly known as mechanical and environmental tests. The expressions "environmental conditioning" and "environmental testing" refer to the environments to which components or equipment may be exposed so that an assessment may be made of their performance under the conditions of use, transport and storage.

The term "measurement procedure" refers to those measurements which are necessary to assess the physical and optical characteristics of a component and may also be used before, during or after a test procedure to measure the effects of environmental conditioning or testing. The return loss and attenuation tests are examples of measurement procedures.

The requirements for the performance of components or equipment subjected to the test and measurement procedures described in this document are not included. The relevant specification for the device under test defines the allowed performance limits.

When drafting a specification or purchase contract, only those tests which are necessary for the relevant components or equipment taking into account the technical and economic aspects should be specified.

The mechanical and environmental test procedures are contained in IEC 61300-2 (all parts) and the measurement procedures in IEC 61300-3 (all parts). Each test or measurement procedure is published as a stand-alone publication so that it may be modified, expanded or cancelled without having an effect on any other test or measurement procedure. However, it should be noted that, where practical, reference is made to other standards as opposed to repeating all or part of already existing standards. As an example, the cold test for fibre optic apparatus refers to IEC 60068-2-1 [2], but it also provides other needed information such as purpose, recommended severities and a list of items to be specified.

Multiple methods may be contained in a test or measurement procedure. As an example, several methods of measuring attenuation are contained in the attenuation measurement procedure.

If more than one method is contained in a test or measurement procedure, the reference method may be identified.

The tests in this document permit the performance of components or equipment to be compared. To assess the overall quality of a production lot, the test procedures should be applied in accordance with a suitable sampling plan and may be supplemented by appropriate additional tests, if necessary.

To provide tests appropriate to the different intensities of an environmental condition, some of the test procedures have a number of degrees of severity. These different degrees of severity are obtained by varying the time, temperature or some other determining factor separately or in combination.

¹ Numbers in square bracket refer to the Bibliography.

FIBRE OPTIC INTERCONNECTING DEVICES AND PASSIVE COMPONENTS – BASIC TEST AND MEASUREMENT PROCEDURES –

Part 1: General and guidance

1 Scope

This part of IEC 61300 provides general information and guidance for the basic test and measurement procedures defined in IEC 61300-2 (all parts) and IEC 61300-3 (all parts) for interconnecting devices, passive components, mechanical splices, fusion splice protectors, fibre management systems and protective housings.

This document ~~should be~~ is used in combination with the relevant specification which defines the tests to be used, the required degree of severity for each of them, their sequence, if relevant, and the permissible performance limits. In the event of conflict between this document and the relevant specification, the latter takes precedence.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-731, *International Electrotechnical Vocabulary – Part 731: Optical fibre communication* (available at www.electropedia.org) 2022

IEC 60617, *Graphical symbols for diagrams* (available at <http://std.iec.ch/iec60617>)

IEC 60793-2-10, *Optical fibres – Part 2-10: Product specifications – Sectional specification for category A1 multimode fibres*

IEC 60793-2-30, *Optical fibres – Part 2-30: Product specifications – Sectional specification for category A3 multimode fibres*

~~IEC 60793-2-40, *Optical fibres – Part 2-40: Product specifications – Sectional specification for category A4 multimode fibres*~~

IEC 60825-1, *Safety of laser products – Part 1: Equipment classification and requirements*

IEC 60825-2, *Safety of laser products – Part 2: Safety of optical fibre communication systems (OFCSs)*

IEC 61280-1-4, *Fibre optic communication subsystem test procedures – Part 1-4: General communication subsystems – Light source encircled flux measurement method*

IEC 61280-4-1, *Fibre-optic communication subsystem test procedures – Part 4-1: Installed cable cabling plant – Multimode attenuation measurement*

IEC 61300-2 (all parts), *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 2: Tests*

IEC 61300-3 (all parts), *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3: Examinations and measurements*

IEC 61300-3-1, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-1: Examinations and measurements – Visual examination*

IEC 61300-3-35, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-35: Examinations and measurements – Visual inspection of fibre optic connectors and fibre-stub transceivers*

~~IEC 61300-3-53, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-53: Examinations and measurements – Encircled angular flux (EAF) measurement method based on two-dimensional far field data from step-index multimode waveguide (including fibre)*~~

3 Terms, definitions and abbreviated terms

3.1 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1.1

test

technical operation that consists of the determination of one or more characteristics of a given product, process or service according to a specified procedure and normally consists of the following steps:

- a) preparation (where required);
- b) preconditioning (where required);
- c) initial examination and measurement (where required);
- d) conditioning;
- e) recovery (where required);
- f) final examination and measurement

3.1.2

device under test

DUT

interconnecting device, passive component, equipment or other item designated to be tested

3.1.3

preparation

preparing the DUT according to the manufacturer's instructions or as specified in the relevant specification

3.1.4

preconditioning

treatment of a DUT with the object of removing or partly counteracting the effects of its previous environmental history or acclimatisation of the test specimen to standard atmospheric conditions

3.1.5 conditioning

exposure of a DUT to environmental or mechanical conditions for a specified duration in order to determine the effects of such conditions on the DUT

3.1.6 recovery

treatment of a DUT after conditioning in order that the properties of the DUT may stabilise before measurement

3.1.7 examination

visual and/or mechanical inspection of a DUT made with or without the use of special equipment

Note 1 to entry: Examination is usually carried out before and after the test, and/or during the test.

3.1.8 measurement

process of obtaining one or more values that can reasonably be attributed to a quantity

[SOURCE: IEC 60050-112:2010, 112-04-01, modified – The adverb "experimentally" has been removed from the definition, as well as the notes.]

3.1.9 uncertainty of measurement

quantified doubt about the result of a measurement

Note 1 to entry: ISO/IEC Guide 98-3:2008 [3] defines uncertainty of measurement.

Note 2 to entry: IEC TR 61282-14 [4] provides the information of measurement uncertainties.

3.1.10 encircled flux

EF

fraction of cumulative near-field power to the total output power as a function of radial distance from the optical centre of the core, defined by Formula (1):

$$EF(r) = \frac{\int_0^r xI(x)dx}{\int_0^R xI(x)dx} \quad (1)$$

where

$I(x)$ is the near-field intensity profile as a function of radial position x ;

R is the maximum range of integration

Note 1 to entry: The encircled flux shall be measured according to IEC 61280-1-4.

3.1.11 encircled angular flux

EAF

fraction of cumulative far-field power to the total output power as a function of incident angle θ from the optical central axis of the far-field pattern, defined by Formula (2):

$$EAF(\theta') = \frac{\int_0^{2\pi} \int_0^{\theta'} I(r, \varphi) \frac{\sin(\theta)}{\cos^3(\theta)} d\theta d\varphi}{\int_0^{2\pi} \int_0^{\theta_{\max}} I(r, \varphi) \frac{\sin(\theta)}{\cos^3(\theta)} d\theta d\varphi} \quad (2)$$

where

$I(r, \varphi)$ is the 2 dimensional far-field intensity profile as a function of moving radius r and argument φ ;

incident angle $\theta' = \tan^{-1}(r/d)$;

d is the distance between luminescent point and far field screen; and

θ_{\max} is the maximum range of integration.

Note 1 to entry: EAF shall be measured according to IEC 61300-3-53.

$$EAF(\theta') = \frac{\int_0^{2\pi} \int_0^{\theta'} I(\theta, \varphi) \frac{\sin(\theta)}{\cos^3(\theta)} d\theta d\varphi}{\int_0^{2\pi} \int_0^{\theta_{\max}} I(\theta, \varphi) \frac{\sin(\theta)}{\cos^3(\theta)} d\theta d\varphi} \quad (2)$$

where

$I(\theta, \varphi)$ is the far-field intensity profile as a function of radial angle and circular angle;

r is the radial distance from the origin corresponding to an angle between one ray emitted from the multimode waveguide and the optical axis of the multimode waveguide, calculated by $d_f \tan \theta$;

φ is a circular angle in polar coordinates;

θ is an angle between one ray emitted from the multimode waveguide and the optical axis;

θ_{\max} is the maximum ray angle, which is approximately 30° for category A3 multimode fibre for example;

d_f is the distance between the end of multimode optical waveguide and far field pattern (FFP) screen.

Note 1 to entry: The encircled angular flux is measured according to IEC 61300-3-53 [5].

3.1.12 differential mode attenuation DMA

variation in attenuation among the propagating modes of a multimode optical fibre

[SOURCE: IEC TR 62614-2:2015 [6], 3.4]

3.1.13 standard uncertainty

uncertainty of a measurement result expressed as a standard deviation

Note 1 to entry: For further information, see the ISO/IEC Guide 98-3.

3.1.14 uncertainty type A

type of uncertainty obtained by a statistical analysis of a series of observations, such as when evaluating certain random effects of measurement

Note 1 to entry: See Annex A and ISO/IEC Guide 98-3.

**3.1.15
uncertainty type B**

type of uncertainty obtained by means other than a statistical analysis of observations, for example an estimation of probable sources of uncertainty, such as when evaluating systematic effects of measurement

Note 1 to entry: See Annex A and ISO/IEC Guide 98-3.

**3.1.16
measurement repeatability**

measurement precision under a set of repeatability conditions of measurement

**3.1.17
measurement reproducibility**

reproducibility measurement precision under reproducibility conditions of measurement

**3.1.18
stability**

ability of a measuring instrument to keep its performance characteristics within a specified range during a specified time interval, all other conditions being the same

**3.1.19
repeatability condition**

condition of measurement that includes the same measurement procedure, same operators, same measuring system, same operating conditions and same location, and replicate measurements on the same or similar objects over a short period of time

**3.1.20
reproducibility condition**

condition of measurement that includes different locations, operators, measuring systems, and replicate measurements on the same or similar objects

3.2 Abbreviated terms

<https://standards.iteh.ai/>

<https://standards.iteh.ai/catalog/standards/iec/b659ecb3-9caf-496a-93ab-e32fa6d9af03/iec-61300-1-2022>

~~For the purposes of this document, the following abbreviations apply:~~

DMA	differential mode attenuation
DUT	device under test
EAF	encircled angular flux
EF	encircled flux
FFP	far field pattern
FP-LD	Fabry-Perot laser diode
GI	graded index
LED	light emitting diode
NA	numerical aperture
SI	step index
VCSEL	vertical cavity surface emitting laser

4 Requirements for IEC 61300-2 (all parts) and IEC 61300-3 (all parts)**4.1 Requirements for IEC 61300-2 (all parts) (tests)**

IEC 61300-2 (all parts) shall contain the following items:

- test apparatus;

- test procedures, ~~stated in the test requirements~~;
- severities;
- details to be specified and reported.

4.2 Requirements for IEC 61300-3 (all parts) (examinations and measurement procedures)

4.2.1 General requirements

IEC 61300-3 (all parts) shall contain the following items:

- measurement apparatus;
- measurement procedures;
- method of calculation (where required);
- consideration of measurement uncertainty;
- details to be specified and reported.

NOTE 1 The measurement uncertainty herein means the measurement uncertainty of the physical value of the performance parameters of DUT, not that for measurement apparatus (instruments).

NOTE 2 The measurement uncertainty is expressed as an absolute value not using "±".

The measurement accuracy, linearity, stability and repeatability of each measurement apparatus are possible to affect the measurement uncertainty. The relation of those factors on the measurement uncertainty should be described. When the reference value, such as the setting values, the initial values, the nominal values, can be defined, the sign "±" can be adopted for the deviation from the reference values (refer to 6.2 and 6.3).

4.2.2 Requirements for attenuation variation

~~For interconnection devices, the attenuation variation is defined as the peak-to-peak variation of attenuation during the test, unless otherwise specified.~~

For interconnecting devices and passive optical components, the attenuation variation is defined as a plus or minus (±) deviation from the original value at the start of the test, unless otherwise specified.

5 Standard atmospheric conditions

Standard atmospheric conditions shall be controlled within some range to ensure proper correlation of data obtained from measurements and tests conducted in various facilities. Test and measurement procedures shall be conducted under the following atmospheric conditions unless otherwise specified. In some cases, special ambient conditions may be needed and can be specified in the relevant specification.

The standard range of atmospheric conditions for carrying out measurements and tests is set out in Table 1.

Table 1 – Standard atmospheric conditions

Temperature	Relative humidity	Air pressure
18 °C to 28 °C	25 % to 75 %	86 kPa to 106 kPa
NOTE Some dimensional measurements require a tighter temperature range of 18 °C to 22 °C as defined in ISO 1 [7].		