

Edition 3.0 2022-09

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –

Part 2-43: Tests – Screen testing of return loss of single-mode PC optical fibre connectors

EC 61300-2-43:2022

Dispositifs d'interconnexion et composants passifs fibroniques – Procédures fondamentales d'essais et de mesures – 3-2022

Partie 2-43: Essais – Sélection des connecteurs PC pour fibres optiques unimodales en fonction de leur affaiblissement de réflexion





THIS PUBLICATION IS COPYRIGHT PROTECTED Copyright © 2022 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Secretariat 3, rue de Varembé CH-1211 Geneva 20 Switzerland Tel.: +41 22 919 02 11 info@iec.ch www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études, ...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Découvrez notre puissant moteur de recherche et consultez gratuitement tous les aperçus des publications. Avec un abonnement, vous aurez toujours accès à un contenu à jour adapté à vos besoins.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 300 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 19 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.



Edition 3.0 2022-09

INTERNATIONAL STANDARD

NORME INTERNATIONALE

Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –

Part 2-43: Tests – Screen testing of return loss of single-mode PC optical fibre connectors

EC 61300-2-43:2022

Dispositifs d'interconnexion et composants passifs fibroniques – Procédures fondamentales d'essais et de mesures – $^{-2022}$

Partie 2-43: Essais – Sélection des connecteurs PC pour fibres optiques unimodales en fonction de leur affaiblissement de réflexion

INTERNATIONAL ELECTROTECHNICAL COMMISSION

COMMISSION ELECTROTECHNIQUE INTERNATIONALE

ICS 33.180.20

ISBN 978-2-8322-5593-3

Warning! Make sure that you obtained this publication from an authorized distributor. Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

 Registered trademark of the International Electrotechnical Commission Marque déposée de la Commission Electrotechnique Internationale

CONTENTS

| F | OREWO | RD | 3 | | |
|---|---|--|----|--|--|
| 1 | Scop | e | .5 | | |
| 2 | Norm | Normative references | | | |
| 3 | Term | Terms, definitions, and abbreviated terms | | | |
| | 3.1 | Terms and definitions | 5 | | |
| | 3.2 | Abbreviated terms | 5 | | |
| 4 General description | | | .6 | | |
| 5 | Apparatus | | | | |
| | 5.1 | General | 6 | | |
| | 5.2 | Source (S) | .6 | | |
| | 5.3 | Detector (D) | .6 | | |
| | 5.4 | Temporary joint (TJ) | .6 | | |
| | 5.5 | Termination (T) | .6 | | |
| | 5.6 | Branching device (BD) | 7 | | |
| | 5.7 | Reflection standard plug (RSP) | 7 | | |
| | 5.8 | Reflection standard cord (RSC) | 7 | | |
| 6 | Proce | edure | 7 | | |
| | 6.1 | Selection of the RSC | 7 | | |
| | 6.2 | Patch cord screen testing | .8 | | |
| _ | 6.3 | Pigtail screen testing. | 8 | | |
| 7 | Detai | Is to be specified and reported | 8 | | |
| A | nnex A (| informative) Screen testing of return loss of pigtails having PC fibre optic | 10 | | |
| Distile men hu 61300-2-43-2022 | | | | | |
| ы | bilograp | ny | 10 | | |
| Fi | gure 1 - | - Measurement set-up for open plug reflection standard | 7 | | |
| Figure 2 – Measurement set-up for mated RSCs | | | | | |
| Figure 3 – Measurement set-up for patch cord screen testing | | | | | |
| Figure 4 – Measurement set-up for pictail screen testing | | | | | |
| Figure $\Delta 1$ – Measurement set up of the screen test method 11 | | | | | |
| Figure A 2 – Relationship between β and α | | | | | |
| Figure A.2. Cumulative probability of roturn loss before test 4 | | | | | |
| Figure A.5 – Cumulative probability of return loss before test | | | | | |
| Figure A.4 – Cumulative probability of return loss after test | | | | | |
| Figure A.5 – Relationship between power and α | | | | | |
| Fi | Figure A.6 – Measurement set-up of the reflected powers15 | | | | |

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTIC INTERCONNECTING DEVICES AND PASSIVE COMPONENTS – BASIC TEST AND MEASUREMENT PROCEDURES –

Part 2-43: Tests – Screen testing of return loss of single-mode PC optical fibre connectors

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61300-2-43 has been prepared by subcommittee 86B: Fibre optic interconnecting devices and passive components, of IEC technical committee 86: Fibre optics. It is an International Standard.

This third edition cancels and replaces the second edition published in 2014. This edition constitutes a technical revision.

This edition includes the following significant technical change with respect to the previous edition: addition of Clause 3 containing terms, definitions, and abbreviated terms.

The text of this International Standard is based on the following documents:

| Draft | Report on voting |
|---------------|------------------|
| 86B/4628/FDIS | 86B/4652/RVD |

- 4 -

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61300 series, published under the general title, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

https://standards.iteh.ai/catalog/standards/sist/41781efc-3ff5-4468-b62c-999ea3dba953/iec-61300-2-43-2022

FIBRE OPTIC INTERCONNECTING DEVICES AND PASSIVE COMPONENTS – BASIC TEST AND MEASUREMENT PROCEDURES –

Part 2-43: Tests – Screen testing of return loss of single-mode PC optical fibre connectors

1 Scope

This part of IEC 61300 aims at screening single-mode physical contact (PC) optical fibre connector plugs of an optical fibre patch cord or an optical fibre pigtail in terms of return loss, thus ensuring minimum return loss when the connector plugs are randomly mated with each other in the field. This document is intended to apply to cylindrical ferrule connector plugs.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61300-3-6, Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-6: Examinations and measurements – Return loss

C 61300-2-43:2022

3htt Terms, definitions, and abbreviated terms efc-3ff5-4468-b62c-999ea3dba953/iec-

61300-2-43-2022

3.1 Terms and definitions

No terms and definitions are listed in this document.

ISO and IEC maintain terminological databased for use in standardization at the following addresses:

- ISO Online browsing platform: available at https://www.iso.org/obp
- IEC Electropedia: available at http://www.electropedia.org/

3.2 Abbreviated terms

- BD branching device
- D detector
- DUT device under test
- PC physical contact
- PDL polarization dependent loss
- RSC reflection standard cord
- RSP reflection standard plug
- S source
- T termination
- TJ temporary joint

4 General description

The domed ferrule end faces of PC connector plugs (not angled) are produced by a polishing process. This polishing process results in a thin, damaged surface layer at the fibre end face of the connector plug. In silica fibres, the refractive index of the damaged layer is slightly higher than that of the original fibre. This high index layer generates optical reflection. When PC connector plugs are mated, return loss occurs as a result of multiple reflections at the two high index layers of the physically contacting fibre end faces. This phenomenon and its effect on return loss is further explained in IEC 61755-2-1.

- 6 -

This test procedure ensures that a designed minimum return loss is achieved when PC connector plugs are randomly mated. It screens patch cords or pigtails by using a pair of reflection standard cords (RSCs). The reflection standard cord has a reflection standard plug (RSP) at one end. The pair of RSCs are selected on the condition that the return loss when the plugs are mated is several decibels higher than the designed minimum return loss. Patch cords which pass this test achieves the designed minimum return loss in over 99 % of cases when randomly mated (see Annex A).

5 Apparatus

5.1 General

The equipment used shall be chosen according to the method used to measure the connector return loss, in accordance with IEC 61300-3-6. For the sake of simplicity, the procedure and figures in this document reflect that of a measurement with an optical continuous wave reflectometer (OCWR). The procedure can be adapted to any of the other measurement methods as deemed fit.

5.2 Source (S)

IEC 61300-2-43:2022

The source consists of an optical emitter, associated drive electronics, an excitation unit, and a fibre connector or fibre pigtail.

5.3 Detector (D)

The detector used consists of an optical detector, the associated electronics, and a means of connecting to an optical fibre. The optical connection may be a receptacle for an optical connector plug, a fibre pigtail, or a bare fibre adapter.

5.4 Temporary joint (TJ)

A TJ is a joint that is made to connect the device under test (DUT) into the measurement circuit. Examples of TJs are a connector, splice, vacuum chuck or micro-manipulator. The loss of the TJ shall be stable, and the TJ shall have a return loss of at least 10 dB greater than the maximum return loss to be measured.

Where a return loss greater than 50 dB is to be measured, a fusion splice is recommended in order to guarantee the prescribed measurement uncertainty.

5.5 Termination (T)

Fibre terminations, T, shall have a high return loss. Three types of terminations are suggested:

- angled fibre ends: the value of the angle depends on the fibre type. A minimum angle of 12° is necessary to achieve the desired high return loss;
- the application of an index matching material to the fibre end;
- attenuation in the fibre, for example, with a mandrel wrap.

Where attenuation is used as a termination, it may be applied between components.

The fibre termination shall have a return loss of at least 20 dB greater than the maximum return loss to be measured.

Where a return loss greater than 50 dB is to be measured, the "attenuation in the fibre" termination technique is advised in order to guarantee the prescribed measurement uncertainty.

5.6 Branching device (BD)

The BD splits light power from the source to the signal and reference ports and couples light power from those ports into the detector.

The splitting ratio of the BD shall be stable and be insensitive to polarization. The PDL is recommended to be less than 0,1 dB. The directivity shall be at least 10 dB higher than the maximum return loss to be measured.

5.7 Reflection standard plug (RSP)

The RSP is a plug connector whose return loss is better than the designed minimum return loss RL_{rs} (in decibels).

5.8 Reflection standard cord (RSC)

The RSC has a RSP at one end. The other end of the RSC is an end or a plug whose return loss is better than the designed minimum return loss RL_{rs} (in decibels).

6 **Procedure**

IEC 61300-2-43:2022

6.1^{ttps} Selection of the RSC¹log/standards/sist/41781efc-3ff5-4468-b62c-999ea3dba953/iec-

The RSC shall be selected by the following procedure.

a) Set up an objective RSC as shown in Figure 1.



Figure 1 – Measurement set-up for open plug reflection standard

b) Set the detector to 14,7 dB as the Fresnel reflection between the air and the silica fibre core as shown in Figure 1. The refractive index of air is 1,0, and the one of silica fibre is 1,452 for single-mode fibre on condition refractive index constant, $\Delta = 0,3$ %, and wavelength, $\lambda = 1,31 \mu m$.

NOTE Measurement uncertainty can be improved by using the actual parameters of fibres which have been employed.

c) Connect another objective RSC as shown in Figure 2, then measure the return loss.



- 8 -

Figure 2 – Measurement set-up for mated RSCs

d) Take the pair of objective RSC's as RSC's on condition that their return loss from the mating point is $RL_{rs} + \beta$ (in decibels), where RL_{rs} is a designed minimum return loss. The value of β shall be set at above 2 dB.

6.2 Patch cord screen testing

Optical fibre patch cords shall be screen tested according to the following procedure.

a) Connect the device under test (DUT) (patch cord) between the RSPs as shown in Figure 3.



Figure 3 – Measurement set-up for patch cord screen testing

- b) Measure the return loss RL_r (in decibels) from the two PC mating points.
- c) Consider the objective patch cord as a screen tested patch cord when RL_r is greater than RL_{rs} .

6.3^{tps} Pigtail screen testing ^{og/standards/sist/41781efc-3ff5-4468-b62c-999ea3dba953/iec-61300-2-43-2022}

Optical fibre pigtails shall be screen tested according to the following procedure.

a) Connect the objective PC connector of DUT (pigtail) to one RSP as shown in Figure 4, and terminate the pigtail fibre end.



Figure 4 – Measurement set-up for pigtail screen testing

- b) Measure the return loss RL_r (in decibels) from the mating point.
- c) Pass the objective pigtail as a screen tested pigtail when RL_r is greater than $RL_{rs} + \alpha$ (in decibels). The value of α shall be set at above 0,6 dB and at less than 5 dB.

7 Details to be specified and reported

The following details, as applicable, shall be specified in the relevant specification and reported in the test report:

- minimum return loss RL_{rs} (in decibels);
- condition of RSPs (the value of β in decibels);
- screening condition for pigtail (the value of α in decibels);

IEC 61300-2-43:2022 © IEC 2022 - 9 -

- attenuation of mating points between the RSPs and the objective connector plugs;
- attenuation and return loss of temporary joint;
- types of termination;
- return loss of termination;
- measurement uncertainty.

iTeh STANDARD PREVIEW (standards.iteh.ai)

IEC 61300-2-43:2022

https://standards.iteh.ai/catalog/standards/sist/41781efc-3ff5-4468-b62c-999ea3dba953/iec-61300-2-43-2022

Annex A

- 10 -

(informative)

Screen testing of return loss of pigtails having PC fibre optic connector

Annex A describes the theoretical background of the screen testing of return loss for pigtails. The basic idea is the same as the screen testing of return loss of patch cords having PC fibre optic connector plugs: select a pair of reference connectors, and a measurement pigtail is screen tested using the reference connector under a condition which is determined by simulation, where the distribution of high refractive index layer caused by polishing process is considered.

Two parameters β and α are introduced into this method. Parameter β is used for the selection of a pair of reference connectors. Parameter α is used as a criterion for screen testing measurement connectors. These two parameters β and α are carefully determined by simulation so that return loss of mating point exceeds certain specified return loss L_{rs} with high probability when the screen tested connectors are randomly connected.

The method assumes the following:

- refractive index of fibre core n_1 is 1,452;
- refractive index of air n_2 is 1,0. A R P R R V R V

The set-up of the measurement and test procedures will be shown first. Figure A.1 shows the set-up with the reference patch cords 1 and 2; 1a and 2a represent reference connector plugs. Points 3a and 3b are the connector plugs of the patch cord under test and 4a is the connector plug of the pigtail under test. The connector plugs represented by 1b, 2b and 5b are angled connectors with high return loss. S is the optical source; D is the optical detector and BD represents the branching device. T is a fibre termination which has a high return loss; it should be made by the application of an index matching material to the fibre end or introducing a high attenuation in the fibre, for example, with a mandrel wrap.