

INTERNATIONAL STANDARD



GROUP SAFETY PUBLICATION

**Safety of ~~power~~ transformers, ~~power supplies~~, reactors, power supply units and
similar ~~products~~ combinations thereof –
Part 2-2: Particular requirements and tests for control transformers and power
~~supplies~~ supply units incorporating control transformers**

IEC 61558-2-2:2022

<https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2022 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

[IEC 61558-2-2:2022](https://standards.iteh.ai/catalog/standards/sist/e53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022)

<https://standards.iteh.ai/catalog/standards/sist/e53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>



IEC 61558-2-2

Edition 3.0 2022-10
REDLINE VERSION

INTERNATIONAL STANDARD



GROUP SAFETY PUBLICATION

**Safety of ~~power~~ transformers, ~~power supplies~~, reactors, power supply units and
~~similar products~~ combinations thereof –
Part 2-2: Particular requirements and tests for control transformers and power
~~supplies~~ supply units incorporating control transformers**

IEC 61558-2-2:2022

<https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.180

ISBN 978-2-8322-5919-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	3
INTRODUCTION	2
1 Scope	7
2 Normative references	7
3 Terms and definitions	9
4 General requirements	10
5 General notes on tests	10
6 Ratings	10
7 Classification	10
8 Marking and other information	10
9 Protection against electric shock	12
10 Change of input voltage setting	12
11 Output voltage and output current under load	13
12 No-load output voltage	13
13 Short-circuit voltage	14
14 Heating	14
15 Short-circuit and overload protection	14
16 Mechanical strength	14
17 Protection against harmful ingress of dust, solid objects and moisture	14
18 Insulation resistance, dielectric strength and leakage current	14
19 Construction	15
20 Components	16
21 Internal wiring	16
22 Supply connection and other external flexible cables or cords	16
23 Terminals for external conductors	16
24 Provisions for protective earthing	16
25 Screws and connections	16
26 Creepage distances, clearances and distances through insulation	16
27 Resistance to heat, fire and tracking	17
28 Resistance to rusting	17
Annexes	18
Bibliography	19
Table 101 – Symbols indicating the kind of transformer	11

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**SAFETY OF ~~POWER~~ TRANSFORMERS, ~~POWER SUPPLIES~~,
REACTORS, POWER SUPPLY UNITS AND ~~SIMILAR PRODUCTS~~
COMBINATIONS THEREOF –****Part 2-2: Particular requirements and tests for control transformers
and power ~~supplies~~ supply units incorporating control transformers**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 61558-2-2:2007. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

International standard IEC 61558-2-2 has been prepared by IEC technical committee 96: Transformers, reactors, power supply units and combinations thereof.

This third edition cancels and replaces the second edition published in 2007. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) adjustment of structure and references in accordance with IEC 61558-1:2017;
- b) new general symbol for control transformers;
- c) new symbol for power supply unit with linearly regulated output voltage.

The text of this document is based on the following documents:

Draft	Report on voting
96/548/FDIS	96/554/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this document is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

It has the status of a group safety publication in accordance with IEC Guide 104.

This document is to be used in conjunction with IEC 61558-1:2017.

This document supplements or modifies the corresponding clauses in IEC 61558-1:2017, so as to convert that publication into the IEC standard: *Particular requirements and tests for control transformers and power supply units incorporating control transformers*.

A list of all parts in the IEC 61558 series published under the general title *Safety of transformers, reactors, power supply units and combinations thereof*, can be found on the IEC website.

Future standards in this series will carry the new general title as cited above. Titles of existing standards in this series will be updated at the time of the next edition.

Where this document states "*addition*", "*modification*" or "*replacement*", the relevant text of IEC 61558-1:2017 is to be adopted accordingly.

In this document, the following print types are used:

- requirements proper: in roman type;
- test specifications: *in italic type*;
- explanatory matter: in smaller roman type.

In the text of this document, the words in **bold** are defined in Clause 3.

Subclauses, notes, figures and tables additional to those in IEC 61558-1:2017 are numbered starting from 101; supplementary annexes are entitled AA, BB, etc.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under www.webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[IEC 61558-2-2:2022](https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022)

<https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>

INTRODUCTION

IEC TC 96 has a group safety function in accordance with IEC Guide 104 for transformers other than those intended to supply distribution networks, in particular transformers and power supply units intended to allow the application of protective measures against electric shock as defined by TC 64, but in certain cases including the limitation of voltage and horizontal safety function for SELV, in accordance with IEC 60364-4-41.

The group safety function (GSF) is used because of responsibility for example for safety extra-low voltage (SELV) in accordance with IEC 61140:2016, 5.2.6 and IEC 60364-4-41:2005, 414.3.1 or control circuits in accordance with IEC 60204-1:2016, 7.2.4.

The group safety function is used for each part of the IEC 61558-2 series because different standards of the IEC 61558 series can be combined in one construction but in certain cases with no limitation of rated output power.

For example an auto-transformer in accordance with IEC 61558-2-13 can be designed with a separate SELV-circuit in accordance with the particular requirements for IEC 61558-2-6 relating to the general requirements of IEC 61558-1.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[IEC 61558-2-2:2022](https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022)

<https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>

SAFETY OF ~~POWER~~ TRANSFORMERS, ~~POWER SUPPLIES,~~ REACTORS, POWER SUPPLY UNITS AND ~~SIMILAR PRODUCTS~~ COMBINATIONS THEREOF –

Part 2-2: Particular requirements and tests for control transformers and power ~~supplies~~ supply units incorporating control transformers

1 Scope

Replacement:

This part of IEC 61558 deals with the safety ~~aspects~~ of **control transformers** and **power ~~supplies~~ supply units** incorporating **control transformers**. **Transformers** incorporating **electronic circuits** are also covered by this document.

NOTE 1 Safety includes electrical, thermal and mechanical ~~safety~~ aspects.

~~This Part 2-2 is applicable to **control transformers** and **power supplies** incorporating both **control transformers** and **electronic circuits**. This Part 2-2 is not applicable to external circuits and their components intended to be connected to the input terminals, output terminals or socket outlets of the **transformer** and **power supplies**.~~

Unless otherwise specified, from here onward, the term **transformer** covers **control transformers** and **power supply units** incorporating **control transformers**.

For **power supply units** (linear) this document is applicable. For **switch mode power supply units** IEC 61558-2-16 is applicable together with this document. Where two requirements are in conflict, the most severe take precedence.

This document does not apply to **transformers** covered by IEC 60076-11.

~~This Part 2-2 applies to **stationary** or **portable**, single-phase or poly-phase, air-cooled (natural or forced), **independent** or **associated control transformers** and **power supplies** incorporating a **control transformer**, having a **rated supply voltage** not exceeding 1 000 V a.c. and **rated supply** and **internal operating frequency** not exceeding 500 Hz.~~

This document is applicable to **stationary** or **portable**, single-phase or polyphase, air-cooled (natural or forced) **independent** or **associated dry-type transformers**. The windings can be encapsulated or non-encapsulated.

The **rated supply voltage** does not exceed 1 000 V AC and the **rated supply frequency** and the **internal operating frequencies** do not exceed 500 Hz.

The **rated thermal output** does not exceed:

- 25 kVA for single-phase ~~**control transformers**~~ and ~~**power supplies**~~ incorporating ~~**control transformers**~~,
- 40 kVA for polyphase ~~**control transformers**~~ and ~~**power supplies**~~ incorporating ~~**control transformers**~~.

This document is applicable to ~~**control transformers**~~ and ~~**power supplies**~~ incorporating ~~**control transformers**~~ without limitation of the **rated thermal output**, subject to an agreement between the purchaser and the manufacturer.

~~This Part 2-2 is applicable to dry-type transformers. The windings may be encapsulated or non-encapsulated.~~

NOTE 2 **Transformers** intended to supply networks are not included in the scope.

The **no-load output voltage** or the **rated output voltage** does not exceed 1 000 V AC or 1 415 V ripple-free DC. For ~~independent-control transformers and independent power supplies incorporating control transformers~~, the **no-load output voltage** and / or the **rated output voltage** is not less than 50 V AC or 120 V ripple-free DC.

This document is not applicable to external circuits and their components intended to be connected to the input terminals and output terminals of the **transformers**.

NOTE 3 **Control Transformers** covered by this document are only used in applications where double or reinforced insulation between circuits is not required by the installation rules or by the end product standard.

NOTE 4 Normally the ~~control transformers and power supplies incorporating control transformers~~ are intended to be used with equipment to provide voltages different from the supply voltage for the functional requirements of the equipment. The protection against electric shock ~~may~~ can be provided (or completed) by other features of the equipment, such as the **body**. Parts of ~~output circuits~~ ~~may~~ can be connected to the **input circuits** or to protective earthing.

~~This Part 2-2 is applicable to control transformers and power supplies incorporating control transformers associated with specific equipment, to the extent decided upon by the relevant IEC technical committees.~~

NOTE 2 Attention is drawn to the following, if necessary:

- for ~~control transformers and power supplies incorporating control transformers~~ intended to be used in vehicles, on board ships, and ~~on-board~~ aircraft, additional requirements (from other applicable standards, national rules, etc.) ~~may be necessary~~;
- measures to protect the **enclosure** and the components inside the enclosure against external influences such as fungus, vermin, termites, solar-radiation, and icing ~~should also be considered~~;
- the different conditions for transportation, storage, and operation of the ~~control transformers and power supplies incorporating control transformers~~ ~~should also be considered~~;
- additional requirements in accordance with other appropriate standards and national rules ~~may~~ can be applicable to ~~control transformers and power supplies incorporating control transformers~~ intended for use in special environments, ~~such as tropical environments~~.

NOTE 3 Future technological development of ~~control transformers and power supplies incorporating control transformers~~ ~~may~~ can necessitate a need to increase the upper limit of the frequencies. Until then this document ~~may~~ can be used as a guidance document.

This group safety publication focusing on safety guidance is primarily intended to be used as a product safety standard for the products mentioned in the scope but is also intended to be used by technical committees in the preparation of publications for products similar to those mentioned in the scope of this group safety publication, in accordance with the principles laid down in IEC Guide 104 and ISO/IEC Guide 51.

One of the responsibilities of a technical committee is, wherever applicable, to make use of basic safety publications and/or group safety publications in the preparation of its publications.

2 Normative references

This clause of IEC 61558-1:2017 is applicable except as follows:

Addition:

~~IEC 60076-11, Power transformers—Part 11: Dry-type transformers~~

IEC 61558-1:2017, *Safety of transformers, reactors, power supply units and combinations thereof – Part 1: General requirements and tests*

IEC 61558-2-16:2021, *Safety of transformers, reactors, power supply units and combinations thereof – Part 2-16: Particular requirements and tests for switch mode power supply units and transformers for switch mode power supply units for general applications*

3 Terms and definitions

~~This clause of Part 1 is applicable except as follows:~~

~~Replacement of the third paragraph:~~

~~When the term **transformer** is used from here forward, it covers **control transformers** and **power supplies** incorporating **control transformer(s)** where applicable.~~

For the purposes of this document, the terms and definitions given in IEC 61558-1:2017 apply, except as follows:

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

Addition:

[IEC 61558-2-2:2022](https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022)

[https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-](https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022)

3.1.101

control transformer

transformer intended to supply power to control circuits (e.g. controlling, signalling, interlocking, etc.)

3.5.101

rated thermal output

product of the **rated output voltage** and the **rated output current**, or for polyphase **transformers**, the appropriate factor (e. g. for three-phase transformers $\sqrt{3}$) times the product of the **rated output voltage** and the **rated output current** delivered in continuous operation loaded at **power factor 1**

Note 1 to entry: If the **transformer** has more than one **output winding** or **and** tapped **output winding** (or both), the **rated output** denotes the sum of the products of **rated output voltage** and **rated output current** for **output circuits** intended to be loaded simultaneously.

3.5.102

admissible instantaneous output

product of the **rated output voltage** and the **rated instantaneous output current**, or for polyphase **transformers**, the appropriate factor (e. g. for three-phase transformers $\sqrt{3}$) times the product of the **rated output voltage** and the **rated instantaneous output current** delivered at **power factor 0,5**

Note 1 to entry: If the **transformer** has more than one **output winding** or **and** tapped **output winding** (or both), the **rated output** denotes the sum of the products of **rated output voltage** and **rated instantaneous output current** for **output circuits** intended to be loaded simultaneously.

3.5.103

rated instantaneous output current

output current for the specific operating conditions at the **rated output voltage** and the **rated supply frequency** at **power factor** 0,5 assigned to the **transformer** by the manufacturer

4 General requirements

This clause of IEC 61558-1:2017 is applicable.

5 General notes on tests

This clause of IEC 61558-1:2017 is applicable.

6 Ratings

This clause of IEC 61558-1:2017 is applicable except as follows:

Replacement Addition:

6.101 The **rated output voltage** shall not exceed 1 000 V AC or 1 415 V ripple-free DC and for **independent transformers** shall exceed 50 V AC or 120 V ripple-free DC.

For **independent transformers**, this output voltage limitation applies even when **output windings**, not intended for interconnection, are connected in series.

6.102 The **rated thermal output** shall not exceed:

- 25 kVA for single-phase **transformers** ~~except~~,
- 40 kVA for polyphase **transformers** ~~except for transformers subject to an agreement between the purchaser and the manufacturer.~~

Transformers without limitation of the **rated thermal output** shall be subject to agreement between the purchaser and the manufacturer.

6.103 The **rated supply frequency** and the **internal operating frequencies** shall not exceed 500 Hz.

6.104 The **rated supply voltage** shall not exceed 1 000 V AC.

Compliance with the requirements of 6.101 to 6.104 is checked by inspection of the marking.

7 Classification

This clause of IEC 61558-1:2017 is applicable except as follows:

7.8

Replacement

Control transformers shall be classified for **overvoltage category III**.

8 Marking and other information

This clause of IEC 61558-1:2017 is applicable except as follows:

8.1 c)

Replacement:

the **transformers** shall be marked with the **rated thermal output** and the **admissible instantaneous output** in volt-ampere, separated by an oblique stroke (e.g. 100/300 VA);

d)

Replacement:

Item d) is not applicable.

h)

Replacement:

~~the transformers shall be marked with one of the graphical symbols shown in 8.11.~~

Replacement of the content up to the first semi-colon by the following:




relevant graphical symbols shown in Table 101 that indicate the kind of **transformer**

8.11

IEC 61558-2-2:2022





<https://standards.iteh.ai/catalog/standards/sist/c53767d1-5c83-4159-b410-5b6203429740/iec-61558-2-2-2022>

Addition:

Symbol or graphical symbol	Explanation or title	Identification
	Fail-safe control transformer	
	Non-short-circuit proof control transformer	
	Short-circuit proof control transformer (inherently or non-inherently)	

The symbol for linear **power supply units** shall be used in conjunction with the symbol indicating the kind of **transformer**.

Table 101 – Symbols indicating the kind of transformer

Symbol or graphical symbol	Explanation or title	Identification
	Fail-safe control transformer	IEC 60417-6036:2010-08
	Non-short-circuit-proof control transformer	IEC 60417-6037:2010-08
	Short-circuit-proof control transformer (inherently or non-inherently)	IEC 60417-6038:2010-08
	Power supply unit, linear	IEC 60417-6210:2013-10

Addition:

[IEC 61558-2-2:2022](#)

8.101 If **transformers** are provided with input tapplings to allow adjustments to the supply voltage, these tapplings shall be marked with the value or the variation (e.g. +5 V or –5 V) of the input voltage corresponding to the tapping.

NOTE If **control transformers** are provided with input tapplings to allow adjustments to the supply voltage, tapplings in steps of 5 % are preferred.

9 Protection against electric shock

This clause of IEC 61558-1:2017 is applicable.

10 Change of input voltage setting

This clause of IEC 61558-1:2017 is applicable.

11 Output voltage and output current under load

This clause of IEC 61558-1:2017 is applicable except as follows:

11.1

Replacement:

When the **transformer** is connected to the **rated supply voltage**, at **rated supply frequency**, and loaded with an impedance at **power factor** 1 resulting in the **rated thermal output** at the **rated output voltage**, the output voltage shall not differ from the rated value by more than $\pm 5\%$.

Compliance is checked by measuring the output voltage when steady-state conditions are established.

Immediately after the **transformer** is loaded with an impedance resulting in the **admissible instantaneous output** at the **rated output voltage** at **power factor** 0,5 (inductive), the output voltage measured shall not be less than 95 % of the measured voltage at the **rated thermal output**.

NOTE—The output voltage measurement for the **admissible instantaneous output** should be carried out within 50 ms after applying this overload to minimise the effects of supplementary heating of the **transformer**.

For **transformers** with more than one **rated supply voltage**, the requirement is applicable for each of the **rated supply voltages**.

12 No-load output voltage

This clause of IEC 61558-1:2017 is applicable except as follows:

Addition:

12.101 The **no-load output voltage** shall not exceed 1 000 V AC or 1 415 V ripple-free DC and for **independent transformers** shall exceed 50 V AC or 120 V ripple-free DC.

For **independent transformers**, this **output voltage** limitation applies even when **output windings**, not intended for interconnection, are connected in series.

NOTE The requirement for series connection does not apply to associated or IP 00 **transformers**.

12.102 The difference between the **no-load output voltage** and the **output voltage** under load shall not be excessive.

The **difference ratio** between the **no-load output voltage** measured in Clause 12 and the **output voltage** under load measured during the test of Clause 11, expressed as a percentage of the latter voltage, shall not exceed 10 %.