



SLOVENSKI STANDARD SIST ETS 300 961 E3:2003

01-december-2003

8 [[[HJb]`W] b]`hY`_ca i b]_UW`g_]`g]ghYa `fZUnU&ZL`E;` c] cf`g`dc`bc` \]f]c]g]h`c`E`
DfY`_cX]f]Ub`Y`f] GA` \$` *` %` \$`ž`f`Un`]]WU) "`&`%`ž`]nXU`U`%` -` *` Ł

Digital cellular telecommunications system (Phase 2+) (GSM); Full rate speech;
Transcoding (GSM 06.10 version 5.2.1 Release 1996)

iteh STANDARD PREVIEW
(standards.iteh.ai)

Ta slovenski standard je istoveten z: **ETS 300 961 Edition 3**
SIST ETS 300 961 E3:2003
<https://standards.iteh.ai/catalog/standards/sist/1cd2983f-cbd0-4c7b-90a7-272a0cd48bc/sist-ets-300-961-e3-2003>

ICS:

33.070.50	Globalni sistem za mobilno telekomunikacijo (GSM)	Global System for Mobile Communication (GSM)
-----------	---	--

SIST ETS 300 961 E3:2003

en

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 961 E3:2003](#)

<https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003>



EUROPEAN
TELECOMMUNICATION
STANDARD

ETS 300 961

December 2000

Third Edition

Source: SMG

Reference: RE/SMG-110610QR2

ICS: 33.020

Key words: Digital cellular telecommunications system, Global System for Mobile communications (GSM)



**Digital cellular telecommunications system (Phase 2+);
Full rate speech;
Transcoding
(GSM 06.10 version 5.2.1 Release 1996)**

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

Internet: secretariat@etsi.fr - <http://www.etsi.org>

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2000. All rights reserved.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 961 E3:2003](https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003)

<https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003>

Contents

Intellectual Property Rights.....	7
Foreword.....	7
1 Scope	9
1.1 Normative references.....	9
1.1.1 Abbreviations.....	10
1.2 Outline description	10
1.3 Functional description of audio parts	10
1.4 PCM Format conversion	11
1.5 Principles of the RPE-LTP encoder	11
1.6 Principles of the RPE-LTP decoder	12
1.7 Sequence and subjective importance of encoded parameters.....	12
2 Transmission characteristics.....	15
2.1 Performance characteristics of the analogue/digital interfaces	15
2.2 Transcoder delay	15
3 Functional description of the RPE-LTP codec	16
3.1 Functional description of the RPE-LTP encoder.....	16
3.1.1 Offset compensation.....	16
3.1.2 Pre-emphasis	16
3.1.3 Segmentation	17
3.1.4 Autocorrelation	17
3.1.5 Schur Recursion	17
3.1.6 Transformation of reflection coefficients to Log.-Area Ratios	17
3.1.7 Quantization and coding of Log.-Area Ratios	18
3.1.8 Decoding of the quantized Log.-Area Ratios	18
3.1.9 Interpolation of Log.-Area Ratios.....	18
3.1.10 Transformation of Log.-Area Ratios into reflection coefficients	19
3.1.11 Short term analysis filtering	19
3.1.12 Sub-segmentation	19
3.1.13 Calculation of the LTP parameters.....	19
3.1.14 Coding/Decoding of the LTP lags.....	20
3.1.15 Coding/Decoding of the LTP gains.....	20
3.1.16 Long term analysis filtering.....	20
3.1.17 Long term synthesis filtering.....	21
3.1.18 Weighting Filter.....	21
3.1.19 Adaptive sample rate decimation by RPE grid selection.....	21
3.1.20 APCM quantization of the selected RPE sequence	22
3.1.21 APCM inverse quantization	23
3.1.22 RPE grid positioning.....	23
3.2 Decoder.....	23
3.2.1 RPE decoding section	23
3.2.2 Long Term Prediction section.....	23
3.2.3 Short term synthesis filtering section.....	24
3.2.4 Post-processing.....	24
4 Codec homing	28
4.1 Functional description	28
4.2 Definitions	28
4.3 Encoder homing.....	29
4.4 Decoder homing.....	29
4.5 Encoder home state.....	30
4.6 Decoder home state.....	30

5	Computational details of the RPE-LTP codec	31
5.1	Data representation and arithmetic operations	31
5.2	Fixed point implementation of the RPE-LTP coder	33
5.2.0	Scaling of the input variable.....	33
5.2.1	Downscaling of the input signal	33
5.2.2	Offset compensation	33
5.2.3	Pre-emphasis.....	34
5.2.4	Autocorrelation.....	34
5.2.5	Computation of the reflection coefficients.....	35
5.2.6	Transformation of reflection coefficients to Log.-Area Ratios.....	36
5.2.7	Quantization and coding of the Log.-Area Ratios.....	36
5.2.8	Decoding of the coded Log.-Area Ratios.....	37
5.2.9	Computation of the quantized reflection coefficients	38
5.2.9.1	Interpolation of the LARpp[1..8] to get the LARp[1..8]	38
5.2.9.2	Computation of the rp[1..8] from the interpolated LARp[1..8]	38
5.2.10	Short term analysis filtering	39
5.2.11	Calculation of the LTP parameters	39
5.2.12	Long term analysis filtering	40
5.2.13	Weighting filter	42
5.2.14	RPE grid selection	42
5.2.15	APCM quantization of the selected RPE sequence	43
5.2.16	APCM inverse quantization	44
5.2.17	RPE grid positioning	44
5.2.18	Update of the reconstructed short term residual signal dp[-120..-1]	44
5.3	Fixed point implementation of the RPE-LTP decoder	44
5.3.1	RPE decoding section	44
5.3.2	Long term synthesis filtering	45
5.3.3	Computation of the decoded reflection coefficients	45
5.3.4	Short term synthesis filtering section	45
5.3.5	De-emphasis filtering.....	46
5.3.6	Upscaling of the output signal.....	47
5.3.7	Truncation of the output variable.....	47
5.4	Tables used in the fixed point implementation of the RPE-LTP coder and decoder	47
6	Digital test sequences.....	48
6.1	Input and output signals	49
6.2	Configuration for the application of the test sequences	49
6.2.1	Configuration 1 (encoder only)	49
6.2.2	Configuration 2 (decoder only)	49
6.3	Test sequences	50
6.3.1	Test sequences for configuration 1.....	50
6.3.2	Test sequences for configuration 2.....	51
6.3.3	Additional Test sequences for Codec Homing	55
6.3.3.1	Codec homing frames	55
6.3.3.2	Sequence for an extensive test of the decoder homing.....	55
6.3.3.3	Sequences for finding the 20 ms framing of the GSM full rate speech encoder	55
6.3.3.4	Formats and sizes of the synchronization sequences	56
Annex A (informative):	Codec performance	58
A.1	Performance of the RPE-LTP	58
A.1.1	Introduction.....	58
A.1.2	Speech performance	58
A.1.2.1	Single encoding	58
A.1.2.2	Speech performance when interconnected with coding systems on an analogue basis.....	59
A.1.2.2.1	Performance with 32 kbit/s ADPCM (G.721, superseded by G.726).....	59
A.1.2.2.2	Performance with another RPE-LTP codec	59
A.1.2.2.3	Performance with encoding other than RPE-LTP and 32 kbit/s ADPCM (G.721, superseded by G.726)	59

A.1.3	Non-speech performance	59
A.1.3.1	Performance with single sine waves	59
A.1.3.2	Performance with DTMF tones.....	60
A.1.3.3	Performance with information tones.....	60
A.1.3.4	Performance with voice-band data.....	60
A.1.4	Delay	60
A.1.5	Bibliography	61
A.2	Subjective relevance of the speech coder output bits.....	62
A.3	Format for test sequence distribution	63
A.3.1	Type of files provided.....	63
A.3.2	File format description.....	64
Annex B (informative):	Test sequence diskettes.....	66
Annex C (informative):	Change Request History	67
History.....		68

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 961 E3:2003](https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003)

<https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003>

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 961 E3:2003](https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003)

<https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003>

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This European Telecommunication Standard (ETS) has been produced by the Special Mobile Group (SMG) Technical Committee of the European Telecommunications Standards Institute (ETSI).

The present document specifies the full rate speech transcoding within the digital cellular telecommunications system.

The associated files (annex B) are supplied with this ETS, the files contain test sequences, as described in clause 6 and annex A.3.

The diskettes are labelled as follows:

- | | |
|------------|--|
| Diskette 1 | ETS 300.961, annex B: Test sequences for the GSM Full Rate speech codec; Test sequences SEQ01.xxx to SEQ05.xxx (Diskette 1 contains LHA compressed files.) |
| Diskette 2 | ETS 300 961, annex B: Test sequences for the GSM Full Rate speech codec with homing frames; Test sequences SEQ01H.* to SEQ02H.*. |
| Diskette 3 | ETS 300 961, annex B: Test sequences for the GSM Full Rate speech codec with homing frames; Test sequences SEQ03H.* to SYNC159.COD. |
| Diskette 4 | ETS 300 961, annex B : 8 bit A-law test sequences for the GSM Full Rate speech codec with and without homing frames (Diskette 4 contains self-extracting files). |
| Diskette 5 | ETS 300 961, annex B: 8 bit μ -law test sequences for the GSM Full Rate speech codec with and without homing frames (Diskette 5 contains self-extracting files). |

The contents of this ETS may be subject to continuing work within SMG and may change following formal SMG approval. Should SMG modify the contents of this ETS, it will be resubmitted for OAP by ETSI with an identifying change of release date and an increase in version number as follows:

Version 5.x.y

where:

- 5 GSM Phase 2+ Release 1996.
- x the second digit is incremented for changes of substance, i.e. technical enhancements, corrections, updates, etc.;
- y the third digit is incremented when editorial only changes have been incorporated in the specification.

The specification from which this ETS has been derived was originally based on CEPT documentation, hence the presentation of this ETS may not be entirely in accordance with the ETSI/PNE rules.

Transposition dates	
Date of adoption of this ETS:	1 December 2000
Date of latest announcement of this ETS (doa):	31 March 2001
Date of latest publication of new National Standard or endorsement of this ETS (dop/e):	30 September 2001
Date of withdrawal of any conflicting National Standard (dow):	30 September 2001

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 961 E3:2003](https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003)

<https://standards.iteh.ai/catalog/standards/sist/1cd2985f-cbd0-4c7b-90a7-272a0cdf48bc/sist-ets-300-961-e3-2003>

1 Scope

The transcoding procedure specified in this European Telecommunication Standard (ETS) is applicable for the full-rate Traffic Channel (TCH) in the digital cellular telecommunications system. The use of this transcoding scheme for other applications has not been considered.

In GSM 06.01, a reference configuration for the speech transmission chain of the digital cellular telecommunications system is shown. According to this reference configuration, the speech encoder takes its input as a 13 bit uniform PCM signal either from the audio part of the mobile station or on the network side, from the PSTN via an 8 bit/A-law to 13 bit uniform PCM conversion. The encoded speech at the output of the speech encoder is delivered to a channel encoder unit which is specified in GSM 05.03. In the receive direction, the inverse operations take place.

The present document describes the detailed mapping between input blocks of 160 speech samples in 13 bit uniform PCM format to encoded blocks of 260 bits and from encoded blocks of 260 bits to output blocks of 160 reconstructed speech samples. The sampling rate is 8000 sample/s leading to an average bit rate for the encoded bit stream of 13 kbit/s. The coding scheme is the so-called Regular Pulse Excitation - Long Term prediction - Linear Predictive Coder, here-after referred to as RPE-LTP.

The present document also specifies the conversion between A-law PCM and 13 bit uniform PCM. Performance requirements for the audio input and output parts are included only to the extent that they affect the transcoder performance. The ETS also describes the codec down to the bit level, thus enabling the verification of compliance to the ETS to a high degree of confidence by use of a set of digital test sequences. These test sequences are described and are included in this ETS on diskette.

1.1 Normative references

The present document incorporates by dated and undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references, the latest edition of the publication referred to applies.

- <https://standards.iteh.ai/catalog/standards/sist/1cd2985f-chd0-4c7b-90a7-272a0cd248bc/sist-ets-300-961-e3-2003>
- [1] GSM 01.04 (ETR 350): "Digital cellular telecommunications system (Phase 2+); Abbreviations and acronyms".
- [2] GSM 05.03 (ETS 300 909): "Digital cellular telecommunications system (Phase 2+); Channel coding".
- [3] GSM 06.01 (ETS 300 960): "Digital cellular telecommunications system (Phase 2+); Full rate speech; Processing functions".
- [4] GSM 11.10 (ETS 300 607): "Digital cellular telecommunications system (Phase 2); Mobile Station (MS) conformity specification".
- [5] ETS 300 085: "Integrated Services Digital Network (ISDN); 3,1kHz telephony teleservice; Attachment requirements for handset terminals (Candidate NET 33)".
- [6] ITU-T Recommendation G.711: "Pulse code modulation (PCM) of voice frequencies".
- [7] ITU-T Recommendation G.712: "Transmission performance characteristics of pulse code modulation".
- [8] ITU-T Recommendation G.726: "40, 32, 24, 16 kbit/s adaptive differential pulse code modulation (ADPCM)".
- [9] ITU-T Recommendation Q.35: "Technical characteristics of tones for the telephone service".

- [10] ITU-T Recommendation V.21: "300 bits per second duplex modem standardized for use in the general switched telephone network".
- [11] ITU-T Recommendation V.23: "600/1 200-band modem standardized for use in the general switched telephone network".
- [12] GSM 06.32 (ETS 300 965): "Digital cellular telecommunications system (Phase 2+); Voice Activity Detector (VAD)".

1.1.1 Abbreviations

Abbreviations used in this ETS are listed in GSM 01.04.

1.2 Outline description

The ETS is structured as follows:

Subclause 1.3 contains a functional description of the audio parts including the A/D and D/A functions. Subclause 1.4 describes the conversion between 13 bit uniform and 8 bit A-law samples. Subclauses 1.5 and 1.6 present a simplified description of the principles of the RPE-LTP encoding and decoding process respectively. In subclause 1.7, the sequence and subjective importance of encoded parameters are given.

Clause 2 deals with the transmission characteristics of the audio parts that are relevant for the performance of the RPE-LTP codec.

Some transmission characteristics of the RPE-LTP codec are also specified in clause 2. Clause 3 presents the functional description of the RPE-LTP coding and decoding procedures, whereas clause 4 describes the computational details of the algorithm. Procedures for the verification of the correct functioning of the RPE-LTP are described in clause 5.

Performance and network aspects of the RPE-LTP codec are contained in annex A.

1.3 Functional description of audio parts

The analogue-to-digital and digital-to-analogue conversion will in principle comprise the following elements:

1) Analogue to uniform digital:

- microphone;
- input level adjustment device;
- input anti-aliasing filter;
- sample-hold device sampling at 8 kHz;
- analogue-to-uniform digital conversion to 13 bits representation.

The uniform format shall be represented in two's complement.

2) Uniform digital to analogue:

- conversion from 13 bit /8 kHz uniform PCM to analogue;
- a hold device;
- reconstruction filter including $x/\sin x$ correction;
- output level adjustment device;
- earphone or loudspeaker.

In the terminal equipment, the A/D function may be achieved either:

- by direct conversion to 13 bit uniform PCM format;
- or by conversion to 8 bit/A-law companded format, based on a standard A-law codec/filter according to ITU-T Recommendation G.711/714, followed by the 8-bit to 13-bit conversion according to the procedure specified in subclause 1.4.

For the D/A operation, the inverse operations take place.

In the latter case it should be noted that the specifications in ITU-T recommendation G.714 (superseded by G.712) are concerned with PCM equipment located in the central parts of the network. When used in the terminal equipment, the present document does not on its own ensure sufficient out-of-band attenuation.

The specification of out-of-band signals is defined in section 2 between the acoustic signal and the digital interface to take into account that the filtering in the terminal can be achieved both by electronic and acoustical design.

1.4 PCM Format conversion

The conversion between 8 bit A-law companded format and the 13-bit uniform format shall be as defined in ITU-T Recommendation G.721 (superseded by G.726), subclause 4.2.1, sub-block EXPAND and subclause 4.2.7, sub-block COMPRESS. The parameter LAW = 1 should be used.

1.5 Principles of the RPE-LTP encoder

A simplified block diagram of the RPE-LTP encoder is shown in figure 1.1. In this diagram the coding and quantization functions are not shown explicitly.

The input speech frame, consisting of 160 signal samples (uniform 13 bit PCM samples), is first pre-processed to produce an offset-free signal, which is then subjected to a first order pre-emphasis filter. The 160 samples are then analysed to determine the coefficients for the short term analysis filter (LPC analysis). These parameters are then used for the filtering of the same 160 samples. The result is 160 samples of the short term residual signal. The filter parameters, termed reflection coefficients, are transformed to log area ratios, LARs, before transmission.

For the following operations, the speech frame is divided into 4 sub-frames with 40 samples of the short term residual signal in each. Each sub-frame is processed blockwise by the subsequent functional elements.

Before the processing of each sub-block of 40 short term residual samples, the parameters of the long term analysis filter, the LTP lag and the LTP gain, are estimated and updated in the LTP analysis block, on the basis of the current sub-block of the present and a stored sequence of the 120 previous reconstructed short term residual samples.

A block of 40 long term residual signal samples is obtained by subtracting 40 estimates of the short term residual signal from the short term residual signal itself. The resulting block of 40 long term residual samples is fed to the Regular Pulse Excitation analysis which performs the basic compression function of the algorithm.

As a result of the RPE-analysis, the block of 40 input long term residual samples are represented by one of 4 candidate sub-sequences of 13 pulses each. The subsequence selected is identified by the RPE grid position (M). The 13 RPE pulses are encoded using Adaptive Pulse Code Modulation (APCM) with estimation of the sub-block amplitude which is transmitted to the decoder as side information.

The RPE parameters are also fed to a local RPE decoding and reconstruction module which produces a block of 40 samples of the quantized version of the long term residual signal.

By adding these 40 quantized samples of the long term residual to the previous block of short term residual signal estimates, a reconstructed version of the current short term residual signal is obtained.

The block of reconstructed short term residual signal samples is then fed to the long term analysis filter which produces the new block of 40 short term residual signal estimates to be used for the next sub-block thereby completing the feedback loop.

1.6 Principles of the RPE-LTP decoder

The simplified block diagram of the RPE-LTP decoder is shown in fig 1.2. The decoder includes the same structure as the feed-back loop of the encoder. In error-free transmission, the output of this stage will be the reconstructed short term residual samples. These samples are then applied to the short term synthesis filter followed by the de-emphasis filter resulting in the reconstructed speech signal samples.

1.7 Sequence and subjective importance of encoded parameters

As indicated in fig 1.1 the three different groups of data are produced by the encoder are:

- the short term filter parameters;
- the Long Term Prediction (LTP) parameters;
- the RPE parameters.

The encoder will produce this information in a unique sequence and format, and the decoder shall receive the same information in the same way. In table 1.1, the sequence of output bits b1 to b260 and the bit allocation for each parameter is shown.

The different parameters of the encoded speech and their individual bits have unequal importance with respect to subjective quality. Before being submitted to the channel encoding function the bits have to be rearranged in the sequence of importance as given in GSM 05.03. The ranking has been determined by subjective testing and the procedure used is described in annex A, subclause A.2.

Table 1.1: Encoder output parameters in order of occurrence and bit allocation within the speech frame of 260 bits/20 ms

Parameter	Parameter number	Parameter name	Var. name	Number of bits	Bit no. (LSB-MSB)
	1		LAR 1	6	b1 - b6
	2		LAR 2	6	b7 - b12
FILTER	3	Log. Area	LAR 3	5	b13 - b17
	4	ratios	LAR 4	5	b18 - b22
PARAMETERS	5	1 - 8	LAR 5	4	b23 - b26
	6		LAR 6	4	b27 - b30
	7		LAR 7	3	b31 - b33
	8		LAR 8	3	b34 - b36

Sub-frame no.1

LTP	9	LTP lag	N1	7	b37 - b43
PARAMETERS	10	LTP gain	b1	2	b44 - b45
	11	RPE grid position	M1	2	b46 - b47
RPE	12	Block amplitude	Xmax1	6	b48 - b53
PARAMETERS	13	RPE-pulse no.1	x1(0)	3	b54 - b56
	14	RPE-pulse no.2	x1(1)	3	b57 - b59
	⋮	⋮	⋮	⋮	⋮
	25	RPE-pulse no.13	x1(12)	3	b90 - b92

Sub-frame no.2

LTP	26	LTP lag	N2	7	b93 - b99
PARAMETERS	27	LTP gain	b2	2	b100- b101
RPE	28	RPE grid position	M2	2	b102- b103
PARAMETERS	29	Block amplitude	Xmax2	6	b104- b109
	30	RPE-pulse no.1	x2(0)	3	b110- b112
	31	RPE-pulse no.2	x2(1)	3	b113- b115

	42	RPE-pulse no.13	x2(12)	3	b146- b148

Table 1.1: Encoder output parameters in order of occurrence and bit allocation within the speech frame of 260 bits/20 ms

Sub-frame no.3

LTP	43	LTP lag	N3	7	b149- b155
PARAMETERS	44	LTP gain	b3	2	b156- b157
RPE	45	RPE grid position	M3	2	b158- b159
PARAMETERS	46	Block amplitude	Xmax3	6	b160- b165
	47	RPE-pulse no.1	x3(0)	3	b166- b168
	48	RPE-pulse no.2	x3(1)	3	b169- b171

	59	RPE-pulse no.13	x3(12)	3	b202- b204

iTeh STANDARD PREVIEW

Sub-frame no.4

(standards.iteh.ai)

LTP	60	LTP lag	N4	7	b205- b211
PARAMETERS	61	LTP gain	b4	2	b212- b213
RPE	62	RPE grid position	M4	2	b214- b215
PARAMETERS	63	Block amplitude	Xmax4	6	b216- b221
	64	RPE-pulse no.1	x4(0)	3	b222- b224
	65	RPE-pulse no.2	x4(1)	3	b225- b227

	76	RPE-pulse no.13	x4(12)	3	b258- b260