

INTERNATIONAL STANDARD

IEC
60958-4

Second edition
2003-05

Digital audio interface –
Part 4:
Professional applications

Interface audionumérique –

Partie 4:
Applications professionnelles

IEC 60958-4:2003

<https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003>



Reference number
IEC 60958-4:2003(E)

Publication numbering

As from 1 January 1997 all IEC publications are issued with a designation in the 60000 series. For example, IEC 34-1 is now referred to as IEC 60034-1.

Consolidated editions

The IEC is now publishing consolidated versions of its publications. For example, edition numbers 1.0, 1.1 and 1.2 refer, respectively, to the base publication, the base publication incorporating amendment 1 and the base publication incorporating amendments 1 and 2.

Further information on IEC publications

The technical content of IEC publications is kept under constant review by the IEC, thus ensuring that the content reflects current technology. Information relating to this publication, including its validity, is available in the IEC Catalogue of publications (see below) in addition to new editions, amendments and corrigenda. Information on the subjects under consideration and work in progress undertaken by the technical committee which has prepared this publication, as well as the list of publications issued, is also available from the following:

- **IEC Web Site** (www.iec.ch)

- **Catalogue of IEC publications**

The on-line catalogue on the IEC web site (http://www.iec.ch/searchpub/cur_fut.htm) enables you to search by a variety of criteria including text searches, technical committees and date of publication. On-line information is also available on recently issued publications, withdrawn and replaced publications, as well as corrigenda.

- **IEC Just Published**

This summary of recently issued publications (http://www.iec.ch/online_news/justpub/jp_entry.htm) is also available by email. Please contact the Customer Service Centre (see below) for further information.

- **Customer Service Centre**

If you have any questions regarding this publication or need further assistance, please contact the Customer Service Centre:

Email: custserv@iec.ch
Tel: +41 22 919 02 11
Fax: +41 22 919 03 00

INTERNATIONAL STANDARD

IEC 60958-4

Second edition
2003-05

Digital audio interface – Part 4: Professional applications

Interface audionumérique –

*Partie 4:
Applications professionnelles*

IEC 60958-4:2003

<https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003>

© IEC 2003 — Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembé, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE

S

For price, see current catalogue

CONTENTS

FOREWORD	3
INTRODUCTION	5
1 Scope	6
2 Normative references	6
3 Terms and definitions	6
4 Interface format	6
4.1 General	6
4.2 Validity bit	6
5 Channel status	7
5.1 General	7
5.2 Professional linear PCM application	7
6 User data	15
6.1 General	15
6.2 Application	15
7 Implementation	15
7.1 General	15
7.2 Transmitter	15
7.3 Receivers	16
8 Electrical requirements	16
8.1 General	16
8.2 Balanced line	16
Bibliography	21
Figure 1 – Simplified example of the configuration of the circuit (balanced)	17
Figure 2 – Intrinsic jitter measurement filter	18
Figure 3 – Jitter attenuation mask (optional)	18
Figure 4 – Eye diagram	19
Figure 5 – A suggested equalizing characteristic for the receiver operating at a frame rate of 48 kHz	19
Figure 6 – Receiver jitter tolerance template	20
Table 1 – Channel status data format for professional linear PCM application	8

INTERNATIONAL ELECTROTECHNICAL COMMISSION

DIGITAL AUDIO INTERFACE –**Part 4: Professional applications**

FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.
- 3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical specifications, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.
- 5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.
- 6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60958-4 has been prepared by IEC technical committee 100: Audio, video and multimedia systems and equipment.

This second edition of IEC 60958-4 cancels and replaces the first edition published in 1999 and constitutes a technical revision.

The text of this standard is based on the following documents:

FDIS	Report on voting
100/643/FDIS	100/669/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The main changes with respect to the previous edition (1999) are listed below.

- The scope specifies the professional application of IEC 60958-1 (generalities have been removed to an introduction).
- A clause on terms and definitions has been added.
- In Table 1, expanded channel status assignments have been added and channel status definitions expanded to accommodate extended sampling frequencies, indication of alignment level and multi-channel options.

- Figure 1 and associated text has been revised to be more generalized. Three notes on cable performance factors have been added.
- The impedance specification is now dependent on maximum frame rate.
- The common-mode balance specification is now dependent on maximum frame rate
- The impedance specification is now dependent on maximum frame rate.

IEC 60958 consists of the following parts under the generic title *Digital audio interface*:

Part 1: General

Part 3: Consumer applications

Part 4: Professional applications

The committee has decided that this publication remains valid until September 2005. At this date, in accordance with the committee's decision, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

WITHDRAWN

iTech Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60958-4:2003](https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003)

<https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003>

INTRODUCTION

The interface specified in this standard is primarily intended to carry monophonic or stereophonic programmes at a 48 kHz sampling frequency and with a resolution of up to 24 bits per sample. It may alternatively be used to carry signals sampled at other rates such as 32 kHz, 44,1 kHz, or 96 kHz. Note that conformity to this interface specification does not require equipment to utilize these rates and also that the capability of the interface to indicate other sample rates does not imply that it is recommended that equipment supports these rates. To eliminate doubt, equipment specifications should define the supported sampling frequencies.

The format is intended for use with shielded twisted-pair cables over distances of up to 100 m without transmission equalization or any special equalization at the receiver and at frame rates of up to 50 kHz. Longer cable lengths and higher frame rates may be used with cables better matched for data transmission, or with receiver equalization, or both.

In both cases, the clock references and auxiliary information are transmitted along with the audio data. Provision is also made to allow the interface to carry non-audio data.

iTech Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 60958-4:2003](https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003)

<https://standards.iteh.ai/catalog/standards/iec/3d456655-a0f6-4d8f-949c-f4026dfe2026/iec-60958-4-2003>

DIGITAL AUDIO INTERFACE –

Part 4: Professional applications

1 Scope

This International Standard specifies the professional application of the interface for the interconnection of digital audio equipment defined in IEC 60958-1.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60268-12:1987, *Sound system equipment – Part 12: Application of connectors for broadcast and similar use*

IEC 60958-1, *Digital audio interface – Part 1: General*

IEC 60958-3, *Digital audio interface – Part 3: Consumer applications*

ISO/IEC 646:1991, *Information technology – ISO 7-bit coded character set for information interchange*

ITU-T Recommendation J.17:1988, *Pre-emphasis used on sound-programme circuits*

ITU-T Recommendation V.11:1996, *Electrical characteristics for balanced double-current interchange circuits operating at data signalling rates up to 10 Mbit/s*

3 Terms and definitions

The terms and definitions given in IEC 60958-1 apply to this part of IEC 60958.

4 Interface format

4.1 General

The interface format as defined in IEC 60958-1 shall be used.

For historical reasons, preambles “B”, “M” and “W”, as defined in 4.3 of IEC 60958-1, shall, for use in professional applications, be referred to as “Z”, “X” and “Y”, respectively.

4.2 Validity bit

For this standard, the validity bit shall be used to indicate whether the main data field bits in the sub-frame are suitable for conversion to an analogue audio signal using linear PCM coding.

5 Channel status

5.1 General

The channel status for each audio signal carries information associated with that audio signal; thus it is possible for different channel status data to be carried in the two sub-frames of the digital audio signal. Examples of information to be carried in the channel status are: length of audio sample words, number of audio channels, sampling frequency, sample address code, alphanumeric source and destination codes, and pre-emphasis.

Channel status information is organized in a 192-bit block, subdivided into 24 bytes, numbered 0 to 23 (see Table 1). The first bit of each block is carried in the frame with preamble “Z”.

The individual bits of a block are numbered 0 to 191.

The primary application is indicated by channel status bit 0.

For the professional applications described here, this first channel status bit equals “1”.

NOTE For consumer digital audio equipment, this first channel status bit equals “0”, and this part of IEC 60958 does not apply.

Secondary applications may be defined within the framework of these primary applications.

5.2 Professional linear PCM application

The specific organization of the channel status data is defined in this clause and summarized in Table 1.

The significance of byte 0, bit 0 is such that a transmission from an interface conforming to IEC 60958-3 (“consumer use”) can be identified. Also, a “professional use” transmission, defined in this part of IEC 60958, can be correctly identified by a “consumer use” receiver. Connection of a “consumer use” transmitter with a “professional use” receiver or vice versa might result in unpredictable operation. Thus, the byte definitions in this clause apply only when bit 0 = “1” and bit 1 = “0” (professional linear PCM use of the channel status block).

Table 1 – Channel status data format for professional linear PCM application

Byte	Bit	Field
0	0	a = "1"
	1	b = "0"
1	2	C
	3	d
2	4	e
	5	f
3	6	g
	7	h
4	8	i
	9	j
5	10	k
	11	n="0"
6	12	l
	13	n="1"
7	14	m
	15	o
8	16	p
	17	q
9	18	r
	19	Reserved but undefined at present
10	20	Reserved but undefined at present
	21	Reserved but undefined at present
11	22	Reserved but undefined at present
	23	Reserved but undefined at present
12	24	Reserved but undefined at present
	25	Reserved but undefined at present
13	26	Reserved but undefined at present
	27	Reserved but undefined at present
14	28	Reserved but undefined at present
	29	Reserved but undefined at present
15	30	Reserved but undefined at present
	31	Reserved but undefined at present
16	32	Reserved but undefined at present
	33	Reserved but undefined at present
17	34	Reserved but undefined at present
	35	Reserved but undefined at present
18	36	Reserved but undefined at present
	37	Reserved but undefined at present
19	38	Reserved but undefined at present
	39	Reserved but undefined at present
20	40	Reserved but undefined at present
	41	Reserved but undefined at present
21	42	Reserved but undefined at present
	43	Reserved but undefined at present
22	44	Reserved but undefined at present
	45	Reserved but undefined at present
23	46	Reserved but undefined at present
	47	Reserved but undefined at present
24	48	Alphanumeric channel origin data
	49	Alphanumeric channel origin data
25	50	Alphanumeric channel origin data
	51	Alphanumeric channel origin data
26	52	Alphanumeric channel origin data
	53	Alphanumeric channel origin data
27	54	Alphanumeric channel origin data
	55	Alphanumeric channel origin data
28	56	Alphanumeric channel origin data
	57	Alphanumeric channel origin data
29	58	Alphanumeric channel origin data
	59	Alphanumeric channel origin data
30	60	Alphanumeric channel origin data
	61	Alphanumeric channel origin data
31	62	Alphanumeric channel origin data
	63	Alphanumeric channel origin data
32	64	Alphanumeric channel origin data
	65	Alphanumeric channel origin data
33	66	Alphanumeric channel origin data
	67	Alphanumeric channel origin data
34	68	Alphanumeric channel origin data
	69	Alphanumeric channel origin data
35	70	Alphanumeric channel origin data
	71	Alphanumeric channel origin data
36	72	Alphanumeric channel origin data
	73	Alphanumeric channel origin data
37	74	Alphanumeric channel origin data
	75	Alphanumeric channel origin data
38	76	Alphanumeric channel origin data
	77	Alphanumeric channel origin data
39	78	Alphanumeric channel origin data
	79	Alphanumeric channel origin data
40	80	Alphanumeric channel destination data
	81	Alphanumeric channel destination data
41	82	Alphanumeric channel destination data
	83	Alphanumeric channel destination data
42	84	Alphanumeric channel destination data
	85	Alphanumeric channel destination data
43	86	Alphanumeric channel destination data
	87	Alphanumeric channel destination data
44	88	Alphanumeric channel destination data
	89	Alphanumeric channel destination data
45	90	Alphanumeric channel destination data
	91	Alphanumeric channel destination data
46	92	Alphanumeric channel destination data
	93	Alphanumeric channel destination data
47	94	Alphanumeric channel destination data
	95	Alphanumeric channel destination data
48	96	Alphanumeric channel destination data
	97	Alphanumeric channel destination data
49	98	Alphanumeric channel destination data
	99	Alphanumeric channel destination data
50	100	Alphanumeric channel destination data
	101	Alphanumeric channel destination data
51	102	Alphanumeric channel destination data
	103	Alphanumeric channel destination data
52	104	Alphanumeric channel destination data
	105	Alphanumeric channel destination data
53	106	Alphanumeric channel destination data
	107	Alphanumeric channel destination data
54	108	Alphanumeric channel destination data
	109	Alphanumeric channel destination data
55	110	Alphanumeric channel destination data
	111	Alphanumeric channel destination data
56	112	Local sample address code (32-bit binary)
	113	Local sample address code (32-bit binary)
57	114	Local sample address code (32-bit binary)
	115	Local sample address code (32-bit binary)
58	116	Local sample address code (32-bit binary)
	117	Local sample address code (32-bit binary)
59	118	Local sample address code (32-bit binary)
	119	Local sample address code (32-bit binary)
60	120	Local sample address code (32-bit binary)
	121	Local sample address code (32-bit binary)
61	122	Local sample address code (32-bit binary)
	123	Local sample address code (32-bit binary)
62	124	Local sample address code (32-bit binary)
	125	Local sample address code (32-bit binary)
63	126	Local sample address code (32-bit binary)
	127	Local sample address code (32-bit binary)
64	128	Local sample address code (32-bit binary)
	129	Local sample address code (32-bit binary)
65	130	Local sample address code (32-bit binary)
	131	Local sample address code (32-bit binary)
66	132	Local sample address code (32-bit binary)
	133	Local sample address code (32-bit binary)
67	134	Local sample address code (32-bit binary)
	135	Local sample address code (32-bit binary)
68	136	Local sample address code (32-bit binary)
	137	Local sample address code (32-bit binary)
69	138	Local sample address code (32-bit binary)
	139	Local sample address code (32-bit binary)
70	140	Local sample address code (32-bit binary)
	141	Local sample address code (32-bit binary)
71	142	Local sample address code (32-bit binary)
	143	Local sample address code (32-bit binary)
72	144	Time of day code (32-bit binary)
	145	Time of day code (32-bit binary)
73	146	Time of day code (32-bit binary)
	147	Time of day code (32-bit binary)
74	148	Time of day code (32-bit binary)
	149	Time of day code (32-bit binary)
75	150	Time of day code (32-bit binary)
	151	Time of day code (32-bit binary)
76	152	Time of day code (32-bit binary)
	153	Time of day code (32-bit binary)
77	154	Time of day code (32-bit binary)
	155	Time of day code (32-bit binary)
78	156	Time of day code (32-bit binary)
	157	Time of day code (32-bit binary)
79	158	Time of day code (32-bit binary)
	159	Time of day code (32-bit binary)
80	160	Time of day code (32-bit binary)
	161	Time of day code (32-bit binary)
81	162	Time of day code (32-bit binary)
	163	Time of day code (32-bit binary)
82	164	Time of day code (32-bit binary)
	165	Time of day code (32-bit binary)
83	166	Time of day code (32-bit binary)
	167	Time of day code (32-bit binary)
84	168	Time of day code (32-bit binary)
	169	Time of day code (32-bit binary)
85	170	Time of day code (32-bit binary)
	171	Time of day code (32-bit binary)
86	172	Time of day code (32-bit binary)
	173	Time of day code (32-bit binary)
87	174	Time of day code (32-bit binary)
	175	Time of day code (32-bit binary)
88	176	Reliability flags
	177	Reliability flags
89	178	Reliability flags
	179	Reliability flags
90	180	Reliability flags
	181	Reliability flags
91	182	Reliability flags
	183	Reliability flags
92	184	Cyclic redundancy check character
	185	Cyclic redundancy check character
93	186	Cyclic redundancy check character
	187	Cyclic redundancy check character
94	188	Cyclic redundancy check character
	189	Cyclic redundancy check character
95	190	Cyclic redundancy check character
	191	Cyclic redundancy check character

a: use of channel status block	j: indication of alignment level
b: linear PCM identification	k: channel number
c: audio signal pre-emphasis	l: channel number
d: lock indication	m: multichannel mode number
e: sampling frequency	n: multichannel mode
f: channel mode	o: digital audio reference signal
g: user bits management	p: reserved but undefined at present
h: use of auxiliary sample bits	q: sampling frequency
i: source word length	r: sampling frequency scaling flag