

TECHNICAL REPORT



**Fibre optic communication system design guidelines –
Part 14: Determination of the uncertainties of attenuation measurements in fibre
plants**

(<https://standards.iteh.ai>)

Document Preview

[IEC TR 61282-14:2024](https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024)

<https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024>





THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

International
Standards
Document Preview
(iteh.ai)

[IEC TR 61282-14:2024](https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024)

<https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024>

TECHNICAL REPORT



**Fibre optic communication system design guidelines –
Part 14: Determination of the uncertainties of attenuation measurements in fibre
plants**

<https://standards.iteh.ai>
Document Preview

[IEC TR 61282-14:2024](https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024)

<https://standards.iteh.ai/catalog/standards/iec/1b8814fe-bf68-4f34-9129-4a5444ec6931/iec-tr-61282-14-2024>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.01

ISBN 978-2-8322-8867-2

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	7
1 Scope.....	8
2 Normative references	8
3 Terms, definitions, and abbreviated terms	8
3.1 Terms and definitions.....	8
3.2 Abbreviated terms.....	10
4 Overview of uncertainty	11
4.1 What is uncertainty?	11
4.2 Origin of uncertainties.....	11
4.3 What may could not be considered as uncertainty?.....	11
5 Fibre cabling attenuation measurement	11
5.1 Test methods	11
5.2 Sources of uncertainty to be considered	12
5.2.1 Analysis.....	12
5.2.2 Uncertainties due to the environment.....	16
5.2.3 Uncertainties due to operator skills	16
5.2.4 Uncertainties due to test methods.....	16
5.2.5 Uncertainties due to measuring instruments	16
5.2.6 Uncertainties due to the setup	18
5.2.7 Uncertainties due to cabling.....	18
6 Uncertainties estimation	19
6.1 Light source power meter measurement methods	19
6.1.1 Measurement model	19
6.1.2 Accumulation of uncertainties	22
6.2 OTDR methods	23
6.2.1 Measurement model for unidirectional methods	23
6.2.2 OTDR bidirectional measurements	24
7 General representation of the formula using sensitivity coefficients	27
8 Calculation	32
8.1 Combined standard uncertainty.....	32
8.2 Expanded uncertainty	32
8.3 Determination of the coverage factor k	32
8.3.1 General approach	32
8.3.2 Discussion.....	32
8.3.3 Typical values of degree of freedom	33
Annex A (informative) Mathematical basis.....	35
A.1 General.....	35
A.2 Type A evaluation of uncertainty	35
A.3 Type B evaluation of uncertainty	36
A.4 Determining the combined standard uncertainty.....	36
A.5 Reporting.....	37
Annex B (informative) Test methods	38
B.1 LSPM test methods as per IEC 61280-4-1 and 61280-4-2.....	38
B.1.1 General	38
B.1.2 Measurement configuration.....	38

B.1.3	One-cord reference configuration	38
B.1.4	Two-cord reference configuration	39
B.1.5	Three-cord reference configuration	39
B.1.6	Equipment cord reference configuration.....	39
B.2	OTDR Test methods as per IEC 61280-4-2 and 61280-4-3.....	39
B.2.1	Unidirectional measurement	39
B.2.2	Bi-directional measurement	40
B.2.3	OTDR test method on PON.....	40
B.2.4	Filtered OTDR on PON	41
B.3	Test methods defined in ISO/IEC 14763-3:2014.....	42
B.3.1	General	42
B.3.2	Channels	43
B.3.3	Links.....	44
Annex C (informative)	Evaluation of uncertainties	45
C.1	Type A uncertainties	45
C.1.1	General	45
C.1.2	Evaluation of optical source instability and associated uncertainties	45
C.2	Type B uncertainties	45
C.2.1	General	45
C.2.2	Evaluation of the power meter noise	46
C.2.3	Elements to be considered for power meter stability analysis.....	46
C.2.4	Evaluation of the centre wavelength dependence (LS or OTDR)	46
C.2.5	Spectral width dependence.....	49
C.2.6	Evaluation of the uncertainties due to MM launch conditions	49
C.2.7	Evaluation of the PDL	50
C.2.8	Uncertainty of absolute power measurement of power meters.....	51
C.2.9	Relative uncertainty arising from non-linearity of the OTDR	51
C.2.10	Uncertainty arising from OTDR noise.....	52
C.2.11	Practical determination of uncertainty arising from OTDR noise	54
C.2.12	Relative uncertainty arising from OTDR cursor placement	57
C.2.13	Considerations on backscatter coefficient	58
Annex D (informative)	Typical values of uncertainties	59
Annex E (informative)	Linear to dB scale conversion of uncertainties.....	63
E.1	Definition of decibel	63
E.2	Conversion of relative uncertainties	63
Bibliography	65
Figure 1	– Fishbone analysis	15
Figure 2	– Measurement model for light source and power meter.....	19
Figure 3	– Measurement model for OTDRs	23
Figure B.1	– Measurement configuration.....	38
Figure B.2	– One-cord reference measurement.....	38
Figure B.3	– Two-cord reference measurement.....	39
Figure B.4	– Three-cord reference measurement	39
Figure B.5	– Equipment cord reference measurement.....	39
Figure B.6	– Location of the cabling under test ports	40
Figure B.7	– Graphic determination of F_1 and F_2	41

Figure B.8 – Graphic determination of F_1 and F_2	42
Figure B.9 – Measurement on channel Channel measurement configuration	43
Figure B.10 – Channel reference measurement	43
Figure B.11 – Link measurement configuration	44
Figure B.12 – Link reference measurement.....	44
Figure C.1 – Typical spectral response of a fibre	47
Figure C.2 – Observed PLC splitter wavelength dependency and mathematical model.....	49
Figure C.3 – Uncertainties due to the launch conditions for a given loss	50
Figure C.4 – Linear regression location for some OTDR method	52
Figure C.5 – Confidence band of the linear regression.....	53
Figure C.6 – OTDR trace and noise	55
Figure C.7 – Noise asymmetry function of R_{DM}	57
Figure C.8 – Measurement validity limits.....	57
Table 1 – Source of uncertainty (raw list).....	12
Table 2 – Uncertainties due to measuring instruments	16
Table 3 – Uncertainties due to the setup.....	18
Table 4 – Uncertainties due to cabling.....	19
Table 5 – Correlation coefficients.....	26
Table 6 – Sensitivity coefficients for LSPM methods in IEC 61280-4-1, IEC 61280-4-2, and IEC 61280-4-3.....	28
Table 7 – Sensitivity coefficients for ISO/IEC 14763-3:2014 OTDR methods in IEC 61280-4-2 and IEC 61280-4-3	30
Table 8 – Values of k_{95} for different values of ν	33
Table 9 – Typical values of ν_j	33
Table C.1 – Spectral attenuation coefficients	48
Table C.2 – Sensitivity coefficients	48
Table D.1 – Typical values of uncertainties and distribution	60
Table D.2 – Typical values of uncertainties related to connectors	62

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 14: Determination of the uncertainties of attenuation measurements in fibre plants

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC TR 61282-14:2019. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC TR 61282-14 has been prepared by 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics. It is a Technical Report.

This document contains an attached file in the form of an Excel spreadsheet. This file is intended to be used as a complement and does not form an integral part of the document.

This third edition cancels and replaces the second edition published in 2019. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) addition of uncertainties calculation for optical time domain reflectometer (OTDR) measurement methods based on the analysis provided in 61280-4-3;
- b) addition of uncertainties calculation for passive optical networks (PON);
- c) update of the list of reference grade connectors;
- d) addition of probability distribution in Table D.1.

The text of this Technical Report is based on the following documents:

Draft	Report on voting
86C/1913/DTR	86C/1923/RVDTR

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Report is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 61282 series, published under the general title *Fibre optic communication system design guidelines*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

~~The determination of the uncertainty of every measurement is a key activity, which should be performed by applying dedicated methods as extensively presented in reference documents such as ISO/IEC Guide 98-3:2008, *Guide to the uncertainty of measurement (GUM)*.~~

~~This document shows a practical application of these methods for the determination of the measurement uncertainty of the attenuation of fibre optic cabling using optical light sources and power meters as defined in IEC 61280-4-1 and IEC 61280-4-2.~~

Reference documents such as ISO/IEC Guide 98-3, *Guide to the uncertainty of measurement (GUM)*, detail methods for the determination of the uncertainty of a measurement.

This document shows a practical application of these methods for the determination of the uncertainty in attenuation measurements of fibre optic cabling as defined in IEC 61280-4-1, IEC 61280-4-2, and IEC 61280-4-3, using optical light sources and power meters or OTDRs, with the exception of multimode OTDRs.

It includes the review of all contributing factors to uncertainty (such as launch conditions, spectral width, stability of source, power meter polarization, resolution, linearity, and quality of test cord connectors) to determine the overall measurement uncertainty. This part of IEC 61282 applies to the measurement of single-mode or multimode fibres without restrictions to the fibre parameters, including mode field diameter, core diameter, and NA. However, numerical values given in Clause C.2 and typical values given in Annex D are not valid for multimode fibres types A2, A3, and A4.

The list of uncertainties presented in this document is related to this particular application and ~~should be reconsidered if~~ measurement conditions that are ~~not~~ compliant with measurement requirements defined by IEC 61280-4-1, IEC 61280-4-2, and IEC 61280-4-3.

The reference document for general uncertainty calculations is ISO/IEC Guide 98-3:2008, and this document does not intend to replace it. This document only presents examples, and ~~should be used~~ it is good practice to use it in conjunction with ISO/IEC Guide 98-3:2008. A brief introduction to the determination of measurement uncertainty according to ISO/IEC Guide 98-3:2008 is given in Annex A.

This document is associated with a calculation spreadsheet (Excel) containing practical calculations.

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 14: Determination of the uncertainties of attenuation measurements in fibre plants

1 Scope

This part of IEC 61282, which is a Technical Report, establishes a detailed analysis and calculations of the uncertainties related to the measurement of the attenuation of both multimode and single-mode optical fibre cabling, using optical light sources and power meters. It also includes simplified analysis and calculation of the uncertainties related to the measurement of the attenuation of single-mode optical fibre cabling using OTDRs.

2 Normative references

~~The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.~~

~~IEC 61280-4-1:2009, Fibre optic communication subsystem test procedures – Part 4-1: Installed cable plant – Multimode attenuation measurement~~

~~IEC 61280-4-2:2014, Fibre optic communication subsystem test procedures – Part 4-2: Installed cable plant – Single-mode attenuation and optical return loss measurement~~

~~ISO/IEC Guide 98-3:2008, Uncertainty of measurement – Part 3: Guide to the expression of uncertainty in measurement (GUM:1995)~~

There are no normative references in this document.

3 Terms, definitions, and abbreviated terms

3.1 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at <https://www.electropedia.org/>
- ISO Online browsing platform: available at <https://www.iso.org/obp>

3.1.1 attenuation

~~A~~
reduction of optical power induced by transmission through a medium such as cabling, characterized by

$$~~L_{dB} = 10 \times \log_{10}(P_{in}/P_{out})~~$$

$$A_{\text{dB}} = 10 \times \log_{10} (P_{\text{in}} / P_{\text{out}})$$

where

P_{in} and P_{out} are the optical powers into and out of the cabling, typically measured in mW

Note 1 to entry: Attenuation is expressed in dB.

3.1.2 calibration

set of operations that establish, under specified conditions, the relationship between the values of quantities indicated by a measuring instrument and the corresponding values realized by standards

3.1.3 encircled flux EF

fraction of the radial-weighted cumulative near field power to the total radial-weighted output power as a function of radial distance from the optical centre of the core

3.1.4 measurement repeatability

measurement precision under a set of repeatability conditions of measurement

3.1.5 measurement reproducibility reproducibility

measurement precision under reproducibility conditions of measurement

3.1.6 polarization dependent loss PDL

maximum variation of attenuation to a variation of the state of polarization (SOP) over all SOPs

Note 1 to entry: PDL is expressed in dB.

3.1.7 nonlinearity

NL

relative difference, for a power meter, between the response at a given input power P and the response at a reference input power P_0 , characterized by

~~$$nl_{P/P_0} = \frac{r(P)}{r(P_0)} - 1$$~~

$$R_{\text{NL}}(P/P_0) = \frac{r(P)}{r(P_0)} - 1$$

where

$r(P) = P_{\text{read}}(P)/P$ is the response of the power meter at input power P ;

$P_{\text{read}}(P)$ is the reading of the power meter at input power P

Note 1 to entry: If expressed in decibels, the nonlinearity is calculated as:

$$\cancel{NL_{P/P_0} = 10 \times \log_{10} \frac{r(P)}{r(P_0)} \text{ (dB)}}$$

$$R_{\text{NLdB}}(P/P_0) = 10 \times \log_{10} \left[\frac{r(P)}{r(P_0)} \right]$$

Note 2 to entry: The nonlinearity is equal to zero at the reference power.

3.1.8 uncertainty of measurement

~~quantified doubt about the result of a measurement~~

parameter, associated with the result of a measurement, that characterizes the dispersion of the values that could reasonably be attributed to the measurand

3.1.9 stability

ability of a measuring instrument to keep its performance characteristics within a specified range during a specified time interval, all other conditions being the same

3.1.10 repeatability condition

condition of measurement that includes the same measurement procedure, same operators, same measuring system, same operating conditions and same location, and replicates measurements on the same or similar objects over a short period of time

3.1.11 reproducibility condition

condition of measurement that includes different locations, operators, measuring systems, and replicate measurements on the same or similar objects

3.1.12 standard uncertainty

“
uncertainty of a measurement result expressed as a standard deviation

Note 1 to entry: For further information, see ISO/IEC Guide 98-3.

3.1.13 type A uncertainty

type of uncertainty obtained by a statistical analysis of a series of observations, such as when evaluating certain random effects of measurement

Note 1 to entry: For further information, see A.2 and ISO/IEC Guide 98-3.

3.1.14 type B uncertainty

type of uncertainty obtained by means other than a statistical analysis of observations, for example an estimation of probable sources of uncertainty, such as when evaluating systematic effects of measurement

Note 1 to entry: For further information, see A.3 and ISO/IEC Guide 98-3.

3.2 Abbreviated terms

APC angled physical contact (description of connector style)

~~CW~~ continuous wave

LSPM light source power meter

NA	numerical aperture
OPM	optical power meter
OTDR	Optical time domain reflectometer
PC	physical contact (description of connector style that is not angled)
PON	passive optical network

4 Overview of uncertainty

4.1 What is uncertainty?

According to ISO/IEC Guide 98-3:2008 (GUM), the uncertainty of a measurement is the quantified doubt that exists about the result of any measurement. For every measurement, even the most careful, there is always a margin of doubt.

For example, when measuring the attenuation of fibre optic cabling, the operator ~~may~~ could observe variations of the displayed power level on the power meter and, hence, be unable to ~~know which value should be recorded~~ decide which value to record. This variation of the displayed value is an element of doubt regarding the result of the measurement.

4.2 Origin of uncertainties

Uncertainties come from measurement devices, the item to be measured, the measurement process, operator skills, references used, and the environment.

4.3 What ~~may~~ could not be considered as uncertainty?

Unknown parameters that contribute directly or indirectly to the quantity to be measured cannot be considered as uncertainties. For example, when measuring ~~a cabling, mode field diameter or numerical aperture of different fibres of cabling~~ the attenuation of cabling that is composed of different fibres, the mode field diameters or numerical apertures (NA) of the different fibres in the cabling are usually unknown; however, a mismatch of these parameters ~~causes~~ can significantly contribute to the measured attenuation.

Also, poor knowledge of measurement conditions generates uncertainties, but ~~itself~~ is not directly an uncertainty. A common example is the wavelength of the optical source: if the wavelength of the source is known with an uncertainty <1 nm, the measurement condition can be precisely specified. Conversely, if the wavelength of the source is known to be within a range of 40 nm, the possible variation of the attenuation of the device under test ~~should~~ can be estimated based on the typical variation of attenuation over the wavelength range for a given length of fibre.

5 Fibre cabling attenuation measurement

5.1 Test methods

~~Three~~ Four attenuation test methods use an optical light source and power meter (LSPM) to measure input and output power levels of the cabling under test to determine the attenuation. These methods are designated respectively,

- one-cord,
- three-cord,
- two-cord, and
- equipment cord method.

The main functional difference between these methods is the way the input power level, known as the reference power level (P_{in}), is measured (see B.1).

Additionally, one test method uses an OTDR to determine the attenuation of the cabling under test (see Annex B).

When the cabling under test is a PON, the one-cord method using a light source and a power meter and two OTDR methods can be used (see Annex B).

Refer to IEC 61280-4-1, IEC 61280-4-2, and IEC 61280-4-3 for more details.

NOTE Test methods presented in ISO/IEC 14763-3 have different names and are slightly different. See Clause B.3

5.2 Sources of uncertainty to be considered

5.2.1 Analysis

An extensive analysis of the source of uncertainties to be considered has been conducted. This resulted in the sorted source of uncertainties listed in Table 1.

Table 1 – Source of uncertainty (raw list)

Source of uncertainty	Type of origin	Index
Measurement source instability (power deviation over time)	Measurement devices	01
Source wavelength	Measurement devices	02
Source spectrum (spectral width)	Measurement devices	03
Laser speckle	Measurement devices	04
Launch condition for multimode fibres (dependent upon the compliance or noncompliance with the EF template and a function of the attenuation of the measured cabling)	Measurement devices	05
Power meter nonlinearity	Measurement devices	06
Power meter reading resolution	Measurement devices	07
Power meter spatial uniformity	References used	08
Power meter polarization sensitivity	Measurement devices	09
Power meter noise	Measurement devices	10
Power meter stability	Measurement devices	11
Power meter calibration	References used	12
OTDR wavelength	Measurement devices	13
OTDR spectrum (spectral width)	Measurement devices	14
OTDR nonlinearity	Measurement devices	15
OTDR reading resolution	Measurement devices	16
OTDR cursors placement	Measurement devices	17
OTDR noise	Measurement devices	18
Test cord connector or fibre attenuation uncertainty	References used	19
Connector mating repeatability (test cord or cabling)	References used or item to be measured	20
Connector PDL	References used or item to be measured	21
Reflections (FP cavity)	References used or item to be measured	22
Connector end face cleanliness	Operator skills	23
Fibre handling	Operator skills	24
Calculation errors	Measurement process	25
NA of the fibre	Item to be measured	26