

INTERNATIONAL STANDARD

IEC
61338-2

First edition
2004-05

Waveguide type dielectric resonators –

Part 2: Guidelines for oscillator and filter applications

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61338-2:2004](#)

<https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004>



Reference number
IEC 61338-2:2004(E)

Publication numbering

As from 1 January 1997 all IEC publications are issued with a designation in the 60000 series. For example, IEC 34-1 is now referred to as IEC 60034-1.

Consolidated editions

The IEC is now publishing consolidated versions of its publications. For example, edition numbers 1.0, 1.1 and 1.2 refer, respectively, to the base publication, the base publication incorporating amendment 1 and the base publication incorporating amendments 1 and 2.

Further information on IEC publications

The technical content of IEC publications is kept under constant review by the IEC, thus ensuring that the content reflects current technology. Information relating to this publication, including its validity, is available in the IEC Catalogue of publications (see below) in addition to new editions, amendments and corrigenda. Information on the subjects under consideration and work in progress undertaken by the technical committee which has prepared this publication, as well as the list of publications issued, is also available from the following:

- **IEC Web Site** (www.iec.ch)

- **Catalogue of IEC publications**

The on-line catalogue on the IEC web site (www.iec.ch/searchpub) enables you to search by a variety of criteria including text searches, technical committees and date of publication. On-line information is also available on recently issued publications, withdrawn and replaced publications, as well as corrigenda.

- **IEC Just Published**

This summary of recently issued publications (www.iec.ch/online_news/justpub) is also available by email. Please contact the Customer Service Centre (see below) for further information.

- **Customer Service Centre**

If you have any questions regarding this publication or need further assistance, please contact the Customer Service Centre: custserv@iec.ch

Email: custserv@iec.ch

Tel: +41 22 919 02 11

Fax: +41 22 919 03 00

INTERNATIONAL STANDARD

IEC 61338-2

First edition
2004-05

Waveguide type dielectric resonators –

Part 2: Guidelines for oscillator and filter applications

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61338-2:2004](https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004)

<https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004>

© IEC 2004 — Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembé, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE

V

For price, see current catalogue

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	5
1 Scope.....	7
2 Normative references	
3 Technical overview	8
4 Fundamentals of waveguide type dielectric resonators	8
4.1 Principle of operation.....	8
4.2 Basic structure	9
5 Dielectric resonator characteristics	9
5.1 Characteristics of dielectric resonator materials	9
5.2 Characteristics of shielding conductor.....	10
5.3 Characteristics of resonance modes	10
5.4 Example of applications	16
6 Application guide for oscillators.....	17
6.1 Practical remarks for oscillators.....	17
6.2 Oscillator using TE _{01δ} mode resonator.....	18
6.3 Oscillator using TEM mode resonator.....	19
Annex A (normative)	29
Bibliography.....	30
Figure 1 – Electromagnetic wave passing through a dielectric waveguide with relative permittivity ϵ^h	20
Figure 2 – TE _{01δ} mode, TM ₀₁₀ mode, and quarter wavelength TEM mode dielectric resonators.....	20
Figure 3 – Equivalent circuits of dielectric resonator coupled to external circuit	21
Figure 4 – Cross-section of TE _{01δ} mode resonator with excitation terminal	21
Figure 5 – Dimension of TE _{01δ} mode resonator	22
Figure 6 – Mode chart for TE _{01δ} mode resonator	22
Figure 7 – Cross-section of TM ₀₁₀ mode resonator with excitation terminal.....	22
Figure 8 – Rectangular type $\lambda/4$ TEM mode resonator mounted on PWB.....	23
Figure 9 – TEM mode resonator with metal terminal moulded by resin	23
Figure 10 – Cylinder type and rectangular type $\lambda/4$ TEM mode resonators.....	23
Figure 11 – $\lambda/4$ TEM mode resonators with stepped inner diameter.....	23
Figure 12 – Microstripline resonator	24
Figure 13 – Stripline resonator	24
Figure 14 – Example of a frequency tuning mechanism of a dielectric resonator	24
Figure 15 – Example of a reflection-type oscillator.....	25
Figure 16 – Example of a feedback-type oscillator	25
Figure 17 – Simplified diagram of a reflection-type oscillator.....	25

Figure 18 – Example of a reflection-type voltage-controlled oscillator.....	26
Figure 19 – Example of a feedback-type voltage-controlled oscillator.....	26
Figure 20 – Configuration of VCO using a TEM mode resonator.....	26
Table 1 – Characteristics of available dielectric resonator materials.....	27
Table 2 – Characteristics of substrate materials	27
Table 3 – Comparison of size and unloaded Q of dielectric resonators with three resonance modes.....	27
Table 4 – Example of applications	28
Table A.1 – References to relevant publications	29

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61338-2:2004](https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004)

<https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

WAVEGUIDE TYPE DIELECTRIC RESONATORS –

Part 2: Guidelines for oscillator and filter applications

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61338-2 has been prepared by IEC technical committee 49: Piezoelectric and dielectric devices for frequency control and selection.

This standard cancels and replaces IEC/PAS 61338-2 published in 2000. This first edition constitutes a technical revision.

The text of this standard is based on the following documents:

FDIS	Report on voting
49/656/FDIS	49/674/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until 2008. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

IEC 61338 consists of the following parts, under the general title *Waveguide type dielectric resonators*:

- Part 1: Generic specification ¹
- Part 1-1: General information and test conditions – General information ²
- Part 1-2: General information and test conditions – Test conditions ²
- Part 1-3: General information and test conditions – Measurement method of complex relative permittivity for dielectric resonator materials at microwave frequency
- Part 1-4: General information and test conditions – Measurement method of complex relative permittivity for dielectric resonator materials at millimeter-wave frequency ³
- Part 2: Guidelines for oscillator and filter applications (the present standard)
- Part 4: Sectional specification ¹
- Part 4-1: Blank detail specification ¹

A bilingual version may be issued at a later date

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61338-2:2004](#)

<https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004>

¹ To be published.

² To be replaced by IEC 61338-1 in the near future.

³ Under consideration.

INTRODUCTION

This part of IEC 61338 gives practical guidance on the use of waveguide type dielectric resonators that are used in telecommunications and radar systems (for general information, standard values, and test conditions, see the other parts of this series).

The features of these dielectric resonators are small size without degradation of quality factor, low mass, high reliability and high stability against temperature and ageing. The dielectric resonators are suitable for applications to miniaturized oscillators and filters with high performance.

This standard has been compiled in response to a generally expressed desire on the part of both users and manufacturers for guidelines for the use of dielectric resonators, so that the resonators may be used to their best advantage. For this purpose, general and fundamental characteristics have been explained in this standard.

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61338-2:2004](#)

<https://standards.iteh.ai/catalog/standards/iec/a6f8a1ec-b883-4810-bb04-048b0e265d03/iec-61338-2-2004>

WAVEGUIDE TYPE DIELECTRIC RESONATORS –

Part 2: Guidelines for oscillator and filter applications

1 Scope

This part of IEC 61338, which contains guidelines for use, is limited to the waveguide type dielectric resonators that are used for oscillator and filter applications. These types of resonators are now widely used in oscillators for direct broadcasting or communication satellite systems, oscillators for radio links, voltage-controlled oscillators for mobile communication systems and so on. In addition, these dielectric resonators are also used as an essential component of miniaturized filters for the same kind of applications.

It is not the aim of this standard either to explain theory or to attempt to cover all the eventualities that may arise in practical circumstances. This standard draws attention to some of the more fundamental questions, which should be considered by the user before he places an order for dielectric resonators for a new application. Such a procedure will be the user's insurance against unsatisfactory performance.

Standard specifications, such as those in the IEC 61338 series and national specifications or detail specifications issued by manufacturers, will define the available combinations of resonance frequency, the quality factor, the temperature coefficient of resonance frequency, etc. These specifications are compiled to include a wide range of dielectric resonators with standardized performances. It cannot be over-emphasized that the user should, wherever possible, select his dielectric resonators from these specifications, when available, even if it may lead to making small modifications to his circuit to enable standard resonators to be used. This applies particularly to the selection of the nominal frequency.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-1, *Environmental testing – Part 1: General and guidance*

IEC 60068-2-1, *Environmental testing – Part 2: Tests – Test A: Cold*

IEC 60068-2-2, *Environmental testing – Part 2: Tests – Tests B: Dry heat*

IEC 60068-2-6, *Environmental testing – Part 2: Tests – Test Fc: Vibration (sinusoidal)*

IEC 60068-2-7, *Environmental testing – Part 2: Tests – Test Ga: Acceleration, steady state*

IEC 60068-2-13, *Environmental testing – Part 2: Tests – Test M: Low air pressure*

IEC 60068-2-14, *Environmental testing – Part 2: Tests – Test N: Change of temperature*

IEC 60068-2-20, *Environmental testing – Part 2: Tests – Test T: Soldering*

IEC 60068-2-21, *Environmental testing – Part 2-21: Tests – Test U: Robustness of terminations*

IEC 60068-2-27, *Environmental testing – Part 2: Tests – Test Ea and guidance: Shock*

IEC 60068-2-29, *Environmental testing – Part 2: Tests – Test Eb and guidance: Bump*

IEC 60068-2-30, *Environmental testing – Part 2: Tests – Test Db and guidance: Damp heat, cyclic (12 + 12-hour cycle)*

IEC 60068-2-58, *Environmental testing – Part 2-58: Tests – Test Td: Test methods for solderability, resistance to dissolution of metallization and to soldering heat of surface mounting devices (SMD)*

IEC 60068-2-78, *Environmental testing – Part 2-78: Tests – Test Cab: Damp heat, steady state*

IEC 61338-1-1, *Waveguide type dielectric resonators – Part 1-1: General information and test conditions – General information*

IEC 61338-1-2, *Waveguide type dielectric resonators – Part 1-2: General information and test conditions – Test conditions*

IEC 61338-1-3, *Waveguide type dielectric resonators – Part 1-3: General information and test conditions – Measurement method of complex relative permittivity for dielectric resonator materials at microwave frequency*

3 Technical overview

It is of prime interest to a user that the resonator characteristics should satisfy particular specifications. The selection of oscillating circuits and dielectric resonators to meet that specification should be a matter of agreement between user and manufacturer.

Resonator characteristics are usually expressed in terms of resonance frequency, quality factor, etc. These characteristics are related to the dielectric characteristics in 5.3.

The specifications shall be satisfied between the lowest and highest temperatures of the specified operating temperature range and before and after environmental tests.

4 Fundamentals of waveguide type dielectric resonators

4.1 Principle of operation

When an electromagnetic wave passes through a dielectric waveguide with a relative permittivity of ϵ' , the interface between air and a dielectric will be a perfect reflector if the angle of incidence is greater than the critical angle θ , $\theta = \arcsin (1/\sqrt{\epsilon'})$, as shown in Figure 1.

In a very rough approximation, the air/dielectric interface can be considered to work as a magnetic wall (open-circuit), on which a normal component of the electric field and a tangential component of a magnetic field vanish. Thus, a dielectric rod with finite length functions as a resonator due to internal reflections of electromagnetic waves at the air/dielectric interface.

The size of a dielectric resonator can be considerably smaller than an empty resonant cavity at the same frequency. This is because the resonance frequency is determined when the resonator dimensions are of the order of half a wavelength of the electromagnetic wave, and because the wavelength is shortened in the dielectric according to the following equation:

$$\lambda_g = \frac{\lambda_0}{\sqrt{\epsilon'}} \quad (1)$$

where λ_g and λ_0 are the wavelengths in a dielectric with relative permittivity ϵ' and in vacuum. This size-reduction effect on microwave components is the biggest advantage in using the dielectric resonator.

4.2 Basic structure

The shape of a dielectric resonator is usually a disc or a cylinder which is a dielectric rod waveguide with finite length. Although the air/dielectric interface is considered to work roughly as a magnetic wall, some of the field actually leaks out (radiates) especially at the end faces, where the angle of incidences is less than the critical angle. In order to prevent such radiation losses, the resonator must be inside some form of shielding conductor.

As in a conventional metal wall cavity, there are various types of dielectric resonator structure and a number of modes can exist in each structure. Among these modes, the one with the lowest resonance frequency for certain diameter/length ratio is designated as the dominant mode. Figure 2 shows the three most commonly utilized dominant modes for dielectric resonators.

The $TE_{01\delta}$ mode dielectric resonator is characterized by a dominant TE (transverse electric) mode field distribution, the field of which leaks in the direction of wave propagation. This kind of mode resonator consists of a disc or a cylindrical-shaped dielectric resonator, a low ϵ' dielectric support, and a shielding conductor made of high-conductivity metals such as copper and silver. A high unloaded quality factor can be achieved using this mode.

The TM_{010} mode dielectric resonator is characterized by a TM (transverse magnetic) mode field distribution. This mode resonator has the middle levels of unloaded Q and size reduction effect between $TE_{01\delta}$ and TEM mode resonators. The TM_{010} mode resonator is often used for high-power applications such as filters for cellular base stations because of its construction which aids in the release of heat.

The TEM (transverse electromagnetic) mode dielectric resonator is characterized by a guided mode field distribution of a TEM mode with standing wave of a quarter wavelength. The inside, outside and one end of walls of a cylindrical dielectric resonator are fired or plated with a high-conductivity metal such as copper and silver. This mode dielectric resonator causes a significant size-reduction effect.

5 Dielectric resonator characteristics

5.1 Characteristics of dielectric resonator materials

The materials used to produce dielectric resonators should have a high relative permittivity (ϵ'), a low loss factor ($\tan \delta$) and a minimal temperature coefficient of resonance frequency (TCF). Table 1 shows the composition of several resonator materials with their dielectric properties at microwave frequencies.

Table 2 shows the dielectric properties of substrate materials. Dielectric resonators are mounted on these boards.

5.1.1 Relative permittivity (ϵ')

Relative permittivity of dielectric resonator materials is independent of frequency (i.e. constant) over the practical microwave frequency range, because the materials are made of para-electric ceramics. Materials with ϵ' from 20 to 100 are now typically used for dielectric resonators.