

INTERNATIONAL STANDARD



**Railway applications – Fixed installations – DC switchgear –
Part 6: DC switchgear assemblies**

IEC 61992-6:2006

<https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006>



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2020 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and definitions clause of IEC publications issued between 2002 and 2015. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

www.iec.ch IEC 61992-6:2006

<https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006>



IEC 61992-6

Edition 1.2 2020-05
CONSOLIDATED VERSION

INTERNATIONAL STANDARD



**Railway applications – Fixed installations – DC switchgear –
Part 6: DC switchgear assemblies**

[IEC 61992-6:2006](https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006)

<https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 45.060.01

ISBN 978-2-8322-8411-7

Warning! Make sure that you obtained this publication from an authorized distributor.

REDLINE VERSION



**Railway applications – Fixed installations – DC switchgear –
Part 6: DC switchgear assemblies**

IEC 61992-6:2006

<https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006>

CONTENTS

1	Scope	6
2	Normative references	6
3	Terms and definitions	6
4	Service requirements	7
5	Characteristics of the assemblies	7
6	Construction characteristics	7
6.1	General	7
6.2	Insulation requirements	8
6.3	Primary connections	9
6.4	Location of the primary connections	9
6.5	Earthing	9
6.5.1	Earthing of the main circuit	9
6.5.2	Earthing of the enclosure	9
6.6	Degree of protection and internal fault	10
6.6.1	Protection against approach to live parts and contact with moving parts	10
6.6.2	Internal arcing	11
6.7	Covers and doors	11
6.8	Inspection windows	11
6.9	Ventilating openings	12
6.10	Partitions and shutters	12
6.10.1	General	12
6.10.2	Partitions	12
6.10.3	Shutters	12
6.10.4	Isolating distances	13
6.11	Interlocks	13
6.12	Temperature-rises	14
6.13	Dielectric strength	14
6.14	Painting and finishing	14
6.15	Noise emission	14
6.16	Cooling and heating	14
6.17	Operating temperature of auxiliary and control equipment	14
6.18	Rated short-time withstand current of busbars	14
7	Information and marking	15
7.1	Information	15
7.2	Marking	15
8	Tests	15
8.1	General	15
8.2	List of the applicable tests	16
8.3	Performance of tests	16
8.3.1	Verification of conformity to the manufacturing drawings and to characteristics of the assembly	16
8.3.2	Operation test	17
8.3.3	Dielectric tests	17
8.3.4	Short-time withstand current tests	19
8.3.5	Mechanical operation test	21

8.3.6	Verification of the degree of protection	21
8.3.7	Temperature-rise tests	21
8.3.8	Electrical operation test	23
8.3.9	Internal arc test	24
Annex A	(informative) Information required	25
A.1	General	25
A.2	Procurement specification	25
A.3	Manufacturer's tender specification	26
A.4	Information and data to be supplied by the manufacturer during the delivery stage	27
Annex B	(normative) Method for testing under conditions of arcing due to an internal fault	29
B.1	Purpose of the test	29
B.2	Characteristics – Rated short-circuit current under internal arcing conditions (I_{Narc})	29
B.3	Test arrangements	29
B.3.1	Test specimen	29
B.3.2	Test circuit	30
B.3.3	Voltage	30
B.3.4	Duration of the test	30
B.4	Test procedure	30
B.4.1	Supply circuit	30
B.4.2	Arc initiation	31
B.4.3	Indicators	32
B.4.4	Repetition of the test	32
B.5	Assessment of the test	32
B.6	Test report	33
Figure 1	– Test arrangement for short-time current withstand test on busbars	20
Figure 2	– Test arrangement for temperature-rise test on main circuits	22
Figure 3	– Test arrangement for temperature-rise test on the busbars	23
Figure B.1	– Room simulation and indicator positioning, functional unit fitted with roof	34
Figure B.2	– Mounting frame for vertical indicators	35
Figure B.3	– Indicators arranged in a checkerboard pattern	35
Table 1	– Degrees of protection	11
Table 2	– List of applicable tests	16
Table B.1	– Sizes of the copper ignition wire	31

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**RAILWAY APPLICATIONS –
FIXED INSTALLATIONS –
DC SWITCHGEAR –****Part 6: DC switchgear assemblies**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendments has been prepared for user convenience.

IEC 61992-6 edition 1.2 contains the first edition (2006-02) [documents 9/891/FDIS and 9/913/RVD], its amendment 1 (2014-04) [documents 9/1792/CDV and 9/1852/RVC] and its amendment 2 (2020-05) [documents 9/2542/CDV and 9/2584A/RVC].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendments 1 and 2. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

International Standard IEC 61992-6 has been prepared by IEC technical committee 9: Electrical equipment and systems for railways.

IEC 61992 consists of the following parts, under the general title *Railway applications – Fixed installations – DC switchgear*:

- Part 1: General
- Part 2: D.C. circuit breakers
- Part 3: Indoor d.c. disconnectors, switch-disconnectors and earthing switches
- Part 4: Outdoor d.c. disconnectors, switch-disconnectors and earthing switches
- Part 5: Surge arresters and low-voltage limiters for specific use in d.c. systems
- Part 6: D.C. switchgear assemblies
- Part 7-1: Measurement, control and protection devices for specific use in d.c. traction systems – Application guide
- Part 7-2: Measurement, control and protection devices for specific use in d.c. traction systems – Isolating current transducers and other current measuring devices
- Part 7-3: Measurement, control and protection devices for specific use in d.c. traction systems – Isolating voltage transducers and other voltage measuring devices

The committee has decided that the contents of the base publication and its amendments will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

[IEC 61992-6:2006](https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006)

<https://standards.iteh.ai/catalog/standards/sist/594685f8-294b-4f8f-a6ce-895cef300199/iec-61992-6-2006>

IMPORTANT – The “colour inside” logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this publication using a colour printer.

RAILWAY APPLICATIONS – FIXED INSTALLATIONS – DC SWITCHGEAR –

Part 6: DC switchgear assemblies

1 Scope

This part of IEC 61992 covers d.c. metal-enclosed and non-metallic enclosed switchgear assemblies used in indoor stationary installations of traction systems, with nominal voltage not exceeding 3 000 V.

It is intended that individual items of equipment, for example circuit breakers, housed in the assembly are designed, manufactured and individually tested (simulating the enclosure when necessary) in accordance with their respective parts of IEC 61992 or, when appropriate, with another applicable standard.

NOTE 1 The requirements covered in this part of IEC 61992 are those concerning the assembly as such, its enclosure and the mutual influence of the equipment enclosed.

NOTE 2 EMC requirements are covered by IEC 62236-5 and additional requirements concerning dependability (RAMS) are covered by IEC 62278.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60243-1:1998, *Electrical strength of insulating materials – Test methods – Part 1: Tests at power frequencies*

IEC 60529:1989, *Degrees of protection provided by enclosures (IP Code)*

IEC 61992-1:2006+A1:2014, *Railway applications – Fixed installations – DC switchgear – Part 1: General*

IEC 61992-2:2006+A1:2014, *Railway applications – Fixed installations – DC switchgear – Part 2: DC circuit-breakers*

IEC 61992-3:2006, *Railway applications – Fixed installations – DC switchgear – Part 3: Indoor d.c. disconnectors, switch-disconnectors and earthing switches*

3 Terms and definitions

~~For the purposes of this document, the terms and definitions given in IEC 61992-1 apply.~~

For the purposes of this document, the terms and definitions given in IEC 61992-1 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>

- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1

internal arc

arcing within a switchgear assembly arising from a fault between active parts and/or between active parts and other conductive parts

3.2

rated short-circuit current under internal arcing conditions

I_{Narc}

current, during the test duration of 150 ms, indicating the maximum allowable value of sustained short-circuit current at the terminals of the incoming unit for which the requirements of this test specification are fulfilled

Note 1 to entry: The value is the maximum value of the prospective sustained short-circuit current.

3.3

compartment under test

compartment of a switchgear assembly which is subject to an internal arc test

4 Service requirements

Normal service requirements are detailed in Clause 4 and Annex B of IEC 61992-1 for indoor installations. In this standard, the pollution degree PD4 and overvoltage categories (see notes to Table 1 of IEC 61992-1) as described in EN 50124-1 are considered to be the normal condition.

(standards.iteh.ai)

5 Characteristics of the assemblies

IEC 61992-6:2006

The main characteristics of an assembly shall be indicated in the procurement specification as follows:

61992-6-2006

- a) type of the assembly enclosure;
- b) list of functional units enclosed;
- c) rated insulation voltages;
- d) rated values of the equipment enclosed as required in relevant standards;
- e) if constructed for an earth fault protection;
- f) detailed protection and control requirements (see IEC 61992-7).

Other important characteristics are listed in Clause A.2.

6 Construction characteristics

6.1 General

Enclosures are either metallic or non-metallic. Non-metallic enclosed switchgear shall not be used for nominal voltages above 1,5 kV.

All requirements specified herein also apply when both conductive and insulating materials are used, except for insulating clearances which shall be designed and tested as appropriate.

A cell made of masonry shall not be considered as an enclosure, as far as this standard is concerned.

The floor surface may be considered as part of an enclosure. The measures to be taken in order to obtain the degree of protection provided by floor surfaces shall be subject to an agreement between purchaser and supplier.

The walls of a room shall not be considered as parts of the enclosure.

Switchgear assemblies and relevant enclosures shall be designed so that normal service, inspection and maintenance operations, earthing of connected cables or busbars, locating of cable faults, voltage tests on connected cables or other apparatus and the elimination of electrostatic charges, can be carried out easily and safely.

All materials used shall be of the quality and of the class most suitable for working under the conditions specified. Special attention is to be paid to its ability to withstand moisture and fire: unless fire behaviour Class F0 is allowed (see Annex B of IEC 61992-1), materials used shall be metallic or of the self-extinguishing type, so that the risk of propagation of fire from one cubicle or compartment to another is minimised.

The selection of materials and the construction of the assembly shall be such that corrosion due to atmospheric and electrolytic effects are minimised.

All identical devices, forming part of an assembly for a given use and with the same characteristics, shall be interchangeable.

Withdrawable switching devices shall be prevented from insertion into functional units on the same switchgear assembly, having a different function or higher current ratings.

Sufficient space shall be provided inside the compartments for the entry and termination of incoming cables without their minimum bending radii being infringed.

The detachable parts of the protection enclosures shall be firmly attached to the fixed parts as specified in 6.7. Accidental untightening or detachment shall not occur because of the operation of the equipment.

All apparatus and connections for the safe operation, control and protection of the equipment concerned, shall be provided whether or not specifically mentioned. The equipment shall be adequately earthed, insulated, screened or enclosed as may be appropriate to ensure the protection of the equipment and safety of those concerned in its operation and maintenance.

Control and auxiliary circuits and contacts shall comply with the requirements of 5.2 of IEC 61992-1.

All components contained within the enclosure shall comply with their relevant standards.

6.2 Insulation requirements

Test voltages and clearances are given in Table 1 of IEC 61992-1. Recommended values for creepage distances are given in Annex D of IEC 61992-1.

The adverse effect of ionisation (due to arcs) on the clearances of other equipment in the assembly shall be taken into account. The minimum clearances between the arc chute of a switching device and metallic or non-metallic parts (i.e. above the arc chute and to the sides) shall be in accordance with those given by the switching device manufacturer.

Insulating material used to fully or partially line a metallic enclosure shall be firmly secured to the enclosure.

In case of withdrawable units, where access within the enclosure is required during maintenance operations, the busbars and all other conductors shall be separated by a barrier. Openings through such a barrier for the circuit and busbar connectors, etc. shall be shuttered and capable of being locked closed.

6.3 Primary connections

Non-withdrawable functional units may be equipped with fixed, removable (bolted or clamped) connectors. Withdrawable functional units may be equipped with plug-in connectors.

6.4 Location of the primary connections

In case of non-withdrawable assemblies, the terminals for the primary connections shall be accessible with the functional units as in normal operating conditions.

6.5 Earthing

NOTE Depending on the d.c. system earthing requirements, "earthing" means connection either to earth or to the return circuit.

6.5.1 Earthing of the main circuit

To ensure safety during maintenance work, all parts of the main circuit to which access is required or provided shall be capable of being earthed through suitable means. This does not apply to those parts, which are withdrawable or removable and which become accessible after being separated from the switchgear.

A withdrawable part, however, shall not be removed from the enclosure unless capacitors on it have been discharged to safe values.

In case of withdrawable circuit breakers, the earth connection shall be made before the shutters are opened and the shutters shall be closed before the earth connection is disconnected.

Earthing switches shall comply with IEC 61992-3. The requirement that it shall be possible to know the operating position of the earthing switch is met if one of the following conditions is fulfilled:

- the isolating distance is visible;
- the position of the earthing switch is clearly visible and the position corresponding to full connection and full isolation are clearly identified;
- the position of the earthing switch is indicated by a reliable indicating device.

6.5.2 Earthing of the enclosure

The purchaser shall indicate in the enquiry how to earth the enclosure (e.g. the return circuit or to earth) in accordance with 6.5.8 of IEC 61992-7-1.

The metallic parts of the enclosures, such as frames, structure and fixed elements, shall be connected to each other and to a suitable earthing terminal, placed in an accessible position, in order to allow the connection to the main earth system of the installation. The earthing terminal shall be suitably protected against corrosion. The standard earth symbol shall be clearly and permanently marked.

An earthing conductor shall be provided extending the whole length of the metal-enclosed switchgear to connect the individual earthing terminals. The current density of the earthing conductor, if of copper, shall not exceed 200 A/mm² based on a specified earth fault of

10 000 A for 1 s; therefore, its cross-section area shall be not less than 50 mm². The earthing conductor shall be terminated by a clearly and permanently marked main earthing terminal.

The continuity of the earth system shall be ensured taking into account the thermal and mechanical stresses caused by the magnitude and duration of the current it may have to carry.

The purchaser shall indicate in the enquiry if the earthing system shall differ from the above.

The purchaser shall specify in the enquiry the maximum earth fault current. The standard value for the duration is 0,25 s due to the typical breaking time of the a.c. rectifier circuit breaker(s). If the purchaser requires a longer duration, he shall specify this in the enquiry.

The terminals and connections shall be adequately dimensioned for the earth fault current.

The enclosure of each functional unit shall be connected to this earthing conductor. All the metallic parts within a functional unit and not belonging to a main, control or auxiliary circuit, shall also be connected to the earthing conductor directly or through metallic structural parts.

In the latter case, earthing of said elements, such as walls and doors of compartments, may be fulfilled by normal construction elements, ensuring an adequate electrical continuity and suitable dimensioning. For any bolts or similar fixing used for earth continuity, the maintenance instructions shall state the requirements for cleaning surfaces and ensuring tightness.

The metallic parts of a withdrawable part which are normally earthed in the service position, shall also remain earth-connected in the test and disconnected positions and between each position.

The purchaser shall indicate in the enquiry if the earthing system deviates from the requirements stated in this subclause.

6.6 Degree of protection and internal fault

6.6.1 Protection against approach to live parts and contact with moving parts

For metal-clad and for compartmented switchgear, the degree of protection shall be specified. If required, separate degrees of protection for doors and walls, for partitions and for the roof of the enclosure shall be specified. For cubicle switchgear, it is only necessary to specify the degree of protection for the enclosure.

The degree of protection against contact of persons with live parts of auxiliary circuits and with any moving parts (other than smooth rotating shafts and moving linkages) shall be indicated by means of the designation specified in Table 1 below, taken from IEC 60529.

Normally, no degree of protection is provided for indoor switchgear assemblies against ingress of water.

Table 1 – Degrees of protection

Degree of protection	Protection against approach of live parts and contact with moving parts
IP20	By fingers or similar objects of diameter greater than 12 mm
IP30	By tools, wires, etc. of diameter of thickness greater than 2,5 mm
IP40	By tools, wires, etc. of diameter of thickness greater than 1,0 mm

NOTE 1 The first characteristic numeral indicates the degree of protection provided by the enclosure against the ingress of solid bodies and approach to live parts for all given enclosure conditions.

NOTE 2 Protection against ingress of water is given by the second numeral.

6.6.2 Internal arcing

Failure within the enclosure of switchgear due to a defect or an exceptional service condition or mal-operation may initiate an exceptional internal arc.

Ventilating openings and vent outlets shall be arranged in such a way that gas or vapour escaping under pressure does not endanger the operator.

A manufacturer may assign a rated short-circuit current under internal arcing conditions I_{Narc} to the equipment. Requirements are given in Clause B.2.

6.7 Covers and doors

Covers and doors which are part of the enclosure shall be metallic if the enclosure is metallic. When they are closed, they shall provide the degree of protection specified for the enclosure.

Covers or doors shall not be made of woven wire mesh, expanded metal or similar. When ventilating openings and vent outlets are incorporated in the cover or door, reference is made to 6.9.

Two categories of covers or doors are recognized with regard to access to compartments at main circuit potential:

- a) those which need not to be opened for the normal purposes of operation or maintenance (fixed covers): it shall not be possible for them to be opened, dismantled or removed without the use of tools or other provisions which may be required by the purchaser;
- b) those which need to be opened for the normal purposes of operation (removable covers, doors): these shall not require tools for their opening or removal; they shall be provided with locking facilities (for example provisions for padlocks), unless the safety of persons is assured by a suitable interlocking device.

NOTE It is recommended, with metal-clad or compartmented switchgear, that doors giving access to live parts be suitable for opening only when the part of the exposed main circuit contained in the compartment being made accessible is dead. Equivalent provisions may also be provided.

6.8 Inspection windows

Inspection windows shall provide at least the degree of protection specified for the enclosure.

They shall be covered by a transparent sheet of mechanical strength comparable to that of the enclosure.

The insulation between live parts of the main circuit and the inspection windows shall withstand the test voltages specified in Table 1 of IEC 61992-1.