

INTERNATIONAL STANDARD

**Electromechanical elementary relays –
Part 1: General requirements**

IEC Standards
(<https://standards.iteh.ai>)
Document Preview

IEC 61810-1:2008

<https://standards.iteh.ai/catalog/standards/iec/60547bad-2bb9-4998-ae8b-bc1a8bf2503c/iec-61810-1-2008>

Withhold



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

<https://standards.iteh.ai/document/iec/61810-1-2008>



IEC 61810-1

Edition 3.0 2008-02

INTERNATIONAL STANDARD

**Electromechanical elementary relays –
Part 1: General requirements**

International Standards
(<https://standards.iteh.ai>)
Document Preview

IEC 61810-1:2008

<https://standards.iteh.ai/catalog/standards/iec/60547bad-2bb9-4998-ae8b-be1a8bf2503c/iec-61810-1-2008>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE **XB**

ICS 29.120.70

ISBN 2-8318-9586-3

CONTENTS

FOREWORD.....	5
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
3.1 Definitions related to general terms	9
3.2 Definitions of relay types	9
3.3 Definitions related to conditions and operations.....	10
3.4 Definitions of operating values	12
3.5 Definitions related to contacts	13
3.6 Definitions related to accessories.....	16
3.7 Definitions related to insulation	16
4 Influence quantities	18
5 Rated values	18
5.1 Rated coil voltage/rated coil voltage range.....	18
5.2 Operative range	19
5.3 Release.....	19
5.4 Reset	19
5.5 Electrical endurance.....	19
5.6 Frequency of operation.....	19
5.7 Contact loads	20
5.8 Ambient temperature.....	20
5.9 Categories of environmental protection	20
5.10 Duty factor	20
6 General provisions for testing	20
7 Documentation and marking	22
7.1 Data	22
7.2 Additional data	23
7.3 Marking.....	23
7.4 Symbols.....	23
8 Heating	24
8.1 Requirements.....	24
8.2 Test procedure	25
8.3 Terminals	26
8.3.1 General	26
8.3.2 Solder terminals	26
8.3.3 Flat quick-connect terminations	26
8.3.4 Screw and screwless type terminals	27
8.3.5 Alternative termination types	27
8.3.6 Sockets	27
9 Basic operating function	27
9.1 General test conditions.....	27
9.2 Operate (monostable relays)	27
9.3 Release (monostable relays).....	28
9.4 Operate/reset (bistable relays)	28
10 Insulation resistance and dielectric strength	28

10.1	Preconditioning	28
10.2	Insulation resistance	28
10.3	Dielectric strength	28
11	Electrical endurance	30
12	Mechanical endurance.....	32
13	Clearances, creepage distances and solid insulation	32
13.1	General provisions	32
13.2	Clearances and creepage distances	33
13.3	Solid insulation.....	37
13.4	Accessible surfaces.....	37
14	Terminations	37
14.1	Screw terminals and screwless terminals	38
14.2	Flat quick-connect terminations	38
14.3	Solder terminals	38
14.3.1	Resistance to soldering heat	38
14.3.2	Solder pins	38
14.3.3	Terminals for surface mounting (SMD).....	38
14.3.4	Other solder terminations (e.g. soldering lugs).....	38
14.4	Sockets	38
14.5	Alternative termination types	39
15	Sealing.....	39
16	Heat and fire resistance.....	39
Annex A (normative)	Explanations regarding relays.....	40
Annex B (informative)	Inductive contact loads.....	43
Annex C (normative)	Test set-up.....	45
Annex D (informative)	Special loads.....	49
Annex E (normative)	Heating test arrangement.....	52
Annex F (normative)	Measurement of clearances and creepage distances.....	53
Annex G (normative)	Relation between rated impulse voltage, nominal voltage and overvoltage category	59
Annex H (normative)	Pollution degrees	60
Annex I (normative)	Proof tracking test	61
Annex J (informative)	Schematic diagram of families of terminations	62
Annex K (normative)	Glow-wire test	63
Annex L (normative)	Ball pressure test	64
Annex M (informative)	Needle flame test.....	65
	Alphabetical list of terms.....	66
	Bibliography.....	67
	Figure A.1 – Diagram explaining terms related to monostable relays	40
	Figure A.2 – Example explaining terms relating to contacts.....	41
	Figure A.3 – Explanations regarding the operative range of the coil voltage.....	41
	Figure A.4 – Explanation regarding the preconditioning and testing of the operate voltage according to 5.2.1 (Class 1) and 9.2	42

Figure A.5 – Explanation regarding the preconditioning and testing of the operate voltage according to 5.2.2 and 9.2	42
Figure C.1 – Standard test circuit.....	45
Figure C.2 – Functional block diagram	46
Figure C.3 – Contact load categories	48
Figure D.1 – Circuit for cable load.....	49
Figure D.2 – Test circuit for inrush current loads (e.g. capacitive loads and simulated tungsten filament lamp loads) – AC circuits.....	50
Figure D.3 – Example for a tungsten filament lamp test for relays rated 10/100 A/250 V~/2,5 ms	50
Figure D.4 – Test circuit for inrush current loads (e.g. capacitive loads and simulated lamp loads) – DC circuits	51
Figure D.5 – Test circuit for inrush current loads (e.g. simulated fluorescent lamp loads) with power-factor correction	51
Figure E.1 – Test arrangement	52
Figure J.1 – Schematic diagram of families of terminations.....	62
Figure L.1 – Ball pressure test apparatus.....	64
Table 1 – Reference values of influence quantities	18
Table 2 – Categories of protection	20
Table 3 – Type testing	21
Table 4 – Required relay data.....	22
Table 5 – Symbols	24
Table 6 – Examples for indication of rated values	24
Table 7 – Thermal classification.....	24
Table 8 – Cross-sectional areas and lengths of conductors dependent on the current carried by the terminal	26
Table 9 – Minimum values of insulation resistance.....	28
Table 10 – Dielectric strength – AC.....	29
Table 11 – Dielectric strength – DC	30
Table 12 – Schematics for contact loading.....	31
Table 13 – Provisions for the dimensioning of clearances and creepage distances	34
Table 14 – Minimum clearances in air for insulation coordination	35
Table 15 – Material groups	35
Table 16 – Minimum creepage distances for equipment subject to long-term stresses	36
Table 17 – Rated insulation voltage according to supply system voltage.....	37
Table 18 – Test conditions for test Tb	38
Table B.1 – Verification of the making and breaking capacity (abnormal conditions)	43
Table B.2 – Verification of the making and breaking capacity (normal conditions)	44
Table B.3 – Electrical endurance test.....	44
Table C.1 – Characteristics of power sources for contact loads	46
Table C.2 – Standard contact load characteristics	47
Table G.1 – Rated impulse voltage for equipment energized directly from the low-voltage mains	59

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTROMECHANICAL ELEMENTARY RELAYS –**Part 1: General requirements**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61810-1 has been prepared by IEC technical committee 94: All-or-nothing electrical relays.

This third edition cancels and replaces the second edition published in 2003. This edition constitutes a technical revision.

The relevant modifications are:

- update of references;
- renumbering of clauses to bring them into a more logical order;
- inclusion of contact load categories (same as in IEC 61810-2 and IEC 61810-7);
- clarifications concerning electrical endurance (Clause 11);
- inclusion of provisions for insulation coordination in accordance with the basic safety standards IEC 60664-3, IEC 60664-4 and IEC 60664-5 (Clause 13);

- renumbering of all annexes in the order they are referenced in the body of the standard;
- inclusion of new Annex C (normative) for the test set-up, and new Annex D (informative) for special loads (based upon similar annexes in IEC 61810-2 and IEC 61810-7);
- improvement of Annex B covering inductive contact loads.

The text of this standard is based on the following documents:

FDIS	Report on voting
94/267/FDIS	94/269/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of IEC 61810 series, published under the general title *Electromechanical elementary relays* can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

A bilingual version of this document may be issued at a later date.

The contents of the corrigendum of February 2010 have been included in this copy.

ELECTROMECHANICAL ELEMENTARY RELAYS –

Part 1: General requirements

1 Scope

This part of IEC 61810 applies to electromechanical elementary relays (non-specified time all-or-nothing relays) for incorporation into equipment. It defines the basic functional requirements and safety-related aspects for applications in all areas of electrical engineering or electronics, such as:

- general industrial equipment,
- electrical facilities,
- electrical machines,
- electrical appliances for household and similar use,
- information technology and business equipment,
- building automation equipment,
- automation equipment,
- electrical installation equipment,
- medical equipment,
- control equipment,
- telecommunications,
- vehicles,
- transportation (e.g. railways).

Compliance with the requirements of this standard is verified by the type tests indicated.

In case the application of a relay determines additional requirements exceeding those specified in this standard, the relay should be assessed in line with this application in accordance with the relevant IEC standard(s) (e.g. IEC 60730-1, IEC 60335-1, IEC 60950-1).

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60038:1983, *IEC standard voltages*
Amendment 1 (1994)
Amendment 2 (1997)

IEC 60050, *International Electrotechnical Vocabulary*

IEC 60068-2-2:2007, *Environmental testing – Part 2-2: Tests – Test B: Dry heat*

IEC 60068-2-17:1994, *Basic environmental testing procedures – Part 2: Tests – Test Q: Sealing*

IEC 60068-2-20:1979, *Basic environmental testing procedures – Part 2: Tests – Test T: Soldering*
Amendment 2 (1987)

IEC 60085:2004, *Electrical insulation – Thermal classification*

IEC 60112:2003, *Method for the determination of the proof and the comparative tracking indices of solid insulating materials*

IEC 60364-4-44:2007, *Low voltage electrical installations – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*

IEC 60417:2007, *Graphical symbols for use on equipment*

IEC 60664-1:2007, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60664-3:2003, *Insulation coordination for equipment within low-voltage systems – Part 3: Use of coating, potting or moulding for protection against pollution*

IEC 60664-4:2005, *Insulation coordination for equipment within low-voltage systems – Part 4: Consideration of high-frequency voltage stress*

IEC 60664-5:2007, *Insulation coordination for equipment within low-voltage systems – Part 5: Comprehensive method for determining clearances and creepage distances equal to or less than 2 mm*

IEC 60695-2-10:2000, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60695-2-11:2000, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products*

IEC 60695-2-12:2000, *Fire hazard testing – Part 2-12: Glowing/hot-wire based test methods – Glow-wire flammability test method for materials*

IEC 60695-2-13:2000, *Fire hazard testing – Part 2-13: Glowing/hot-wire based test methods – Glow-wire ignitability test method for materials*

IEC 60695-10-2:2003, *Fire hazard testing – Part 10-2: Abnormal heat – Ball pressure test*

IEC 60721-3-3:2002, *Classification of environmental conditions – Part 3-3: Classification of groups of environmental parameters and their severities – Stationary use at weatherprotected locations*

Amendment 1 (1995)

Amendment 2 (1996)

IEC 60999-1:1999, *Connecting devices – Electrical copper conductors – Safety requirements for screw-type and screwless-type clamping units – Part 1: General requirements and particular requirements for clamping units for conductors from 0,2 mm² up to 35 mm² (included)*

IEC 61210:1993, *Connecting devices – Flat quick-connect terminations for electrical copper conductors – Safety requirements*

IEC 61760-1:2006, *Surface mounting technology – Part 1: Standard method for the specification of surface mounting components (SMDs)*

IEC 61984:2001, *Connectors – Safety requirements and tests*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050, in particular IEC 60050-444 and the following apply.

An alphabetical list of terms can be found at the end of this standard.

NOTE In the text of this standard, the term *relay* is used instead of *elementary relay* to improve the readability.

3.1 Definitions related to general terms

3.1.1

marking

identification of a relay which, when completely given to the manufacturer of this relay, allows the unambiguous indication of its electrical, mechanical, dimensional and functional parameters

EXAMPLE Through the indication of the trade mark and the type designation on the relay, all relay-specific data can be derived from the type code.

3.1.2

intended use

use of a relay for the purpose for which it was made, and in the manner intended by the manufacturer

3.1.3

relay technology categories

categorization of relays, based upon environmental protection

NOTE Six categories are in use (RT 0 to RT V).

[IEV 444-01-11, modified]

3.1.4

pulse width modulation

PWM

pulse time modulation in which the pulse duration varies in accordance with a given function of the value of the modulating signal

[IEV 702-06-57]

3.2 Definitions of relay types

3.2.1

electrical relay

device designed to produce sudden and predetermined changes in one or more output circuits when certain conditions are fulfilled in the electric input circuits controlling the device

[IEV 444-01-01]

NOTE 1 For the purpose of this standard, output circuits are contact circuits.

NOTE 2 For the purpose of this standard, the term "coil" is used to denote "input circuit", although other types of input circuits are possible.

3.2.2

all-or-nothing relay

electrical relay, which is intended to be energized by a quantity, the value of which is either within its operative range or effectively zero

NOTE "All-or-nothing relays" include both "elementary relays" and "time relays".

[IEV 444-01-02]

3.2.3

elementary relay

all-or-nothing relay which operates and releases without any intentional time delay

[IEV 444-01-03, modified]

3.2.4

electromechanical relay

electrical relay in which the intended response results mainly from the movement of mechanical elements

[IEV 444-01-04]

3.2.5

electromagnetic relay

electromechanical relay in which the designed response is produced by means of electromagnetic forces

[IEV 444-01-05]

3.2.6

monostable relay

electrical relay which, having responded to an energizing quantity and having changed its condition, returns to its previous condition when that quantity is removed

[IEV 444-01-07]

3.2.7

bistable relay

electrical relay which, having responded to an energizing quantity and having changed its condition, remains in that condition after the quantity has been removed; a further appropriate energization is required to make it change its condition

[IEV 444-01-08]

NOTE Bistable relays are also called latching relays.

3.2.8

polarized relay

electrical relay, the change of condition of which depends upon the polarity of its DC energizing quantity

[IEV 444-01-09, modified]

3.2.9

non-polarized relay

electrical relay, the change of condition of which does not depend upon the polarity of its energizing quantity

[IEV 444-01-10]

3.3 Definitions related to conditions and operations

3.3.1

release condition

for a monostable relay, specified condition of the relay when it is not energized; for a bistable relay, one of the specified conditions, as declared by the manufacturer

[IEV 444-02-01]

NOTE See Figure A.1.

3.3.2

operate condition

for a monostable relay, specified condition of the relay when it is energized by the specified energizing quantity and has responded to that quantity; for a bistable relay, the condition other than the release condition as declared by the manufacturer

[IEV 444-02-02]

NOTE See Figure A.1.

3.3.3

operate (verb)

change from the release condition to the operate condition

[IEV 444-02-04]

NOTE See Figure A.1.

3.3.4**release (verb)**

for a monostable relay, change from the operate condition to the release condition

[IEV 444-02-05]

NOTE See Figure A.1.

3.3.5**reset (verb)**

for a bistable relay, change from the operate condition to the release condition

[IEV 444-02-06]

3.3.6**cycle**

operation and subsequent release/reset

[IEV 444-02-11]

3.3.7**frequency of operation**

number of cycles per unit of time

[IEV 444-02-12]

3.3.8**continuous duty**

duty in which the relay remains energized for a period long enough to reach thermal equilibrium

[IEV 444-02-13]

3.3.9**intermittent duty**

duty in which the relay performs a series of identical cycles, the durations in the energized and unenergized conditions being specified; the duration of energization of the relay is such as will not permit the relay to reach thermal equilibrium

[IEV 444-02-14, modified]

3.3.10**temporary duty**

duty in which the relay remains energized for insufficient duration to reach thermal equilibrium, the time intervals of energization being separated by unenergized time intervals of duration sufficient to restore equality of temperature between the relay and the surrounding medium

[IEV 444-02-16]

3.3.11**duty factor**

ratio of the duration of energization to the total period in which intermittent or continuous or temporary duty takes place

NOTE The duty factor can be expressed as a percentage of the total period.

[IEV 444-02-15]

3.3.12**thermal resistance (of the coil)**

quotient of the temperature rise of the relay coil by the input power, measured after a period long enough to reach thermal equilibrium

NOTE The thermal resistance usually is given in K/W.

[IEV 444-02-17]

3.3.13

ambient temperature

temperature(s) prescribed for the air surrounding the relay under certain conditions, when the relay is mounted as indicated by the manufacturer

3.3.14

limiting continuous thermal withstand power

highest steady state value of the applied electric power that a relay can withstand continuously, and under specified conditions, while satisfying specified temperature rise requirements

[IEV 444-03-18, modified]

NOTE Comprises both the applied power at the coil(s) and the contact(s).

3.3.15

thermal equilibrium

variation of less than 1 K between any two out of three consecutive measurements made at an interval of 5 min

3.3.16

rated value

value of a quantity used for specification purposes, established for a specific set of operating conditions

[IEV 444-02-18, modified]

3.3.17

test value

value of a quantity for which the relay shall comply with a specified action during a test

[IEV 444-02-20]

3.3.18

actual value

value of a quantity determined by measurement on a specific relay, during performance of a specified function

[IEV 444-02-21]

3.3.19

mechanical endurance

number of cycles under specified conditions with unloaded contact(s)

[IEV 444-07-10, modified]

3.4 Definitions of operating values

3.4.1

energizing quantity

electrical quantity which, when applied to the coil(s) of a relay under specified conditions, enables it to fulfil its purpose

NOTE For relays, the energizing quantity is usually a voltage. Therefore, the input voltage as energizing quantity is used in the definitions given in 3.4. Where a relay is energized by a given current instead, the respective terms and definitions apply with "current" used instead of "voltage".

[IEV 444-03-01, modified]

3.4.2

operate voltage

set voltage (for bistable relays only)

value of the coil voltage at which a relay operates