## INTERNATIONAL STANDARD



First edition 1993-04-15

# Reciprocating internal combustion engine driven alternating current generating sets -

### Part 2:

## iTeh Signes ARD PREVIEW

### (standards.iteh.ai)

Groupes électrogènes à courant alternatif entraînés par moteurs alternatifs à cômbustion interne https://standards.itch.ai/catalog/standards/sist/b7229a84-611d-45a6-91da-Partie 2: Moteurs d59d98b30416/iso-8528-2-1993



Reference number ISO 8528-2:1993(E)

### Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75% of the member bodies casting a vote.

International Standard ISO 8528-2 was prepared by Technical Committee ISO/TC 70, Internal combustion engines, Sub-Committee SC 2, Performance and tests.

#### <u>ISO 8528-2:1993</u>

ISO 8528 consists of the holdowing oparts i/ounderstand on derstand and a standard and a standar

- Part 1: Application, ratings and performance
- Part 2: Engines
- Part 3: Alternating current generators for generating sets
- Part 4: Controlgear and switchgear
- Part 5: Generating sets
- Part 6: Test methods
- Part 7: Technical declarations for specification and design
- Part 8: Low-power general-purpose generating sets
- Part 9: Measurement and evaluation of mechanical vibration

© ISO 1993

International Organization for Standardization

Case Postale 56 • CH-1211 Genève 20 • Switzerland

Printed in Switzerland

All rights reserved. No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

- Part 10: Measurement of airborne noise Enveloping surface method
- Part 11: Security generating sets with uninterruptible power systems

Parts 7, 8, 9 and 10 are in course of preparation. Part 11 is at an early stage of preparation and may be split into two parts.

### iTeh STANDARD PREVIEW (standards.iteh.ai)

<u>ISO 8528-2:1993</u> https://standards.iteh.ai/catalog/standards/sist/b7229a84-611d-45a6-91dad59d98b30416/iso-8528-2-1993

## iTeh STANDARD PREVIEW (standards.iteh.ai)

### This page intentionally left blank

https://standards.iteh.ai/catalog/standards/sist/b7229a84-611d-45a6-91dad59d98b30416/iso-8528-2-1993

### Reciprocating internal combustion engine driven alternating current generating sets -

### Part 2: Engines

#### Scope 1

This part of ISO 8528 specifies the principal characteristics of a reciprocating internal combustion (RIC) engine when used for alternating current (a.c.) gen R erating set applications.

(standards.iengines - Performance - Part 4: Speed governing. It applies to RIC engines for a.c. generating sets for ISO 3046-5:1978, Reciprocating internal combustion land and marine use, excluding generating sets engines — Performance — Part 5: Torsional viused on aircraft or to propel land vehicles and loco-/standards.iteh.ai/catalog/standards/sis tbration84-611d-45a6-91damotives. d59d98b30416/iso-8528-2-1993

For some specific applications (for example, essential hospital supplies, high rise buildings, etc.), supplementary requirements may be necessary. The provisions of this part of ISO 8528 should be regarded as a basis.

The terms which define the speed governing and the speed characteristics of RIC engines are listed and explained where they apply specifically to the use of the engine for driving generators.

For other reciprocating-type prime movers (e.g. sewage gas engines, steam engines), the provisions of this part of ISO 8528 should be used as a basis.

#### Normative references 2

The following standards contain provisions which, through reference in this text, constitute provisions of this part of ISO 8528. At the time of publication, the editions indicated were valid. All standards are subject to revision, and parties to agreements based on this part of ISO 8528 are encouraged to investigate the possibility of applying the most recent editions of the standards indicated below. Members of IEC and ISO maintain registers of currently valid International Standards.

ence conditions and declarations of power, fuel consumption and lubricating oil consumption. ISO 3046-4:1978, Reciprocating internal combustion

ISO 3046-1:1986, Reciprocating internal combustion

engines - Performance - Part 1: Standard refer-

ISO 3046-6:1990, Reciprocating internal combustion engines - Performance - Part 6: Overspeed pro-

ISO 8528-1:1993, Reciprocating internal combustion engine driven alternating current generating sets -Part 1: Application, ratings and performance.

ISO 8528-5:1993, Reciprocating internal combustion engine driven alternating current generating sets -Part 5: Generating sets.

#### **Symbols** 3

tection.

- Declared speed, in revolutions per minute n<sub>r</sub>
- Firing speed, in revolutions per minute  $n_{\rm sf}$
- Maximum permissible speed, in revolutions n<sub>max</sub> per minute
- Partial-load speed, in revolutions per minna ute
- Declared no-load speed, in revolutions per  $n_{\rm i,r}$ minute

#### ISO 8528-2:1993(E)

- Lowest adjustable no-load speed, in revoln<sub>i,min</sub> utions per minute
- Highest adjustable no-load speed, in revoln<sub>i,max</sub> utions per minute
- Setting speed of overspeed limiting den<sub>d,s</sub> vices, in revolutions per minute
- Operating speed of overspeed limiting den<sub>d.o</sub> vices, in revolutions per minute
- Related range of speed setting δns
- Range of speed setting  $\Delta n_{\rm s}$
- Downward range of speed setting  $\Delta n_{\rm s.do}$
- Related downward range of speed setting  $\delta n_{\rm s,do}$
- Upward range of speed setting  $\Delta n_{\rm s.up}$
- Related upward range of speed setting  $\delta n_{s,up}$
- Rate of change of speed setting vn
- $\delta n_{st}$ Speed droop
- $\Delta \delta n_{st}$ Speed/power characteristic deviation
- Engine power, in kilowatts take due account of any particular characteristic of Р the connected electrical load and of any load ac-
- Actual engine power, in kilowatts Standard septance conditions expected by the customer. Pa
- ISO 8528-5.1.2, ISO standard power Declared engine power, in kilowatts  $P_r$
- Response time, in secondsdards.iteh.ai/catalog/standards/sist/b7229a84-611d-45a6-91dat<sub>r</sub> d59d98b30416/is
- Brake mean effective pressure, in kilo $p_{me}$ pascals
- Swept volume of the engine, in cubic centi- $V_{\rm st}$ metres

#### Other regulations and additional 4 requirements

4.1 For RIC engines driving a.c. generating sets used on board ships and offshore installations which have to comply with rules of a classification society, the additional requirements of the classification society shall be observed. The classification society shall be stated by the customer prior to placing of the order.

For engines operating in non-classed equipment, such additional requirements are in each case subject to agreement between the manufacturer and customer.

4.2 If special requirements from regulations of any other authority (e.g. inspecting and/or legislative authorities) have to be met, the authority shall be stated by the customer prior to placing of the order.

Any further additional requirements shall be subject to agreement between the manufacturer and customer

#### **General characteristics** 5

#### 5.1 Power characteristics

#### 5.1.1 General

The power output required at the RIC engine coupling (net brake power as defined in ISO 3046-1) shall take into account the required electrical power for the customer's plant, the electrical power required for the essential independent auxiliaries (see ISO 3046-1) and the power loss in the a.c. generator.

In addition to the steady-state power requirement, sudden power changes due to additional loads, e.g. caused by electric motor starting, shall be taken into account since they affect the power output characteristics of RIC engines and voltage characteristics of a.c. generators.

The generating set manufacturer shall therefore

## 5.1.3 Service power

facturer in accordance with ISO 3046-1.

The RIC engine power (see ISO 8528-1) required for a particular application, under site conditions to drive the a.c. generator with any essential independent auxiliaries (see ISO 3046-1), and with the generating set developing rated electrical power, shall be determined in accordance with ISO 3046-1.

In order to ensure a continuous supply of electrical power to the connected load, it is essential that the actual power output required from the RIC engine driving the generator is not more than the service power. The RIC engine driving the generator shall provide additional power to meet any specified transient load requirements. Overload power, as defined in ISO 3046-1, is not available.

#### 5.2 Main characteristics of the RIC engine

The main characteristics of the RIC engine to be used by the generating set manufacturer shall be given by the engine manufacturer, specifying

- the power under ISO standard and service conditions;

- the declared speed;
- the fuel and lubricating oil consumptions under ISO standard conditions.

These characteristics declared by the engine manufacturer enable the generating set manufacturer and customer to confirm that the main characteristics of the RIC engines available are suitable for the application.

In order to evaluate the generating set service conditions (in particular, sudden-load acceptance) it is necessary to establish the brake mean effective pressure,  $p_{me}$ , in kilopascals<sup>1</sup>), of the engine used, corresponding to the engine power when the generating set is operating at its declared power and rated frequency, and defined as follows:

$$p_{\rm me} = \frac{KP}{V_{\rm st} n_{\rm r}}$$

where  $K = 1.2 \times 10^5$  for a four-stroke engine and  $0.6 \times 10^5$  for a two-stroke engine.

#### 5.3 Low-load operation

life of the RIC engine. The onus is on the RIC engine manufacturer to provide the generating set manufacturer with data of the minimum load the RIC engine is capable of sustaining indefinitely without deterioration. If the generating set is to be operated at lower loads than this minimum load, the onus is on the RIC engine manufacturer to specify, and if necessary recommend, the measures to be adopted and/or corrective procedures to be used.

#### 6 Speed characteristics

#### 6.1 General

The choice of governing system shall be based upon the steady-state and transient speed performance requested by the customer. The generating set manufacturer shall ensure that a suitable governing system, approved by the RIC engine manufacturer, is selected to meet the application requirements.

NOTE 1 ISO 3046-4 establishes general requirements and parameters of speed governing systems. ISO 3046-6 establishes general requirements for overspeed protection devices.

The customer shall be made aware that extended RDThe terms, symbols and definitions for speed running under low load may affect the reliability and characteristics are given in 6.2 to 6.5.

<u>ISO 8528-2:1993</u> https://standards.iteh.ai/catalog/standards/sist/b7229a84-611d-45a6-91dad59d98b30416/iso-8528-2-1993

### 6.2 General speed terms

No.	Term	Symbol	Definition
6.2.1	Declared speed	n <sub>r</sub>	Engine speed at declared power corresponding to the rated frequency of the generating set.
6.2.2	Firing speed (starting speed)	n <sub>sf</sub>	Engine speed to which an engine must be accelerated from rest by the use of an external supply of energy separate from the fuel feed system before the engine becomes self-sustaining.
6.2.3	Partial-load speed	n <sub>a</sub>	Steady-state engine speed of an engine running at <i>a</i> % of the declared power: $a = 100 \times \frac{P_{a}}{P_{r}}$
		iTeh S	EXAMPLE 45 % power: $a = 45$ (see figure 2) For $a = 45$ $n_a = n_{i,r} - \frac{P_a}{P_r} (n_{i,r} - n_r)$ $= n_{i,r} - 0.45 (n_{i,r} - n_r)$ Corresponding values of declared speed and partial-load speed are based on an unchanged speed setting.
6.2.4	Delcared no-load speed	n <sub>i,r</sub>	Steady-state engine speed without load at the same speed setting as for the declared speed $n_r$ (it is a particular case of 6.2.3; see figure 1). ISO 8528-2:1993

https://standards.iteh.ai/catalog/standards/sist/b7229a84-611d-45a6-91da-

<sup>6.3</sup> Speed setting terms of governor (see 9d98b30416/iso-8528-2-1993 figure 1)

No.	Term	Symbol	Definition
6.3.1	Lowest adjustable no-load speed	n <sub>i,min</sub>	Lowest steady-state engine speed without load obtainable on the gov- ernor speed setting device.
6.3.2	Highest adjustable no-load speed	n <sub>i,max</sub>	Highest steady-state engine speed without load obtainable on the gov- ernor speed setting device.
6.3.3	Range of speed set- ting	$\Delta n_{s}$	Range between the highest and lowest adjustable no-load speeds: $\Delta n_{\rm s} = n_{\rm i,max} - n_{\rm i,min}$
	Related range of speed setting	δn <sub>s</sub>	Range of speed setting, expressed as a percentage of the declared speed: $\delta n_{\rm s} = \frac{n_{\rm i,max} - n_{\rm i,min}}{n_{\rm r}} \times 100$

No.	Term	Symbol	Definition
6.3.3.1	Downward range of speed setting	$\Delta n_{ m s,do}$	Range between the declared no-load speed and the lowest adjustable no-load speed: $\Delta n_{\rm s,do} = n_{\rm i,r} - n_{\rm i,min}$
	Related downward range of speed set- ting	δ <b>n<sub>s,do</sub></b>	Downward range of speed setting, expressed as a percentage of the declared speed: $\delta n_{s,do} = \frac{n_{i,r} - n_{i,min}}{n_r} \times 100$
6.3.3.2	Upward range of speed setting	∆n <sub>s,up</sub>	Range between the highest adjustable no-load speed and the declared no-load speed: $\Delta n_{s,up} = n_{i,max} - n_{i,r}$
	Related upward range of speed set- ting	δ <i>n</i> <sub>s,up</sub>	Upward range of speed setting, expressed as a percentage of the de- clared speed: $\delta n_{s,up} = \frac{n_{i,max} - n_{i,r}}{n_r} \times 100$
6.3.4	Rate of change of speed setting	h STA (sta	Rate of change of speed setting under remote control, expressed as a percentage of the related range of speed setting per second: $\frac{(n_{i,max} - n_{i,min})/n_r}{n_r} \times 100$

## ISO 8528-2:1993 6.4 Steady-state speed terms of governor/standards/sist/b7229a84-611d-45a6-91da-

No.	Term	Symbol	Definition
6.4.1	Speed droop	δn <sub>st</sub>	Difference between the declared no-load speed and the declared speed at declared power, for a fixed speed setting (see figure 1). It is expressed as a percentage of the declared speed. $\delta n_{\rm st} = \frac{n_{\rm i,r} - n_{\rm r}}{n_{\rm r}} \times 100$
6.4.2	Speed/power charac- teristic curve		Curve of steady-state speeds in the power range between no-load and declared power plotted against RIC engine power (see figures 1 and 2).
6.4.3	Speed/power charac- teristic deviation	Δδ <i>n</i> <sub>st</sub>	Maximum deviation from a linear speed power characteristic curve in the power range between no-load and declared power, expressed as a percentage of the declared speed (see figure 2).

### 6.5 Overspeed terms

No.	Term	Symbol	Definition
6.5.1	Maximum permiss- ible speed	n <sub>max</sub>	Speed of the engine specified by the RIC engine manufacturer which lies a safe amount below the speed limit (see note 2 and figure 3).
6.5.2	Setting speed of overspeed limiting device	n <sub>d,s</sub>	Speed of the engine, the exceeding of which activates the overspeed limiting device (see figure 3).