

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Electrical installations of buildings –
Part 5-55: Selection and erection of electrical equipment – Other equipment**
(standards.iteh.ai)

**Installations électriques des bâtiments –
Partie 5-55: Choix et mise en œuvre des matériels électriques – Autres matériels**

IEC 60364-5-55:2011
<https://standards.iteh.ai/catalog/standards/sist/b0144b01-5076-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2011 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

[IEC 60364-5-55.2011](mailto:IEC.60364-5-55.2011)

- Electropedia: www.electropedia.org ds.iteh.ai/catalog/standards/sist/b6144f61-5676-42c9-ba8b-

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00



IEC 60364-5-55

Edition 2.0 2011-12

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Electrical installations of buildings –
Part 5-55: Selection and erection of electrical equipment – Other equipment**
(standards.iteh.ai)

**Installations électriques des bâtiments –
Partie 5-55: Choix et mise en œuvre des matériels électriques – Autres matériels**
IEC 60364-5-55:2011
3b3b0f59c271/iec-60364-5-55-2011

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

U

ICS 91.140

ISBN 978-2-88912-845-7

CONTENTS

FOREWORD.....	3
550 Introduction	5
550.1 Scope	5
550.2 Normative references	5
550.3 Terms and definitions.....	6
551 Low-voltage generating sets	7
551.1 Scope	7
551.2 General requirements	8
551.3 Protective measure: extra-low-voltage provided by SELV and PELV	9
551.4 Fault protection (protection against indirect contact)	9
551.5 Protection against overcurrent	10
551.6 Additional requirements for installations where the generating set provides a supply as a switched alternative to the normal supply to the installation	11
551.7 Additional requirements for installations where the generating set may operate in parallel with other sources including systems for distribution of electricity to the public	11
551.8 Requirements for installations incorporating stationary batteries	12
559 Luminaires and lighting installations	13
559.1 Scope	13
559.2 Terms and definitions.....	13
559.3 General requirements for installations.....	14
559.4 Protection of the surroundings against thermal effects	14
559.5 Wiring systems for lighting installations.....	14
559.6 Independent lamp controlgear, e.g. ballasts	16
559.7 Compensation capacitors	16
559.8 Protection against electric shock for display stands for luminaires.....	16
559.9 Stroboscopic effect	16
559.10 Ground recessed luminaires.....	17
Annex A (informative) List of notes concerning certain countries.....	18
Annex B (informative) Explanation of symbols used in luminaires, in controlgear for luminaires and in the installation of the luminaires	24
Bibliography.....	26

ITC STANDARD PREVIEW
(standards.iteh.ai)

[IEC 60364-5-55:2011](http://standards.iteh.ai/catalog/standards/sis/b6144f61-5676-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011)

<http://standards.iteh.ai/catalog/standards/sis/b6144f61-5676-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTRICAL INSTALLATIONS OF BUILDINGS –**Part 5-55: Selection and erection of electrical equipment –
Other equipment**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60364-5-55 has been prepared by IEC technical committee 64: Electrical installations and protection against electric shock.

This second edition cancels and replaces the first edition, published in 2001, its Amendment 1 (2001) and its Amendment 2 (2008).

The major technical changes with respect to the previous edition are listed below:

- additional requirements for connection of luminaires to the fixed wiring;
- modification of requirements regarding the fixing of luminaires;
- inclusion of alternative solutions for connecting devices used for through wiring and for connection of luminaires to the supply;
- withdrawal of Clause 556, as IEC 60364-5-56 now covers this matter.

The text of this standard is based on the following documents:

FDIS	Report on voting
64/1805/FDIS	64/1813/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 60364 series, under the general title *Low-voltage electrical installations*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[IEC 60364-5-55:2011](https://standards.iteh.ai/catalog/standards/sist/b6144f61-5676-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011)

<https://standards.iteh.ai/catalog/standards/sist/b6144f61-5676-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011>

ELECTRICAL INSTALLATIONS OF BUILDINGS –

Part 5-55: Selection and erection of electrical equipment – Other equipment

550 Introduction

550.1 Scope

This part of IEC 60364 covers requirements for the selection and erection of low-voltage generating sets and for the selection and erection of luminaires and lighting installations intended to be part of the fixed installation.

550.2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-195, *International Electrotechnical Vocabulary – Part 195: Earthing and protection against electric shock*

IEC 60050-826, *International Electrotechnical Vocabulary – Part 826: Electrical installations*

IEC 60079 (all parts), *Explosive atmospheres*

IEC 60245-3, *Rubber insulated cables – Rated voltages up to and including 450/750 V – Part 3: Heat resistant silicone insulated cables*

IEC 60331-11, *Tests for electric cables under fire conditions – Circuit integrity – Part 11: Apparatus – Fire alone at a flame temperature of at least 750 °C*

IEC 60331-21, *Tests for electric cables under fire conditions – Circuit integrity – Part 21: Procedures and requirements – Cables of rated voltage up to and including 0,6/1,0 kV*

IEC 60364-1:2005, *Low-voltage electrical installations – Part 1: Fundamental principles, assessment of general characteristics, definitions*

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-42, *Low-voltage electrical installations – Part 4-42: Protection for safety – Protection against thermal effects*

IEC 60364-4-43, *Low-voltage electrical installations – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-5-53:2001, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60364-7-712, *Electrical installations of buildings – Part 7-712: Requirements for special installations or locations – Solar photovoltaic (PV) power supply systems*

IEC 60364-7-717, *Low-voltage electrical installations – Part 7-717: Requirements for special installations or locations – Mobile or transportable units*

IEC 60417 (all parts), *Graphical symbols for use on equipment*

IEC 60570, *Electrical supply track systems for luminaires*

IEC 60598 (all parts), *Luminaires*

IEC 60598-2-13:2006, *Luminaires – Part 2-13: Particular requirements – Ground recessed luminaires*

IEC 60598-2-22:1997, *Luminaires – Part 2-22: Particular requirements – Luminaires for emergency lighting*

IEC 60670 (all parts), *Boxes and enclosures for electrical accessories for household and similar fixed electrical installations*

IEC 60670-21, *Boxes and enclosures for electrical accessories for household and similar fixed electrical installations – Part 21: Particular requirements for boxes and enclosures with provision for suspension means*

IEC 60702-1, *Mineral insulated cables and their terminations with a rated voltage not exceeding 750 V – Part 1: Cables*

IEC 60702-2, *Mineral insulated cables and their terminations with a rated voltage not exceeding 750 V – Part 2: Terminations*

IEC 60998 (all parts), *Connecting devices for low-voltage circuits for household and similar purposes – Part 1: General requirements*

IEC 61048:2006, *Auxiliaries for lamps – Capacitors for use in tubular fluorescent and other discharge lamp circuits – General and safety requirements*

IEC 61535, *Installation couplers intended for permanent connection in fixed installations*

IEC 61995 (all parts), *Devices for the connection of luminaires for household and similar purposes*

ISO 8528-12, *Reciprocating internal combustion engine driven alternating current generating sets – Part 12: Emergency power supply to safety services*

550.3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

550.3.1

self-contained battery unit

unit comprising a battery and a charging and testing unit

550.3.2

non-maintained mode

operating mode of electrical equipment, essential for safety services, operating only when the normal supply fails

550.3.3

maintained mode

operating mode of electrical equipment, essential for safety services, operating at all times

550.3.4

safety services

those services in a building which are essential

- for the safety of persons,
- for avoiding damage to the environment or other material

NOTE Examples of safety services include

- emergency (escape) lighting,
- fire pumps,
- fire brigade lifts,
- alarm systems, such as fire alarms, smoke alarms, CO alarms and intruder alarms,
- evacuation systems,
- smoke extraction systems,
- essential medical equipment.

550.3.5 electrical safety source

source intended to maintain the supply to electrical equipment essential for the safety services

550.3.6 electrical supply system for safety services see IEC 60050-826

550.3.7 rated operating time of a safety source

operating time for which a safety source is designed under normal operating conditions.

551 Low-voltage generating sets

IEC 60364-5-55:2011

<https://standards.iteh.ai/catalog/standards/sist/b6144f61-5676-42c9-ba8b-3b3b0f59c271/iec-60364-5-55-2011>

551.1 Scope

This clause provides requirements for the selection and erection of low-voltage and extra-low voltage generating sets intended to supply, either continuously or occasionally, all or part of the installation. Requirements are also included for installations with the following supply arrangements:

- supply to an installation which is not connected to a system for distribution of electricity to the public;
- supply to an installation as an alternative to a system for distribution of electricity to the public;
- supply to an installation in parallel with a system for distribution of electricity to the public supply;
- appropriate combinations of the above.

This part does not apply to self-contained items of extra-low voltage electrical equipment which incorporate both the source of energy and the energy-using load and for which a specific product standard exists that includes the requirements for electrical safety.

NOTE Requirements of the electricity distributor should be ascertained before a generating set is installed in an installation that is connected to a system for distribution of electricity to the public.

551.1.1 Generating sets with the following power sources are considered:

- combustion engines;
- turbines;
- electric motors;

- photovoltaic cells (IEC 60364-7-712 also applies);
- electrochemical accumulators;
- other suitable sources.

551.1.2 Generating sets with the following electrical characteristics are considered:

- mains-excited and separately excited synchronous generators;
- mains-excited and self-excited asynchronous generators;
- mains-commutated and self-commutated static converters with or without by-pass facilities;
- generating sets with other suitable electrical characteristics.

551.1.3 The use of generating sets for the following purposes is considered:

- supply to permanent installations;
- supply to temporary installations;
- supply to portable equipment which is not connected to a permanent installation;
- supply to mobile units (IEC 60364-7-717 also applies).

551.2 General requirements

551.2.1 The means of excitation and commutation shall be appropriate for the intended use of the generating set and the safety and proper functioning of other sources of supply shall not be impaired by the generating set.

NOTE See 551.7 for particular requirements where the generating set may operate in parallel with a system for the distribution of electricity to the public.

[IEC 60364-5-55:2011](https://standards.iteh.ai/catalog/standards/sist/b6144861-5676-42a9-b96b-3b3b050c271/iec-60364-5-55-2011)

551.2.2 The prospective short-circuit current and prospective earth fault current shall be assessed for each source of supply or combination of sources which can operate independently of other sources or combinations. The short-circuit breaking capacity of protective devices within the installation and, where appropriate, connected to a system for distribution of electricity to the public, shall not be exceeded for any of the intended methods of operation of the sources.

NOTE Attention should be given to the power factor specified for protective devices in the installation.

551.2.3 The capacity and operating characteristics of the generating set shall be such that danger or damage to equipment does not arise after the connection or disconnection of any intended load as a result of the deviation of the voltage or frequency from the intended operating range. Means shall be provided to automatically disconnect such parts of the installation as may be necessary if the capacity of the generating set is exceeded.

NOTE 1 Attention should be given to the size of individual loads as a proportion of the capacity of the generating set and to motor starting currents.

NOTE 2 Attention should be given to the power factor specified for protective devices in the installation.

NOTE 3 The installation of a generating set within an existing building or installation may change the conditions of external influence for the installation (see IEC 60364-1), for example by the introduction of moving parts, parts at high temperature or by the presence of inflammable fluids and noxious gases, etc.

551.2.4 Provision for isolation shall meet the requirements of Clause 537 for each source or combination of sources of supply.

551.3 Protective measure: extra-low-voltage provided by SELV and PELV

551.3.1 Additional requirements for SELV and PELV where the installation is supplied from more than one source

Where a SELV or PELV system may be supplied by more than one source, the requirements of 414.3 of IEC 60364-4-41:2005 shall apply to each source. Where one or more of the sources is earthed, the requirements for PELV systems in 414.4 of IEC 60364-4-41:2005 shall apply.

If one or more of the sources does not meet the requirements of 414.3, the system shall be treated as a FELV system and the requirements of 411.7 of IEC 60364-4-41:2005 shall apply.

551.3.2 Additional requirements where it is necessary to maintain the supply to an extra-low voltage system

Where it is necessary to maintain the supply to an extra-low voltage system following the loss of one or more sources of supply, each source of supply or combination of sources of supply which can operate independently of other sources or combinations shall be capable of supplying the intended load of the extra-low voltage system. Provisions shall be made so that the loss of low-voltage supply to an extra-low voltage source does not lead to danger or damage to other extra-low voltage equipment.

NOTE Such precautions may be necessary in supplies for safety services (see Clause 35 of IEC 60364-1:2005).

551.4 Fault protection (protection against indirect contact)

551.4.1 Fault protection shall be provided for the installation in respect of each source of supply or combination of sources of supply that can operate independently of other sources or combinations of sources.

<https://standards.iteh.ai/catalog/standards/sist/b6144f61-5676-42c9-ba8b-385b01962714/iec-60364-5-55-2011>

The fault protective provisions shall be selected or precautions shall be taken to ensure that where fault protective provisions are achieved in different ways within the same installation or part of an installation according to the active sources of supply, no influence shall occur or conditions arise that could impair the effectiveness of the fault protective provisions.

NOTE This might, for example, require the use of a transformer providing electrical separation between parts of the installation using different earthing systems.

551.4.2 The generating set shall be connected so that any provision within the installation for protection by residual current devices in accordance with IEC 60364-4-41 remains effective for every intended combination of sources of supply.

NOTE Connection of live parts of the generator with earth may affect the protective measures.

551.4.3 Protection by automatic disconnection of supply

551.4.3.1 General

Where the protective measure automatic disconnection of supply is used for protection against electric shock, the requirements of Clause 411 of IEC 60364-4-41:2005 apply, except as modified for the particular cases given in 551.4.3.2 or 551.4.3.3.

551.4.3.2 Additional requirements for installations where the generating set provides a supply as a switched alternative to the normal supply to the installation

Protection by automatic disconnection of supply shall not rely upon the connection to the earthed point of the distribution system when the generator is operating as a switched alternative. A suitable means of earthing shall be provided.

551.4.3.3 Additional requirements for installations incorporating static converters

551.4.3.3.1 Where fault protection for parts of the installation supplied by the static converter relies upon the automatic closure of the by-pass switch and the operation of protective devices on the supply side of the by-pass switch is not within the time required by Clause 411 of IEC 60364-4-41:2005, supplementary equipotential bonding shall be provided between simultaneously accessible exposed-conductive-parts and extraneous-conductive-parts on the load side of the static converter in accordance with 415.2 of IEC 60364-4-41:2005.

The resistance of supplementary equipotential bonding conductors required between simultaneously accessible conductive parts shall fulfill the following condition:

$$R \leq \frac{50 \text{ V}}{I_a}$$

where

I_a is the maximum earth fault current which can be supplied by the static converter alone for a period of up to 5 s.

NOTE Where such equipment is intended to operate in parallel with a system for distribution of electricity to the public, the requirements of 551.7 also apply.

551.4.3.3.2 Precautions shall be taken or equipment shall be selected so that the correct operation of protective devices is not impaired by d.c. currents generated by a static converter or by the presence of filters.

551.4.3.3.3 A means of isolation shall be installed on both sides of a static converter.

This requirement does not apply on the power source side of a static converter which is integrated in the same enclosure as the power source.

551.5 Protection against overcurrent

551.5.1 Where overcurrent protection of the generating set is required, it shall be located as near as practicable to the generator terminals.

NOTE The contribution to the prospective short-circuit current by a generating set may be time-dependent and may be much less than the contribution made by a system where the source is a mv/lv transformer.

551.5.2 Where a generating set is intended to operate in parallel with another source of supply, including a supply from a system for distribution of electricity to the public, or where two or more generating sets may operate in parallel, harmonic currents shall be limited so that the thermal rating of conductors is not exceeded.

The effects of harmonic currents may be limited as follows:

- the selection of generating sets with compensated windings;
- the provision of a suitable impedance in the connection to generator star points;
- the provision of switches which interrupt the circuit but which are interlocked so that at all times fault protection is not impaired;
- the provision of filtering equipment;
- other suitable means.

NOTE 1 Consideration should be given to the maximum voltage which may be produced across an impedance connected to limit harmonics.

NOTE 2 Monitoring equipment complying with IEC 61557-12 provides information on level of disturbances resulting from the presence of harmonics.

551.6 Additional requirements for installations where the generating set provides a supply as a switched alternative to the normal supply to the installation

551.6.1 Precautions complying with the relevant requirements of IEC 60364-5-53 for isolation shall be taken, so that the generator cannot operate in parallel with the public supply system for distribution of electricity to the public. Suitable precautions may include:

- an electrical, mechanical or electro-mechanical interlock between the operating mechanisms or control circuits of the change-over switching devices;
- a system of locks with a single transferable key;
- a three-position, break-before-make, change-over switch;
- an automatic change-over switching device with a suitable interlock;
- other means providing equivalent security of operation.

NOTE Isolation should include supplies to the control circuits of the generator.

551.6.2 For TN-S systems where the neutral is not switched, any residual current device shall be positioned to avoid incorrect operation due to the existence of any parallel neutral-earth path.

NOTE 1 It may be desirable in TN systems to disconnect the neutral of the installation from the neutral or PEN of the system for distribution of electricity to the public to avoid disturbances such as induced voltage surges caused by lightning.

NOTE 2 See also 444.4.7 of IEC 60364-4-44:2007.

551.7 Additional requirements for installations where the generating set may operate in parallel with other sources including systems for distribution of electricity to the public

551.7.1 Where a generating set is used as an additional source of supply in parallel with another source, protection against thermal effects in accordance with IEC 60364-4-42 and protection against overcurrent in accordance with IEC 60364-4-43 shall remain effective in all situations.

Except where an uninterruptible power supply is provided to supply specific items of current using equipment within the final circuit to which it is connected, such a generating set shall be installed on the supply side of all the protective devices for the final circuits of the installation.

551.7.2 A generating set used as an additional source of supply in parallel with another source shall be installed:

- on the supply side of all the protective devices for the final circuits of the installation, or
- on the load side of all the protective devices for a final circuit of the installation, but in this case all the following additional requirement shall be fulfilled:
 - a) the conductors of the final circuit shall meet the following requirement:

$$I_z \geq I_n + I_g$$

where

I_z is the current-carrying capacity of the final circuit conductors;

I_n is the rated current of the protective device of the final circuit;

I_g is the rated output current of the generating set; and

- b) a generating set shall not be connected to a final circuit by means of a plug and socket; and
- c) a residual current device providing protection of the final circuit in accordance with Clause 411 or Clause 415 of IEC 60364-4-41:2005 shall disconnect all live conductors including the neutral conductor; and
- d) the line and neutral conductors of the final circuit and of the generating set shall not be connected to earth downstream of the protective device of the final circuit.

NOTE Where the generating set is installed in a final circuit on the load side of all the protective devices for that final circuit, except where the protective devices for the final circuit disconnect the line and the neutral conductors, the disconnection time in accordance with 411.3.2 of IEC 60364-4-41:2005 is the combination of the disconnection time of the protective device for the final circuit and the time taken for the output voltage of the generating set to be reduced to less than 50 V.

551.7.3 In selecting and using a generating set to run in parallel with another source, including the system for distribution of electricity to the public, care shall be taken to avoid adverse effects to that system and to other installations in respect of power factor, voltage changes, harmonic distortion, d.c. current injection, unbalance, starting, synchronizing or voltage fluctuation effects. In the case of a system for distribution of electricity to the public, the distributor shall be consulted in respect of particular requirements. Where synchronization is necessary, the use of automatic synchronizing systems which consider frequency, phase and voltage is to be preferred.

551.7.4 Where a generating set is intended to run in parallel with the system for distribution of electricity to the public, means of automatic switching shall be provided to disconnect the generating set from the system for distribution of electricity to the public in the event of loss of that supply or deviation of the voltage or frequency at the supply terminals from values declared for normal supply.

The type of protection and the sensitivity and operating times depend upon the protection of the system for distribution of electricity to the public and the number of generating sets connected and shall be agreed by the distributor.

In case of presence of static converters, the means of switching shall be provided on the load side of this static converter.

551.7.5 Where a generating set is intended to run in parallel with the system for distribution of electricity to the public, means shall be provided to prevent the connection of a generating set to the system for distribution of electricity to the public in the event of loss of that supply or deviation of the voltage or frequency at the supply terminals from values declared for normal supply.

551.7.6 Where a generating set is intended to run in parallel with the system for distribution of electricity to the public, means shall be provided to enable the generating set to be isolated from the system for distribution of electricity to the public. The accessibility of this means of isolation shall comply with national rules and distribution system operator requirements.

551.7.7 Where a generating set may also operate as switched alternative to the distribution system, the installation shall also comply with 551.6.

551.8 Requirements for installations incorporating stationary batteries

551.8.1 Stationary batteries shall be installed so that they are accessible only to skilled or instructed persons.

NOTE This generally requires the battery to be installed in a secure location, or, for smaller batteries, a secure enclosure.

The location or enclosure shall be adequately ventilated.

551.8.2 Battery connections shall have basic protection by insulation or enclosures or shall be arranged so that two bare conductive parts having between them a potential difference exceeding 120 V cannot be inadvertently touched simultaneously.

559 Luminaires and lighting installations

559.1 Scope

The particular requirements of this clause apply to the selection and erection of luminaires and lighting installations intended to be part of the fixed installation.

Additional requirements for specific types of lighting installations are covered in

- IEC 60364-7-702 for installations in swimming pools and fountains;
- IEC 60364-7-711 for installations in exhibitions, shows and stands;
- IEC 60364-7-713 for electrical installations in furniture;
- IEC 60364-7-714 for outdoor lighting installations;
- IEC 60364-7-715 for extra-low-voltage lighting installations.

The requirements of this clause do not apply to:

- high-voltage signs supplied at low voltage (called neon-tube);

NOTE 1 Requirements for high-voltage signs supplied at low voltage (called neon-tube) are included in IEC 60598-2-14.

- signs and luminous-discharge-tube installations operating from a no-load rated output voltage exceeding 1 kV but not exceeding 10 kV;
- temporary festoon lighting.

NOTE 2 Safety requirements for luminaires are covered by IEC 60598 series.

559.2 Terms and definitions

For the purposes of this clause, the general terms and definitions of IEC 60364-1, the IEC 60598 series, IEC 60050-195, IEC 60050-826 and IEC 60570, as well as the following apply.

559.2.1

luminaire

apparatus which distributes, filters or transforms the light transmitted from one or more lamps and which includes, except the lamps themselves, all the parts necessary for fixing and protecting the lamps and, where necessary, circuit auxiliaries together with the means for connecting them to the electric supply

[IEC 60050-845:1987, 845-10-01]

559.2.2

display stands for luminaires

permanent stands in sales rooms or part of sales rooms which are used to display luminaires

NOTE The following items are not regarded as display stands:

- trade fair stands, in which luminaires remain connected for the duration of the fair;
- temporary exhibition panels with permanently connected luminaires;
- exhibition panels with a range of luminaires which can be connected with a plug-in device.