

INTERNATIONAL STANDARD

**Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –
Part 3-3: Examinations and measurements – Active monitoring of changes in attenuation and return loss**

IEC 61300-3-3:2009

<https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-ade9-eb1fdd604ace/iec-61300-3-3-2009>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2009 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

www.iec.ch

<https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-adc9-eb1fdd604ace/iec-61300-3-3-2009>



IEC 61300-3-3

Edition 3.0 2009-03

INTERNATIONAL STANDARD

**Fibre optic interconnecting devices and passive components – Basic test and measurement procedures –
Part 3-3: Examinations and measurements – Active monitoring of changes in attenuation and return loss**

[IEC 61300-3-3:2009](https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-ade9-eb1fdd604ace/iec-61300-3-3-2009)

<https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-ade9-eb1fdd604ace/iec-61300-3-3-2009>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE

R

ICS 33.180.20

ISBN 978-2-88910-496-3

CONTENTS

FOREWORD.....	4
1 Scope.....	6
2 Normative references	6
3 General description	6
3.1 Test method	6
3.2 Precautions	7
4 Apparatus.....	7
4.1 Methods 1, 2 and 3.....	7
4.1.1 General	7
4.1.2 Source (S).....	7
4.1.3 Launch condition (E).....	8
4.1.4 Monitoring equipment	8
4.1.5 Detector D.....	9
4.1.6 Stress fixture	9
4.1.7 Branching device BD	9
4.1.8 Temporary joints.....	9
4.1.9 Data acquisition.....	9
4.1.10 Monitor sample.....	9
4.1.11 Reference fibre.....	10
4.2 Methods 4 and 5.....	11
4.2.1 General	11
4.2.2 OTDR.....	11
4.2.3 Buffer fibre	11
4.2.4 Optical switches	11
5 Procedure	13
5.1 Monitoring attenuation and return loss of a single sample – method 1	13
5.1.1 General	13
5.1.2 Attenuation monitoring – method 1	13
5.1.3 Return loss monitoring – method 1	14
5.2 Monitoring attenuation and return loss of multiple samples using a 1 × N branching device – method 2.....	14
5.2.1 General	14
5.2.2 Attenuation monitoring – method 2	14
5.2.3 Return loss monitoring – method 2	14
5.3 Monitoring attenuation and return loss of multiple samples using two 1 × N optical switches – method 3	14
5.3.1 General	14
5.3.2 Attenuation – method 3.....	14
5.3.3 Return loss – method 3.....	15
5.4 Bidirectional OTDR monitoring of attenuation and return loss of multiple samples – method 4	16
5.4.1 General	16
5.4.2 Attenuation – method 4.....	16
5.4.3 Return loss – method 4.....	18
5.5 Unidirectional OTDR monitoring of attenuation and return loss of multiple samples – method 5	19
6 Details to be specified	19

6.1	Method 1	19
6.2	Methods 2 and 3.....	20
6.3	Methods 4 and 5.....	20
Figure 1	– Method 1 – Monitoring attenuation and return loss of a single sample undergoing stress testing.....	10
Figure 2	– Method 2 – Monitoring attenuation and return loss of multiple samples using a 1 × N branching device	10
Figure 3	– Method 3 – Monitoring attenuation and return loss of multiple samples using two 1 × N optical switches	11
Figure 4	– Method 4 – Bidirectional OTDR monitoring of attenuation and return loss of multiple samples.....	12
Figure 5	– Method 5 – Unidirectional OTDR monitoring of attenuation and return loss of multiple samples	13
Figure 6	– Cut-back measurement location (transmission)	15
Figure 7	– Typical OTDR trace caused by the reflection from a DUT	17
Figure 8	– Cut-back measurement location (OTDR)	18
Table 1	– Example values for Rayleigh backscatter coefficient.....	19

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61300-3-3:2009](https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-adc9-eb1fdd604ace/iec-61300-3-3-2009)

<https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-adc9-eb1fdd604ace/iec-61300-3-3-2009>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**FIBRE OPTIC INTERCONNECTING DEVICES
AND PASSIVE COMPONENTS –
BASIC TEST AND MEASUREMENT PROCEDURES –****Part 3-3: Examinations and measurements –
Active monitoring of changes in attenuation and return loss**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61300-3 has been prepared by subcommittee 86B: Fibre optic interconnecting devices and passive components, of IEC technical committee 86: Fibre optics.

This third edition cancels and replaces the second edition published in 2003. This edition constitutes a minor revision.

The change with respect to the previous edition is the structure of the document.

The text of this standard is based on the following documents:

FDIS	Report on voting
86B/2808/FDIS	86B/2830/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of IEC 61300 series, published under the general title *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61300-3-3:2009](https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-adc9-eb1fdd604ace/iec-61300-3-3-2009)

<https://standards.iteh.ai/catalog/standards/iec/1fd0f69d-3407-4035-adc9-eb1fdd604ace/iec-61300-3-3-2009>

FIBRE OPTIC INTERCONNECTING DEVICES AND PASSIVE COMPONENTS – BASIC TEST AND MEASUREMENT PROCEDURES –

Part 3-3: Examinations and measurements – Active monitoring of changes in attenuation and return loss

1 Scope

This part of IEC 61300 describes the procedure to monitor changes in attenuation and/or return loss of a component or an interconnecting device, when subjected to an environmental or mechanical test. Such a procedure is commonly referred to as active monitoring. In many instances, it is more efficient to monitor attenuation and return loss at the same time.

The procedure may be applied to measurements on single samples or to simultaneous measurements on multiple samples, both at single wavelengths and multiple wavelengths, by using branching devices and/or switches as appropriate.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61300-1, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 1: General and guidance*

IEC 61300-3-1, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-1: Examinations and measurements – Visual examination*

IEC 61300-3-6, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-6: Examinations and measurements – Return loss*

IEC 61300-3-35, *Fibre optic interconnecting devices and passive components – Basic test and measurement procedures – Part 3-35: Examinations and measurements – Fibre optic cylindrical connector endface visual and automated inspection*¹

3 General description

3.1 Test method

The procedure describes a number of active monitoring measurement methods. Method 1 describes the situation where a single sample is subject to mechanical or environmental stress testing. Methods 2 and 3 describe methods for monitoring changes in the optical performance of multiple samples. Methods 4 and 5 measure changes in the optical performance of samples using an OTDR. Methods 4 and 5 may be used only when the OTDR averaging time is much less than the variation time of the test conditions. Where there is any form of uncertainty over the measurement method used, method 1 shall be considered to be the reference method.

¹ To be published.

All methods are capable of being configured to monitor changes in attenuation and return loss at the same time. The required optical test parameters shall be defined in the relevant specification.

Where a group of samples is being monitored over a period of time, say several days or weeks, it is usual to employ some form of automated data acquisition. Also, since the changes in optical performance can be very small, it is important to ensure high measurement stability over time.

3.2 Precautions

The following requirements shall be met.

- a) Precautions shall be taken to ensure that cladding modes do not affect the measurement.
- b) Precautions shall be taken to prevent movement in the position of the fibre cables between the sample(s) and the test apparatus, to avoid changes in optical performance caused by bending losses.
- c) The stability performance of the test equipment shall be $\leq 0,05$ dB or 10 % of the attenuation to be measured, whichever is the lower value. The stability shall be maintained over the measurement time. The required measurement resolution shall be 0,01 dB for both multimode and single-mode.
- d) To achieve consistent results, clean and inspect all samples prior to measurement in accordance with the manufacturer's instructions. Visual examination shall be undertaken in accordance with IEC 61300-3-1 and IEC 61300-3-35.
- e) The power in the fibre shall be at a level that does not generate non-linear scattering effects (typically < 3 mW).
- f) It is common to be monitoring changes in optical performance that are small in comparison with the polarization dependence of the components under test (DUT) and of parts of the test apparatus such as branching devices, switches and detectors. Therefore, it is usually necessary to specify light sources with a low degree of polarization or to couple the source to low polarization-inducing optics.
- g) Particularly, when measuring wavelength dependent components such as multiplexers or attenuators, it is necessary to use a light source that does not emit light at extraneous wavelengths at levels that can affect the measurement accuracy.
- h) Reflected powers from the test apparatus shall be at a level that does not affect the measurement accuracy.
- i) Care must be taken when using switches or branching devices for multimode measurements. In many cases, these devices will modify the launched mode power distribution or result in modal detection non-uniformity, which will give rise to measurement inaccuracies.

4 Apparatus

4.1 Methods 1, 2 and 3

4.1.1 General

The apparatus used for methods 1, 2 and 3 of this procedure is shown in Figures 1, 2 and 3. The apparatus consists of the following.

4.1.2 Source (S)

The source consists of an optical emitter, the means to connect to it, and associated drive electronics. In addition to meeting the stability and power level requirements, the source shall have the following characteristics.

Centre wavelength: as detailed in the performance and product standard

Spectral width: filtered LED ≤ 150 nm full width at half maximum (FWHM)

Spectral width: LD < 10 nm FWHM

For multimode fibres, broadband sources such as an LED shall be used.

NOTE 1 The interference of modes from a coherent source will create speckle patterns in multimode fibre. These speckle patterns give rise to speckle or modal noise and are observed as power fluctuations, since their characteristic times are longer than the resolution time of the detector. As a result, it may be impossible to achieve stable launch conditions using coherent sources for multimode measurements. Consequently, lasers should be avoided in favour of LEDs or other incoherent sources for measuring multimode components.

For single-mode fibres, either an LED or an LD may be used.

There are a number of methods of monitoring performance at multiple wavelengths. One method, illustrated in Figure 3, shows independent light sources joined by an optical switch SW3.

NOTE 2 It is particularly important to consider the wavelength dependence of the test apparatus when monitoring multiple wavelengths. For example, different switch ports may not have the same wavelength dependence. This can affect comparative measurements made between any channel “i” and the reference channel, since they will be connected to different switch ports. It is therefore necessary, in such circumstances, to complete an accurate spectral characterization of the test set-up prior to use.

4.1.3 Launch condition (E)

The launch condition shall be specified in accordance with Annex B of IEC 61300-1.

4.1.4 Monitoring equipment

Where multiple measurements are made, suitable apparatus is required to permit monitoring of the light through the multiple paths.

In Figure 2, individual monitoring channels are established by dividing the light into N paths using a $1 \times N$ branching device (BD). This method is practical for a small number of DUTs, since it requires a multiplicity of branching devices and detectors.

In Figure 3, active switching of the light paths through the DUTs is used. The apparatus consists of a directional branching device and two $1 \times N$ computer-controlled optical switches. The channel number of these switches is sufficiently large to accommodate the DUTs under test, one or more reference lines, and a reference reflectance channel.

NOTE The design of systems to test multiple samples requires the trade-off of a number of factors such as cost and measurement capability. When testing multimode samples, for example, it may be inappropriate to use branching devices and/or optical switches, due to the problems surrounding modal losses and the associated cost of the test apparatus. However, optical switches may be cost-effective for testing single-mode samples, particularly when the cost of suitable sources and detectors and the measurement stability requirements are considered.

Switch parameters which shall be considered for this test include the following.

a) Repeatability

The switches shall be capable of high repeatability in per-channel insertion loss, since this parameter will directly detract from the accuracy of the measurement of attenuation or return loss of the DUT. Furthermore, since environmental tests are generally carried out over extended periods the switch repeatability shall be considered over the full duration of the test.

b) Return loss

The return loss characteristics of the switch shall be such that they do not unduly influence the measurement in methods 2 and 3.

c) Wavelength dependence