

# TECHNICAL REPORT



---

**Guideline for combining different single-mode fibres types**  
**(standards.iteh.ai)**

IEC TR 62000:2010

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-7fcfab7d8214/iec-tr-62000-2010>



**THIS PUBLICATION IS COPYRIGHT PROTECTED**  
**Copyright © 2010 IEC, Geneva, Switzerland**

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland  
Email: [inmail@iec.ch](mailto:inmail@iec.ch)  
Web: [www.iec.ch](http://www.iec.ch)

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: [www.iec.ch/online\\_news/justpub](http://www.iec.ch/online_news/justpub)

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: [www.iec.ch/webstore/custserv](http://www.iec.ch/webstore/custserv)

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: [csc@iec.ch](mailto:csc@iec.ch)  
Tel.: +41 22 919 02 11  
Fax: +41 22 919 03 00

STANDARD PREVIEW

(standards.iteh.ai)

IEC TR 62000:2010

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12->

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12->



# TECHNICAL REPORT



---

**Guideline for combining different single-mode fibres types**  
**(standards.iteh.ai)**

IEC TR 62000:2010

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-7fcfab7d8214/iec-tr-62000-2010>

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

PRICE CODE



---

ICS 33.180.10

ISBN 978-2-88912-268-4

## CONTENTS

FOREWORD.....	3
1 Scope.....	5
2 Abbreviations.....	6
3 System issues.....	6
4 Fibre issues.....	6
4.1 General.....	6
4.2 Cut-off wavelength.....	7
4.3 Splicing issues.....	7
4.4 Combination of fibre parameters: chromatic dispersion coefficient and slope, polarization mode dispersion (PMD).....	8
4.5 Non-linear effects.....	8
5 Launch fibres, pigtails, patch-cords and jumper cables.....	9
6 Attenuation.....	9
7 Summary.....	9
Bibliography.....	11

## **iTeh STANDARD PREVIEW** **(standards.iteh.ai)**

[IEC TR 62000:2010](https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-7fcfab7d8214/iec-tr-62000-2010)

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-7fcfab7d8214/iec-tr-62000-2010>

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

**GUIDELINE FOR COMBINING DIFFERENT SINGLE-MODE FIBRES TYPES**

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC 62000, which is a technical report, has been prepared by subcommittee 86A: Fibres and cables, of IEC technical committee 86: Fibre optics.

This second edition cancels and replaces the first edition (2005) and constitutes a technical revision.

The major technical changes with respect to the previous edition are considerations concerning B6 fibres.

The text of this technical report is based on the following documents:

Enquiry draft	Report on voting
86A/1276/DTR	86A/1283/RVC

Full information on the voting for the approval of this technical report can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

**IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.**

IEC TR 62000:2010

<https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-7fcfab7d8214/iec-tr-62000-2010>

## GUIDELINE FOR COMBINING DIFFERENT SINGLE-MODE FIBRES TYPES

### 1 Scope

This technical report provides guidelines concerning single-mode fibre compatibility.

A given type of single-mode fibre, for example B4, may have different implementations by suitably optimising several of the following parameters: mode field diameter (hence effective area), chromatic dispersion coefficient, slope of the chromatic dispersion curve, cable cut-off wavelength.

This guideline indicates the items that should be taken into account when planning to connect: (1) different implementations of single-mode fibres of the same type, e.g. different implementations of type B single-mode fibres, and (2) single-mode fibres of different types, e.g. B1.1 with B4. See IEC 60793-2-50 for the attributes and definitions of single-mode fibre. The attributes and definitions of fibres covered in this technical report are given in Table 1.

**Table 1 – Correspondence table of various single-mode fibres**

<b>Common name</b>	<b>Use (IEC 60793-2-50)</b>	<b>IEC Class</b>	<b>ITU-T Recommendation</b>
<b>Dispersion unshifted single-mode fibre</b>	Optimised for use in the 1 310 nm region but can be used in the 1 550 nm region	B1.1	G.652 A, B
<b>Cut-off shifted single-mode fibre</b>	Optimised for low loss in the 1 550 nm region, with cut off wavelength shifted above the 1 310 nm region	B1.2	G.654
<b>Extended band dispersion unshifted single-mode fibre</b>	Optimised for use in the 1 310 nm region but can be used in the O, E, S, C and L-band (i.e. throughout the 1 260 nm to 1 625 nm range).	B1.3	G.652 C, D
<b>Dispersion shifted single-mode fibre</b>	Optimised for single channel transmission in the 1 550 nm region. Multiple channels can only be transmitted if care is taken to avoid the effects of four wave mixing by, for example, moderating the power levels or appropriate spacing or placement of the channels	B.2	G.653
<b>Non-zero dispersion-shifted single-mode fibre</b>	Optimised for multiple channel transmission in the 1 550 nm region with a cut off wavelength that may be shifted above the 1 310 nm region	B4	G.655
<b>Wideband non-zero dispersion-shifted single-mode fibre</b>	Optimised for multiple channel transmission in the wavelength range of 1 460 to 1 625 nm with the positive value of the chromatic dispersion coefficient that is greater than some non-zero value over the same wavelength range.	B5	G.656
<b>Bend loss optimised</b>	Bending loss insensitive single-mode fibre suitable for use in the access networks, including inside buildings at the end of these networks.  B6_a fibres are suitable to be used in the O, E, S, C and L-band (i.e. throughout the 1 260 nm to 1 625 nm range) and meet the requirements of B1.3 fibres.	B6_a	G.657.A
	Bending loss insensitive single-mode fibre suitable for use in the access networks, including inside buildings at the end of these networks.	B6_b	G.657.B

<i>Common name</i>	<i>Use (IEC 6079-2-50)</i>	<i>IEC Class</i>	<i>ITU-T Recommendation</i>
	B6_b fibres are suitable for transmission at 1 310 nm, 1 550 nm, and 1 625 nm for restricted distances that are associated with in-building transport of signals.		

This guide does not consider the connection of fibres with the same implementation from different manufacturers, which is already considered by the standardisation procedure.

## 2 Abbreviations

- OTDR: Optical Time Domain Reflectometre
- PMD: Polarization Mode Dispersion
- DWDM: Dense Wavelength Division Multiplexing
- NRZ: Non Return to Zero
- RZ: Return to Zero

## 3 System issues

The different characteristics of B type fibres can be explicitly combined to optimise system performance in terms of the dispersion characteristic (global dispersion coefficients, slope) of the link. It is in fact possible to combine fibres with opposite signs of the dispersion coefficient in a given wavelength range to bring the total link dispersion to near-zero in that range. The final result will however depend on the accuracy of individual fibre dispersion measurements and the ability to match lengths.

[IEC TR 62000:2010](https://standards.iteh.ai/catalog/standards/sist/ed720a5d-bca9-428b-8c12-6cab7d8214/iec-tr-62000-2010)

The process of combining fibres with different dispersion coefficient characteristics can be one of the ways to make dispersion management in a transmission line (the most common one being the periodical insertion of dispersion compensating modules).

Combining fibres with different effective area is also a possible way to minimise the overall impact of non-linear effects. For instance, it is possible to place large effective area fibres in the initial section of a link, where the propagating power is relatively large. In this case, the large core reduces the associated non-linear effects. For link sections away from the source, where power levels are reduced, fibres with smaller effective area may be used, to take advantage of a possible reduction of the dispersion slope or to increase the efficiency of Raman amplification. The relative size and placement of fibres with large effective area versus fibres with smaller effective area are critical issues in system design.

Splice loss considerations (see section 4.3) should also be taken into account when fibres with different effective area or mode field diameter are combined.

## 4 Fibre issues

### 4.1 General

Most fibre characteristics are wavelength dependent: the actual operating wavelengths of the system shall therefore be taken into account when considering the following comments and suggestions.

The compatibility between the fibre specified characteristics (e.g. attenuation and dispersion) and the system operating wavelength must be considered.



## 4.2 Cut-off wavelength

Different fibres have been historically developed for operation in different wavelength ranges: they can therefore have different cut-off wavelengths. If the source wavelength is below the cut-off wavelength, undesirable multi-modal propagation and modal noise could occur.

It should however be considered that the cut-off wavelength is reduced after cabling and installation. The amount of the reduction depends on the refractive index profile, i.e. on the fibre type. If fibre cut-off wavelength is specified, it can be assumed that, after cabling and installation, the cut-off will be down-shifted by several tens of nanometres (depending on the fibre type). Cable cut-off wavelength is therefore specified in Standards. See IEC 60793-2-50 and IEC 60793-1-44.

These considerations should be applied when connecting different fibre types, e.g. type B4 with B1, in order to avoid multimodal operation and noise, which could affect the system performance, depending on the source wavelength. A launch from another single-mode fibre will typically serve as a mode filter which can significantly reduce or eliminate the potential for multimode transmission.

## 4.3 Splicing issues

The very different mode field diameter ranges, typical of the several fibre families, have an effect on splice losses when fibres of different categories are spliced together. Care must be taken to properly adjust splicing equipment and to correctly evaluate the splicing losses among different fibre families, which can show increases in comparison with conventional splice losses.

The optimal set-up parameters of fusion splicers are not the same for the different types of fibres (e.g. B1 versus B6 fibres) or combinations of different implementations of fibres.

Some B6\_b fibres may cause difficulties with the core alignment systems of some fusion splicing machines because the characteristics that provide improved bend loss performance can interact with the splicer alignment field of view. Amended splice programs or specialist fusion splicing technology has eliminated this problem on many fusion splicers. An alternative and recommended approach is to use an outside diameter (OD) or cladding alignment fusion splicing program as is generally used with multimode optical fibres. Since recent advances in fibre manufacturing technology have resulted in improved fibre geometry – with fibre core concentricity errors typically less than 0,5  $\mu\text{m}$  - the splice losses encountered are usually < ~0,1 dB.

Another factor that has to be taken into account when using an OTDR to measure the splice loss across fibres with different mode field diameters is that the bidirectional method is strictly required. The mismatch of mode fields can make a splice appear to have much more loss from one direction than the other. Negative loss or “gain” can also be apparent with uni-directional OTDR measurements. See IEC TR 62316 for more information.

When using an OTDR to measure the distance between splices of various sections of fibre with different mode field diameters, the apparent distance can be different than the actual distance because the group velocity for the different fibres may not be the same. For accurate length measurements, the OTDR length calibration setting must be adjusted according to the section and type of fibre that is present.

Most of the previous considerations also apply to mechanical (temporary or permanent) connections.