

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE  
COMITÉ INTERNATIONAL SPÉCIAL DES PERTURBATIONS RADIOÉLECTRIQUES

BASIC EMC PUBLICATION  
PUBLICATION FONDAMENTALE EN CEM

**Specification for radio disturbance and immunity measuring apparatus and methods –  
Part 1-6: Radio disturbance and immunity measuring apparatus – EMC antenna calibration**

CISPR 16-1-6:2014

**Spécifications des méthodes et des appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques –  
Partie 1-6: Appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques – Étalonnage des antennes CEM**





## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2017 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

#### IEC publications search - [webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

#### IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [sales@iec.ch](mailto:sales@iec.ch).

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

#### IEC Glossary - [std.iec.ch/glossary](http://std.iec.ch/glossary)

67 000 electrotechnical terminology entries in English and French extracted from the Terms and definitions clause of IEC publications issued between 2002 and 2015. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

### A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

### A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

#### Recherche de publications IEC -

[webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

#### Service Clients - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: [sales@iec.ch](mailto:sales@iec.ch).

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

#### Glossaire IEC - [std.iec.ch/glossary](http://std.iec.ch/glossary)

67 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et définitions des publications IEC parues entre 2002 et 2015. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.



CISPR 16-1-6

Edition 1.1 2017-01  
CONSOLIDATED VERSION

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE  
COMITÉ INTERNATIONAL SPÉCIAL DES PERTURBATIONS RADIOÉLECTRIQUES

BASIC EMC PUBLICATION  
PUBLICATION FONDAMENTALE EN CEM

**Specification for radio disturbance and immunity measuring apparatus and methods –  
Part 1-6: Radio disturbance and immunity measuring apparatus – EMC antenna calibration**

**Spécifications des méthodes et des appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques –  
Partie 1-6: Appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques – Étalonnage des antennes CEM**

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

ICS 33.100.10; 33.100.20

ISBN 978-2-8322-3840-0

**Warning! Make sure that you obtained this publication from an authorized distributor.  
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**



## REDLINE VERSION

## VERSION REDLINE



INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE  
COMITÉ INTERNATIONAL SPÉCIAL DES PERTURBATIONS RADIOÉLECTRIQUES

BASIC EMC PUBLICATION  
PUBLICATION FONDAMENTALE EN CEM

**Specification for radio disturbance and immunity measuring apparatus and methods –  
Part 1-6: Radio disturbance and immunity measuring apparatus – EMC antenna calibration**

**Spécifications des méthodes et des appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques –  
Partie 1-6: Appareils de mesure des perturbations radioélectriques et de l'immunité aux perturbations radioélectriques – Étalonnage des antennes CEM**



## CONTENTS

FOREWORD .....	10
1 Scope .....	12
2 Normative references .....	12
3 Terms, definitions and abbreviations .....	13
3.1 Terms and definitions .....	13
3.1.1 Antenna terms .....	13
3.1.2 Antenna factor terms .....	16
3.1.3 Measurement site terms .....	17
3.1.4 Other terms .....	18
3.2 Abbreviations .....	19
4 Fundamental concepts .....	20
4.1 General .....	20
4.2 The concept of antenna factor .....	20
4.3 Calibration methods for 30 MHz and above .....	21
4.3.1 General .....	21
4.3.2 Antenna minimum separation distances .....	21
4.3.3 General considerations for the TAM .....	21
4.3.4 General considerations for the SSM .....	21
4.3.5 General considerations for the SAM .....	22
4.4 Measurement uncertainties for antenna calibration measurement results .....	22
4.5 Summary of methods of measurement to obtain AF .....	23
5 Calibration methods for the frequency range 9 kHz to 30 MHz .....	25
5.1 Calibration of monopole antennas .....	25
5.1.1 General .....	25
5.1.2 Calibration by the ECSM .....	26
5.2 Calibration of loop antennas .....	32
5.2.1 General .....	32
5.2.2 TEM (Crawford) cell method .....	32
6 Frequencies, equipment and functional checks for calibrations at or above 30 MHz .....	35
6.1 Calibration frequencies .....	35
6.1.1 Calibration frequency ranges and increments .....	35
6.1.2 Transition frequency for hybrid antennas .....	36
6.2 Measurement instrumentation requirements for antenna calibrations .....	37
6.2.1 Equipment types .....	37
6.2.2 Mismatch .....	38
6.2.3 Dynamic range and reproducibility of SIL measurement .....	40
6.2.4 Signal-to-noise ratio .....	40
6.2.5 Antenna masts and cables .....	41
6.3 Functional checks of an AUC .....	41
6.3.1 General .....	41
6.3.2 Balance of an antenna .....	41
6.3.3 Cross-polar performance of an antenna .....	41
6.3.4 Radiation patterns of an antenna .....	42
7 Basic parameters and equations common to antenna calibration methods for frequencies above 30 MHz .....	43
7.1 Summary of methods for measurements to obtain AF .....	43

7.2	Site insertion loss measurements.....	43
7.2.1	General .....	43
7.2.2	SIL and SA measurement procedure.....	43
7.2.3	Common uncertainty components of a SIL measurement.....	45
7.3	Basic equations for the calculation of AF from SIL and SA measurements .....	46
7.3.1	Antenna factor from SIL measurements .....	46
7.3.2	Relationship of AF and SIL for a free-space calibration site .....	46
7.3.3	Relationship of AF and SIL for a calibration site with a metal ground plane .....	47
7.4	Equations for AF and measurement uncertainties using the TAM, SSM, and SAM.....	48
7.4.1	TAM .....	48
7.4.2	SSM .....	53
7.4.3	SAM .....	55
7.5	Parameters for specifying antenna phase centre and position .....	57
7.5.1	General .....	57
7.5.2	Reference position and phase centres of LPDA and hybrid antennas.....	58
7.5.3	Phase centres of horn antennas .....	61
8	Details for TAM, SAM, and SSM calibration methods for frequencies of 30 MHz and above .....	63
8.1	General.....	63
8.2	Considerations for $F_a$ calibrations using TAM .....	63
8.2.1	General considerations .....	63
8.2.2	Calibration site and antenna set-up considerations for use with the TAM .....	63
8.2.3	Antenna parameters for a free-space environment or a ground-plane site .....	65
8.2.4	Validation of calibration method.....	66
8.3	Considerations for $F_a$ calibrations using the SAM .....	66
8.3.1	General considerations and calibration site for use of the SAM .....	66
8.3.2	Calibration procedures and antenna set-ups for $F_a$ by the SAM.....	67
8.3.3	Parameters of the STA .....	67
8.4	SSM calibrations at a ground-plane site, 30 MHz to 1 GHz .....	68
8.4.1	General considerations and calibration site for SSM .....	68
8.4.2	Calibration procedure for SSM.....	69
8.4.3	Calculation of $F_a$ .....	69
8.4.4	Uncertainties of $F_a$ obtained using SSM .....	70
9	Calibration procedures for specific antenna types for frequencies of 30 MHz and above .....	71
9.1	General.....	71
9.2	Calibrations for biconical and hybrid antennas in a free-space environment for 30 MHz to 300 MHz, and tuned dipoles for 60 MHz to 1 000 MHz .....	71
9.2.1	General considerations and calibration site requirements .....	71
9.2.2	Calibration procedure and antenna set-up for use with the SAM .....	71
9.2.3	Uncertainties of $F_a$ determined by the SAM .....	72
9.2.4	Antenna set-up for use with the TAM (alternative) .....	74
9.3	Calibration of biconical (30 MHz to 300 MHz) and hybrid antennas, using the SAM and VP at a ground-plane site.....	74
9.3.1	General considerations and calibration site requirements .....	74
9.3.2	Calibration procedure and antenna set-up .....	75
9.3.3	Uncertainties of $F_a$ determined with the SAM.....	76

9.4	Calibration of LPDA, hybrid, and horn antennas in a free-space environment, 200 MHz to 18 GHz.....	77
9.4.1	General considerations and calibration site for a free-space environment.....	77
9.4.2	Calibrations using the TAM.....	79
9.4.3	Antenna set-up for use with the SAM.....	80
9.4.4	Alternative antenna set-up for site with absorber on the ground.....	80
9.5	Calibration of horn and LPDA antennas in a FAR, 1 GHz to 18 GHz.....	81
9.5.1	Calibration using the TAM.....	81
9.5.2	Calibration and antenna set-up for the SAM.....	85
Annex A (informative) Background information and rationale for the methods of antenna calibration.....		86
A.1	Rationale for the need for several calibration methods and for use of a ground-plane site.....	86
A.2	Special measures for calibration of omnidirectional antennas.....	87
A.2.1	General.....	87
A.2.2	Difficulties with calibration of omnidirectional antennas.....	88
A.2.3	Minimizing reflections from antenna supports and radiation from cables.....	88
A.2.4	Field taper and monocone set-up for VP biconical calibration.....	89
A.2.5	Use of HP or VP in a FAR.....	90
A.2.6	Substitution where the STA is the same model as the AUC.....	90
A.3	Calibrations using broadband calculable dipole antennas.....	90
A.3.1	Disadvantages of tuned dipole antennas.....	90
A.3.2	Advantages of broadband calculable dipole antennas.....	91
A.3.3	Disadvantages of calculable dipole antennas.....	91
A.4	Rationale for $F_a$ and biconical/LPDA antenna cross-over frequency.....	91
A.4.1	Rationale for $F_a$ .....	91
A.4.2	Cross-over frequency from biconical to LPDA antennas.....	92
A.4.3	Biconical element designs.....	92
A.5	Sources of increased uncertainty in measurement of $F_a$ by the SSM.....	93
A.6	Calibration of LPDA antennas using smaller separation distances.....	95
A.6.1	Calibration of LPDA antennas using smaller separation distances.....	95
A.6.2	Correction of electric field strength to account for phase centre of LPDA antennas.....	96
A.7	Cross-polar discrimination of LPDA antennas.....	97
A.8	Tips for measurement instrumentation.....	98
A.8.1	Signal-to-noise ratio.....	98
A.8.2	Connector pin depth.....	100
A.8.3	Effect of added adaptor in a “cable-through” measurement.....	100
A.8.4	Compression level.....	101
A.8.5	Source power slope function above 6 GHz.....	101
A.8.6	Frequency increment for detection of resonances.....	101
A.8.7	Return loss or VSWR.....	101
A.9	Uncertainty considerations.....	102
A.9.1	General.....	102
A.9.2	Achievable uncertainties for $F_a$ .....	102
A.9.3	Uncertainties of dipoles above a ground plane.....	102
A.9.4	Verification of uncertainty by comparison of methods.....	103
Annex B (normative) Calibration of biconical antennas and tuned dipole antennas above a ground plane using the TAM and the SAM.....		104

B.1	General.....	104
B.2	Characteristics of biconical antennas and dipole antennas.....	104
B.3	Frequencies .....	104
B.4	Measurement of $F_a(h,p)$ of biconical and tuned dipole antennas and derivation of $F_a$ by averaging $F_a(h,p)$ , 30 MHz to 300 MHz .....	105
B.4.1	General .....	105
B.4.2	Measurement of $F_a(h,H)$ by the SAM and derivation of $F_a$ .....	105
B.4.3	Measurement of $F_a(h,H)$ by the TAM and derivation of $F_a$ .....	108
B.5	Measurement of $F_a$ of tuned dipoles placed high above a ground plane in the frequency range 30 MHz to 1 000 MHz.....	110
B.5.1	General .....	110
B.5.2	Measurement of $F_a$ by the SAM.....	110
B.5.3	Measurement of $F_a$ by the TAM.....	112
Annex C (informative) Rationale for the equations used in antenna calibration and relevant information about antenna characteristics for uncertainty analysis in the frequency range 30 MHz to 1 GHz .....		114
C.1	General.....	114
C.2	Antenna factor and antenna gain .....	114
C.2.1	Relationship between AF and gain for antennas in a free-space environment.....	114
C.2.2	Relationship between AF and gain for monopole antennas on a large ground plane .....	116
C.3	Equations for the insertion loss between antennas.....	116
C.3.1	Site insertion loss measured at a free-space calibration site .....	116
C.3.2	Site insertion loss measured at a metal ground-plane site .....	118
C.3.3	Site attenuation measured at a metal ground-plane site.....	120
C.4	Uncertainty contribution caused by near-field effects .....	121
C.5	Uncertainty contribution due to the antenna proximity coupling .....	122
C.6	Uncertainty contribution due to the ground plane reflection .....	124
C.6.1	Coupling to image in ground plane.....	124
C.6.2	Correction factors $\Delta F_{a,SSM}$ for $F_a$ of biconical antenna .....	129
C.7	Uncertainty contribution due to the antenna radiation pattern.....	130
C.7.1	General .....	130
C.7.2	Biconical antennas .....	131
C.7.3	LPDA antennas.....	131
C.7.4	Hybrid antennas .....	132
C.7.5	Horn and LPDA antennas from 1 GHz to 18 GHz.....	133
Annex D (informative) Background information and rationale for calibration of antennas at frequencies above 1 GHz.....		136
D.1	Mismatch uncertainty .....	136
D.2	Mutual coupling between antennas and chamber reflection .....	136
D.3	Antenna separation distance and phase centre .....	136
D.4	Example gain of DRH at 1 m distance .....	138
Annex E (informative) Notes for measurement uncertainty budgets.....		140
E.1	General.....	140
E.2	Notes for measurement uncertainty budgets .....	140
Annex F (informative) Mismatch uncertainties from a two-port device connected between a transmit port and a receive port .....		150
Annex G (informative) Verification method for calibration of monopole antennas and uncertainty analysis of the ECSM.....		152

G.1	Verification method for calibration of monopole antennas by the plane wave method from 5 MHz to 30 MHz.....	152
G.1.1	Calibration procedure .....	152
G.1.2	Uncertainty evaluation for the calibration of monopole antennas by the plane wave method.....	153
G.2	Uncertainty analysis of the ECSM .....	153
G.2.1	Effect of rod length longer than $\lambda/8$ .....	153
G.2.2	Effect on AF of monopole antenna mounted on a tripod .....	155
G.2.3	Monopole antenna receiving an electric field .....	156
G.2.4	Equivalent capacitance substitution method (ECSM) .....	156
G.2.5	Uncertainties associated with the ECSM.....	158
G.2.6	An alternative to the dummy antenna, for which $F_{ac} = V_D - V_L$ .....	160
Annex H (informative)	Helmholtz coil method for calibration of loop antennas up to 150 kHz .....	161
H.1	Measurement procedure .....	161
H.2	Uncertainties.....	163
Annex I (normative)	Antenna pattern measurement method in the frequency range above 1 GHz, with measurement uncertainty budget.....	165
I.1	General.....	165
I.2	Test set-up .....	165
I.3	Test method.....	167
I.4	Test report .....	170
I.5	Uncertainty budget.....	170
Bibliography	.....	172
Figure 1	– Set-up for AF determination using a network analyzer.....	29
Figure 2	– Set-up for AF determination using a measuring receiver and signal generator.....	29
Figure 3	– Example of mounting a capacitor in the dummy antenna .....	30
Figure 4	– Block diagram of TEM cell set-up for passive loop antennas .....	34
Figure 5	– Block diagram of TEM cell set-up for active loop antennas.....	34
Figure 6	– Example of resonant spike due to poor biconical element connections, using 2 MHz increment.....	36
Figure 7	– Antenna set-up for SIL measurement at a free-space calibration site .....	44
Figure 8	– Antenna set-up for SIL and SA measurement at a ground-plane calibration site .....	44
Figure 9	– Antenna set-up for the TAM at a free-space calibration site .....	49
Figure 10	– Antenna set-up for the TAM at a calibration site with a metal ground plane .....	52
Figure 11	– Antenna set-up for the SSM .....	54
Figure 12	– Antenna set-up for the SAM at a calibration site with a metal ground plane.....	56
Figure 13	– Separation distance relative to the phase centre of an LPDA antenna .....	59
Figure 14	– LPDA antenna with a tapered curved geometry .....	61
Figure 15	– Separation distance with respect to the phase centre of horn antennas (see [49] for details).....	62
Figure 16	– Schematic of a DRH showing relative locations of field point and phase centre of the DRH.....	63
Figure 17	– Biconical antenna set-up for SAM using vertical polarization, showing the paired monocone antenna and an example collapsible-element biconical AUC .....	76

Figure 18 – Test set-up for the calibration of LPDA and hybrid antennas positioned at a large height.....	79
Figure 19 – Set-up for LPDA antennas above absorber.....	81
Figure 20 – Set-up for transmission measurements using a network analyzer .....	83
Figure A.1 – Illustration of the angles of the electromagnetic rays subtended from the scanned LPDA antenna to the fixed height LPDA antenna and to the ground plane .....	94
Figure A.2 – $F_a$ of biconical antenna with 200 $\Omega$ balun measured by the VP method of 9.3, and by the SSM method of 8.4 without correction.....	95
Figure A.3 – $F_a$ of biconical antenna with 200 $\Omega$ balun measured by the VP method of 9.3, and by the SSM method of 8.4 with correction .....	95
Figure A.4 – Separation distance relative to the phase centre of an LPDA antenna.....	97
Figure A.5 – Statistical properties of multiple $S_{21}$ sweeps (minimum, maximum, and mean value).....	99
Figure A.6 – Standard deviation of $S_{21}$ .....	99
Figure A.7 – Normalized standard deviation of $S_{21}$ .....	100
Figure C.1 – Simplified model of a receive antenna .....	115
Figure C.2 – Insertion loss measurement for antenna calibration at a free-space calibration site .....	117
Figure C.3 – Insertion loss measurement for antenna calibration at a calibration site with a metal ground plane .....	119
Figure C.4 – Comparison of field strength given by Equation (C.17) versus in near-field region given by Equation (C.31).....	122
Figure C.5 – Theoretical calculations of proximity coupling effects on the AF from the TAM (free-space conditions) .....	124
Figure C.6 – Deviation of AF from free-space value, $F_a$ , caused by mutual coupling to the image in a metal ground plane (theoretical results) .....	126
Figure C.7 – Variation of $F_a(h,H)$ of biconical antenna with 50 $\Omega$ balun, 30 MHz to 320 MHz at heights every 0,5 m above a ground plane from 1 m to 4 m.....	127
Figure C.8 – AF of Figure C.7 normalized to free-space AF .....	127
Figure C.9 – Variation of $F_a(h,H)$ of biconical antenna with 200 $\Omega$ balun, 30 MHz to 320 MHz at heights every 0,5 m above a ground plane from 1 m to 4 m.....	128
Figure C.10 – Diagram of one triangular section of a biconical antenna element.....	130
Figure C.11 – Examples of radiation patterns (relative realized gain) of two example biconical antennas compared to ideal half-wave tuned dipole antenna.....	131
Figure C.12 – Examples of radiation patterns (relative realized gain) of three example LPDA antennas, compared to ideal half-wave tuned dipole antenna.....	132
Figure C.13 – Examples of radiation patterns (relative realized gain) of an example hybrid antenna, compared to ideal half-wave tuned dipole antenna.....	133
Figure C.14 – Example radiation patterns for classical DRH antenna .....	134
Figure C.15 – Example radiation patterns for novel DRH antenna .....	134
Figure C.16 – Example radiation patterns for classical LPDA antenna .....	135
Figure C.17 – Example radiation patterns for V-type LPDA antenna.....	135
Figure D.1 – Relative phase centres of a DRH antenna and an LPDA antenna .....	137
Figure D.2 – A transmission system between a horn antenna and an LPDA antenna .....	138
Figure D.3 – Measured AFs of a DRH antenna at 4,5 GHz.....	138
Figure D.4 – Graph showing the realized gain at 1 m for a DRH antenna .....	139
Figure E.1 – Comparison of measured and predicted SIL for calculable dipole antenna – 60 MHz element.....	143

Figure E.2 – Comparison of measured and predicted SIL for calculable dipole antenna – 180 MHz element.....	144
Figure E.3 – Reflectivity of chamber absorbing materials .....	148
Figure E.4 – Laser alignment system .....	148
Figure F.1 – Flow graph representation of a two-port device between a transmit port and a receiver port.....	150
Figure F.2 – Signal flow reduction.....	150
Figure G.1 – Diagram showing how the brass rod connects to the type N male bulkhead connector.....	153
Figure G.2 – Graph of the magnitude of the tan(...) ratio term in Equation (4) of 5.1.2.2 .....	154
Figure G.3 – Graphical presentation of Equation (4) of 5.1.2.2 self-capacitance $C_a$ of a 1 m monopole .....	154
Figure G.4 – Graphical presentation of Equation (5) of 5.1.2.2 height correction factor $L_h$ .....	155
Figure G.5 – Calibration set-up consisting of a biconical and a loop antenna, and an elevated monopole antenna with vertical feed wires.....	156
Figure G.6 – Equivalent circuit representation for a monopole antenna system .....	156
Figure G.7 – Monopole antenna calibration using the ECSM .....	157
Figure G.8 – Equivalent circuit representation for the ECSM.....	157
Figure G.9 – Simplified circuit representation for Figure G.8 .....	158
Figure G.10 – Circuit for dummy antenna simulating the effects of the antenna effective height, $h_e$ .....	160
Figure H.1 – Diagram of Helmholtz coil method set-up.....	161
Figure H.2 – Variation of $H/I$ across the central plane between the coils .....	163
Figure I.1 – Typical set-up for antenna pattern measurement.....	166
Figure I.2 – Definition of $d_1$ .....	166
Figure I.3 – Definition of $d_2$ .....	167
Figure I.4 – With $d_1$ held constant, $d_2$ is increased in $x$ cm steps .....	168
Figure I.5 – With $d_2$ held constant, $d_1$ is increased in $x$ cm steps .....	168
Figure I.6 – Distance and angle correction.....	170
Table 1 – Summary of calibration methods above 30 MHz for $F_a$ .....	24
Table 2 – Calibration methods above 30 MHz by subclause number .....	25
Table 3 – Frequency increments for monopole antenna calibration .....	26
Table 4 – Example measurement uncertainty budget for $F_{ac}$ of a monopole antenna calibrated by the ECSM using Equation (9) .....	32
Table 5 –Example measurement uncertainty budget for $F_{aH}$ of a loop antenna measured in a TEM cell .....	35
Table 6 – Frequency increments for broadband antenna calibration.....	35
Table 7 – Example measurement uncertainty budget for common components of a SIL measurement result evaluated from Equation (20) .....	46
Table 8 – Parameters used to determine phase centres of segments A and B.....	61
Table 9 – Example measurement uncertainty budget for $F_a$ of a horizontally-polarized biconical antenna measured by the SSM.....	70
Table 10 – Example measurement uncertainty budget for $F_a$ of a biconical antenna measured by the SAM in a FAR over the frequency range 30 MHz to 300 MHz.....	73

Table 11 – Example measurement uncertainty budget for $F_a$ of a tuned dipole antenna obtained by the SAM in a FAR at a free-space calibration site, using a calculable tuned dipole as the STA in the frequency range above 60 MHz .....	74
Table 12 – Example measurement uncertainty budget for $F_a$ of a biconical antenna measured using the SAM for vertical polarization over the frequency range 30 MHz to 300 MHz .....	77
Table 13 – Example measurement uncertainty budget for $F_a$ of LPDA and hybrid antennas measured by the TAM at 4 m height for the frequency range 200 MHz to 3 GHz .....	80
Table 14 – Example measurement uncertainty budget for $F_a$ of a horn antenna measured by the TAM above 1 GHz for 3 m separation in free space.....	84
Table A.1 – Example type N male and female connector pin depths and tolerances using a type N pin-depth gauge .....	100
Table A.2 – Typical type N adaptor characteristics.....	101
Table B.1 – Antenna set-up for the SAM for tuned dipole antennas with averaging of $F_a(h,H)$ .....	105
Table B.2 – Antenna set-up for the SAM for biconical antennas with averaging of $F_a(h,H)$ .....	106
Table B.3 – Example measurement uncertainty budget for $F_a(h,H)$ of a biconical antenna measured by the SAM over the frequency range 30 MHz to 300 MHz .....	106
Table B.4 – Example measurement uncertainty budget for $F_a$ of a biconical antenna obtained by the SAM with averaging of $F_a(h,H)$ in the frequency range below 300 MHz .....	108
Table B.5 – Example measurement uncertainty budget for $F_a(h,H)$ of a biconical antenna obtained by the TAM with the antenna set-up specified in Table B.2.....	109
Table B.6 – Example measurement uncertainty budget for $F_a$ of a biconical antenna obtained by the TAM with averaging of $F_a(h,H)$ in the frequency range below 300 MHz .....	109
Table B.7 – Antenna set-ups for the SAM for determining $F_a$ of tuned dipole antennas at specific frequencies in the range 30 MHz to 1 000 MHz .....	111
Table B.8 – Example measurement uncertainty budget for $F_a$ of a tuned dipole antenna obtained by the SAM using the antenna set-ups specified in Table B.7 .....	112
Table B.9 – Example measurement uncertainty budget for $F_a$ of a tuned dipole antenna obtained by the TAM using the antenna set-ups specified in Table B.7 .....	113
Table C.1 – Examples of the antenna height range $h$ for horizontal polarization for an error $\leq 0,3$ dB .....	128
Table C.2 – Correction factors $\Delta F_{a,SSM}$ to convert AF measured by SSM to $F_a$ .....	129
Table C.3 – Mechanical dimensions for the biconical antenna [52].....	130
Table G.1 – Example measurement uncertainty budget for $F_a$ of a monopole antenna measured by the SAM.....	153
Table H.1 – Example measurement uncertainty budget for $F_{aH}$ of a loop antenna measured by the Helmholtz coil method for the frequency range 50 kHz to 150 kHz .....	164
Table I.1 – Correction of angle $\alpha$ for a distance of $d_1 = 3$ m (refer to Figure I.6).....	169
Table I.2 – Example measurement uncertainty budget for antenna pattern measurement above 1 GHz.....	171

INTERNATIONAL ELECTROTECHNICAL COMMISSION  
INTERNATIONAL SPECIAL COMMITTEE ON RADIO INTERFERENCE

---

**SPECIFICATION FOR RADIO DISTURBANCE AND IMMUNITY  
MEASURING APPARATUS AND METHODS –**

**Part 1-6: Radio disturbance and immunity measuring apparatus –  
EMC antenna calibration**

**FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

**This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.**

**CISPR 16-1-6 edition 1.1 contains the first edition (2014-12) [documents CISPR/A/1087/FDIS and CISPR/A/1098/RVD] and its amendment 1 (2017-01) [documents CISPR/A/1195/FDIS and CISPR/A/1204/RVD].**

**In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.**