

INTERNATIONAL STANDARD

NORME INTERNATIONALE

High-voltage switchgear and controlgear –
Part 211: Direct connection between power transformers and gas-insulated
metal-enclosed switchgear for rated voltages above 52 kV

Appareillage à haute tension –
Partie 211: Raccordements directs entre transformateurs de puissance et
appareillage sous enveloppe métallique à isolation gazeuse de tensions
assignées supérieures à 52 kV



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2014 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 14 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 55 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Catalogue IEC - webstore.iec.ch/catalogue

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

Recherche de publications IEC - www.iec.ch/searchpub

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 14 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

Plus de 55 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**High-voltage switchgear and controlgear –
Part 211: Direct connection between power transformers and gas-insulated
metal-enclosed switchgear for rated voltages above 52 kV**

**Appareillage à haute tension –
Partie 211: Raccordements directs entre transformateurs de puissance et
appareillage sous enveloppe métallique à isolation gazeuse de tensions
assignées supérieures à 52 kV**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.130.10

ISBN 978-2-8322-1534-0

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	4
1 General.....	6
1.1 Scope.....	6
1.2 Normative references.....	6
2 Normal and special service conditions.....	7
2.1 Normal service conditions.....	7
2.2 Special service conditions.....	7
3 Terms and definitions.....	7
4 Rating.....	8
4.1 Rated voltage (U_r).....	8
4.2 Rated insulation level.....	8
4.3 Rated frequency (f_r).....	9
4.4 Rated continuous current (I_r) and temperature rise.....	9
4.5 Rated short-time withstand current (I_k) and rated thermal short-time current (I_{th}).....	9
4.6 Rated peak withstand current (I_p) and rated dynamic current (I_d).....	9
4.7 Rated duration of short-circuit (t_k) and rated duration (t_{th}).....	9
4.8 Rated filling pressure p_{re} of gas for insulation.....	9
5 Design and construction.....	10
5.1 Limits of supply.....	10
5.2 Pressure withstand requirements.....	11
5.3 Gas and vacuum tightness.....	11
5.4 Mechanical forces applied on the connection interface.....	12
5.5 Mechanical forces applied on the bushing flange.....	12
5.6 Horizontal and vertical displacement.....	13
5.7 Vibrations.....	13
6 Type tests.....	14
6.1 General.....	14
6.2 Dielectric tests.....	14
6.2.1 Dielectric tests of bushing.....	14
6.2.2 Dielectric tests of transformer connection in a single phase enclosure.....	14
6.2.3 Dielectric tests of transformer connection in a three phase enclosure.....	14
6.3 Cantilever load withstand tests.....	14
6.4 Gas tightness tests.....	15
7 Routine tests.....	15
7.1 General.....	15
7.2 External pressure test of the bushing.....	15
7.3 Tightness tests.....	15
8 Standard dimensions and tolerances.....	15
8.1 Single-phase direct connection between oil-filled transformer and switchgear.....	15
8.2 Three-phase direct connection between oil-filled transformer and switchgear.....	15
8.3 Connection between gas-insulated transformer and switchgear.....	16

8.4	Transformer tolerances	16
8.5	Mounting of the transformer on its foundation	16
9	Information to be given with enquiries, tenders and orders	16
10	Transport, storage, erection, operation and maintenance	16
	Bibliography.....	21
	Figure 1 – Typical direct connection between power transformer and gas-insulated metal-enclosed switchgear.....	17
	Figure 2 – Standard dimensions for typical direct connection between power transformer and gas-insulated metal-enclosed switchgear	18
	Figure 3 – Transformer tolerances for a typical direct connection shown on the example of a three-phase power transformer connected to a single-phase gas-insulated metal-enclosed switchgear.....	19
	Figure 4 – Transformer tolerances for a typical direct connection shown on the example of a three-phase power transformer connected to a three-phase gas-insulated metal-enclosed switchgear up to 170 kV	20
	Table 1 – Moment and forces applied on the bushing flange and transformer	13

iTeh STANDARD PREVIEW **(standards.iteh.ai)**

[IEC 62271-211:2014](https://standards.iteh.ai/catalog/standards/sist/97ae0470-2fd9-48c5-9bf5-519e03ca26ab/iec-62271-211-2014)

<https://standards.iteh.ai/catalog/standards/sist/97ae0470-2fd9-48c5-9bf5-519e03ca26ab/iec-62271-211-2014>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 211: Direct connection between power transformers and gas-insulated metal-enclosed switchgear for rated voltages above 52 kV

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62271-211 has been prepared by subcommittee 17C: High-voltage switchgear and controlgear assemblies, of IEC technical committee 17: Switchgear and controlgear.

This first edition cancels and replaces the first edition of IEC/TR 61639:1996 and constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) transfer from technical report to international standard;
- b) the minimum voltage rating was changed from 72,5 kV to above 52 kV;
- c) update of normative references;
- d) definition of insulated junction including limit of supply;

- e) definition of dielectric test of gas-insulated metal-enclosed switchgear for transformer connection in a three phase enclosure;
- f) addition of interface tolerances at transformer side;
- g) addition of transformer tolerances in service;
- h) addition of exceptional loads for bushings and flanges;
- i) consideration of oil- and gas-insulated transformers;
- j) inclusion of three-phase enclosed direct connections.

The text of this standard is based on the following documents:

FDIS	Report on voting
17C/596/FDIS	17C/600/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 62271 series, published under the general title *High-voltage switchgear and controlgear*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed, [IEC 62271-211:2014](#)
- withdrawn, <https://standards.iteh.ai/catalog/standards/sist/97ae0470-2fd9-48c5-9bf5-519e03ca26ab/iec-62271-211-2014>
- replaced by a revised edition, or
- amended.

The contents of the corrigendum 1 of August 2015 and corrigendum 2 of August 2017 have been included in this copy.

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 211: Direct connection between power transformers and gas-insulated metal-enclosed switchgear for rated voltages above 52 kV

1 General

1.1 Scope

This part of IEC 62271 is applicable to single and three phase direct connections between gas-insulated metal-enclosed switchgear (GIS) for rated voltages above 52 kV and transformer arrangements to establish electrical and mechanical interchange ability and to determine the limits of supply of for the transformer connection.

Direct connections are immersed on one end in the transformer oil or insulating gas and on the other end in the insulating gas of the switchgear.

Transformer arrangements are single-phase transformers with single-phase enclosed arrangement, three-phase transformers with three single-phase enclosed arrangements or three-phase transformers with a three-phase enclosed arrangement with three transformer bushings.

The connection satisfies the requirements of IEC 62271-203 for gas-insulated metal-enclosed switchgear, IEC 60076 for power transformer and IEC 60137 for completely immersed bushings.

<https://standards.iteh.ai/catalog/standards/sist/97ae0470-2fd9-48c5-9bf5->

For the purpose of this international standard the term "switchgear" is used for "gas-insulated metal-enclosed switchgear".

1.2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60076 (all parts), *Power transformers*

IEC 60137:2008, *Insulated bushings for alternating voltages above 1 000 V*

IEC 61936-1, *Power installations exceeding 1 kV a.c. – Part 1: Common rules*

IEC 62271-1:2007, *High-voltage switchgear and controlgear – Part 1: Common specifications*

IEC 62271-203:2011, *High-voltage switchgear and controlgear – Part 203: Gas-insulated metal-enclosed switchgear for rated voltages above 52 kV*

IEC 62271-207, *High-voltage switchgear and controlgear – Part 207: Seismic qualification for gas-insulated switchgear assemblies for rated voltages above 52 kV*

2 Normal and special service conditions

2.1 Normal service conditions

Subclauses 2.1 of IEC 62271-1:2007 and IEC 62271-203:2011 are applicable.

2.2 Special service conditions

Subclauses 2.2 of IEC 62271-1:2007 and IEC 62271-203:2011 are applicable.

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 62271-1, as well as the following apply.

3.1 bushing

device that enables a conductor to pass through a transformer tank, and insulates the conductor from it

Note 1 to entry: The means of attachment (flange or fixing device) to the tank forms part of the bushing.

[SOURCE: IEC 60050-471:2007, 471-02-01, modified – update of the definition]

iTeh STANDARD PREVIEW

3.2 completely immersed bushing (standards.iteh.ai)

a bushing both ends of which are intended to be immersed in an insulating medium other than ambient air (e.g. oil or gas)

IEC 62271-211:2014

[SOURCE: IEC 60050-471:2007, 471-02-04]
<https://standards.iteh.ai/catalog/standards/sist/97ae0470-2fd9-48c5-9bf5-519c05ca20ab/iec-62271-211-2014>

3.3 gas-insulated switchgear enclosure

part of gas-insulated metal-enclosed switchgear retaining the insulating gas under the prescribed conditions necessary to maintain safely the highest insulation level, protecting the equipment against external influences and providing a high degree of protection to personnel

[SOURCE: 3.103 of IEC 62271-203:2011]

3.4 main circuit end terminal

part of the main circuit of a gas-insulated metal enclosed switchgear forming part of the connection interface

[SOURCE: 3.2 of IEC 62271-209:2007]

3.5 transformer connection enclosure

part of the gas-insulated metal-enclosed switchgear which houses one end of a completely immersed bushing fitted on a power transformer and a main circuit end terminal

3.6 maximum operating gas pressure

maximum pressure of the gaseous insulating medium in which one end of the bushing is immersed, when in operation, the switchgear-power transformer connection assembly carrying its rated normal current at the maximum ambient air temperature

3.7**design pressure of the enclosure**

relative pressure used to determine the design of the enclosure

Note 1 to entry: It is at least equal to the maximum operating gas pressure in the enclosure at the highest temperature that the gas used for insulation can reach under specified maximum service conditions

[SOURCE: 3.113 of IEC 62271-203:2011, modified – update of the note to entry]

3.8**rated filling pressure p_{re} of gas for insulation**

pressure (in Pa), for insulation, referred to the standard atmospheric air conditions of +20 °C and 101,3 kPa, which may be expressed in relative or absolute terms, to which the assembly is filled before being put into service

[SOURCE: 3.6.5.1 of IEC 62271-1:2007, modified – update of the term and the definition]

3.9**minimum functional pressure p_{me} for insulation**

pressure (in Pa), for insulation, referred to the standard atmospheric air conditions of +20 °C and 101,3 kPa, which may be expressed in relative or absolute terms at which and above which the characteristics of the switchgear-power-transformer connection are maintained and at which replenishment becomes necessary

[SOURCE: 3.6.5.5 of IEC 62271-1:2007, modified – update of the term and the definition]

3.10**insulated junction**

all parts which are needed to insulate the transformer from the switchgear including but not limited to the insulating flange

3.11**proctor density**

moisture-density relationship of a soil for a given compactive effort depending on the amount of water the soil contains during soil compaction of controlled magnitude

4 Rating**4.1 Rated voltage (U_r)**

The rated voltage shall be the rated voltage of the switchgear, selected from the following standard values:

72,5 kV – 100 kV – 123 kV – 145 kV – 170 kV – 245 kV – 300 kV – 362 kV – 420 kV – 550 kV

NOTE Values 800 kV and higher are not considered because there is little experience at this time.

4.2 Rated insulation level

The rated insulation level for the GIS part in the transformer connection enclosure shall be selected from the values given in the product standard IEC 62271-203. The rated insulation level for the transformer bushing shall be selected from the values given in the product standard IEC 60137.

NOTE Transformers can be tested at other insulation level values, according to the relevant standard.

The rated insulation level for a direct connection has to fulfil at least the requirements of IEC 62271-203.

4.3 Rated frequency (f_r)

Subclause 4.3 of IEC 62271-1:2007 applies.

4.4 Rated continuous current (I_r) and temperature rise

The dimensions of the connection interfaces shown in Figure 2 allow a maximum value of 3 150 A for the rated continuous current. The connection interface is shown in Figure 1 as parts 3 and 4.

The contact surfaces of the connection interface shall be silver-coated, copper-coated or bare copper.

For the rated continuous current, the connection between switchgear and power transformer shall be designed that the temperature of the transformer connection enclosure and the temperature of the connection interface do not exceed the values given in 4.4.2 of IEC 62271-203:2011.

4.5 Rated short-time withstand current (I_k) and rated thermal short-time current (I_{th})

For the rated short-time withstand current of the GIS part of the transformer connection 4.5 of IEC 62271-1:2007 is applicable and for the rated thermal short-time current of the bushing 4.3 of IEC 60137:2008.

It is recommended to apply the same short-time currents for GIS and bushing.

4.6 Rated peak withstand current (I_p) and rated dynamic current (I_d)

For the rated peak withstand current of the GIS part of the transformer connection 4.6 of IEC 62271-1:2007 is applicable and for the rated dynamic current of the bushing 4.4 of IEC 60137:2008.

It is recommended to apply the same value for the rated peak withstand current for the GIS and the rated dynamic current for the bushing.

4.7 Rated duration of short-circuit (t_k) and rated duration (t_{th})

For the rated duration of the short-circuit current of the GIS part of the transformer connection 4.7 of IEC 62271-1:2007 is applicable and for the rated duration of the bushing 4.3 of IEC 60137:2008.

It is recommended to apply the same value for the rated duration of short circuit for the GIS and the rated duration for the bushing.

4.8 Rated filling pressure p_{re} of gas for insulation

The rated filling pressure p_{re} (or density) of gas for insulating is assigned by the switchgear manufacturer.

If SF₆ is used as the insulating gas, the minimum functional pressure for insulation p_{me} , used to determine the design of the transformer bushing insulation, shall be not more than 0,35 MPa (absolute) at 20 °C.

For higher rated lightning impulse withstand voltage (BIL) the minimum functional pressure may be increased.

If a gas different from SF₆ or a gas mixture is used, the minimum functional pressure shall be chosen to provide the same dielectric strength. The minimum functional pressure shall be below the maximum operating pressure and design pressure of the enclosure.

5 Design and construction

5.1 Limits of supply

A typical direct connection is shown in Figure 1.

The limits of supply of the switchgear manufacturer and transformer manufacturer shall be according to Figure 1.

To minimize circulating currents between the switchgear and the transformer, bonding connections according to IEC 61936-1 shall be provided by the switchgear manufacturer between the different single phase switchgear enclosures; capable of carrying continuously the rated current of the transformer in normal operation. If circulating currents higher than 250 A are expected via the single-phase transformer connection enclosure, an insulated junction between the GIS and the transformer is necessary, see Figure 1 Part 9. This applies to the direct connection of three-phase and single-phase power transformers according IEC 60076 series.

NOTE 1 The tank of a transformer is not designed to carry any considerable, undefined continuous circulating currents. Practical experiences have shown that a load current of up to 1 250 A can be carried without additional precautions in the enclosure of the interface between the GIS and the transformer. This is due to the fact that approximately 80 % of the load current is carried by the bonding connection of the switchgear, to be installed preferably at the end of the switchgear enclosure at the transformer. Thus, approximately 20 % of the load current, therefore up to 250 A, could generate continuous circulating currents in the transformer enclosure. The confirmation of the current value in the bonding connection and through the transformer enclosure can be made by calculation.

IEC 62271-211:2014

NOTE 2 The user clarifies with the transformer manufacturer to confirm the maximum acceptable current via the transformer encapsulation to avoid the insulated junction, if possible.

An insulated junction may be also needed to achieve isolation between the transformer tank and the neighbouring earthed switchgear enclosures, and to achieve correct operation of the user's protection schemes for GIS and transformer faults.

The insulation level across the insulated junction shall be designed to withstand a power-frequency test voltage of 5 kV, r.m.s., for 1 min.

To limit the very-fast-front transient ground potential rises which may occur when a switching device operates, non-linear resistors may be connected in parallel with the insulated junction. The number and the characteristics of the non-linear resistors shall be determined by the switchgear manufacturer. [1]¹

According to this standard two different locations (shown in Figure 1) are acceptable for the insulated junction

- a) location "A" between the flange of the transformer connection enclosure, part 6 in Figure 1, and the flange of the bushing, part 10 in Figure 1, or
- b) location "B" between the transformer connection enclosure, part 6 in Figure 1, and the next switchgear housing, part 14 in Figure 1.

If the insulated junction is needed, the standard dimensions in accordance with Clause 8 shall be kept.

¹ Numbers in square brackets refer to the Bibliography.

Independent of the existence of an insulated junction, bonding connections between the single-phase enclosures of the switchgear need be provided by the switchgear manufacturer in accordance with IEC 61936-1 and IEC 62271-203.

Bonding connections always need to be provided between single-phase enclosed direct connection arrangements of single-phase, two-phase or three-phase transformers.

Bonding connections need not be provided for a three-phase transformer with a three-phase enclosed direct connection arrangement.

In the case of not having an insulated junction, bonding connections shall be designed not exceeding the permitted value of circulating current via the transformer tank as specified in this clause.

Without an insulated junction the bonding connection shall be made at the end of the transformer connection enclosure towards the bushing, i.e. location marked "A" in Figure 1.

With an insulated junction, in case of location marked "A" in Figure 1 the bonding connection shall be made at the end of the transformer connection enclosure towards the bushing.

In case of location marked "B" in Figure 1 the bonding connection shall be made at the end of the switchgear housing towards the bushing.

The transformer, including the bushing, shall be able to withstand very fast transient voltages which are generated by the switchgear.

If an insulated junction is applied, its design shall be also able to withstand the same value of the very fast transient voltages generated by the switchgear.

NOTE 3 Alternatively to the insulating junction an insulating spacer can be used.

5.2 Pressure withstand requirements

The maximum operating gas pressure used to determine the mechanical strength of the bushing shall be at least 0,85 MPa (absolute) at 20 °C.

The transformer connection enclosure and all pressurized connected parts shall satisfy the requirements provided in 5.103 of IEC 62271-203:2011 for the design pressure determined by the switchgear manufacturer as specified in 5.103.2 of IEC 62271-203:2011.

The design pressure of the transformer connection enclosure may be lower than the maximum operating gas pressure which is used to determine the mechanical strength of the bushing.

5.3 Gas and vacuum tightness

Subclause 5.15 of IEC 62271-203:2011 is applicable with the following addition:

For conditions up to the maximum occurring gas operating pressure, the bushing shall prevent insulating media, gas, diffusing into the transformer.

The bushing shall prevent entering insulating media, gas or oil, into the GIS.

The bushing shall be capable of withstanding the vacuum conditions when the transformer connection enclosure is evacuated, as part of the gas filling process and shall be capable of withstanding the vacuum conditions when the transformer is evacuated as part of its gas or oil filling process.