

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A
per phase and not subject to conditional connection**

**Compatibilité électromagnétique (CEM) –
Partie 3-3: Limites – Limitation des variations de tension, des fluctuations de
tension et du papillotement dans les réseaux publics d'alimentation basse
tension, pour les matériels ayant un courant assigné ≤ 16 A par phase et non
soumis à un raccordement conditionnel**



THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2017 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing 20 000 terms and definitions in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

65 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Catalogue IEC - webstore.iec.ch/catalogue

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

Recherche de publications IEC - www.iec.ch/searchpub

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

65 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A
per phase and not subject to conditional connection**

**Compatibilité électromagnétique (CEM) –
Partie 3-3: Limites – Limitation des variations de tension, des fluctuations de
tension et du papillotement dans les réseaux publics d'alimentation basse
tension, pour les matériels ayant un courant assigné ≤ 16 A par phase et non
soumis à un raccordement conditionnel**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 33.100.10

ISBN 978-2-8322-4401-2

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

REDLINE VERSION

VERSION REDLINE



**Electromagnetic compatibility (EMC) –
Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker
in public low-voltage supply systems, for equipment with rated current ≤ 16 A
per phase and not subject to conditional connection**

**Compatibilité électromagnétique (CEM) –
Partie 3-3: Limites – Limitation des variations de tension, des fluctuations de
tension et du papillotement dans les réseaux publics d'alimentation basse
tension, pour les matériels ayant un courant assigné ≤ 16 A par phase et non
soumis à un raccordement conditionnel**

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
4 Assessment of voltage changes, voltage fluctuations and flicker	10
4.1 Assessment of a relative voltage change, $d(t)$	10
4.2 Assessment of the short-term flicker value, P_{St}	11
4.2.1 General	11
4.2.2 Flickermeter	11
4.2.3 Simulation method	11
4.2.4 Analytical method	11
4.2.5 Use of $P_{St} = 1$ curve	12
4.3 Assessment of long-term flicker value, P_{lt}	12
5 Limits	12
6 Test conditions	13
6.1 General.....	13
6.2 Measurement uncertainty	14
6.3 Test supply voltage	14
6.4 Reference impedance.....	14
6.5 Observation period	15
6.6 General test conditions.....	15
Annex A (normative) Application of limits and type test conditions for specific equipment.....	19
Annex B (normative) Test conditions and procedures for measuring d_{max} voltage changes caused by manual switching	27
Annex C (informative) Determination of steady state voltage and voltage change characteristics, as defined in IEC 61000-4-15:2010	28
Annex D (informative) Input relative voltage fluctuation $\Delta V/V$ for $P_{St} = 1,0$ at output [IEC/TR 61000-3-7:2008]	33
Bibliography.....	34
Figure 1 – Reference network for single-phase and three-phase supplies derived from a three-phase, four-wire supply.....	16
Figure 2 – Curve for $P_{St} = 1$ for rectangular equidistant voltage changes	17
Figure 3 – Shape factors F for double-step and ramp-voltage characteristics	17
Figure 4 – Shape factors F for rectangular and triangular voltage characteristics	18
Figure 5 – Shape factor F for motor-start voltage characteristics having various front times.....	18
Figure C.1 – Evaluation of $U_{hp}(t)$	32
Table 1 – Assessment method	11
Table A.1 – Test conditions for hotplates	19
Table A.2 – Electrode parameters.....	24

Table A.3 – Frequency factor R related to repetition rate " r "	25
Table C.1 – Test specification for $d_C - d_{\max} - t_d(t) > 3,3\%$ (from Table 12 of IEC 61000-4-15: 2010).....	31
Table C.2 – Test specification for $d_C - d_{\max} - t_d(t) > 3,3\%$ (from Table 13 of IEC 61000-4-15: 2010).....	31
Table D.1 – Input relative voltage fluctuation $\Delta V/V$ for $P_{St} = 1,0$ at output	33

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[IEC 61000-3-3:2013](#)

<https://standards.iteh.ai/catalog/standards/iec/t9332e58-c6f5-42f1-86ff-dd165c9fe868/iec-61000-3-3-2013>

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.

IEC 61000-3-3 edition 3.1 contains the third edition (2013-05) [documents 77A/809/FDIS and 77A/816/RVD] and its amendment 1 (2017-05) [documents 77A/952/FDIS and 77A/960/RVD].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

International Standard IEC 61000-3-3 has been prepared by subcommittee 77A: EMC – Low frequency phenomena, of IEC technical committee 77: Electromagnetic compatibility.

This standard forms part 3-3 of IEC 61000 series of standards. It has the status of a product family standard.

This third edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) This edition takes account of the changes made in IEC 61000-4-15:2010.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 61000 series, published under the general title *Electromagnetic compatibility (EMC)*, can be found on the IEC website.

The committee has decided that the contents of the base publication and its amendment will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

IEC 61000 is published in separate parts according to the following structure:

Part 1: General

General considerations (introduction, fundamental principles)

Definitions, terminology

Part 2: Environment

Description of the environment

Classification of the environment

Compatibility levels

Part 3: Limits

Emission limits

Immunity limits (in so far as they do not fall under the responsibility of product committees)

Part 4: Testing and measurement techniques

Measurement techniques

Testing techniques

Part 5: Installation and mitigation guidelines

Installation guidelines

Mitigation methods and devices

Part 9: Miscellaneous

[IEC 61000-3-3:2013](https://standards.iteh.ai/catalog/standards/iec/9332e58-c6f5-42f1-86ff-dd165c9fe868/iec-61000-3-3-2013)

<https://standards.iteh.ai/catalog/standards/iec/9332e58-c6f5-42f1-86ff-dd165c9fe868/iec-61000-3-3-2013>

Each part is further subdivided into sections which are to be published either as International Standards or as Technical Reports.

These standards and reports will be published in chronological order and numbered accordingly.

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection

1 Scope

This part of IEC 61000 is concerned with the limitation of voltage fluctuations and flicker impressed on the public low-voltage system.

It specifies limits of voltage changes which may be produced by an equipment tested under specified conditions and gives guidance on methods of assessment.

This part of IEC 61000 is applicable to electrical and electronic equipment having an input current equal to or less than 16 A per phase, intended to be connected to public low-voltage distribution systems of between 220 V and 250 V line to neutral at 50 Hz, and not subject to conditional connection.

Equipment which does not comply with the limits of this part of IEC 61000 when tested with the reference impedance Z_{ref} of 6.4, and which therefore cannot be declared compliant with this part, may be retested or evaluated to show conformity with IEC 61000-3-11. Part 3-11 is applicable to equipment with rated input current ≤ 75 A per phase and subject to conditional connection.

The tests according to this part are type tests. Particular test conditions are given in Annex A and the test circuit is shown in Figure 1.

NOTE 1 The limits in this standard relate to the voltage changes experienced by consumers connected at the interface between the public supply low-voltage network and the equipment user's installation. Consequently, if the actual impedance of the supply at the supply terminals of equipment connected within the equipment user's installation exceeds the test impedance, it is possible that supply disturbance exceeding the limits could occur.

NOTE 2 The limits in this standard are based mainly on the subjective severity of flicker imposed on the light from 230 V 60 W coiled-coil filament lamps by fluctuations of the supply voltage. For systems with nominal voltage less than 220 V line to neutral and/or frequency of 60 Hz, the limits and reference circuit values are under consideration.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC/TR 60725, *Consideration of reference impedances and public supply impedances for use in determining disturbance characteristics of electrical equipment having a rated current ≤ 75 A per phase*

IEC 60974-1, *Arc welding equipment – Part 1: Welding power sources*

IEC 61000-3-2, *Electromagnetic compatibility (EMC) – Part 3-2: Limits – Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)*

IEC 61000-3-11, *Electromagnetic compatibility (EMC) – Part 3-11: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems – Equipment with rated current ≤ 75 A and subject to conditional connection*

IEC 61000-4-15:2010, *Electromagnetic compatibility (EMC) – Part 4-15: Testing and measurement techniques – Flickermeter – Functional and design specifications*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1

flicker

impression of unsteadiness of visual sensation induced by a light stimulus whose luminance or spectral distribution fluctuates with time

[SOURCE: IEC 60050-161:1990, 161-08-13]

3.2

voltage change characteristic

$d(t)$

time function of the relative r.m.s. voltage change evaluated as a single value for each successive half period between zero-crossings of the source voltage, except during time intervals in which the voltage is in a steady-state condition for at least 1 s

Note 1 to entry: For detailed information about the evaluation of a voltage change characteristic and the definition of a steady state condition see Annex C and IEC 61000-4-15:2010.

3.3

d_c

maximum steady state voltage change during an observation period

Note 1 to entry: For detailed information about the calculation of d_c see Annex C and IEC 61000-4-15:2010.

3.4

d_{max}

maximum absolute voltage change during an observation period

Note 1 to entry: For detailed information about the calculation of d_{max} see Annex C and IEC 61000-4-15:2010.

3.5

T_{max}

maximum time duration during the observation period that the voltage deviation $d(t)$ exceeds the limit for d_c

Note 1 to entry: During a voltage change characteristic the time duration T_{max} is accumulated until a new steady state condition is established.

Note 2 to entry: The T_{max} limit evaluation in this standard is generally intended to evaluate the inrush current pattern of the equipment under test. Thus, as soon as a new steady state condition is established, the T_{max} evaluation is ended. When a new voltage change occurs that exceeds the limit for d_c , a new T_{max} evaluation is started. The maximum duration that $d(t)$ exceeds the limit for d_c for any of the individual T_{max} evaluations during the observation period, is used for the comparison against the T_{max} limit, and is reported for the test.

3.6

nominal test voltage

U_n

nominal test voltage used to calculate percentages for the various directly measured parameters

Note 1 to entry: If no steady state condition is achieved during the observation period, U_n is used for the calculation of d_{\max} and T_{\max} .

Note 2 to entry: U_n is not necessarily equal to the nominal voltage of the public supply.

3.7

P_{st}

short-term flicker severity

Note 1 to entry: If not specified differently, the P_{st} evaluation time is 10 minutes. For the purpose of power quality surveys and studies, other time intervals may be used, and have to be defined in the index. For example a 1 minute interval should be written as $P_{\text{st},1\text{min}}$.

3.8

P_{lt}

long-term flicker severity

$$P_{\text{lt}} = \sqrt[3]{\frac{\sum_{i=1}^N P_{\text{st},i}^3}{N}}$$

where $P_{\text{st},i}$ ($i = 1, 2, 3, \dots$) are consecutive readings of the short-term severity P_{st}

Note 1 to entry: Unless otherwise specified, P_{lt} is calculated over discrete T_{long} periods. Each time a T_{long} period has expired, a new P_{lt} calculation is started.

3.9

flickermeter

instrument designed to measure any quantity representative of flicker

Note 1 to entry: Measurements are normally P_{st} and P_{lt} and may also include the directly measured parameters specified in 3.2 to 3.5.

[SOURCE: IEC 60050-161:1990, 161-08-14]

3.10

flicker impression time

t_f

value with a time dimension which describes the flicker impression of a voltage change characteristic

3.11

shape factor

F

value derived from the type of voltage fluctuation, such as a step, double step, or ramp pattern

Note 1 to entry: The shape factor is mainly needed when the analytical method is used to calculate P_{st} .

3.12

interface point

interface between a public supply network and a user's installation

3.13

conditional connection

connection of equipment requiring the user's supply at the interface point to have an impedance lower than the reference impedance Z_{ref} in order that the equipment emissions comply with the limits in this part

Note 1 to entry: Meeting the voltage change limits may not be the only condition for connection; emission limits for other phenomena such as harmonics, may also have to be satisfied.

4 Assessment of voltage changes, voltage fluctuations and flicker

4.1 Assessment of a relative voltage change, $d(t)$

The basis for flicker evaluation is the voltage change characteristic at the terminals of the equipment under test, that is the difference $\Delta U_{\text{hp}}(t)$ of any two successive values of the phase-to-neutral voltages $U_{\text{hp}}(t_1)$ and $U_{\text{hp}}(t_2)$:

$$\Delta U_{\text{hp}}(t) = U_{\text{hp}}(t_1) - U_{\text{hp}}(t_2) \quad (1)$$

NOTE 1 See Annex C for relevant definitions that are taken from IEC 61000-4-15:2010.

The r.m.s. values $U_{\text{hp}}(t_1)$, $U_{\text{hp}}(t_2)$ of the voltage shall be measured or calculated. When deducing r.m.s. values from oscillographic waveforms, account should be taken of any waveform distortion that may be present.

The voltage change at the EUT terminals, ΔU , is due to the change of the voltage drop across the complex reference impedance \underline{Z} , caused by the complex fundamental input current change, $\Delta \underline{I}$, of the equipment under test. ΔI_p and ΔI_q are the active and reactive parts respectively of the current change, $\Delta \underline{I}$.

$$\Delta \underline{I} = \Delta I_p - j\Delta I_q = \underline{I}(t_1) - \underline{I}(t_2) \quad (2)$$

NOTE 2 I_q is positive for lagging currents and negative for leading currents.

NOTE 3 If the harmonic distortion of the currents $I(t_1)$ and $I(t_2)$ is less than 10 %, the total r.m.s. value can be applied instead of the r.m.s. values of their fundamental currents, taking account of the phase angles of the fundamental currents.

NOTE 4 For single-phase and symmetrical three-phase equipment the voltage change can be, provided X is positive (inductive), approximated to:

$$\Delta U_{\text{hp}} = |\Delta I_p R + \Delta I_q X| \quad (3)$$

where ΔI_p and ΔI_q are the active and reactive parts respectively of the current change $\Delta \underline{I}$ and R and X are the elements of the complex reference impedance Z (see Figure 1).

The relative voltage change is given by:

$$d = \Delta U_{\text{hp}} / U_n \quad (4)$$

The $d_{\text{max},i}$ evaluation ends as soon as a new steady state condition is established, or at the end of the observation period. The polarity of change(s) may be indicated as follows: if the maximum voltage deviation is observed during a reduction in voltage with respect to the previous $d_{\text{end},i}$ the resulting $d_{\text{max},i}$ value is positive; if the maximum voltage deviation is observed during a voltage increase with respect to the previous $d_{\text{end},i}$ the resulting $d_{\text{max},i}$ value is negative.