



Designation: C 1533 – 02

Standard Guide for General Design Considerations for Hot Cell Equipment¹

This standard is issued under the fixed designation C 1533; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon (ϵ) indicates an editorial change since the last revision or reapproval.

1. Scope

1.1 Intent:

1.1.1 The intent of this guide is to provide general design and operating considerations for the safe and dependable operation of remotely operated hot cell equipment. Hot cell equipment is hardware used to handle, process, or analyze nuclear or radioactive material in a shielded room. The equipment is placed behind radiation shield walls and cannot be directly accessed by the operators or by maintenance personnel because of the radiation exposure hazards. Therefore, the equipment is operated remotely, either with or without the aid of viewing.

1.1.2 This guide may apply to equipment in other radioactive remotely operated facilities such as suited entry repair areas, canyons or caves, but does not apply to equipment used in commercial power reactors.

1.1.3 This guide does not apply to equipment used in gloveboxes.

1.2 Caveats:

1.2.1 This guide does not address considerations relating to the design, construction, operation, or safety of hot cells, caves, canyons, or other similar remote facilities. This guide deals only with equipment intended for use in hot cells.

1.2.2 Specific design and operating considerations are found in other ASTM documents.

1.2.3 The system of units employed in this guide shall be the inch-pound unit, also known as U.S. Customary Units. These units are commonly used in the United States of America and defined by the National Institute of Standards and Technology, including certain other units accepted for use with these terms.

1.3 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety and health practices and determine the applicability of regulatory requirements prior to use.*

2. Referenced Documents

2.1 ASTM Standards:

C 859 Terminology Relating to Nuclear Materials²

D 5144 Guide for Use of Protective Coating Standards in Nuclear Power Plants³

2.2 Other Standards:

10CFR830.120 Nuclear Safety Management Quality Assurance Requirements⁴

ASME NQA-1 Quality Assurance Requirements for Nuclear Facility Applications⁵

ISO 9001 Quality Management Systems⁶

3. Terminology

3.1 The terminology employed in this guide conforms to industry practice insofar as practicable.

3.2 For definitions of terms not described in this guide, refer to Terminology C 859.

3.3 Definitions of Terms Specific to This Standard:

3.3.1 *canyon*—a long narrow, remotely operated and maintained radiological area within a facility. Work within a canyon is generally accomplished with overhead cranes with the aid of remote viewing capability.

3.3.2 *cave*—typically a small-scale hot cell facility, but is sometimes used synonymously with hot cells.

3.3.3 *electro-mechanical manipulator (E/M)*—usually mounted on a crane bridge, wall, pedestal, or ceiling and is used to handle heavy equipment in a hot cell. The E/M is operated remotely using controls from the uncontaminated side of the hot cell. Most E/Ms have lifting capacities of 100 lbs. or more.

3.3.4 *hot cell*—an isolated shielded room that provides a controlled environment for containing highly radioactive and contaminated material and equipment. The radiation levels within a hot cell are typically several hundred roentgens per hour or higher.

3.3.5 *master-slave manipulator*—a device used to handle radioactively contaminated items or nuclear material in a hot cell. The uncontaminated portion of the manipulator is called the master and the contaminated portion is called the slave. The slave replicates the motion of the master.

3.3.6 *mockup*—an area designated for the testing of hot cell equipment or the process of qualifying said equipment prior to

³ Annual Book of ASTM Standards, Vol 06.02.

⁴ Available from Superintendent of Documents U.S. Government Printing Office, Washington, DC 20402

⁵ Available from ASME, Three Park Avenue, New York, NY 10016.

⁶ Available from ANSI, 11 W. 42nd St., 13th Floor, New York, NY 10036.

¹ This guide is under the jurisdiction of ASTM Committee C26 on Nuclear Fuel Cycle and is the direct responsibility of Subcommittee C26.14 on Remote Systems. Current edition approved June 10, 2002. Published August 2002.

² Annual Book of ASTM Standards, Vol 12.01.

sending it into the hot cell for operation. A mockup is usually equipped with master-slave manipulators and electro-mechanical manipulators and cranes to simulate the hot cell dimensional envelope and operations.

3.3.7 *radiation absorbed dose (RAD)*—also called *total accumulated dose*, is a measure of the amount of energy deposited by ionizing radiation in any material.

3.3.8 *roentgen equivalent man (REM)*—a measure of the damaging effects of ionizing radiation to man. A millirem is one one-thousandth of a REM.

4. Significance and Use

4.1 The purpose of this guide is to provide general guidelines for the design and operation of hot cell equipment to ensure longevity and reliability throughout the period of service.

4.2 It is intended that this guide record the general conditions and practices that experience has shown is necessary to minimize equipment failures and maximize the effectiveness and utility of hot cell equipment. It is also intended to alert designers to those features that are highly desirable for the selection of equipment that has proven reliable in high radiation environments.

4.3 This guide is intended as a supplement to other standards, and to federal and state regulations, codes, and criteria applicable to the design of equipment intended for hot cell use.

4.4 This guide is intended to be generic and to apply to a wide range of types and configurations of hot cell equipment.

5. Quality Assurance Requirements

5.1 The fabricator and owner-operator of hot cell equipment should have a quality assurance program. Hot cell equipment should be designed according to stringent quality assurance requirements and undergo quality control inspections as outlined by the agency of jurisdiction. QA programs may be required to comply with 10CFR830.120, ASME NQA-1, or ISO 9001.

6. Nuclear Safety

6.1 The handling and processing of special nuclear materials requires the avoidance of criticality incidents. Equipment intended for use in handling materials having a special nuclear material content should undergo a criticality assessment analysis in accordance with the requirements of ANS 8.1 and other such standards and regulations as may be applicable.

7. Design Considerations

7.1 Hot cell equipment should be designed and fabricated to remain dimensionally stable throughout its life cycle.

7.2 Fabrication materials should be resistant to radiation damage, or materials subject to such damage should be shielded or placed and attached so as to be readily replaceable.

7.3 Special consideration should be given to designing hot cell equipment that may be exposed to or may create high temperatures, high rate of temperature changes, caustic conditions, or pressure changes. Abrupt changes in the hot cell temperature or pressure may cause the hot cell windows to crack and potentially lose containment. The effect of handling and operating high temperature hot cell equipment on the

master-slave manipulators or other in-cell handling equipment should be considered to preclude damage to those items.

7.4 Preventive maintenance based on previous experience in similar environments and similar duty should be performed as required to prevent unscheduled repair of failed components.

7.5 Hot cell equipment may be required to be leak tight when handling liquids. Leak tightness prevents radioactive liquid from entering the interior of hot cell equipment where it can cause corrosion, shorting of electrical components, higher chronic radiation to components and complicates decontamination.

7.6 Hot cell equipment should generally be designed to function indefinitely within the highly radioactive environment. However, in many cases this may not be possible since radiation degrades some materials over time. Alpha, beta, gamma, and neutron radiation can severely damage most organic materials, e.g., oils, plastics, and elastomers. Commercially available equipment containing organic materials may require disassembly and the internal components replaced with more radiation resistant materials. If suitable alternate materials cannot be used, special shielding may have to be integrated into the design to protect the degradable components. In the case of some electronic equipment, it may be possible to separate and move the more radiation sensitive components outside of the hot cell and operate the equipment in the hot cell remotely. Where possible and appropriate, equipment should be designed to withstand an accumulative radiation dose of approximately 1×10^8 RADs (H₂O)[⁶⁰Co].

7.7 Since hot cells have a limited amount of space, the equipment designs should be standardized where possible to reduce the number of one-of-a-kind parts. Standardization of hot cell equipment will reduce design time, fabrication costs, operator training time, maintenance costs, and the number of special tools required to perform a certain operation. Standardization in design, drawing control and excellent quality control assure that components are interchangeable. Specially designed equipment should be standardized for use with equipment in similar applications or systems to reduce spare parts inventories and to maintain familiarity for the operators. Commercially available components should be used, and modified if necessary, wherever possible in preference to specially designed equipment.

7.8 All hot cell equipment should be designed in modules for ease of replacement, maintainability, interchangeability, and ease of disposal. The modules should be designed to be remotely removable and installed using the in-cell handling equipment, that is, master-slave manipulators, cranes, etc. Consideration should also be given to the transfer path to get equipment into the hot cell and size equipment modules accordingly. Components with a higher probability of failure should be made modular for ease of replacement. Remotely operated electrical connectors must be compatible with the hot cell materials handling equipment. Drawings of hot cell equipment should reflect the as-built configuration for all replaceable components to provide reliable documentation control. Interfacing components should be toleranced to fit the in-field conditions. Replaceable components should be labeled with a standard identification and the component weight. Examples of

modular designs might include subassemblies of removable motors, resolvers, valves, limit switches, and electrical cables.

7.9 The hot cell atmosphere can have an adverse affect on hot cell equipment. Hot cells can have air or inert gas atmospheres and are usually kept at a negative differential pressure of 1.0 to 2.0 in. of water gauge with respect to the surrounding operating areas. Hot cells with inert atmospheres or very low moisture content can make it difficult to operate some types of equipment. Some brush type motors, for example, will stall or simply fail to operate. One solution has been to replace the motor brushes with high altitude type brushes made of silver-graphite or use brushless motors. A good understanding of the effects of the hot cell atmosphere on equipment is essential when purchasing or designing new hot cell equipment.

7.10 It is generally advisable to perform qualification testing on new hot cell equipment in a mockup facility prior to putting the equipment into service. The mockup generally uses the same equipment interfaces such as cranes, electro-mechanical manipulators, and master-slave manipulators as the hot cell. The mockup is generally located in a non-radioactive and non-contaminated area. Any new equipment to be used in a hot cell should be assembled, disassembled, and operated in the mockup to verify that it can be installed, removed, maintained, and operated successfully in the hot cell environment. The mockup area is also useful for training purposes and troubleshooting. Oftentimes the mockup testing will identify deficiencies in the equipment design or operation that without mockup testing would render the equipment useless in the hot cell. Care should be taken during the mockup testing and hardware installation to ensure that the operability and integrity of the equipment is not compromised.

7.11 Design considerations should include the limited capabilities of the overhead handling systems, the inability to have direct access to the equipment, and the limited viewing capabilities. Limitations include the top-only access for component replacement and the fact that operators will only be able to directly view one or two faces of the system. Equipment designs should provide for unobstructed viewing (directly or indirectly using cameras) of remotely separable interfaces so that any tools or equipment needed to perform the in-cell maintenance functions can be engaged, disengaged, or positioned in full view. The equipment modules should be designed so that they can be reached, disconnected, and maneuvered using the in-cell materials handling equipment.

7.12 Hot cell equipment should be designed with assembly features to assure accurate positioning, aligning, mating, and fastening of components. Examples include alignment pins, captured bolts, countersink or tapered guides, and thread lead-ins. Close attention to fabrication tolerances is essential to ensure that replaceable parts are interchangeable. Refer to other standards referenced in 2.2.

7.13 The method of hot cell equipment repair should be considered during the design phase. Typically, it is difficult to perform repairs of failed hot cell components. The preferred practice is to disassemble and replace failed components rather than attempting to repair the failed part. Equipment that cannot be repaired or replaced using the in-cell handling systems is

generally transferred to a suited entry repair area where personnel in anti-contamination clothing perform hands-on repairs. Equipment that will be repaired in a suited entry repair area should be capable of being decontaminated to levels suitable for contact maintenance.

7.14 Hot cell designed equipment should include design features to minimize the amount of decontamination required for repair or disposal. Since the method of decontamination may involve rigorous chemical cleaning and decontamination procedures, the choice of component materials should be compatible with the decontamination techniques and solutions. For example, some decontamination solutions may not be compatible with aluminum. All surfaces should have a smooth finish, such as a 128 or better, to make the items easier to decontaminate for disposal or repair. Contamination “traps” in equipment should be avoided or eliminated where possible. Hollow pedestals welded on equipment for the mounting of motors, gearboxes, bearings, and like components should not have through holes or threaded openings.

7.15 Design considerations for disposal at end-of-life of hot cell equipment should always be considered early in the design process. Equipment that has been in a hot cell for an extended period of time may be difficult to decontaminate to acceptable levels for disposal because of the amount of fixed contamination. Also, some materials may become activated when exposed to radiation over a period of time, which may cause the material to be classified as a mixed hazardous waste. The use of these materials should be avoided where possible because of the complications of disposal. Components that are fastened together are sometimes preferable to welded components because they are easier to disassemble into sections more suitable for disposal and can sometimes be done remotely using manipulators. Where welding components together is required, skip welding should be avoided to prevent potential contamination traps. Welded components may require specialized cutting equipment in a contaminated room by personnel in anti-contamination clothing to reduce the size of the hardware in order to fit it into waste disposal containers. These operations increase the radiation exposure to personnel. Designers should become familiar with the specific contaminated equipment disposal methods at their facilities and incorporate equipment design features to reduce the disposal time, cost, and radiation exposure to personnel.

7.16 The interfacing systems should be factored into the hot cell equipment design. Master-slave manipulators positioned above the windows and overhead crane or electro-mechanical manipulator systems are used to operate and handle the hot cell equipment. The designer should consider the location of the equipment in the hot cell and its proximity to the master-slave manipulators, electro-mechanical manipulators, cranes, and service penetrations. Small removable equipment modules should be designed based on the type of master-slave manipulator grip, lifting capacity, and reach. The lifting capacity of master-slave manipulators is typically 10 to 50lb. Larger and heavier equipment should have design features to interface with the lifting cranes or electro-mechanical manipulators.