

# INTERNATIONAL STANDARD

## NORME INTERNATIONALE

**Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations – Part 1: Circuit-breakers for a.c. operation**

**Petit appareillage électrique – Disjoncteurs pour la protection contre les surintensités pour installations domestiques et analogues – Partie 1: Disjoncteurs pour le fonctionnement en courant alternatif**



## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2015 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
Fax: +41 22 919 03 00  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

#### IEC Catalogue - [webstore.iec.ch/catalogue](http://webstore.iec.ch/catalogue)

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

#### IEC publications search - [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary of electronic and electrical terms, containing 20 000 terms and definitions in English and French, with equivalent terms in 15 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

#### IEC Glossary - [std.iec.ch/glossary](http://std.iec.ch/glossary)

65 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

#### IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [csc@iec.ch](mailto:csc@iec.ch).

### A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

### A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

#### Catalogue IEC - [webstore.iec.ch/catalogue](http://webstore.iec.ch/catalogue)

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

#### Recherche de publications IEC - [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 15 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

#### Glossaire IEC - [std.iec.ch/glossary](http://std.iec.ch/glossary)

65 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

#### Service Clients - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: [csc@iec.ch](mailto:csc@iec.ch).

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE

---

**Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations –  
Part 1: Circuit-breakers for a.c. operation**

**Petit appareillage électrique – Disjoncteurs pour la protection contre les surintensités pour installations domestiques et analogues –  
Partie 1: Disjoncteurs pour le fonctionnement en courant alternatif**

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

---

ICS 29.120.50

ISBN 978-2-8322-3744-1

**Warning! Make sure that you obtained this publication from an authorized distributor.  
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

## CONTENTS

FOREWORD .....	9
1 Scope .....	11
2 Normative references .....	12
3 Terms and definitions .....	13
3.1 Devices .....	13
3.2 General terms .....	14
3.3 Constructional elements .....	16
3.4 Conditions of operation .....	18
3.5 Characteristic quantities .....	19
3.6 Definitions related to insulation co-ordination .....	23
4 Classification .....	25
4.1 General .....	25
4.2 According to the number of poles: .....	25
4.3 According to the protection against external influences: .....	26
4.4 According to the method of mounting: .....	26
4.5 According to the methods of connection .....	26
4.5.1 According to the fixation system: .....	26
4.5.2 According to the type of terminals: .....	26
4.6 According to the instantaneous tripping current (see 3.5.17) .....	26
4.7 According to the $I^2t$ characteristic .....	26
5 Characteristics of circuit-breakers .....	26
5.1 List of characteristics .....	26
5.2 Rated quantities .....	27
5.2.1 Rated voltages .....	27
5.2.2 Rated current ( $I_n$ ) .....	27
5.2.3 Rated frequency .....	27
5.2.4 Rated short-circuit capacity ( $I_{cn}$ ) .....	28
5.2.5 Rated making and breaking capacity of an individual pole ( $I_{cn1}$ ) .....	28
5.3 Standard and preferred values .....	28
5.3.1 Preferred values of rated voltage .....	28
5.3.2 Preferred values of rated current .....	29
5.3.3 Standard values of rated frequency .....	29
5.3.4 Values of rated short-circuit capacity .....	29
5.3.5 Standard ranges of instantaneous tripping .....	30
5.3.6 Standard values of rated impulse withstand voltage ( $U_{imp}$ ) .....	30
6 Marking and other product information .....	30
7 Standard conditions for operation in service .....	32
7.1 General .....	32
7.2 Ambient air temperature range .....	32
7.3 Altitude .....	32
7.4 Atmospheric conditions .....	33
7.5 Conditions of installation .....	33
7.6 Pollution degree .....	33
8 Requirements for construction and operation .....	33
8.1 Mechanical design .....	33

8.1.1	General .....	33
8.1.2	Mechanism .....	33
8.1.3	Clearances and creepage distances (see Annex B) .....	35
8.1.4	Screws, current-carrying parts and connections .....	37
8.1.5	Terminals for external conductors .....	38
8.1.6	Non-interchangeability .....	40
8.1.7	Mechanical mounting of plug-in type circuit-breakers .....	41
8.2	Protection against electric shock .....	41
8.3	Dielectric properties and isolating capability .....	41
8.3.1	General .....	41
8.3.2	Dielectric strength at power frequency .....	42
8.3.3	Isolating capability .....	42
8.3.4	Dielectric strength at rated impulse withstand voltage ( $U_{imp}$ ) .....	42
8.4	Temperature-rise .....	42
8.4.1	Temperature-rise limits .....	42
8.4.2	Ambient air temperature .....	42
8.5	Uninterrupted duty .....	43
8.6	Automatic operation .....	43
8.6.1	Standard time-current zone .....	43
8.6.2	Conventional quantities .....	44
8.6.3	Tripping characteristic .....	44
8.7	Mechanical and electrical endurance .....	45
8.8	Performance at short-circuit currents .....	45
8.9	Resistance to mechanical shock and impact .....	45
8.10	Resistance to heat .....	45
8.11	Resistance to abnormal heat and to fire .....	46
8.12	Resistance to rusting .....	46
8.13	Power loss .....	46
9	Tests .....	46
9.1	Type tests and test sequences .....	46
9.2	Test conditions .....	47
9.3	Test of indelibility of marking .....	48
9.4	Test of reliability of screws, current-carrying parts and connections .....	48
9.5	Tests of reliability of screw-type terminals for external copper conductors .....	50
9.6	Test of protection against electric shock .....	51
9.7	Test of dielectric properties .....	52
9.7.1	Resistance to humidity .....	52
9.7.2	Insulation resistance of the main circuit .....	52
9.7.3	Dielectric strength of the main circuit .....	53
9.7.4	Insulation resistance and dielectric strength of auxiliary circuits .....	54
9.7.5	Verification of impulse withstand voltages (across clearances and across solid insulation) and of leakage current across open contacts .....	54
9.8	Test of temperature-rise and measurement of power loss .....	57
9.8.1	Ambient air temperature .....	57
9.8.2	Test procedure .....	58
9.8.3	Measurement of the temperature of parts .....	58
9.8.4	Temperature-rise of a part .....	58
9.8.5	Measurement of power loss .....	58
9.9	28-day test .....	58

9.10	Test of tripping characteristic .....	59
9.10.1	General .....	59
9.10.2	Test of time-current characteristic.....	59
9.10.3	Test of instantaneous tripping, of correct opening of the contacts and of the trip-free function .....	59
9.10.4	Test of effect of single-pole loading on the tripping characteristic of multipole circuit-breakers.....	60
9.10.5	Test of effect of ambient temperature on the tripping characteristic .....	60
9.11	Verification of mechanical and electrical endurance .....	61
9.11.1	General test conditions .....	61
9.11.2	Test procedure .....	61
9.11.3	Condition of the circuit-breaker after test .....	62
9.12	Short-circuit tests.....	62
9.12.1	General .....	62
9.12.2	Values of test quantities .....	63
9.12.3	Tolerances on test quantities .....	63
9.12.4	Test circuit for short-circuit performance.....	63
9.12.5	Power factor of the test circuit .....	65
9.12.6	Measurement and verification of $I^2t$ and of the peak current ( $I_p$ ) .....	65
9.12.7	Calibration of the test circuit .....	65
9.12.8	Interpretation of records .....	65
9.12.9	Condition of the circuit-breaker for test .....	66
9.12.10	Behaviour of the circuit-breaker during short-circuit tests.....	67
9.12.11	Test procedure .....	67
9.12.12	Verification of the circuit breaker after short circuit tests .....	72
9.13	Mechanical stresses .....	73
9.13.1	Mechanical shock .....	73
9.13.2	Resistance to mechanical stresses and impact .....	74
9.14	Test of resistance to heat.....	77
9.15	Resistance to abnormal heat and to fire .....	78
9.16	Test of resistance to rusting.....	79
Annex A	(informative) Determination of short-circuit power factor .....	93
A.1	General.....	93
A.2	Method 1 – Determination from d.c. component .....	93
A.3	Method 2 – Determination with pilot generator .....	93
Annex B	(normative) Determination of clearances and creepage distances .....	94
B.1	General.....	94
B.2	Orientation and location of a creepage distance.....	94
B.3	Creepage distances where more than one material is used.....	94
B.4	Creepage distances split by floating conductive part.....	94
B.5	Measurement of creepage distances and clearances .....	94
Annex C	(normative) Test sequences and number of samples .....	99
C.1	Test sequences .....	99
C.2	Number of samples to be submitted for full test procedure and acceptance criteria .....	101
C.3	Number of samples to be submitted for simplified test procedure .....	101
Annex D	(informative) Co-ordination under short-circuit conditions between a circuit-breaker and another short-circuit protective device (SCPD) associated in the same circuit.....	105

D.1	General.....	105
D.2	Overview.....	105
D.3	General requirements for the co-ordination of a circuit-breaker with another SCPD .....	106
D.3.1	General consideration.....	106
D.3.2	Take-over current .....	106
D.3.3	Behaviour of C <sub>1</sub> in association with another SCPD .....	106
D.4	Type and characteristics of the associated SCPD .....	106
D.5	Verification of selectivity .....	107
D.6	Verification of back-up protection.....	107
D.6.1	Determination of the take-over current.....	107
D.6.2	Verification of back-up protection.....	107
D.6.3	Tests for verification of back-up protection .....	108
D.6.4	Results to be obtained .....	109
Annex E (normative)	Special requirements for auxiliary circuits for safety extra-low voltage .....	112
Annex F (informative)	Examples of terminals .....	113
Annex G (informative)	Correspondence between ISO and AWG copper conductors .....	116
Annex H (normative)	Arrangement for short-circuit test.....	117
Annex I (normative)	Routine tests .....	120
I.1	General.....	120
I.2	Tripping tests.....	120
I.3	Verification of clearances between open contacts .....	120
Annex J (normative)	Particular requirements for circuit-breakers with screwless type terminals for external copper conductors.....	121
J.1	Scope .....	121
J.2	Normative references.....	121
J.3	Terms and definitions.....	121
J.4	Classification .....	122
J.5	Characteristics of circuit-breakers .....	122
J.6	Marking.....	122
J.7	Standard conditions for operation in service.....	122
J.8	Constructional requirements .....	123
J.8.1	Connection or disconnection of conductors .....	123
J.8.2	Dimensions of connectable conductors .....	123
J.8.3	Connectable cross-sectional areas .....	124
J.8.4	Insertion and disconnection of conductors .....	124
J.8.5	Design and construction of terminals .....	124
J.8.6	Resistance to ageing .....	125
J.9	Tests .....	125
J.9.1	Test of reliability of screwless terminals.....	125
J.9.2	Tests of reliability of terminals for external conductors: mechanical strength .....	126
J.9.3	Cycling test.....	126
J.10	Reference documents .....	128
Annex K (normative)	Particular requirements for circuit-breakers with flat quick-connect terminations .....	130
K.1	Scope .....	130
K.2	Normative references.....	130

K.3	Terms and definitions.....	130
K.4	Classification .....	131
K.5	Characteristics of circuit-breakers.....	131
K.6	Marking.....	131
K.7	Standard conditions for operation in service.....	131
K.8	Constructional requirements .....	131
K.8.1	Clearances and creepage distances (see Annex B) .....	131
K.8.2	Terminals for external conductors .....	132
K.9	Tests .....	132
K.9.1	Mechanical overload-force.....	132
K.10	Reference documents .....	136
Annex L (normative) Specific requirements for circuit-breakers with screw-type terminals for external untreated aluminium conductors and with aluminium screw-type terminals for use with copper or with aluminium conductors .....		
L.1	Scope .....	137
L.2	Normative references.....	137
L.3	Terms and definitions.....	137
L.4	Classification .....	138
L.5	Characteristics of circuit-breakers.....	138
L.6	Marking.....	138
L.7	Standard conditions for operation in service.....	138
L.8	Constructional requirements .....	139
L.9	Tests .....	139
L.9.1	Test conditions .....	141
L.9.2	Current cycling test.....	141
Bibliography.....	<a href="https://standards.iteh.ai/catalog/standards/sist/3e342d5e-f37e-4088-98c8-806690701067/iec-60898-1-2015">https://standards.iteh.ai/catalog/standards/sist/3e342d5e-f37e-4088-98c8-806690701067/iec-60898-1-2015</a>	147
<p style="text-align: center; color: red; font-weight: bold; font-size: 1.2em;">ITIH STANDARD PREVIEW (standards.iteh.ai)</p>		
Figure 1	– Thread forming tapping screw (3.3.22).....	79
Figure 2	– Thread cutting tapping screw (3.3.23) .....	79
Figure 3	– Typical diagram for all short circuit tests except for 9.12.11.2.2) .....	80
Figure 4	– Typical diagram for short circuit tests according to 9.12.11.2.2) .....	81
Figure 5	– Detail of impedance Z and Z <sub>1</sub> .....	81
Figure 6	– Example of short-circuit making or breaking test record in the case of a single-pole device on single phase a.c.....	83
Figure 7	– Mechanical shock test apparatus (9.13.1) .....	84
Figure 8	– Standard test finger (9.6) .....	85
Figure 9	– Mechanical impact test apparatus (9.13.2) .....	86
Figure 10	– Striking element for pendulum for mechanical impact test apparatus (9.13.2).....	87
Figure 11	– Mounting support for mechanical impact test (9.13.2).....	88
Figure 12	– Example of mounting for a rear fixed circuit-breaker for mechanical impact test (9.13.2).....	89
Figure 13	– Example of mounting of a panel board type circuit-breaker for mechanical impact test (9.13.2).....	90
Figure 14	– Application of force for mechanical test on a rail-mounted circuit-breaker (9.13.2.4).....	91
Figure 15	– Ball-pressure test apparatus.....	91



Figure 16 – Example of application of force for mechanical test on two-pole plug-in circuit-breaker, the holding in position of which depends solely on the plug-in connections (9.13.2.5) .....	92
Figure 17 – Diagrammatic representation (9.15) .....	92
Figure B.1 – Examples of methods of measuring creepage distances and clearances .....	98
Figure D.1 – Overcurrent co-ordination between a circuit-breaker and a fuse or back-up protection by a fuse – Operating characteristics .....	110
Figure D.2 – Total selectivity between two circuit-breakers .....	110
Figure D.3 – Back-up protection by a circuit-breaker – Operating characteristics .....	111
Figure F.1 – Examples of pillar terminals .....	113
Figure F.2 – Examples of screw terminals and stud terminals .....	114
Figure F.3 – Examples of saddle terminals .....	115
Figure F.4 – Examples of lug terminals .....	115
Figure H.1 – Test arrangement .....	118
Figure H.2 – Grid circuit .....	118
Figure H.3 – Grid circuit .....	119
Figure J.1 – Connecting samples .....	126
Figure J.2 – Examples of screwless-type terminals .....	128
Figure K.1 – Example of position of the thermocouple for measurement of the temperature-rise .....	133
Figure K.2 – Dimensions of male tabs .....	134
Figure K.3 – Dimensions of round dimple detents (see Figure K.2) .....	135
Figure K.4 – Dimensions of rectangular dimple detents (see Figure K.2) .....	135
Figure K.5 – Dimensions of hole detents .....	135
Figure K.6 – Dimensions of female connectors .....	136
Figure L.1 – General arrangement for the test .....	145
Figure L.2 .....	145
Figure L.3 .....	146
Figure L.4 .....	146
Figure L.5 .....	146
Figure L.6 .....	146
Table 1 – Preferred values of rated voltage .....	29
Table 2 – Ranges of instantaneous tripping .....	30
Table 3 – Rated impulse withstand voltage as a function of the nominal voltage of the installation .....	30
Table 4 – Minimum clearances and creepage distances .....	36
Table 5 – Connectable cross-sections of copper conductors for screw-type terminals .....	39
Table 6 – Temperature-rise values .....	42
Table 7 – Time-current operating characteristics .....	44
Table 8 – Maximum power loss per pole .....	46
Table 9 – List of type tests .....	47
Table 10 – Cross-sectional areas (S) of test copper conductors corresponding to the rated currents .....	48
Table 11 – Screw thread diameters and applied torques .....	49

Table 12 – Pulling forces .....	50
Table 13 – Test voltage of auxiliary circuits .....	54
Table 14 – Test voltage for verification of impulse withstand voltage .....	56
Table 15 – Test voltage for verifying the suitability for isolation, referred to the rated impulse withstand voltage of the circuit breakers and the altitude where the test is carried out .....	57
Table 16 – Applicability of short-circuit tests .....	63
Table 17 – Power factor ranges of the test circuit .....	65
Table 18 – Ratio $k$ between service short-circuit capacity ( $I_{CS}$ ) and rated short-circuit capacity ( $I_{CN}$ ) .....	69
Table 19 – Test procedure for $I_{CS}$ in the case of single- and two-pole circuit-breakers .....	70
Table 20 – Test procedure for $I_{CS}$ in the case of three- and four-pole circuit-breakers .....	70
Table 21 – Test procedure for $I_{CS}$ in the case of three-phase tests for single-pole circuit-breakers of rated voltage 230/400 V .....	71
Table 22 – The test procedure for $I_{CN}$ .....	71
Table 23 – Test procedure for $I_{CN}$ in the case of three-phase tests for single-pole circuit-breakers of rated voltage 230/400 V .....	72
Table C.1 – Test sequences .....	100
Table C.2 – Number of samples for full test procedure .....	101
Table C.3 – Reduction of samples for series of circuit-breakers having different numbers of poles .....	103
Table C.4 – Test sequences for a series of circuit-breakers being of different instantaneous tripping classifications .....	104
Table J.1 – Connectable conductors .....	124
Table J.2 – Cross-sections of copper conductors connectable to screwless-type terminals .....	124
Table J.3 – Pull forces .....	126
Table K.1 – Informative table on colour code of female connectors in relationship with the cross section of the conductor .....	131
Table K.2 – Overload test forces .....	132
Table K.3 – Dimensions of tabs .....	133
Table K.4 – Dimensions of female connectors .....	136
Table L.1 – Marking for terminals .....	138
Table L.2 – Connectable cross-sections of aluminium conductors for screw-type terminals .....	139
Table L.3 – List of tests according to the material of conductors and terminals .....	140
Table L.4 – Connectable conductors and their theoretical diameters .....	140
Table L.5 – Cross sections (S) of aluminium test conductors corresponding to the rated currents .....	141
Table L.6 – Test conductor length .....	142
Table L.7 – Equalizer and busbar dimensions .....	142
Table L.8 – Test current as a function of rated current .....	144
Table L.9 – Example of calculation for determining the average temperature deviation $D_{av}$ .....	144

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ELECTRICAL ACCESSORIES –  
CIRCUIT-BREAKERS FOR OVERCURRENT PROTECTION  
FOR HOUSEHOLD AND SIMILAR INSTALLATIONS –****Part 1: Circuit-breakers for a.c. operation**

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60898-1 has been prepared by sub-committee 23E: Circuit-breakers and similar equipment for household use, of IEC technical committee 23: Electrical accessories.

This bilingual version (2016-11) corresponds to the English version, published in 2015-03.

This second edition cancels and replaces the first edition published in 2002, Amendment 1:2002 and Amendment 2:2003. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) Revision of 9.5 Terminals
- b) Revision of the test of glow wire

c) Simplification of the figures for short circuit tests.

The text of this standard is based on the following documents:

FDIS	Report on voting
23E/881/FDIS	23E/894/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

The French version of this standard has not been voted upon.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

In this standard, the following print types are used:

- Requirements proper: in roman type.
- *Test specifications: in italic type.*
- Explanatory matter: in smaller roman type.

A list of all parts in the IEC 60898 series, published under the general title *Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations*, can be found on the IEC website.

IEEh STANDARD PREVIEW

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

[IEC 60898-1:2015](#)

- reconfirmed, <https://standards.iteh.ai/catalog/standards/sist/3e342d5e-f37e-4088-98c8-8066907010b7/iec-60898-1-2015>
- withdrawn,
- replaced by a revised edition, or
- amended.

The contents of the corrigendum of November 2015 have been included in this copy.

# ELECTRICAL ACCESSORIES – CIRCUIT-BREAKERS FOR OVERCURRENT PROTECTION FOR HOUSEHOLD AND SIMILAR INSTALLATIONS –

## Part 1: Circuit-breakers for a.c. operation

### 1 Scope

This part of IEC 60898 applies to a.c. air-break circuit-breakers for operation at 50 Hz, 60 Hz or 50/60 Hz, having a rated voltage not exceeding 440 V (between phases), a rated current not exceeding 125 A and a rated short-circuit capacity not exceeding 25 000 A.

As far as possible, it is in line with the requirements contained in IEC 60947-2.

These circuit-breakers are intended for the protection against overcurrents of wiring installations of buildings and similar applications; they are designed for use by uninstructed people and for not being maintained.

They are intended for use in an environment with pollution degree 2.

They are suitable for isolation.

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

Circuit-breakers of this standard, with exception of those rated 120 V or 120/240 V (see Table 1), are suitable for use in IT systems.

<https://standards.iteh.ai/catalog/standards/sist/3e342d5e-f37e-4088-98c8-12015>

This standard also applies to circuit-breakers having more than one rated current, provided that the means for changing from one discrete rating to another is not accessible in normal service and that the rating cannot be changed without the use of a tool.

This standard does not apply to

- circuit-breakers intended to protect motors;
- circuit-breakers, the current setting of which is adjustable by means accessible to the user.

For circuit-breakers having a degree of protection higher than IP20 according to IEC 60529, for use in locations where arduous environmental conditions prevail (e.g. excessive humidity, heat or cold or deposition of dust) and in hazardous locations (e.g. where explosions are liable to occur), special constructions may be required.

This standard does not apply to circuit-breakers for a.c. and d.c. operation, which is covered by IEC 60898-2.

This standard does not apply to circuit-breakers which incorporate residual current tripping devices, which is covered by IEC 61009-1, IEC 61009-2-1, and IEC 61009-2-2.

A guide for coordination under short-circuit conditions between a circuit-breaker and another short-circuit protective device (SCPDS) is given in Annex D. For more severe overvoltage conditions, circuit-breakers complying with other standards (e.g. IEC 60947-2) should be used.

For an environment with a higher pollution degree, enclosures giving the appropriate degree of protection should be used.

NOTE Circuit-breakers within the scope of this standard can also be used for protection against electric shock in case of fault, depending on their tripping characteristics and on the characteristics of the installation. The criterion of application for such purposes is dealt with by installation rules.

This standard contains all requirements necessary to ensure compliance with the operational characteristics required for these devices by type tests.

It also contains the details relative to test requirements and methods of testing necessary to ensure reproducibility of test results.

This standard states

- a) the characteristics of circuit-breakers;
- b) the conditions with which circuit-breakers shall comply, with reference to:
  - 1) their operation and behaviour in normal service;
  - 2) their operation and behaviour in case of overload;
  - 3) their operation and behaviour in case of short-circuits up to their rated short-circuit capacity;
  - 4) their dielectric properties;
- c) the tests intended for confirming that these conditions have been met and the methods to be adopted for the tests;
- d) the data to be marked on the devices;
- e) the test sequences to be carried out and the number of samples (see Annex C);
- f) the co-ordination under short-circuit conditions with another short-circuit protective device (SCPD) associated in the same circuit (see Annex D);
- g) the routine tests to be carried out on each circuit-breaker to reveal unacceptable variations in material or manufacture, likely to affect safety (see Annex I).

## 2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050 (all parts), *International Electrotechnical Vocabulary (IEV)*. Available from: <http://www.electropedia.org/>

IEC 60227 (all parts), *Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V*

IEC 60269 (all parts), *Low-voltage fuses*

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60417, *Graphical symbols for use on equipment*. Available from: <http://www.graphical-symbols.info/equipment>

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60664-1:2007, *Insulation co-ordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60695-2-10, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60695-2-11:2000, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products*

IEC 60947-1:2007, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-2:2006, *Low-voltage switchgear and controlgear – Part 2: Circuit-breakers*

IEC 61545:1996, *Connecting devices – Devices for the connection of aluminium conductors in clamping units of any material and copper conductors in aluminium bodied clamping units*

### 3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-441, as well as the following apply.

#### 3.1 Devices

##### 3.1.1

##### **switching device**

device designed to make or break the current in one or more electric circuits

[SOURCE: IEC 60050-441:1984, 441-14-01]

##### 3.1.2

##### **mechanical switching device**

switching device designed to close and open one or more electric circuits by means of separable contacts

[SOURCE: IEC 60050-441:1984, 441-14-02]

##### 3.1.3

##### **fuse**

device that, by the fusing of one or more of its specially designed and proportioned components, opens the circuit in which it is inserted and breaks the current when this exceeds a given value for a sufficient time

[SOURCE: IEC 60050-441:1984, 441-18-01, modified – "The fuse comprises all the parts that form the complete device" has been deleted.]

##### 3.1.4

##### **circuit-breaker**

<mechanical> mechanical switching device, capable of making, carrying and breaking currents under normal circuit conditions and also making, carrying for a specified time, and automatically breaking currents under specified abnormal circuit conditions such as those of short-circuit

[SOURCE: IEC 60050-441:1984, 441-14-20]

##### 3.1.5

##### **plug-in circuit-breaker**

circuit-breaker having one or more plug-in terminals (see 3.3.20) and designed for use with appropriate means for the plug-in connection