

INTERNATIONAL STANDARD

NORME INTERNATIONALE

High-voltage switchgear and controlgear –
IEC STANDARD PREVIEW
Part 104: Alternating current switches for rated voltages higher than 52 kV
(standards.iteh.ai)

Appareillage à haute tension –
IEC 62271-104:2015
Partie 104: Interrupteurs à courant alternatif pour tensions assignées
supérieures à 52 kV
<http://standards.iteh.ai/catalog/standards/sst/04429e3-cc0c-4242-b0b1-8d9ca5982c62/iec-62271-104-2015>





THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2015 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembé
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 15 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Glossary - std.iec.ch/glossary

More than 60 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Catalogue IEC - webstore.iec.ch/catalogue

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 15 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Recherche de publications IEC - www.iec.ch/searchpub

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

Glossaire IEC - std.iec.ch/glossary

Plus de 60 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.



IEC 62271-104

Edition 2.0 2015-02

INTERNATIONAL STANDARD

NORME INTERNATIONALE

High-voltage switchgear and controlgear –
iTeh STANDARD PREVIEW
Part 104: Alternating current switches for rated voltages higher than 52 kV
(standards.iteh.ai)

Appareillage à haute tension – [IEC 62271-104:2015](#)
Partie 104: Interrupteurs à courant alternatif pour tensions assignées
supérieures à 52 kV [8d9ca5982c62/iec-62271-104-2015](#)

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.130.10; 29.130.99

ISBN 978-2-8322-2245-4

Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

CONTENTS

FOREWORD.....	6
1 General	8
1.1 Scope	8
1.2 Normative references	9
2 Normal and special service conditions.....	9
3 Terms and definitions	9
3.1 General terms	9
3.2 Assemblies	9
3.3 Parts of assemblies.....	9
3.4 Switching devices	10
3.6 Operation.....	11
3.7 Characteristic quantities	11
4 Ratings.....	13
4.1 Rated voltage (U_r).....	13
4.2 Rated insulation level	13
4.3 Rated frequency (f_r)	13
4.4 Rated normal current and temperature rise (I_r)	13
4.5 Rated short-time withstand current (I_k)	13
4.6 Rated peak withstand current (I_p).....	13
4.7 Rated duration of short-circuit (t_k)	13
4.8 Rated supply voltage of closing and opening devices and of auxiliary and control circuits (U_a).....	13
4.9 Rated supply frequency of closing and opening devices and of auxiliary circuits	13
4.10 Rated pressure of compressed gas supply for controlled pressure systems	14
4.11 Rated filling levels for insulation and/or operation	14
4.101 Rated earth fault breaking current	14
4.102 Rated short-circuit making current	14
4.103 Rated mainly active load-breaking current	14
4.104 Rated closed-loop breaking current	14
4.105 Rated capacitive switching currents	14
4.105.1 Rated line-charging breaking current	14
4.105.2 Rated cable-charging breaking current	14
4.105.3 Rated single capacitor bank breaking current.....	14
4.105.4 Rated back-to-back capacitor bank breaking current	14
4.105.5 Single capacitor bank inrush making current.....	15
4.105.6 Rated back-to-back capacitor bank inrush making current	15
4.105.7 Rated cable and line-charging breaking current under earth fault conditions	15
4.106 Inductive load switching	15
4.106.1 Shunt reactor breaking current	15
4.106.2 Rated no-load transformer breaking current.....	15
4.107 Rated mechanical terminal load	15
4.108 Coordination of rated values for a general-purpose switch.....	15
4.109 Coordination of rated values for limited-purpose and special-purpose switches	16

5	Design and construction	16
5.1	Requirements for liquids in high-voltage switches	16
5.2	Requirements for gases in high-voltage switches	16
5.3	Earthing of high-voltage switches	17
5.4	Auxiliary and control equipment.....	17
5.5	Dependent power operation.....	17
5.6	Stored energy operation	17
5.7	Independent manual or power operation (independent unlatched operation)	17
5.8	Operation of releases	17
5.9	Low- and high-pressure interlocking and monitoring devices	17
5.10	Nameplates.....	17
5.11	Interlocking devices	18
5.12	Position indication	19
5.13	Degree of protection provided by enclosures.....	19
5.14	Creepage distances for outdoor insulators	19
5.15	Gas and vacuum tightness	19
5.16	Liquid tightness.....	19
5.17	Fire hazard (flammability)	19
5.18	Electromagnetic compatibility (EMC).....	19
5.19	X-ray emission	19
5.20	Corrosion	19
5.101	iTeh STANDARD PREVIEW Closing mechanism	19
5.102	Mechanical strength	19
5.103	Position of the movable contact <u>system</u> and its indicating or signalling device	19
5.103.1	Securing the position	19
5.103.2	Indication of position	20
5.103.3	Auxiliary contacts for signalling	20
6	Type tests	20
6.1	General.....	20
6.2	Dielectric tests	21
6.3	Radio interference voltage (r.i.v.) tests	22
6.4	Measurement of the resistance of circuits	22
6.5	Temperature rise tests	22
6.6	Short-time withstand current and peak withstand current tests	22
6.7	Verification of the protection	22
6.8	Tightness tests.....	22
6.9	Electromagnetic compatibility tests (EMC)	22
6.10	Additional tests on auxiliary and control circuits	22
6.11	X-radiation test procedure for vacuum interrupters	22
6.101	Mechanical operation tests	22
6.101.1	Arrangement of the switch for tests	22
6.101.2	Tests for general-purpose switches	23
6.101.3	Tests for limited-purpose and special-purpose switches	24
6.101.4	Condition of switch during and after mechanical operation tests	24
6.101.5	Operation under severe ice conditions	24
6.101.6	Static terminal load tests	24
6.102	Miscellaneous provision for making and breaking tests	25
6.102.1	Arrangement of the switch for tests	25

6.102.2	Behaviour of switch during breaking tests	26
6.102.3	Condition of switch after breaking tests	26
6.102.4	Condition of switch during and after short-circuit making tests.....	26
6.103	Test circuits for making and breaking tests	27
6.103.1	General	27
6.103.2	Earthing of test circuit and switch	27
6.103.3	Mainly active load circuit (test duty 1 and test duty 3)	28
6.103.4	Closed-loop circuits (test duty 2)	31
6.103.5	Test circuits for short-circuit making tests (test duty 6).....	35
6.103.6	Test circuits for breaking tests under earth fault conditions (test duties 7a and 7b).....	37
6.104	Test quantities	37
6.104.1	Test frequency	37
6.104.2	Test voltage for breaking tests	37
6.104.3	Breaking current	38
6.104.4	Test voltage for short-circuit making tests.....	39
6.104.5	Short-circuit making current.....	40
6.105	Capacitive current switching tests.....	40
6.105.1	Applicability	40
6.105.2	General	41
6.105.3	Characteristics of supply circuits.....	41
6.105.4	Earthing of the supply circuit.....	41
6.105.5	Characteristics of the capacitive circuit to be switched	41
6.105.6	Waveform of the current	41
6.105.7	Test voltage.....	41
6.105.8	Test current	42
6.105.9	Test duties.....	42
6.105.10	Tests with specified TRV	43
6.105.11	Criteria to pass the test	43
6.106	Inductive load switching (test duty 5)	43
6.106.1	No-load transformer circuit (test duty 5a).....	43
6.106.2	Shunt-reactor current switching tests (test duty 5b).....	43
6.107	Tests for general-purpose switches	44
6.108	Tests for limited-purpose switches	45
6.109	Tests for special-purpose switches	45
6.110	Type test reports	45
7	Routine tests	46
7.1	Dielectric tests on main circuit	46
7.2	Tests on auxiliary and control circuits	46
7.3	Measurement of the resistance of the main circuit.....	46
7.4	Tightness test	46
7.5	Design and visual checks	46
7.101	Mechanical operating tests	46
8	Guide to the selection of high-voltage switches	47
8.1	Selection of rated values	47
8.2	Continuous or temporary overload due to changed service conditions	47
8.101	General.....	47
8.102	Conditions affecting application	47

8.103	Insulation coordination	47
9	Information to be given with enquiries, tenders and orders.....	48
9.1	Information with enquiries and orders	48
9.2	Information with tenders	48
10	Transport, storage, installation, operation and maintenance.....	48
11	Safety	48
12	Influence of the high-voltage switch on the environment	48
	Bibliography	49

Figure 1 – Single-phase test circuit for mainly active load current switching for test duties 1 and 3.....28

Figure 2 – Single-phase test circuit for transmission line closed loop and parallel-transformer current switching test, for test duties 2a and 2b.....28

Figure 3 – Three-phase test circuit for mainly active load current switching, for test duties 1 and 3.....29

Figure 4 – Supply and load side transient for mainly active load current switching tests (see Table 4)

30

Figure 5 – Three-phase test circuit for transmission line closed loop and parallel-transformer current switching test for test duties 2a and 2b.....31

Figure 6 – Illustration of the transient associated with transmission line closed loop current breaking tests (see Table 5)

33

Figure 7 – Three-phase test circuit for short circuit making current test for test duty 6

36

Figure 8 – Single-phase test circuit for short circuit making current test for test duty 6

36

[IEC 62271-104:2015](#)

Table 1 – Preferred values of line and cable charging currents for a general-purpose switch

16

Table 2 – Nameplate information

18

Table 3 – Type tests

21

Table 4 – Supply circuit TRV parameters for mainly active load current breaking tests

30

Table 5 – TRV parameters for transmission line closed loop current breaking tests

32

Table 6 – Test duties for single-phase tests on three-pole switches having a non-simultaneity between poles of 0,25 cycle or less

33

Table 7 – Test duties for single-phase tests on three-pole switches having more than 0,25 cycle non-simultaneity and switches operated pole after pole

34

Table 8 – TRV parameters for parallel transformer current breaking tests.....

35

Table 9 – Test duties for three-phase tests on three-pole switches

37

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –**Part 104: Alternating current switches
for rated voltages higher than 52 kV****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62271-104 has been prepared by subcommittee 17A: High-voltage switchgear and controlgear, of IEC technical committee 17: Switchgear and controlgear.

This second edition replaces and cancels the first edition published in 2009 and constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- the title was changed such that the voltage range now is >52 kV instead of ≥52 kV;
- the references have been updated;
- the comments in 17A/1063/RVC have been addressed.

The text of this standard is based on the following documents:

FDIS	Report on voting
17A/1079/FDIS	17A/1082/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

This standard is to be read in conjunction with IEC 62271-1 (2007), IEC 62271-100 (2008), IEC 62271-102 (2001) and IEC 62271-110 (2012). In order to simplify the indication of corresponding requirements, the same numbering of clauses and subclauses is used as in IEC 62271-1. Modifications to these clauses and subclauses are given under the same numbering, whilst additional subclauses are numbered from 101.

A list of all parts in the IEC 62271 series, published under the general title *High-voltage switchgear and controlgear*, can be found on the IEC website..

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- iTeh STANDARD PREVIEW
(standards.iteh.ai)**
- reconfirmed,
 - withdrawn,
 - replaced by a revised edition, or
 - amended. [IEC 62271-104:2015](#)
<https://standards.iteh.ai/catalog/standards/sist/caf429e3-ccbc-4242-b6b1-8d9ca5982c62/iec-62271-104-2015>

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 104: Alternating current switches for rated voltages higher than 52 kV

1 General

1.1 Scope

Subclause 1.1 of IEC 62271-1:2007 is not applicable, and is replaced as follows:

This part of IEC 62271 is applicable to three-pole alternating current switches for rated voltages higher than 52 kV, having making and breaking current ratings, for indoor and outdoor installations, and for rated frequencies up to and including 60 Hz.

This standard is also applicable to the operating devices of these switches and to their auxiliary equipment.

NOTE 1 Switches for gas insulated switchgear are covered by this standard.

NOTE 2 Switches having a disconnecting function and called switch-disconnectors are also covered by IEC 62271-102.

NOTE 3 Earthing switches are not covered by this standard. Earthing switches forming an integral part of a switch are covered by IEC 62271-102.

The main object of this standard is to establish requirements for switches used in transmission and distribution systems. General-purpose switches for this application are designed to comply with the following service applications.

- carrying rated normal current continuously;
- carrying short-circuit currents for a specified time;
- switching of mainly active loads;
- switching of no-load transformers;
- switching of the charging current of unloaded cables, overhead lines or busbars;
- switching of closed-loop circuits;
- making short-circuit currents.

A further object of this standard is to establish requirements for limited-purpose and special-purpose switches used in transmission and distribution systems.

Limited-purpose switches comply with one or more of the service applications indicated above.

Special-purpose switches may comply with one or more of the service applications indicated above and, in addition, are suitable for one or more of the following applications:

- switching single capacitor banks;
- switching back-to-back capacitor banks;
- switching shunt reactors including secondary or tertiary reactors switched from the primary side of the transformer;
- applications requiring an increased number of operating cycles;
- switching under earth fault conditions in non-effectively earthed neutral systems.

1.2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-441:1984, *International Electrotechnical Vocabulary – Chapter 441: Switchgear, controlgear and fuses*

IEC 60071 (all parts), *Insulation co-ordination*

IEC 60071-1, *Insulation co-ordination – Part 1: Definitions, principles and rules*

IEC 60270, *High-voltage test techniques – Partial discharge measurements*

IEC 62271-1:2007, *High-voltage switchgear and controlgear – Part 1: Common specifications*
IEC 62271-1:2007/AMD1:2011

IEC 62271-100:2008, *High-voltage switchgear and controlgear – Part 100: Alternating-current circuit-breakers*
IEC 62271-100:2008/AMD1:2012

IEC 62271-102:2001, *High-voltage switchgear and controlgear – Part 102: Alternating current disconnectors and earthing switches*
IEC 62271-102:2001/AMD1:2011
IEC 62271-102:2001/AMD2:2013

IEC 62271-110:2012, *High-voltage switchgear and controlgear – Part 110: Inductive load switching*
<https://standards.iteh.ai/catalog/standards/sist/can429ccbc-4242-66b1-8d9ca5982c62/iec-62271-104-2015>

2 Normal and special service conditions

Clause 2 of IEC 62271-1:2007/AMD 1:2011 is applicable.

3 Terms and definitions

Clause 3 of IEC 62271-1:2007 is applicable with the the following additions.

For the purposes of this document, definitions of general terms are based on IEC 60050-441 and IEC 60071-1.

Additional terms and definitions are based solely on IEC 60050-441.

3.1 General terms

Subclause 3.1 of IEC 62271-1:2007 is applicable.

3.2 Assemblies

Subclause 3.2 of IEC 62271-1:2007 is applicable.

3.3 Parts of assemblies

Subclause 3.2 of IEC 62271-1:2007 is applicable.

3.4 Switching devices

Subclause 3.4 of IEC 62271-1:2007 is applicable, with the following additions.

3.4.101

switch

switching device capable of making, carrying and breaking currents under normal circuit conditions, which may include specified operating overload conditions and also carrying for a specified time currents under specified abnormal circuit conditions, such as those of short-circuit

[SOURCE: IEC 60050-441:1984, 441-14-10, modified – deletion of the word "mechanical" in the definition and deletion of the note.]

3.4.102

switch-disconnector

switch which, in the open position, satisfies the isolating requirements specified for a disconnector

[SOURCE: IEC 60050-441:1984, 441-14-12]

3.4.103

general-purpose switch

switch capable of performing, with currents up to its rated breaking currents, all making and breaking operations which may normally occur; capable of carrying and making short-circuit currents

*iteh STANDARD PREVIEW
(standards.iteh.ai)*

Note 1 to entry: Refer to 4.108 for specific ratings of a general-purpose switch.

[IEC 62271-104:2015](#)

3.4.104

limited-purpose switch

<https://standards.iteh.ai/catalog/standards/sist/caf429e3-ccbc-4242-b6b1-8d9ca5982c62/iec-62271-104-2015>

switch which complies with one or more, but not with all, service applications of a general-purpose switch

3.4.105

special-purpose switch

switch suitable for switching requirements other than those specified for a general-purpose switch

Note 1 to entry: Examples of such requirements are capacitor bank switching, shunt reactor switching, switching under earth fault conditions, and a capability of an increased number of operating cycles.

3.4.106

class C1 switch

special-purpose switch with low probability of restrike during capacitive current breaking as demonstrated by specific type tests

3.4.107

class C2 switch

special-purpose switch with very low probability of restrike during capacitive current breaking as demonstrated by specific type tests

3.4.108

single capacitor bank switch

special-purpose switch intended for switching of a single capacitor bank with charging currents up to its rated single capacitor bank breaking current

3.4.109**back-to-back capacitor bank switch**

special-purpose switch intended for breaking capacitor bank-charging currents, with one or more capacitor banks connected to the bus or supply side of the switch, up to its rated back-to-back capacitor bank breaking current

3.4.110**shunt reactor switch**

special-purpose switch intended for switching a shunt reactor, including secondary or tertiary reactors switched from the primary side of the transformer

3.5 Parts of switches

Subclause 3.5 of IEC 62271-1:2007 is applicable.

3.6 Operation

Subclause 3.6 of IEC 62271-1:2007 is applicable.

3.7 Characteristic quantities

Subclause 3.7 of IEC 62271-1:2007 is applicable, with the following additions.

3.7.101**breaking capacity (of a switching device or a fuse)**

value of prospective current that a switching device or a fuse is capable of breaking at a stated voltage under prescribed conditions of use and behaviour

Note 1 to entry: The voltage to be stated and the conditions to be prescribed are dealt with in the relevant publications.

[IEC 62271-104:2015](https://standards.iteh.ai/catalog/standards/sist/cat429e3-ccbc-4242-b6b1-3d9ca59c79-iec-62271-104-2015)

<https://standards.iteh.ai/catalog/standards/sist/cat429e3-ccbc-4242-b6b1-3d9ca59c79-iec-62271-104-2015>

Note 2 to entry: For switching devices, the breaking capacity may be termed according to the kind of current included in the prescribed conditions, e.g. line-charging breaking capacity, cable charging breaking capacity, single capacitor bank breaking capacity, etc.

[SOURCE: IEC 60050-441:1984, 441-17-08]

3.7.102**mainly active load breaking capacity**

breaking capacity when opening a mainly active load circuit in which the load can be represented by resistors and reactors in parallel

3.7.103**no-load transformer breaking capacity**

breaking capacity when opening a no-load transformer circuit

3.7.104**closed-loop breaking capacity**

breaking capacity when opening a closed transmission line loop circuit, or a transformer in parallel with one or more transformers, i.e. a circuit in which both sides of the switch remain energized after breaking, and in which the voltage appearing across the terminals is substantially less than the system voltage

3.7.105**cable-charging breaking capacity**

breaking capacity when opening a cable circuit at no load

3.7.106**line-charging breaking capacity**

breaking capacity when opening an overhead line circuit at no load

3.7.107**busbar charging breaking capacity**

breaking capacity when opening a busbar circuit at no load

3.7.108**single capacitor bank breaking capacity**

breaking capacity when opening a single capacitor bank circuit connected to a supply that does not include another capacitor bank adjacent to the bank being switched

3.7.109**back-to-back capacitor bank breaking capacity**

breaking capacity when opening a capacitor bank circuit connected to a supply that includes one or more capacitor banks adjacent to the bank being switched

3.7.110**capacitor bank inrush making current**

high frequency and high magnitude current occurring when closing a capacitor bank circuit onto a supply including one or more capacitor banks adjacent to the bank being switched

Note 1 to entry: The frequency and magnitude of the inrush current depend upon the values of capacitance and the values of the inductance between the capacitor banks.

3.7.111**shunt reactor breaking capacity**

breaking capacity when opening a shunt reactor circuit including secondary or tertiary reactors switched from the primary side of the transformer

3.7.112**earth-fault breaking capacity**

breaking capacity in the faulty phase of a non-effectively earthed neutral system when clearing an earth fault on an unloaded cable or overhead line on the load side of the switch
IEC 62271-104:2015
<https://standards.iteh.ai/standards/iec-62271-104-3-2015-06-01/>
8d9ca5982c62/iec-62271-104-2015

3.7.113**cable and line charging breaking capacity under earth fault conditions**

breaking capacity in the sound phases of an effectively earthed neutral or non-effectively earthed neutral system when switching off an unloaded cable or overhead line, with an earth fault on the supply side of the switch

3.7.114**breaking current (of a switching device or a fuse)**

current in a pole of a switching device or in a fuse at the instant of initiation of the arc during a breaking process

[SOURCE: IEC 60050-441:1984 441-17-07]

3.7.115**(peak)-making current**

peak value of the first major loop of the current in a pole of a switch during the transient period following the initiation of current during a making operation

Note 1 to entry: The peak value may differ from one pole to another and from one operation to another as it depends on the instant of current initiation relative to the wave of the applied voltage.

Note 2 to entry: Where, for a polyphase circuit, a single value of (peak) making current is referred to, it is, unless otherwise stated, the highest value in any phase.

3.7.116**short-circuit making capacity**

making capacity for which the prescribed conditions include a short-circuit at the terminals of the switching device

[SOURCE: IEC 60050-441:1984, 441-17-10]

3.7.117 simultaneity between poles

maximum difference between the instant of contact touch in the first pole and the last pole when closing and the maximum time difference between the instant of contact separation between the first pole and the last pole when opening

4 Ratings¹

Clause 4 of IEC 62271-1:2007/AMD 1:2011 is applicable with the the following additions.

4.1 Rated voltage (U_r)

Subclause 4.1 of IEC 62271-1:2007/AMD 1:2011 is applicable with the following addition:

The 1 100 kV and 1 200 kV voltage ratings do not apply to switches.

4.2 Rated insulation level

Subclause 4.2 of IEC 62271-1:2007/AMD 1:2011 is applicable.

4.3 Rated frequency (f_r)

iTeH STANDARD PREVIEW
(standards.iteh.ai)

4.4 Rated normal current and temperature rise (I_r)

Subclause 4.4 of IEC 62271-1:2007 is applicable.
<http://standards.iteh.ai/calling-features/sist/caf429e3-ccbc-4242-b6b1-8d9ca5982c62/iec-62271-104-2015>

4.5 Rated short-time withstand current (I_k)

Subclause 4.5 of IEC 62271-1:2007 is applicable.

4.6 Rated peak withstand current (I_p)

Subclause 4.6 of IEC 62271-1:2007/AMD 1:2011 is applicable.

4.7 Rated duration of short-circuit (t_k)

Subclause 4.7 of IEC 62271-1:2007 is applicable.

4.8 Rated supply voltage of closing and opening devices and of auxiliary and control circuits (U_a)

Subclause 4.8 of IEC 62271-1:2007 is applicable.

4.9 Rated supply frequency of closing and opening devices and of auxiliary circuits

Subclause 4.9 of IEC 62271-1:2007 is applicable.

¹ Note concerning the rated values:

In English, the terms “rated making current” and “rated breaking current” are now used where formerly “rated making capacity” and “rated breaking capacity” were used, the intended meaning being adequately conveyed by the use of “rated”. In French, the terms “pouvoir de fermeture assigné” and “pouvoir de coupure assigné” continue to be used.