

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



DC or AC supplied electronic controlgear for LED modules – Performance requirements

(standards.iteh.ai)

Appareillages électroniques alimentés en courant continu ou alternatif pour modules de LED – Exigences de performances

IEC 62384-2020  
<https://standards.iteh.ai/catalog/standards/sis/7fd86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020>



## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2020 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

#### IEC publications search - [webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

#### IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [sales@iec.ch](mailto:sales@iec.ch).

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary on electrotechnology, containing more than 22,000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

#### IEC Glossary - [std.iec.ch/glossary](http://std.iec.ch/glossary)

67,000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

### A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

### A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

#### Recherche de publications IEC -

[webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

#### Service Clients - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: [sales@iec.ch](mailto:sales@iec.ch).

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

#### Glossaire IEC - [std.iec.ch/glossary](http://std.iec.ch/glossary)

67 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



DC or AC supplied electronic controlgear for LED modules – Performance requirements

[standards.iteh.ai](https://standards.iteh.ai)

Appareillages électroniques alimentés en courant continu ou alternatif pour modules de LED – Exigences de performances

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

ICS 29.140.99; 31.080.99

ISBN 978-2-8322-8308-0

**Warning! Make sure that you obtained this publication from an authorized distributor.**  
**Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

## CONTENTS

FOREWORD .....	3
1 Scope .....	5
2 Normative references .....	5
3 Terms and definitions .....	5
4 General notes on tests .....	6
5 Classification .....	7
5.1 Classification according to the load .....	7
5.2 Classification according to the output voltage .....	7
5.3 Classification according to the output current .....	7
6 Marking .....	7
6.1 Mandatory marking .....	7
6.2 Optional marking .....	7
7 Output voltage and current .....	8
7.1 Starting and connecting requirements .....	8
7.2 Voltage and current during operation .....	8
7.3 Capacitive load requirement .....	8
8 Total circuit power .....	8
9 Circuit power factor .....	9
10 Supply current .....	9
11 Operational tests for abnormal conditions .....	9
12 Endurance .....	10
Annex A (normative) Tests .....	11
A.1 General requirements .....	11
A.1.1 General .....	11
A.1.2 Ambient temperature .....	11
A.1.3 Supply voltage and frequency .....	11
A.1.4 Magnetic effects .....	11
A.1.5 Instrument characteristics .....	11
A.2 Measurement of capacitive load current .....	12
Annex B (informative) Guidance on quoting product life and failure rate .....	13
Bibliography .....	14
Figure A.1 – Test circuit for measurement of capacitive load current .....	12

**ITEH STANDARD PREVIEW**  
**(standards.iteh.ai)**  
<https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020>  
**IEC 62384:2020**

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

**DC OR AC SUPPLIED ELECTRONIC CONTROLGEAR FOR  
LED MODULES – PERFORMANCE REQUIREMENTS**

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62384 has been prepared by subcommittee 34C: Auxiliaries for lamps, of IEC technical committee 34: Lamps and related equipment.

This second edition cancels and replaces the first edition published in 2006 and Amendment 1:2009. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) scope extension (direct current from 250 V to 1 000 V);
- b) new specifications for measuring the power factor for controlgear with settable/non-constant output (for instance, to allow for constant light output);
- c) deletion of audio frequency requirements;
- d) selection of current test circuit by module capacitance (instead of selecting by having or not having logic circuitry) plus test circuit setup changes.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
34C/1488/FDIS	34C/1489/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

This document is to be read in conjunction with IEC 61347-2-13.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

## iTeh STANDARD PREVIEW

**IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this publication using a colour printer.**

[IEC 62384:2020](#)

<https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020>

# DC OR AC SUPPLIED ELECTRONIC CONTROLGEAR FOR LED MODULES – PERFORMANCE REQUIREMENTS

## 1 Scope

This document specifies performance requirements for electronic controlgear for use on DC or AC supplies up to 1 000 V (alternating current at 50 Hz or 60 Hz) and with an output frequency which can deviate from the supply frequency, associated with LED modules according to IEC 62031. Controlgear for LED modules specified in this document are designed to provide constant voltage or current. Deviations from the pure voltage and current types do not exclude the gear from this document.

NOTE 1 The tests in this document are type tests. Requirements for testing individual controlgear during production are not included.

NOTE 2 Requirements for controlgear which incorporate means for varying the output power are under consideration.

NOTE 3 It can be expected that controlgear complying with this document will ensure satisfactory operation between 92 % and 106 % of the rated supply voltage, taking into account the specifications of the LED module manufacturer.

## 2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61347-1, *Lamp controlgear – Part 1: General and safety requirements*

IEC 61347-2-13, *Lamp controlgear – Part 2-13: Particular requirements for d.c. or a.c. supplied electronic controlgear for LED modules*

## 3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 61347-1 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

### 3.1

#### total circuit power

total power dissipated by controlgear and LED module(s) in combination, at rated supply voltage of the controlgear and at the highest rated output load

### 3.2

#### circuit power factor

$\lambda$

ratio of the measured circuit power to the product of the supply voltage (RMS) and the supply current (RMS)

### 3.3

#### **controlgear for LED module circuitry with high input capacitance**

controlgear suitable for LED modules which present high capacitance connected directly or indirectly to the input terminals

Note 1 to entry: Examples are LED modules with switch mode power supply conversion circuits, like buck or boost regulators.

Note 2 to entry: Typically, capacitances above 100 nF are considered high capacitance.

### 3.4

#### **controlgear for LED module circuitry with low input capacitance**

controlgear suitable for LED modules which present low capacitance or no capacitance connected directly or indirectly to the input terminals

Note 1 to entry: Examples are LED modules with only LEDs or with logic circuits intended for thermal protection, but not directly modifying the power supplied by the controlgear, or linear voltage regulators.

Note 2 to entry: Typically, capacitances of 100 nF and below are considered low capacitance.

## 4 General notes on tests

### 4.1 The tests given in this document are type tests.

The requirements and tolerances permitted by this document are based on testing of a type test sample submitted by the manufacturer for that purpose. In principle this type test sample should consist of units having characteristics typical of the manufacturer's production and be as close to the production centre point values as possible.

NOTE It can be expected with the tolerances given in this document that products manufactured in accordance with the type test sample will comply with this document for the majority of the production. Due to the production spread however, it is inevitable that there will sometimes be products outside the specified tolerances. For guidance on sampling plans and procedures for inspection by attributes see IEC 60410.

### 4.2 For tests which are carried out with a LED module or LED modules, this (these) LED module(s) shall fulfil the following requirements:

The power of the LED module(s) when measured at its (their) rated voltage or rated current (direct current and/or alternating current) shall not differ from the rated power by more than +6 % and –0 %.

### 4.3 The tests shall be carried out in the order of the clauses, unless otherwise specified.

### 4.4 One specimen shall be subjected to all the tests.

4.5 In general all the tests are made on each type of controlgear or, where a range of similar controlgear is involved for each rated power in the range or on a representative selection from the range as agreed with the manufacturer.

4.6 The tests shall be made under the conditions specified in Clause A.1. Since up to now data with regard to LED modules have not been published in an IEC standard, they shall be made available by the LED module manufacturer.

4.7 All controlgear covered by this document shall comply with the requirements of IEC 61347-2-13.

4.8 The tests shall be carried out with the length of the output cable of both 20 cm and 200 cm unless otherwise declared by the manufacturer.



## 5 Classification

### 5.1 Classification according to the load

a) Single value load controlgear

This type of controlgear is designed for use with one specific output power only, which may be dissipated by one or more LED modules.

b) Multiple value load controlgear

This type of controlgear is designed for use with one or more LED modules with a total load within the declared power range.

### 5.2 Classification according to the output voltage

a) Controlgear having a stabilized output voltage.

b) Controlgear without a stabilized output voltage.

### 5.3 Classification according to the output current

a) Controlgear having a stabilized output current.

b) Controlgear without a stabilized output current.

## 6 Marking

### 6.1 Mandatory marking

#### 6.1.1 Controlgear shall be clearly marked as follows:

Circuit power factor, for example  $\lambda = 0,9$ .

For controlgear where the power factor is not constant all over the rated output range and/or controlgear with a supply voltage range, the power factor may be different for different combinations of supply voltage and output power. In this case the controlgear shall be marked with a range of power factor values, for example  $\lambda = 0,8 - 0,9$ .

If the power factor is less than 0,95 leading, it shall be followed by the letter "C", for example  $\lambda = 0,9 C$ .

6.1.2 In addition to the above mandatory marking, the following information shall either be given on the controlgear or made available in the manufacturer's catalogue or the like:

- if applicable: limits of the permissible temperature range;
- if applicable: an indication that the controlgear has a stabilized output voltage;
- if applicable: an indication that the controlgear has a stabilized output current;
- if applicable: an indication that the controlgear is suitable for operation with a mains supply dimmer;
- if applicable: an indication of the operation mode, for example phase control;
- if applicable:  $P_{\text{rated\_min}}$ , the rated minimum output power for the proper operation of the controlgear.

NOTE  $P_{\text{rated\_min}}$  can be combined with  $P_{\text{rated}}$  in only one marking. e.g.  $P_{\text{rated}} = 20 \text{ W} \dots 60 \text{ W}$ .

### 6.2 Optional marking

The following information may either be given on the controlgear or made available in the manufacturer's catalogue or the like:

- total circuit power;

- b) if applicable: a symbol which indicates that the controlgear is a short-circuit proof type (the symbol is under consideration).

## 7 Output voltage and current

### 7.1 Starting and connecting requirements

After starting or connecting a LED module, the output should be within 110 % of its rated value within 2 s. Maximum current or maximum voltage shall not exceed the values given by the manufacturer. This performance is tested with the minimum rated power.

NOTE If the output voltage is AC, 110 % is the percentage of the RMS value, if DC, 110 % is the percentage of the DC value.

### 7.2 Voltage and current during operation

For controlgear having a non-stabilized output voltage, when supplied with the rated supply voltage, the output voltage shall not differ by more than  $\pm 10$  % from the rated voltage of the LED modules. For controlgear having a stabilized output voltage, when supplied at any supply voltage between 92 % and 106 % of the rated supply voltage, the output voltage shall not differ by more than  $\pm 10$  % from the rated voltage of the LED modules.

For controlgear having a non-stabilized output current, when supplied with the rated supply voltage, the output current shall not differ by more than  $\pm 10$  % from the rated current of the LED modules. For controlgear having a stabilized output current, when supplied at any supply voltage between 92 % and 106 % of the rated supply voltage, the output current shall not differ by more than  $\pm 10$  % from the rated current of the LED modules.

Multiple load controlgear shall be tested with both the minimum and maximum load.

[IEC 62384:2020](https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020)

### 7.3 Capacitive load requirement

<https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020>

The LED module or any additional control unit connected to the controlgear may contain capacitors for control and/or driving circuitry on the modules and current pulses may be generated when connecting the LED module to the controlgear. Controlgear overcurrent detection shall not be disturbed during the starting process of the controlgear.

For test conditions, see Clause A.2. Figure A.1a) describes a test circuit during the starting process of the controlgear and Figure A.1b) describes a test circuit for connecting the load during steady state operation.

The test according to Figure A.1b) may be waived under the condition that it is specified by the manufacturer in the product information of the controlgear that the LED module must be connected prior to starting the controlgear in order to ensure proper starting of the LED module.

If the load detection circuit of the controlgear does not allow operation with pure resistive load, the resistor R is to be substituted with equivalent LED load.

*Compliance: The controlgear overvoltage detection shall not act during the starting phase or when connecting the load in the steady state phase.*

## 8 Total circuit power

At rated voltage, the total circuit power shall not be more than 110 % of the value declared by the manufacturer, when the controlgear is operated with LED module(s).

## 9 Circuit power factor

The measured circuit power factor shall not be less than the marked value by more than 0,05 when the controlgear is operated at the rated output power range with LED module(s) and the whole combination is supplied with rated voltage and frequency.

For controllable controlgear, the power factor is measured with the controlgear adjusted to provide the maximum output power.

Controlgear designed to provide, in combination with a LED module, constant luminous flux, are measured with a load not using the rated output power at 0 h, but with the controlgear providing the maximum output power.

The DUT may be specially prepared in a way that the output power is set to the maximum value compensating the luminous flux depreciation of the load at the end of life.

For controlgear with a supply voltage range, the test shall be performed with the combination of supply voltage range and output power range which gives the lowest and highest power factor (e.g. minimum supply voltage, maximum rated output power and maximum supply voltage, minimum rated output power). The measured power factors shall not be less than the lowest and highest marked values by more than 0,05 respectively.

## 10 Supply current

At rated voltage, the supply current shall not differ by more than +10 % from the value marked on the controlgear or declared in the manufacturer's literature, when that controlgear is operated on its rated power with LED module(s).

[IEC 62384:2020](https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-1000623842020/iec-62384-2020)

[https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-](https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-1000623842020/iec-62384-2020)

## 11 Operational tests for abnormal conditions

The controlgear shall not be damaged under the following conditions.

### a) Test without LED module(s) inserted

The controlgear shall be supplied with rated voltage for 1 h without LED module(s) inserted. At the end of this test, the LED module(s) shall be connected and shall operate normally.

### b) Test for reduced LED module resistance

Under consideration.

### c) Tests for short-circuit proof controlgear

The controlgear is short-circuited for 1 h.

The 1 h test shall be completed also in the case of a thermal protection acting.

After these tests and after restoration of a possible protecting device, the controlgear shall function normally.

## 12 Endurance

**12.1** The controlgear shall be subjected to a temperature cycling shock test and a supply voltage switching test as follows:

a) Temperature cycling shock test

The non-energized controlgear shall be stored firstly at  $-10^{\circ}\text{C}$  or if the controlgear is marked with a lower value, at that value for 1 h. The controlgear is then moved into a cabinet having a temperature of  $t_c$  and stored for 1 h. Five such temperature cycles shall be carried out.

b) Supply voltage switching test

At rated supply voltage the controlgear shall be switched on and off for 30 s. The cycling shall be repeated 200 times with no load and 800 times under maximum load conditions.

LED modules failing during this test shall be replaced immediately.

At the end of these tests the controlgear shall operate an appropriate LED module or LED modules correctly for 15 min.

**12.2** The controlgear shall then be operated with an appropriate LED module(s) at rated supply voltage and at the ambient temperature which produces  $t_c$ , until a test period of 200 h has passed. At the end of this time, and after cooling down to room temperature, the controlgear shall operate an appropriate LED module(s) correctly for 15 min. During this test the LED module(s) is (are) placed outside the test enclosure at an ambient temperature of  $(25 \pm 5)^{\circ}\text{C}$ .

ITEH STANDARD PREVIEW  
(standards.iteh.ai)

[IEC 62384:2020](https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020)

<https://standards.iteh.ai/catalog/standards/sist/91d86548-9c85-4b9b-9a16-0e6f7b623d05/iec-62384-2020>