



SLOVENSKI STANDARD

SIST ETS 300 417-5-1 E1:2003

01-december-2003

DfYbcg]b`a i `hjd`Y_g]fUb`Y`fHAŁĚ; YbYf] bY`nU hYj Y`nUdfYbcgbc`Z b_W]cbUbcgh
cdfYa YĚ) !%`XY. : i b_W]Y`d`Ugh]`dch]`df]`d`Yn]c\ fcb]`X][]H]b]` \]YfU\]]`fD8 <Ł

Transmission and Multiplexing (TM); Generic requirements of transport functionality of equipment; Part 5-1: Plesiochronous Digital Hierarchy (PDH) path layer functions

iteh STANDARD PREVIEW
(standards.iteh.ai)

Ta slovenski standard je istoveten z: **ETS 300 417-5-1 Edition 1**

SIST ETS 300 417-5-1 E1:2003
<https://standards.iteh.ai/catalog/standards/sist/1c9d5803-530b-4500-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>

ICS:

33.040.20 Prenosni sistem Transmission systems

SIST ETS 300 417-5-1 E1:2003 en

iTeh STANDARD PREVIEW
(standards.iteh.ai)

SIST ETS 300 417-5-1 E1:2003

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>



EUROPEAN
TELECOMMUNICATION
STANDARD

ETS 300 417-5-1

March 1998

Source: TM

Reference: DE/TM-01015-5-1

ICS: 33.020

Key words: PDH, SDH, transmission, transport, path

**Transmission and Multiplexing (TM);
Generic requirements of transport functionality of equipment;
Part 5-1: Plesiochronous Digital Hierarchy (PDH)
path layer functions**

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2a111111/ets-300-417-5-1>

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

Internet: secretariat@etsi.fr - <http://www.etsi.fr> - <http://www.etsi.org>

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1998. All rights reserved.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[SIST ETS 300 417-5-1 E1:2003](https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>

Contents

Contents	3
Foreword	7
Introduction	7
1 Scope	9
2 References	9
3 Definitions, abbreviations and symbols	10
3.1 Definitions	10
3.2 Abbreviations	10
3.3 Symbols and Diagrammatic Conventions	13
4 P4e path layer functions	14
4.1 P4e connection functions	16
4.2 P4e trail termination functions	17
4.2.1 P4e trail termination source P4e_TT_So	17
4.2.2 P4e trail termination sink P4e_TT_Sk	18
4.3 P4e adaptation functions	20
4.3.1 P4e to P31x adaptation source P4e/P31x_A_So/i	20
4.3.2 P4e to P31x Adaptation Sink P4e/P31x_A_Sk/i	22
4.3.3 P4e to P31e adaptation source P4e/P31e_A_So/i	24
4.3.4 P4e to P31e adaptation sink P4e/P31e_A_Sk/i	26
4.3.5 P4e to P31s adaptation source P4e/P31s_A_So/i	28
4.3.6 P4e to P31s adaptation sink P4e/P31s_A_Sk/i	30
4.4 P4e layer monitoring functions	33
4.4.1 P4e layer non-intrusive monitoring function P4em_TT_Sk	33
4.5 P4e PDH equipment clock adaptation source P4e_PEC	35
5 P31e path layer functions	36
5.1 P31e connection functions	37
5.2 P31e trail termination functions	38
5.2.1 P31e trail termination source P31e_TT_So	38
5.2.2 P31e trail termination sink P31e_TT_Sk	39
5.3 P31e adaptation functions	41
5.3.1 P31e to P22x adaptation source P31e/P22x_A_So/i	41
5.3.2 P31e to P22x adaptation sink P31e/P22x_A_Sk/i	43
5.3.3 P31e to P22e adaptation source P31e/P22e_A_So/i	45
5.3.4 P31e to P22e adaptation sink P31e/P22e_A_Sk/i	47
5.4 P31e layer monitoring functions	49
5.4.1 P31e layer non-intrusive monitoring function P31em_TT_Sk	49
5.5 P31e PDH equipment clock adaptation source P31e_PEC	51
6 P22e path layer functions	52
6.1 P22e connection functions	53
6.2 P22e trail termination functions	54
6.2.1 P22e trail termination source P22e_TT_So	54
6.2.2 P22e trail termination sink P22e_TT_Sk	55
6.3 P22e adaptation functions	57
6.3.1 P22e to P12x adaptation source P22e/P12x_A_So/i	57
6.3.2 P22e to P12x adaptation sink P22e/P12x_A_Sk/i	59
6.3.3 P22e to P12s adaptation source P22e/P12s_A_So/i	61
6.3.4 P22e to P12s adaptation sink P22e/P12s_A_Sk/i	63
6.4 P22e layer monitoring functions	65
6.4.1 P22e layer non-intrusive monitoring function P22em_TT_Sk	65
6.5 P22e PDH equipment clock adaptation source P22e_PEC	67
7 P12s path layer functions	68

7.1	P12s connection functions	71
7.2	P12s trail termination functions	72
7.2.1	P12s trail termination source P12s_TT_So	72
7.2.2	P12s trail termination sink P12s_TT_Sk.....	74
7.3	P12s adaptation functions.....	77
7.3.1	P12s to P0-31c adaptation source P12s/P0-31c_A_So	77
7.3.2	P12s to P0-31c adaptation sink P12s/P0-31c_A_Sk.....	78
7.3.3	P12s to SD adaptation source P12s/SD_A_So	79
7.3.4	P12s to SD adaptation sink P12s/SD_A_Sk.....	79
7.3.5	P12s to ATM VP compound adaptation source P12s/Avp_A_So	79
7.3.6	P12s to ATM VP compound adaptation sink P12s/Avp_A_Sk.....	79
7.3.7	P12s Layer Clock adaptation source P12s-LC_A_So	79
7.4	P12s layer monitoring functions	80
7.4.1	P12s layer non-intrusive monitoring function P12sm_TT_Sk.....	80
8	P31s path layer functions	82
8.1	P31s connection functions	83
8.2	P31s trail termination functions	84
8.2.1	P31s trail termination source P31s_TT_So	84
8.2.2	P31s trail termination sink P31s_TT_Sk.....	86
8.3	P31s adaptation functions.....	88
8.3.1	P31s layer to VC-12, VC-11 layer compound adaptation source function P31s/SX_A_So	88
8.3.1.1	P31s layer to TUG adaptation source function P31s/TUG_A_So	90
8.3.1.2	TUG termination source function TUG_T_So.....	92
8.3.1.3	TUG to VC-12 layer adaptation source function TUG/S12_A_So/M	93
8.3.1.4	TUG to VC-11 layer adaptation source function TUG/S11_A_So/M	96
8.3.2	P31s layer to VC-12, VC-11 layer compound adaptation sink function P31s/SX_A_Sk	100
8.3.2.1	P31s layer to TUG adaptation sink function P31s/TUG_A_Sk	102
8.3.2.2	TUG termination sink function TUG_T_Sk	104
8.3.2.3	TUG to VC-12 layer adaptation sink function TUG/S12_A_Sk/M	105
8.3.2.4	TUG to VC-11 layer adaptation sink function TUG/S11*_A_Sk/M	107
8.3.3	P31s layer to P0s layer adaptation source P31s/P0s_A_So	109
8.3.4	P31s layer to P0s layer adaptation sink P31s/P0s_A_Sk.....	110
8.3.5	P31s to V0x adaptation source P31s/V0x_A_So.....	111
8.3.6	P31s to V0x adaptation sink P31s/V0x_A_Sk.....	112
8.3.7	P31s to DCC adaptation source P31s/DCC_A_So	113
8.3.8	P31s to DCC adaptation sink P31s/DCC_A_Sk.....	114
8.3.9	P31s to SD adaptation source P31s/SD_A_So	115
8.3.10	P31s to SD adaptation sink P31s/SD_A_Sk.....	115
8.3.11	P31s to ATM VP compound adaptation source P31s/Avp_A_So	115
8.3.12	P31s to ATM VP compound adaptation sink P31s/Avp_A_Sk.....	115
8.3.13	P31s Layer Clock adaptation source P31s-LC_A_So	115
8.4	P31s layer monitoring functions	116
8.4.1	P31s non-intrusive monitoring function P31sm_TT_Sk	116
8.5	P31s layer trail protection functions	118
8.6	P31s tandem connection sublayer functions.....	119
8.6.1	P31s tandem connection trail termination source function (P31sD_TT_So).....	119
8.6.2	P31s tandem connection trail termination sink function (P31sD_TT_Sk) ..	122
8.6.3	P31s tandem connection to p31s adaptation source function (P31sD/P31s_A_So).....	127
8.6.4	P31s tandem connection to p31s adaptation sink function (P31sD/P31s_A_Sk).....	128
8.6.5	P31s tandem connection non-intrusive trail termination sink function (P31sDm_TT_Sk).....	129

9	P4s path layer functions	133
9.1	P4s connection functions	134
9.2	P4s trail termination functions	135
9.2.1	P4s trail termination source P4s_TT_So	135
9.2.2	P4s trail termination sink P4s_TT_Sk	137
9.3	P4s adaptation functions	139
9.3.1	P4s layer to VC-3, VC-2, VC-12, and VC-11 layer compound adaptation source function P4s/SX-TUG3_A_So	139
9.3.1.1	P4s layer to TUG3 adaptation source function P4s/TUG3_A_So	141
9.3.1.2	TUG3 trail termination source function TUG3_T_So	143
9.3.1.3	TUG3 to VC-3 layer adaptation source function TUG3/S3_A_So/K.0.0	144
9.3.1.4	TUG3 to VC-2 layer adaptation source function TUG3/S2_A_So/K.L.0	147
9.3.1.5	TUG3 to VC-12 layer adaptation source function TUG3/S12_A_So/K.L.M	150
9.3.1.6	TUG3 to VC-11 layer adaptation source function TUG3/S11*_A_So/K.L.M	153
9.3.2	P4s layer to VC-3, VC-2, VC-12, and VC-11 layer compound adaptation sink function P4s/SX-TUG3_A_Sk	157
9.3.2.1	P4s layer to TUG3 adaptation sink function P4s/TUG3_A_Sk	159
9.3.2.2	TUG3 trail termination sink function TUG3_T_Sk	161
9.3.2.3	TUG3 to VC-3 layer adaptation sink function TUG3/S3_A_Sk/K.0.0	162
9.3.2.4	TUG3 to VC-2 layer adaptation sink function TUG3/S2_A_Sk	164
9.3.2.5	TUG3 to VC-12 layer adaptation sink function TUG3/S12_A_Sk/K.L.M	166
9.3.2.6	TUG3 to VC-11 layer adaptation sink function TUG3/S11*_A_Sk/K.L.M	168
9.3.3	P4s layer to VC-2, VC-12, and VC-11 layer compound adaptation source function P4s/SX-TUG2_A_So	170
9.3.3.1	P4s layer to TUG2 adaptation source function P4s/TUG2_A_So	172
9.3.3.2	TUG2 trail termination source function TUG2_T_So	173
9.3.3.3	TUG2 to VC-2 layer adaptation source function TUG2/S2_A_So/L.0	174
9.3.3.4	TUG2 to VC-12 layer adaptation source function TUG2/S12_A_So/L.M	177
9.3.3.5	TUG2 to VC-11 layer adaptation source function TUG2/S11*_A_So/L.M	180
9.3.4	P4s layer to VC-2, VC-12, and VC-11 layer compound adaptation sink function P4s/SX-TUG2_A_Sk	184
9.3.4.1	P4s layer to TUG2 adaptation sink function P4s/TUG2_A_Sk	186
9.3.4.2	TUG2 trail termination sink function TUG2_T_Sk	188
9.3.4.3	TUG2 to VC-2 layer adaptation sink function TUG2/S2_A_Sk/L.0	189
9.3.4.4	TUG2 to VC-12 layer adaptation sink function TUG2/S12_A_Sk/L.M	191
9.3.4.5	TUG2 to VC-11 layer adaptation sink function TUG2/S11*_A_Sk/L.M	193
9.3.5	P4s layer to P0s layer adaptation source P4s/P0s_A_So	195
9.3.6	P4s layer to P0s layer adaptation sink P4s/P0s_A_Sk	196
9.3.7	P4s to V0x adaptation source P4s/V0x_A_So	197
9.3.8	P4s to V0x adaptation sink P4s/V0x_A_Sk	198
9.3.9	P4s to DCC adaptation source P4s/DCC_A_So	199
9.3.10	P4s to DCC adaptation sink P4s/DCC_A_Sk	200
9.3.11	P4s to SD adaptation source P4s/SD_A_So	201
9.3.12	P4s to SD adaptation sink P4s/SD_A_Sk	201
9.3.13	P4s to ATM VP compound adaptation source P4s/Avp_A_So	201

iTech STANDARD PREVIEW
(standards.itd.cn)

<https://standards.itd.cn/catalog/standards/sstd-1998-03-01-4380-4380-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>

	9.3.14	P4s to ATM VP compound adaptation sink P4s/Avp_A_Sk	201
	9.3.15	P4s Layer Clock adaptation source P4s-LC_A_So	201
9.4		P4s layer monitoring functions	202
	9.4.1	P4s non-intrusive monitoring function P4sm_TT_Sk	202
9.5		P4s layer trail protection functions	204
9.6		P4s tandem connection sublayer functions.....	205
	9.6.1	P4s tandem connection trail termination source function (P4sD_TT_So)..	205
	9.6.2	P4s tandem connection trail termination sink function (P4sD_TT_Sk)	208
	9.6.3	P4s tandem connection to p4s adaptation source function (P4sD/P4s_A_So).....	213
	9.6.4	P4s tandem connection to p4s adaptation sink function (P4sD/P4s_A_Sk)	214
	9.6.5	P4s tandem connection non-intrusive trail termination sink function (P4sDm_TT_Sk).....	215
10		P4x path layer functions	219
11		P32x path layer functions	219
12		P31x path layer functions	219
13		P22x path layer functions	219
14		P12x path layer functions	219
15		P11x path layer functions	219
16		P0s path layer functions	220
17		P0-31c path layer functions	220
Annex A (informative):		Relationship between TU-2/12 address, and location of columns within a P4s TUG3 structured payload.....	221
Annex B (informative):		Relationship between TU-2/12 address, and location of columns within a P4s TUG2 structured payload.....	224
Annex C (informative):		Bibliography	227
History			228

iTech STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 417-5-1 E1:2003](https://standards.iteh.ai/catalog/standards/sist/ets-300-417-5-1-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/ets-300-417-5-1-e1-2003>

Foreword

This European Telecommunication Standard (ETS) has been produced by the Transmission and Multiplexing (TM) Technical Committee of the European Telecommunications Standards Institute (ETSI) in order to provide inter-vendor and inter-operator compatibility of Synchronous Digital Hierarchy (SDH) equipments.

Transposition dates	
Date of adoption of this ETS:	6 March 1998
Date of latest announcement of this ETS (doa):	30 June 1998
Date of latest publication of new National Standard or endorsement of this ETS (dop/e):	31 December 1998
Date of withdrawal of any conflicting National Standard (dow):	31 December 1998

This ETS consists of 8 parts as follows:

- Part 1: "Generic processes and performance" (ETS 300 417-1-1 [8]).
- Part 2: "SDH and PDH Physical section layer functions" (ETS 300 417-2-1).
- Part 3: "STM-N regenerator and multiplex section layer functions" (ETS 300 417-3-1).
- Part 4: "SDH path layer functions" (ETS 300 417-4-1 [10]).
- Part 5: "PDH path layer functions" (ETS 300 417-5-1).**
- Part 6: "Synchronization distribution layer functions" (ETS 300 417-6-1 [11]).
- Part 7: "Auxiliary layer functions" (ETS 300 417-7-1).
- Part 8: "Compound and major compound functions" (ETS 300 417-8-1).

Introduction

The atomic PDH path layer functions are defined below used in plesiochronous and synchronous operation. They describe the functionality of PDH multiplex equipments described in the ITU-T Recommendations G.751 [6] and G.742 [5] for signal hierarchies P4e, P31e and P22e. In addition they describe the functionality of synchronous PDH equipment described in ETS 300 167 [2] for P12s layer signals, and ETS 300 337 [9] for P31s and P4s signals.

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 417-5-1 E1:2003](https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>

1 Scope

This European Telecommunication Standard (ETS) specifies a library of basic building blocks and a set of rules by which they are combined in order to describe a digital transmission equipment. The library comprises the functional building blocks needed to completely specify the generic functional structure of the European digital transmission hierarchy. Equipment which is compliant with this ETS can be described as an interconnection of a subset of these functional blocks contained within this ETS. The interconnections of these blocks should obey the combination rules given. The generic functionality is described in the ETS 300 417-1-1 [8].

2 References

This ETS incorporates by dated or undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references subsequent amendments to, or revisions of, any of these publications apply to this ETS only when incorporated in it by amendments or revisions. For undated references the latest edition of the publication referred to applies.

- [1] ETS 300 147: "Transmission and Multiplexing (TM); Synchronous Digital Hierarchy (SDH); Multiplexing structure".
- [2] ETS 300 167 (1993): "Transmission and Multiplexing (TM); Functional characteristics of 2 048 kbit/s interfaces".
- [3] ITU-T Recommendation G.703 (1991): "Physical/electrical characteristics of hierarchical digital interfaces".
- [4] ITU-T Recommendation G.704 (1995): "Synchronous frame structures used at 1 544, 6 312, 2 048, 8 488 and 44 736 kbit/s hierarchical levels".
- [5] ITU-T Recommendation G.742 (1988): "Second order digital multiplex equipment operating at 8 448 kbit/s and using positive justification".
- [6] ITU-T Recommendation G.751 (1988): "Digital multiplex equipments operating at the third order bit rate of 34 368 kbit/s and the fourth order bit rate of 139 264 kbit/s and using positive justification".
- [7] ITU-T Recommendation G.823: "The control of jitter and wander within digital networks which are based on the 2 048 kbit/s hierarchy".
- [8] ETS 300 417-1-1 [8] (1996): "Transmission and Multiplexing (TM); Generic functional requirements for Synchronous Digital Hierarchy (SDH) equipment; Part 1-1: Generic processes and performance".
- [9] ETS 300 337: "Transmission and Multiplexing (TM); Generic frame structures for the transport of various signals (including Asynchronous Transfer Mode (ATM) cells and Synchronous Digital Hierarchy (SDH) elements) at the ITU-T Recommendation G.702 hierarchical rates of 2 048 kbit/s, 34 368 kbit/s and 139 264 kbit/s".
- [10] ETS 300 417-4-1: "Transmission and Multiplexing (TM); Generic requirements of transport functionality of equipment; Part 4-1: Synchronous Digital Hierarchy (SDH) path layer functions".
- [11] ETS 300 417-6-1: "Transmission and Multiplexing (TM); Generic requirements of transport functionality of equipment; Part 6-1: Synchronization layer functions".
- [12] EN 301 163: "Transmission and Multiplexing (TM); Generic requirements of Asynchronous Transfer Mode (ATM) transport functionality within equipment".

- [13] ETS 300 166 (1993): "Transmission and Multiplexing (TM); Physical and electrical characteristics of hierarchical digital interfaces for equipment using the 2048 kbit/s - based plesiochronous or synchronous digital hierarchies".

3 Definitions, abbreviations and symbols

3.1 Definitions

The functional definitions are described in the ETS 300 417-1-1 [8].

3.2 Abbreviations

For the purposes of this ETS, the following abbreviations apply:

A	Adaptation function
AcSL	Accepted Signal Label
AcTI	Accepted Trace Identifier
AI	Adapted Information
AIS	Alarm Indication Signal
AP	Access Point
APId	Access Point Identifier
ATM	Asynchronous Transfer Mode
Avp	ATM VP layer
BIP	Bit Interleaved Parity
BIP-N	Bit Interleaved Parity, width N
BITS	Building Integrated Timing Supply
C	Connection function
CH	Channel
CI	Characteristic Information
CK	Clock
CM	Connection Matrix
CMI	Coded Mark Inversion
Co	Connection
CP	Connection Point
CRC	Cyclic Redundancy Check
CRC-N	Cyclic Redundancy Check, width N
Cs	supervisory-unequipped Connection function
CSES	Consecutive Severely Errored Seconds
CTF	Compound Timing Function
Ctrl	Control
D	Data
DCC	Data Communications Channel
DEC	DECrement
DEG	DEGraded
DEGTHR	DEGraded THReshold
DL	Data Link
DPRING	Dedicated Protection RING
DROP	Decreased Received Optical Power
DXC	Digital Cross Connect
E0	Electrical interface signal 64 kbit/s
E11	Electrical interface signal 1 544 kbit/s
E12	Electrical interface signal 2 048 kbit/s
E22	Electrical interface signal 8 448 kbit/s
E31	Electrical interface signal 34 368 kbit/s
E32	Electrical interface signal 44 736 kbit/s
E4	Electrical interface signal 139 264 kbit/s
EBC	Errored Block Count
EDC	Error Detection Code
EDCV	Error Detection Code Violation
EFS	Equipment Functional Specification
EMF	Equipment Management Function
EQ	EQuipment
Ex	ITU-T Recommendation G.703 [3] type Electrical signal, bit rate order x

ExSL	Expected Signal Label
ExTI	Expected Trace Identifier
F_B	Far-end Block
FAS	Frame Alignment Signal
FASE	Frame Alignment Signal Error
FO	Frame Offset information
FOP	Failure Of Protocol
FS	Frame Start signal
HDB3	High Density Bipolar of order 3
HDLC	High-level Data Link Control procedure
HO	Higher Order
HOVC	Higher Order Virtual Container
HP	Higher order Path
ID	IDentifier
IF	In Frame state
INC	INCrement
IOS	Intra-Office Section
IS	Intermediate System
ISDN	Integrated Services Digital Network
ISO	International Standardization Organization
LC	Link Connection
LO	Lower Order
LOF	Loss Of Frame
LOM	Loss Of Multiframe
LOP	Loss Of Pointer
LOS	Loss Of Signal
LOVC	Lower Order Virtual Container
LPx	Lower order Path for VC-x (x = 11, 12, 2, 3)
LT	Line Termination
M&CF	Management & Communication Function
MC	Matrix Connection
MFP	MultiFrame Present
MI	Management Information
MON	MONitored
MP	Management Point
N.C.	Not Connected
N_B	Near-end Block
NC	Network Connection
NCI	No CRC-4 Multiframe Indication
NDF	New Data Flag
NE	Network Element
NMON	Not MONitored
NNI	Network Node Interface
NU	National Use (bits, bytes)
OAM	Operation, Administration and Management
OFS	Out of Frame Second
OOF	Out Of Frame state
OS	Operations System
OS	Optical Section
OSC	OSCillator
OSI(x)	Open Systems Interconnection, layer x
OW	Order Wire
P	Protection
P0_31c	1 984 kbit/s layer
P0s	64 kbit/s layer (transparent)
P11x	1 544 kbit/s layer (transparent)
P12s	2 048 kbit/s PDH path layer with synchronous 125 μs frame structure as specified in ETS 300 167 [2]
P12x	2 048 kbit/s layer (transparent)
P22e	8 448 kbit/s PDH path layer with 4 plesiochronous 2 048 kbit/s
P22x	8 448 kbit/s layer (transparent)
P31e	34 368 kbit/s PDH path layer with 4 plesiochronous 8 448 kbit/s

STANDARD PREVIEW
(standards.iteh.ai)

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8124-eb4d1ef591b/sist-ets-300-417-5-1-e1-2003>

P31s	34 368 kbit/s PDH path layer with synchronous 125 μ s frame structure as specified in ETS 300 337 [9]
P31x	34 368 kbit/s layer (transparent)
P32x	44 736 kbit/s layer (transparent)
P4e	139 264 kbit/s PDH path layer with 4 plesiochronous 34 368 kbit/s
P4s	139 264 kbit/s PDH path layer with synchronous 125 μ s frame structure as specified in ETS 300 337 [9]
P4x	139 264 kbit/s layer (transparent)
PDH	Plesiochronous Digital Hierarchy
PEC	PDH Equipment Clock
PJE	Pointer Justification Event
PLM	PayLoad Mismatch
PM	Performance Monitoring
Pn	Plesiochronous signal, Level n
POH	Path OverHead
PRC	Primary Reference Clock
PS	Protection Switching
PSC	Protection Switch Count
PTR	PoinTeR
PU	PDH Unit
QOS	Quality Of Service
RDI	Remote Defect Indicator
REI	Remote Error Indicator
RI	Remote Information
RLT	Regenerated Line Termination
RNCI	Remote No CRC-4 Multiframe Indication
RP	Remote Point
RS	Regenerator Section
RS1	STM-1 Regenerator Section
RS16	STM-16 Regenerator Section
RS4	STM-4 Regenerator Section
RSOH	Regenerator Section OverHead
RxSL	Received Signal Label
RxTI	Received Trace identifier
SASE	Stand-Alone Synchronization Equipment
SD	synchronization distribution layer, Signal Degrade
SEC	SDH Equipment Clock
SES	Severely Errored Second
SESR	Severely Errored seconds Ratio
SF	Signal Fail
Sk	Sink
SMF	Sub-Multi-Frame
SNC	Sub-Network Connection
SNC/I	Inherently monitored Sub-Network Connection protection
SNC/N	Non-intrusively monitored Sub-Network Connection protection
So	Source
SOH	Section OverHead
SPRING	Shared Protection RING
SSD	Server Signal Degrade
SSF	Server Signal Fail
SSM	Synchronization Status Message
SSU	Synchronization Supply Unit
TCP	Termination Connection Point
TD	Transmit Degrade
TF	Transmit Fail
TFAS	trail Trace identifier Frame Alignment Signal
TG	Timing Generator
TI	Timing Information
TIM	Trace Identifier Mismatch
TM	Transmission_Medium
TP	Timing Point
TPmode	Termination Point mode
TR	Threshold Report

TS	Time Slot
TSD	Trail Signal Degrade
TSF	Trail Signal Fail
TSL	Trail Signal Label
TT	Trail Termination function
TTI	Trail Trace Identifier
TTP	Trail Termination Point
TTs	Trail Termination supervisory function
TU	Tributary Unit
TUG	Tributary Unit Group
TUG-m	Tributary Unit Group, level m
TU-m	Tributary Unit, level m
TxSL	Transmitted Signal Label
TxTI	Transmitted Trace Identifier
UAS	UnAvailable Second
UNEQ	Unequipped
UNI	User Network Interface
USR	USeR channels
UVC	Unequipped VC
VC	Virtual Container
VC-n	Virtual Container, level n
VMR	Violation Monitoring and Removal
VP	Virtual Path
W	Working

3.3 Symbols and Diagrammatic Conventions

The symbols and diagrammatic conventions are described in the ETS 300 417-1-1 [8].

iteh STANDARD PREVIEW
(standards.iteh.ai)

[SIST ETS 300 417-5-1 E1:2003](https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/1c9d3803-530b-4360-8374-95eb2d0e65fb/sist-ets-300-417-5-1-e1-2003>