

ETSI TS 125 302 V8.3.0 (2009-07)

Technical Specification

Universal Mobile Telecommunications System (UMTS); Services provided by the physical layer (3GPP TS 25.302 version 8.3.0 Release 8)



iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b80afb72-323a-4550-9547-342a541097f0/etsi-ts-125-302-v8.3.0-2009-07>



Reference

RTS/TSGR-0225302v830

Keywords

UMTS**ETSI**

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaicor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2009.
All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™**, **TIPHON™**, the TIPHON logo and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.

3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

LTE™ is a Trade Mark of ETSI currently being registered

for the benefit of its Members and of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

ETSI STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b80a2b72-323a-4550-9547-342a541097f0/etsi-ts-125-302-v8.3.0-2009-07>

Contents

Intellectual Property Rights	2
Foreword.....	2
Foreword.....	7
1 Scope	8
2 References	8
3 Definitions and abbreviations.....	8
3.1 Definitions	8
3.2 Abbreviations	9
4 Interfaces to the physical layer.....	10
4.1 Interface to MAC.....	11
4.2 Interface to RRC.....	11
5 Services and functions of the physical layer	11
5.1 General	11
5.2 Overview of L1 functions.....	12
5.3 L1 interactions with L2 retransmission functionality.....	12
6 Model of physical layer of the UE	13
6.1 Uplink models	13
6.2 Downlink models	17
7 Formats and configurations for L1 data transfer	29
7.1 General concepts about Transport Channels	29
7.1.1 Transport Block	30
7.1.2 Transport Block Set	30
7.1.3 Transport Block Size	30
7.1.4 Transport Block Set Size	30
7.1.5 Transmission Time Interval	30
7.1.6 Transport Format	31
7.1.6a Transport Format for HS-DSCH.....	32
7.1.7 Transport Format for E-DCH.....	32
7.1.7a Transport Format Set	33
7.1.8 Transport Format Combination.....	34
7.1.9 Transport Format Combination Set	34
7.1.10 Transport Format Indicator (TFI)	35
7.1.11 Transport Format Combination Indicator (TFCI).....	35
7.1.12 Rate matching	35
7.1.13 HARQ information	36
7.1.14 Transport Format and Resource Indication (TFRI)	36
7.1.15 E-DCH Transport Format Combination Indication (E-TFCI)	36
7.2 Types of Transport Channels.....	36
7.3 Compressed Mode.....	38
8 UE Simultaneous Physical Channels combinations.....	39
8.1 FDD Uplink.....	39
8.2 FDD Downlink	41
8.3 TDD Uplink.....	45
8.3.1 3.84/7.68 Mcps TDD Uplink	45
8.3.2 1.28 Mcps TDD Uplink	46
8.4 TDD Downlink.....	48
8.4.1 3.84/7.68 Mcps TDD Downlink	48
8.4.2 1.28 Mcps TDD Downlink	49
8.4.3 3.84 Mcps TDD IMB Downlink.....	54
9 Measurements provided by the physical layer	54

9.1	Model of physical layer measurements	55
9.2	UE Measurements	56
9.2.1	SFN-CFN observed time difference	56
9.2.2	Void	56
9.2.3	CPICH E_c/N_0	56
9.2.4	Void	56
9.2.5	CPICH RSCP	56
9.2.6	P-CCPCH RSCP	57
9.2.7	Timeslot ISCP	57
9.2.8	Void	57
9.2.9	SIR	57
9.2.10	UTRA carrier RSSI	57
9.2.11	GSM carrier RSSI	57
9.2.12	Transport channel BLER	58
9.2.13	UE transmitted power	58
9.2.14	UE Rx-Tx time difference	58
9.2.15	SFN-SFN Observed time difference	58
9.2.16	UE GPS Timing of Cell Frames for UE positioning	58
9.2.17	Timing Advance (T_{ADV}) for 1.28 Mcps TDD	59
9.2.18	UE GPS code phase	59
9.2.19	UE GANSS Timing of Cell Frames for UE positioning	59
9.2.20	UE GANSS code measurement	59
9.3	UTRAN Measurements	60
9.3.1	Received total wide band power	60
9.3.2	Transmitted carrier power	60
9.3.3	Transmitted code power	60
9.3.4	Void	60
9.3.5	Physical channel BER	60
9.3.6	Transport channel BER	60
9.3.7	RX timing deviation	61
9.3.8	Timeslot ISCP	61
9.3.9	RSCP	61
9.3.10	Round Trip Time	61
9.3.11	Void	61
9.3.12	Acknowledged PRACH preambles	61
9.3.13	Void	61
9.3.14	Void	62
9.3.15	SIR	62
9.3.16	PRACH Propagation Delay	62
9.3.17	UTRAN GPS Timing of Cell Frames for UE positioning	62
9.3.18	SIR ERROR	62
9.3.19	Received SYNC_UL Timing Deviation	62
9.3.20	Cell Sync Burst Timing	63
9.3.21	Cell Sync Burst SIR	63
9.3.22	SFN-SFN Observed time difference	63
9.3.23	Angle of Arrival (AOA) for 1.28 Mcps TDD	63
9.3.24	HS-SICH reception quality	63
9.3.25	Transmitted carrier power of all codes not used for HS-PDSCH or HS-SCCH transmission	64
9.3.26	UpPTS interference (1.28Mcps TDD)	64
9.3.27	DL Transmission Branch Load	64
9.3.28	Received scheduled E-DCH power share (RSEPS)	65
9.3.29	UTRAN GANSS Timing of Cell Frames for UE positioning	65
9.3.30	Common E-DCH resource usage	65
10	Primitives of the physical layer	66
10.1	Generic names of primitives between layers 1 and 2	66
10.1.1	PHY-Access-REQ	67
10.1.2	PHY-Access-CNF	67
10.1.3	PHY-Data-REQ	68
10.1.4	PHY-Data-IND	68
10.1.5	Void	68
10.1.6	Void	68

10.1.7	PHY-Status-IND.....	68
10.2	Generic names of primitives between layers 1 and 3	69
10.2.1	STATUS PRIMITIVES	69
10.2.1.1	CPHY-Sync-IND	69
10.2.1.2	CPHY-Out-of-Sync-IND	69
10.2.1.3	CPHY-Measurement-REQ.....	69
10.2.1.4	CPHY-Measurement-IND.....	70
10.2.1.5	CPHY-Error-IND.....	70
10.2.1.6	Void.....	70
10.2.2	CONTROL PRIMITIVES	70
10.2.2.1	CPHY-TrCH-Config-REQ.....	70
10.2.2.2	CPHY-TrCH-Config-CNF	70
10.2.2.3	CPHY-TrCH-Release-REQ	71
10.2.2.4	CPHY-TrCH-Release-CNF.....	71
10.2.2.5	CPHY-RL-Setup-REQ.....	71
10.2.2.6	CPHY-RL-Setup-CNF	71
10.2.2.7	CPHY-RL-Release-REQ.....	71
10.2.2.8	CPHY-RL-Release-CNF	71
10.2.2.9	CPHY-RL-Modify-REQ.....	71
10.2.2.10	CPHY-RL-Modify-CNF	71
10.2.2.11	CPHY-Commit-REQ	72
10.2.2.12	Void.....	72
10.2.2.13	Void.....	72
10.2.2.14	Void.....	72
10.2.2.15	Void.....	72
10.2.2.16	CPHY-Out-of-Sync-Config-REQ	72
10.2.2.17	CPHY-Out-of-Sync-Config-CNF	72
10.2.2.18	CPHY-MBMS-Config-REQ.....	72
10.2.2.19	CPHY-MBMS-Config-CNF	72
10.3	Parameter definition	73
10.3.1	Error code	73
10.3.2	Event value	73
10.3.3	Access Information	73
10.3.4	Transport Format Subset.....	73
10.3.5	Physical channel description.....	73
10.3.5.1	Primary SCH.....	73
10.3.5.2	Secondary SCH.....	73
10.3.5.3	Primary CCPCH.....	73
10.3.5.4	Secondary CCPCH.....	74
10.3.5.4a	Secondary CCPCH frame type 2.....	74
10.3.5.5	PRACH	74
10.3.5.6	Uplink DPDCH+DPCCH.....	75
10.3.5.7	Uplink DPCH.....	75
10.3.5.8	Downlink DPCH	75
10.3.5.8a	F-DPCH (FDD only).....	76
10.3.5.9	Void.....	76
10.3.5.10	PICH	76
10.3.5.11	AICH.....	76
10.3.5.12	Void.....	76
10.3.5.13	Void.....	76
10.3.5.14	Void.....	76
10.3.5.15	Void.....	76
10.3.5.16	PDSCH (TDD only).....	77
10.3.5.17	PUSCH.....	77
10.3.5.18	DwPCH (1.28 Mcps TDD only)	77
10.3.5.19	UpPCH (1.28 Mcps TDD only)	77
10.3.5.20	FPACH (1.28 Mcps TDD only)	77
10.3.5.21	PNBSCH (Physical Node B Synchronisation channel).....	78
10.3.5.22	HS-SCCH.....	78
10.3.5.23	HS-SICH (TDD only)	78
10.3.5.24	E-AGCH	78
10.3.5.25	E-DPCCH (FDD only).....	78

10.3.5.26 E-DPDCH (FDD only).....78

10.3.5.27 E-HICH78

10.3.5.28 E-RGCH (FDD only)79

10.3.5.28a E-RUCCH (TDD only)79

10.3.5.29 MICH.....79

10.3.6 Feedback information79

10.3.7 HARQ process80

10.3.8 HS-DSCH information80

10.3.9 HARQ status80

10.3.10 E-DCH information80

10.3.11 MBMS information.....80

11 Transport block transmission80

Annex A (normative): Description of Transport Formats81

Annex B (informative): Example of Transport format attributes for AMR speech codec.....84

Annex C (informative): Change history85

History89

iTeh STANDARD PREVIEW
 (standards.iteh.ai)
 Full standard:
<https://standards.iteh.ai/catalog/standards/sist/b80afb72-323a-4550-9547-342a541097f0/etsi-ts-125-302-v8.3.0-2009-07>

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/bc29fb72-323a-4550-9547-342a541097f0/etsi-ts-125-302-v8.3.0-2009-07>

1 Scope

The present document is a technical specification of the services provided by the physical layer of UTRA to upper layers.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 23.110: "UMTS Access Stratum; Services and Functions".
- [2] 3GPP TS 25.301: "Radio Interface Protocol Architecture".
- [3] 3GPP TS 25.212: "Multiplexing and channel coding (FDD)".
- [4] 3GPP TS 25.222: "Multiplexing and channel coding (TDD)".
- [5] 3GPP TS 25.224: "Physical Layer Procedures (TDD)".
- [6] 3GPP TS 25.215: "Physical Layer – Measurements (FDD)".
- [7] 3GPP TS 25.213: "Spreading and modulation (FDD)".
- [8] 3GPP TS 25.214: "Physical layer procedures (FDD)".
- [9] 3GPP TS 25.123: "Requirements for Support of Radio Resource Management (TDD)".
- [10] 3GPP TS 25.133: "Requirements for Support of Radio Resource Management (FDD)".
- [11] 3GPP TS 25.225: "Physical Layer – Measurements (TDD)".
- [12] 3GPP TS 25.221: "Physical channels and mapping of transport channels onto physical channels (TDD)".
- [13] 3GPP TS 25.331: "Radio Resource Control (RRC); protocol specification".
- [14] 3GPP TS 25.346: "Introduction of the Multimedia Broadcast Multicast Service (MBMS) in the Radio Access Network (RAN); Stage 2".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in [3] and the following apply:

E-DCH active set (FDD only): The set of cells which carry the E-DCH for one UE. In CELL_FACH state and Idle mode, the E-DCH active set contains the Serving E-DCH cell only.

Serving E-DCH cell: Cell from which the UE receives Absolute Grants from the Node-B scheduler. A UE has one Serving E-DCH cell.

Serving E-DCH RLS or Serving RLS (FDD only):: Set of cells which contains at least the Serving E-DCH cell and from which the UE can receive and combine one Relative Grant. The UE has only one Serving E-DCH RLS.

Non-serving E-DCH RL or Non-serving RL (FDD only):: Cell which belongs to the E-DCH active set but does not belong to the Serving E-DCH RLS and from which the UE can receive one Relative Grant. The UE can have zero, one or several Non-serving E-DCH RL(s).

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

ARQ	Automatic Repeat Request
BCCH	Broadcast Control Channel
BCH	Broadcast Channel
C-	Control-
CC	Call Control
CCCH	Common Control Channel
CCH	Control Channel
CCTrCH	Coded Composite Transport Channel
CN	Core Network
CQI	Channel Quality Indicator
CRC	Cyclic Redundancy Check
DC	Dedicated Control (SAP)
DCA	Dynamic Channel Allocation
DCCH	Dedicated Control Channel
DCH	Dedicated Channel
DL	Downlink
DRNC	Drift Radio Network Controller
DSCH	Downlink Shared Channel
DTCH	Dedicated Traffic Channel
E-AGCH	E-DCH Absolute Grant Channel
E-DCH	Enhanced DCH
E-DPCCH	E-DCH Dedicated Physical Control Channel (FDD only)
E-DPDCH	E-DCH Dedicated Physical Data Channel (FDD only)
E-HICH	E-DCH HARQ Acknowledgement Indicator Channel
E-PUCH	E-DCH Physical Uplink Channel (TDD only)
E-RGCH	E-DCH Relative Grant Channel (FDD only)
E-RUCCH	E-DCH Random access Uplink Control Channel (TDD only)
E-TFC	E-DCH Transport Format Combination
E-UCCH	E-DCH Uplink Control Channel (3.84 Mcps and 7.68 Mcps TDD only)
FACH	Forward Link Access Channel
FCS	Fame Check Sequence
FDD	Frequency Division Duplex
F-DPCH	Fractional Dedicated Physical Channel (FDD only)
GC	General Control (SAP)
GANSS	Galileo and Additional Navigation Satellite Systems
GNSS	Global Navigation Satellite System
GPS	Global Positioning System
HARQ	Hybrid Automatic Repeat Request
HS-DPCCH	High Speed Dedicated Physical Control CHannel
HS-DSCH	High Speed Downlink Shared CHannel
HS-SCCH	High Speed Shared Control CHannel
HS-SICH	High Speed Shared Information CHannel
HO	Handover
ITU	International Telecommunication Union
kbps	kilo-bits per second
L1	Layer 1 (physical layer)
L2	Layer 2 (data link layer)

L3	Layer 3 (network layer)
LAC	Link Access Control
LAI	Location Area Identity
MAC	Medium Access Control
MBMS	Multimedia Broadcast Multicast Service
MCCH	MBMS point-to-multipoint Control Channel
MICH	MBMS notification Indicator Channel
MM	Mobility Management
MSCH	MBMS point-to-multipoint Scheduling Channel
MTCH	MBMS point-to-multipoint Traffic Channel
Nt	Notification (SAP)
PCCH	Paging Control Channel
PCH	Paging Channel
PDU	Protocol Data Unit
PHY	Physical layer
PhyCH	Physical Channels
RACH	Random Access Channel
RLC	Radio Link Control
RNC	Radio Network Controller
RNS	Radio Network Subsystem
RNTI	Radio Network Temporary Identity
RRC	Radio Resource Control
SAP	Service Access Point
SDU	Service Data Unit
SRNC	Serving Radio Network Controller
SRNS	Serving Radio Network Subsystem
SS	Synchronisation Shift
TCH	Traffic Channel
TDD	Time Division Duplex
TFCI	Transport Format Combination Indicator
TFI	Transport Format Indicator
TFRI	Transport Format and Resource Indicator
TMSI	Temporary Mobile Subscriber Identity
TPC	Transmit Power Control
TSN	Transmission Sequence Number
U-	User-
UE	User Equipment
UL	Uplink
UMTS	Universal Mobile Telecommunications System
URA	UTRAN Registration Area
UTRA	UMTS Terrestrial Radio Access
UTRAN	UMTS Terrestrial Radio Access Network

4 Interfaces to the physical layer

The physical layer (layer 1) is the lowest layer in the OSI Reference Model and it supports all functions required for the transmission of bit streams on the physical medium.

The physical layer interfaces the Medium Access Control (MAC) Layer and the Radio Resource Control (RRC) Layer as depicted in figure 1.




Figure 1: Interfaces with the Physical Layer

4.1 Interface to MAC

The physical layer interfaces the MAC entity of layer 2. Communication between the Physical Layer and MAC is in an abstract way performed by means of PHY-primitives defined which do not constrain implementations.

NOTE: The terms physical layer and layer 1, will be used synonymously in this description.

The PHY-primitives exchanged between the physical layer and the data link layer provide the following functions:

- transfer of transport blocks over the radio interface;
- indicate the status of the layer 1 to layer 2.

4.2 Interface to RRC

The physical layer interfaces the RRC entity of layer 3 in the UE and in the network.

Communication is performed in an abstract way by means of CPHY-primitives. They do not constrain implementations.

The CPHY-primitives exchanged between the physical layer and the Network layer provide the following function:

- control of the configuration of the physical layer.

The currently identified exchange of information across that interface has only a local significance to the UE or Network.

5 Services and functions of the physical layer

5.1 General

The physical layer offers data transport services to higher layers. The access to these services is through the use of transport channels via the MAC sub-layer. The characteristics of a transport channel are defined by its transport format (or format set), specifying the physical layer processing to be applied to the transport channel in question, such as convolutional channel coding and interleaving, and any service-specific rate matching as needed.

The physical layer operates exactly according to the L1 radio frame timing. A transport block is defined as the data accepted by the physical layer to be jointly CRC protected. The transmission block timing is then tied exactly to the TTI timing, e.g. every transmission block is generated precisely every TTI.

A UE can set up multiple transport channels simultaneously, each having own transport characteristics (e.g. offering different error correction capability). Each transport channel can be used for information stream transfer of one radio bearer or for layer 2 and higher layer signalling messages.

The multiplexing of transport channels onto the same or different physical channels is carried out by L1. Except for HS-DSCH and E-DCH the Transport Format Combination Indication field (TFCI) shall uniquely identify the transport format used by each transport channel of the Coded Composite Transport Channel within the current radio frame.

In case of HS-DSCH the identification of the transport format and channelisation codes is realised with the Transport Format and Resource Indication field (TFRI) on an associated shared control channel.

In case of FDD E-DCH the identification of the transport format is realised with the E-DCH Transport Format Combination Indication field (E-TFCI) on a associated dedicated control channel.

In the case of TDD E-DCH the identification of the transport format is realised with the E-DCH Transport Format Combination Indication field (E-TFCI) multiplexed onto E-PUCH.

5.2 Overview of L1 functions

The physical layer performs the following main functions:

- FEC encoding/decoding of transport channels;
- measurements and indication to higher layers (e.g. FER, SIR, interference power, transmission power, etc...);
- macrodiversity distribution/combining and soft handover execution;
- error detection on transport channels;
- multiplexing of transport channels and demultiplexing of coded composite transport channels;
- rate matching;
- mapping of coded composite transport channels on physical channels;
- modulation and spreading/demodulation and despreading of physical channels;
- frequency and time (chip, bit, slot, frame) synchronisation;
- closed-loop power control;
- power weighting and combining of physical channels;
- RF processing;
- support of Uplink Synchronisation as defined in [5] (TDD only);
- timing advance on uplink channels (TDD only).

5.3 L1 interactions with L2 retransmission functionality

Provided that the RLC PDUs are mapped one-to-one onto the Transport Blocks, Error indication may be provided by L1 to L2. For that purpose, the L1 CRC can be used for individual error indication of each RLC PDU.

The L1 CRC may serve multiple purposes:

- error indication for uplink macro diversity selection combining (L1);
- error indication for each erroneous Transport Block in transparent and unacknowledged mode RLC;
- quality indication;
- error indication for each erroneous Transport Block in acknowledged mode RLC.

Regardless of the result of the CRC check, all Transport Blocks are delivered to L2 along with the associated error indications for transport channel other than HS-DSCH and E-DCH. In case of HS-DSCH and E-DCH an error indication is provided to L2 in case of CRC failure.