

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE

BASIC SAFETY PUBLICATION

PUBLICATION FONDAMENTALE DE SÉCURITÉ

**Electrical installations of buildings –  
Part 5-54: Selection and erection of electrical equipment – Earthing  
arrangements, protective conductors and protective bonding conductors**

**Installations électriques des bâtiments –  
Partie 5-54: Choix et mise en oeuvre des matériels électriques – Mises à la terre,  
conducteurs de protection et conducteurs d'équipotentialité de protection**

<https://standards.itech.ai/en/standards/iec/fds762b8-dbfd-4b7c-91e5-0d3388832475/iec-60364-5-54-2002>





## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2002 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland  
Email: [inmail@iec.ch](mailto:inmail@iec.ch)  
Web: [www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: [www.iec.ch/online\\_news/justpub](http://www.iec.ch/online_news/justpub)

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: [www.iec.ch/webstore/custserv](http://www.iec.ch/webstore/custserv)

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: [csc@iec.ch](mailto:csc@iec.ch)

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

### A propos de la CEI

La Commission Electrotechnique internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

### A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: [www.iec.ch/searchpub/cur\\_fut-f.htm](http://www.iec.ch/searchpub/cur_fut-f.htm)

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: [www.iec.ch/online\\_news/justpub](http://www.iec.ch/online_news/justpub)

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: [www.electropedia.org](http://www.electropedia.org)

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: [www.iec.ch/webstore/custserv/custserv\\_entry-f.htm](http://www.iec.ch/webstore/custserv/custserv_entry-f.htm)

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: [csc@iec.ch](mailto:csc@iec.ch)

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE

BASIC SAFETY PUBLICATION  
PUBLICATION FONDAMENTALE DE SÉCURITÉ

**Electrical installations of buildings –  
Part 5-54: Selection and erection of electrical equipment – Earthing  
arrangements, protective conductors and protective bonding conductors**

**Installations électriques des bâtiments –  
Partie 5-54: Choix et mise en œuvre des matériels électriques – Mises à la terre,  
conducteurs de protection et conducteurs d'équipotentialité de protection**

<https://standards.iteh.ai/en/standards/iec/fdc762b8-dbfd-4b7c-91e5-0d3388832475/iec-60364-5-54-2002>

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

PRICE CODE  
CODE PRIX

S

## CONTENTS

FOREWORD.....	3
INTRODUCTION.....	5
541 General.....	6
541.1 Scope .....	6
541.2 Normative references .....	6
541.3 Definitions.....	7
542 Earthing arrangements.....	8
542.1 General requirements.....	8
542.2 Earth electrodes .....	8
542.3 Earthing conductors .....	10
542.4 Main earthing terminal.....	11
543 Protective conductors.....	11
543.1 Minimum cross-sectional areas.....	11
543.2 Types of protective conductors .....	13
543.3 Electrical continuity of protective conductors.....	14
543.4 PEN conductors .....	14
543.6 Arrangement of protective conductors.....	15
543.7 Reinforced protective conductors for protective conductor currents exceeding 10 mA.....	15
544 Protective bonding conductors (equipotential bonding conductors).....	15
544.1 Protective bonding conductors for the connection to the main earthing terminal.....	15
544.2 Protective bonding conductors for supplementary bonding .....	15
Annex A (normative) Method for deriving the factor $k$ in 543.1.2 (see also IEC 60724 and IEC 60949).....	16
Annex B (informative) Illustration of earthing arrangements, protective conductors and protective bonding conductors.....	19
Bibliography.....	21
Table 54.1 – Minimum size requirements for earth electrodes of commonly used material from the point of view of corrosion and mechanical strength where embedded in the soil for commonly used material.....	9
Table 54.2 – Minimum cross-sectional areas of earthing conductors buried in the soil.....	10
Table 54.3 – Minimum cross-sectional area of protective conductors .....	12
Table A.54.1 – Value of the parameters for different materials .....	16
Table A.54.2 – Values of $k$ for insulated protective conductors not incorporated in cables, and not bunched with other cables .....	17
Table A.54.3 – Values of $k$ for bare protective conductors in contact with cable covering but not bunched with other cables .....	17
Table A.54.4 – Values of $k$ for protective conductors as a core incorporated in a cable, or bunched with other cables or insulated conductors .....	17
Table A.54.5 – Values of $k$ for protective conductors as a metallic layer of a cable e.g. armour, metallic sheath, concentric conductor, etc.....	18
Table A.54.6 – Value of $k$ for bare conductors where there is no risk of damage to any neighbouring material by the temperature indicated .....	18

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ELECTRICAL INSTALLATIONS OF BUILDINGS –****Part 5-54: Selection and erection of electrical equipment –  
Earthing arrangements, protective conductors  
and protective bonding conductors**

## FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.
- 3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical specifications, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.
- 5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.
- 6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

IEC 60364-5-54 has been prepared by IEC technical committee 64, Electrical installations and protection against electric shock.

This second edition replaces the first edition, published in 1980, its amendment 1 (1982), as well as some clauses of IEC 60364-5-548, published in 1996, and its amendment (1998), and constitutes a technical revision.

The text of this standard is based on the following documents:

FDIS	Report on voting
64/1231/FDIS	64/1249/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

It has the status of a basic safety publication in accordance with IEC Guide 104.

This publication has been drafted, as close as possible, in accordance with the ISO/IEC Directives, Part 3.

Annex A forms an integral part of this standard.

Annex B is for information only.

The committee has decided that the contents of this publication will remain unchanged until 2007. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

Withdrawn

iTech Standards  
(<https://standards.iteh.ai>)  
Document Preview

[IEC 60364-5-54:2002](https://standards.iteh.ai/iec/60364-5-54:2002)

<https://standards.iteh.ai/iec/60364-5-54:2002>

## INTRODUCTION

Clause numbering is sequential, preceded by the number of this part (e.g. 541). Numbering of figures and tables takes the number of this part followed by a sequential number, i.e. Table 54.1, 54.2, etc. Numbering of figures and tables in annexes takes the letter of the annex, followed by the number of the part, followed by a sequential number, e.g. A.54.1, A.54.2, etc.

Withdrawing

iTech Standards  
(<https://standards.iteh.ai>)  
Document Preview

IEC 60364-5-54:2002  
<https://standards.iteh.ai/en/standards/iec/iec762b8-dbfd-4b7c-91e5-0d3388832475/iec-60364-5-54-2002>

## ELECTRICAL INSTALLATIONS OF BUILDINGS –

### Part 5-54: Selection and erection of electrical equipment – Earthing arrangements, protective conductors and protective bonding conductors

#### 541 General

##### 541.1 Scope

This part of IEC 60364 addresses the earthing arrangements, protective conductors and protective bonding conductors in order to satisfy the safety of the electrical installation.

##### 541.2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050(195), *International Electrotechnical Vocabulary (IEV) – Part 195: Earthing and protection against electric shock*

IEC 60287-1-1, *Electric cables – Calculation of the current rating – Part 1-1: Current rating equations (100 % load factor) and calculation of losses – General*

IEC 60364-4-41, *Electrical installations of buildings – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-43, *Electrical installations of buildings – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-4-44, *Electrical installations of buildings – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*

IEC 60364-5-52, *Electrical installations of buildings – Part 5-52: Selection and erection of electrical equipment – Wiring systems*

IEC 60724, *Short-circuit temperature limits of electric cables with rated voltages of 1 kV ( $U_m = 1,2$  kV) and 3 kV ( $U_m = 3,6$  kV)*

IEC 60853-2, *Calculation of the cyclic and emergency current rating of cables – Part 2: Cyclic rating of cables greater than 18/30 (36) kV and emergency ratings for cables of all voltages*

IEC 60909-0, *Short-circuit currents in three-phase a.c. systems – Part 0: Calculation of currents*

IEC 60949, *Calculation of thermally permissible short-circuit currents, taking into account non-adiabatic heating effects*



IEC 61024-1, *Protection of structures against lightning – Part 1: General principles*

IEC 61140, *Protection against electric shock – Common aspects for installation and equipment*

IEC Guide 104, *The preparation of safety publications and the use of basic safety publications and group safety publications*

### 541.3 Definitions

For the purposes of this part of IEC 60364, the definitions of IEC 61140, together with the following definitions taken from IEC 60050(195), apply.

Definitions used for earthing arrangements, protective conductors and protective bonding conductors are illustrated in annex B and listed here as follows:

#### 541.3.1

##### **exposed-conductive-part**

conductive part of equipment which can be touched and which is not normally live, but which can become live when basic insulation fails

[IEV 195-06-10]

#### 541.3.2

##### **main earthing terminal**

(main earthing busbar)

terminal or busbar which is part of the earthing arrangement of an installation enabling the electric connection of a number of conductors for earthing purposes

[IEV 195-02-33]

#### 541.3.3

##### **earth electrode**

conductive part, which may be embedded in a specific conductive medium, e.g. concrete or coke, in electric contact with the earth

[IEV 195-02-01]

#### 541.3.4

##### **protective conductor**

conductor provided for purposes of safety, for example protection against electric shock

[IEV 195-02-09]

#### 541.3.5

##### **protective bonding conductor**

protective conductor provided for protective-equipotential-bonding

[IEV 195-02-10]

### **541.3.6 earthing conductor**

conductor which provides a conductive path, or part of the conductive path, between a given point in a system or in an installation or in equipment and an earth electrode

[IEV 195-02-03]

NOTE For the purposes of this part of IEC 60364, an earthing conductor is the conductor which connects the earth electrode to a point in the equipotential bonding system, usually the main earthing terminal.

### **541.3.7 extraneous-conductive-part**

conductive part not forming part of the electrical installation and liable to introduce an electric potential, generally the electric potential of a local earth

[IEV 195-06-11]

## **542 Earthing arrangements**

### **542.1 General requirements**

**542.1.1** The earthing arrangements may be used jointly or separately for protective and functional purposes according to the requirements of the electrical installation. The requirements for protective purposes shall always take precedence.

**542.1.2** Where provided, earth electrodes within an installation shall be connected to the main earthing terminal using an earthing conductor.

**542.1.3** Consideration shall be given to the earthing arrangements which are used in high-voltage and low-voltage systems (see IEC 60364-4-44, clause 442).

**542.1.4** The requirements for earthing arrangements are intended to provide a connection to earth:

- which is reliable and suitable for the protective requirements of the installation;
- which can carry earth fault currents and protective conductor currents to earth without danger from thermal, thermo-mechanical and electromechanical stresses and from electric shock arising from these currents;
- which, if relevant, is also suitable for functional requirements.

### **542.2 Earth electrodes**

**542.2.1** Materials and dimensions of the earth electrodes shall be selected to withstand corrosion and to have adequate mechanical strength.

For commonly used materials, the common minimum sizes from the point of view of corrosion and mechanical strength for earth electrodes where embedded in the soil are given in table 54.1.

NOTE If a lightning protection system (LPS) is present, the IEC 61024-1 applies.

**Table 54.1 – Common minimum sizes for earth electrodes of commonly used material from the point of view of corrosion and mechanical strength where embedded in the soil**

Material	Surface	Shape	Minimum size				
			Diameter mm	Cross-sectional area mm <sup>2</sup>	Thickness mm	Thickness of coating/sheathing	
						Individual value µm	Average value µm
Steel	Hot-dip galvanized <sup>a</sup> or Stainless <sup>a, b</sup>	Strip <sup>c</sup>		90	3	63	70
		Sections		90	3	63	70
		Round rod for deep earth electrodes	16			63	70
		Round wire for surface electrode <sup>g</sup>	10				50 <sup>e</sup>
		Pipe	25		2	47	55
	Copper- sheathed	Round rod for deep earth electrode	15			2 000	
	With electro- deposited copper coating	Round rod for deep earth electrode	14			90	100
Copper	Bare <sup>a</sup>	Strip		50	2		
		Round wire for surface electrode <sup>g</sup>		25 <sup>f</sup>			
		Rope	1,8 for individual strands of wire	25			
		Pipe	20		2		
	Tin-coated	Rope	1,8 for individual strands of wire	25		1	5
	Zinc-coated	Strip <sup>d</sup>		50	2	20	40

<sup>a</sup> Can also be used for electrodes to be embedded in concrete.

<sup>b</sup> No coating applied.

<sup>c</sup> As rolled strip or slit strip with rounded edges.

<sup>d</sup> Strip with rounded edges.

<sup>e</sup> In the case of continuous bath-coating, only 50 µm thickness is technically feasible at present.

<sup>f</sup> Where experience shows that the risk of corrosion and mechanical damage is extremely low, 16 mm<sup>2</sup> can be used.

<sup>g</sup> An earth electrode is considered to be a surface electrode when installed at a depth not exceeding 0,5 m.

**542.2.2** The efficacy of any earth electrode depends upon local soil conditions. One or more earth electrodes suitable for the soil conditions and the value of resistance to earth required, shall be selected.

**542.2.3** The following are examples of earth electrodes which may be used:

- underground structural networks embedded in foundations (foundation earthing);
- plates;
- metal reinforcement of concrete (except pre-stressed concrete) embedded in the earth;
- rods or pipes;
- tapes or wires;
- metal sheaths and other metal coverings of cables according to local conditions or requirements;
- other suitable underground metalwork according to local conditions or requirements.

NOTE 1 In Austria, Belgium, Finland, France, Germany, Sweden, Switzerland and the UK, water pipes are not permitted as earth electrodes.

NOTE 2 In Italy it is permitted to use a water pipe system, but only with the consent of the water distributor.

**542.2.4** When selecting type and embedded depth of earth electrode, consideration shall be given to local conditions and regulations so that soil drying and freezing will be unlikely to increase the earth resistance of the earth electrode to such a value that would impair the protective measures against electric shock (see IEC 60364-4-41).

NOTE In Germany, there is an obligation to erect in every new building a foundation earth electrode according to National Standard DIN 18014.

**542.2.5** Consideration shall be given to electrolytic corrosion when using different materials in an earthing arrangement.

**542.2.6** A metallic pipe for flammable liquids or gases shall not be used as an earth electrode.

NOTE This requirement does not preclude the protective bonding of such pipes for compliance with IEC 60364-4-41.

**542.3 Earthing conductors**

**542.3.1** Earthing conductors shall comply with 543.1 and where buried in the soil, their cross-sectional areas shall be in accordance with table 54.2.

In TN systems, where no noticeable fault current is expected to pass in the earth electrode, the earthing conductor may be dimensioned according to 544.1.1

**Table 54.2 – Minimum cross-sectional areas of earthing conductors buried in the soil**

	Mechanically protected	Mechanically unprotected
Protected against corrosion	2,5 mm <sup>2</sup> Cu 10 mm <sup>2</sup> Fe	16 mm <sup>2</sup> Cu 16 mm <sup>2</sup> Fe
Not protected against corrosion	25 mm <sup>2</sup> Cu 50 mm <sup>2</sup> Fe	